

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
22 December 2011 (22.12.2011)

PCT

(10) International Publication Number
WO 2011/160130 A2


- (51) International Patent Classification:
H01L 31/10 (2006.01) *H01L 31/04* (2006.01)
- (21) International Application Number:
PCT/US2011/041108
- (22) International Filing Date:
20 June 2011 (20.06.2011)
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:
61/356,536 18 June 2010 (18.06.2010) US
- (71) Applicant (for all designated States except US):
SIONYX, INC [US/US]; 100 Cummings Ctr., 243-f,
Beverly, MA 01915-6506 (US).
- (72) Inventors; and
- (75) Inventors/Applicants (for US only): **CAREY, James**
[US/US]; 117 Vernon Unit 2, Waltham, MA 02453 (US).
MILLER, Drake [US/US]; 130552 Sw Jacob Ct.,
Tigard, OR 97224 (US).
- (74) Agents: **ALDER, Todd, B.** et al.; THORPE NORTH &
WESTERN, LLP, P.O. Box 1219, Sandy, UT
84091-1219 (US).

- (81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PE, PG, PH, PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.
- (84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:

— without international search report and to be republished upon receipt of that report (Rule 48.2(g))

(54) Title: HIGH SPEED PHOTSENSITIVE DEVICES AND ASSOCIATED METHODS



(57) Abstract: High speed optoelectronic devices and associated methods are provided. In one aspect, for example, a high speed optoelectronic device can include a silicon material having an incident light surface, a first doped region and a second doped region forming a semiconductive junction in the silicon material, and a textured region coupled to the silicon material and positioned to interact with electromagnetic radiation. The optoelectronic device has a response time of from about 1 picosecond to about 5 nanoseconds and a responsivity of greater than or equal to about 0.4 A/W for electromagnetic radiation having at least one wavelength from about 800 nm to about 1200 nm.

WO 2011/160130 A2

HIGH SPEED PHOTSENSITIVE DEVICES AND ASSOCIATED METHODS**PRIORITY DATA**

This application claims the benefit of U.S. Provisional Patent Application Serial No. 61/356,536, filed on June 18, 2010, which is incorporated herein by reference.

BACKGROUND

Many imaging applications such as hands-free gesture control, video games, medical, and machine vision, as well as communication applications utilize various optoelectronic devices, such as photodetectors and imaging arrays of photodetectors. Communication applications typically use, for example, fiber optical networks because such networks perform well in the near infrared wavelengths of light where optical fibers experience lower signal loss. Applications for laser marking and range finding commonly use lasers with near infrared wavelengths such 1064 nm. Other applications such as depth perception applications utilize imagers that can detect near infrared wavelengths such as 850 nm or 940 nm. These wavelengths are commonly generated from light emitting diodes or laser diodes made with gallium arsenide (GaAs). All of these applications require detectors or detector arrays with fast response time, typically faster than what can be achieved with a thick (eg > 100 um) thick active layer of silicon. Therefore, the silicon devices utilized for these applications are often thin and have specific design considerations included to reduce response time. However, as the active layer of silicon becomes thinner, the response at longer wavelengths (eg 850 nm, 940 nm, and 1064 nm) because much lower than that of a thick silicon device layer. Thick silicon devices with high response at longer wavelengths, on the other hand, have slow response time and are difficult to deplete.

SUMMARY

The present disclosure provides high speed optoelectronic devices and associated methods. In one aspect, for example, a high speed optoelectronic device can include a silicon material having an incident light surface, a first doped region and a second doped region forming a semiconductive junction in the silicon material, and a textured region coupled to the silicon material and positioned to interact with

1 electromagnetic radiation. The optoelectronic device has a response time of from
2 about 1 picosecond to about 5 nanoseconds and a responsivity of greater than or equal
3 to about 0.4 A/W for electromagnetic radiation having at least one wavelength from
4 about 800 nm to about 1200 nm. In another aspect, the optoelectronic device has a
5 responsivity of greater than or equal to about 0.5 A/W for electromagnetic radiation
6 having at least one wavelength from about 800 nm to about 1200 nm. In yet another
7 aspect, the optoelectronic device has a responsivity of greater than or equal to about
8 0.45 A/W for electromagnetic radiation having a wavelength of about 850 nm. In a
9 further aspect, the silicon material has a thickness of from about 1 μm to about 100
10 μm . In yet a further aspect, dark current of the device during operation is from about
11 100 pA/cm² to about 10 nA/cm².

12 In another aspect, a high speed optoelectronic device can include a silicon
13 material having an incident light surface, a first doped region and a second doped
14 region forming a semiconductive junction in the silicon material, and a textured
15 region coupled to the silicon material and positioned to interact with electromagnetic
16 radiation. The optoelectronic device has a response time of from about 1 picosecond
17 to about 5 nanoseconds and a responsivity of greater than or equal to about 0.3 A/W
18 for electromagnetic radiation having a wavelength of about 940 nm.

19 In yet another aspect, high speed optoelectronic device can include a silicon
20 material having an incident light surface, a first doped region and a second doped
21 region forming a semiconductive junction in the silicon material, and a textured
22 region coupled to the silicon material and positioned to interact with electromagnetic
23 radiation. The optoelectronic device has a response time of from about 1 picosecond
24 to about 5 nanoseconds and a responsivity of greater than or equal to about 0.05 A/W
25 for electromagnetic radiation having a wavelength of about 1060 nm.

26 In another aspect, a photodiode array can include a silicon material having an
27 incident light surface, at least two photodiodes in the silicon material, each
28 photodiode including a first doped region and a second doped region forming a
29 junction, and a textured region coupled to the silicon material and positioned to
30 interact with electromagnetic radiation. The photodiode array has a response time of
31 from about 1 picosecond to about 5 nanoseconds and a responsivity of greater than or
32 equal to about 0.4 A/W for electromagnetic radiation having at least one wavelength
33 from about 800 nm to about 1200 nm. In one aspect, the silicon material has a
34 thickness of from about 1 μm to about 100 μm .

1 In yet another aspect, a method of increasing the speed of an optoelectronic
2 device can include doping at least two regions in a silicon material to form at least one
3 junction, and texturing the silicon material to form a textured region positioned to
4 interact with electromagnetic radiation. The optoelectronic device has a response
5 time of from about 1 picosecond to about 5 nanoseconds and a responsivity of greater
6 than or equal to about 0.4 A/W for electromagnetic radiation having at least one
7 wavelength from about 800 nm to about 1200 nm. In one aspect, the device can
8 include a further doped region intended to quickly bring carriers from the side
9 opposite junction to the junction region.

10 11 **BRIEF DESCRIPTION OF THE DRAWINGS**

12 FIG. 1 is a graphical representation of the absorption characteristics of a fast
13 (or thin) photodetector device based on standard silicon compared to the absorption
14 characteristics of a photodetecting device based on silicon but having a textured
15 region in accordance with one aspect of the present disclosure;

16 FIG. 2 is a schematic view of a photosensitive device in accordance with
17 another aspect of the present disclosure;

18 FIG. 3 is a schematic view of a photosensitive device in accordance with yet
19 another aspect of the present disclosure;

20 FIG. 4 is a schematic view of a photosensitive device in accordance with a
21 further aspect of the present disclosure;

22 FIG. 5 is a schematic view of a photosensitive device in accordance with yet a
23 further aspect of the present disclosure;

24 FIG. 6 is a schematic view of a photosensitive device in accordance with
25 another aspect of the present disclosure;

26 FIG. 7 is a schematic view of a photosensitive device in accordance with yet
27 another aspect of the present disclosure;

28 FIG. 8 is a schematic view of a photosensitive array device in accordance with
29 a further aspect of the present disclosure;

30 FIG. 9 is an illustration of a time of flight measurement in accordance with
31 another aspect of the present disclosure;

32 FIG. 10a is a schematic view of a pixel configuration for a photoimager array
33 in accordance with another aspect of the present disclosure;

1 FIG. 10b is a schematic view of a pixel configuration for a photoimager array
2 in accordance with another aspect of the present disclosure;

3 FIG. 10c is a schematic view of a pixel configuration for a photoimager array
4 in accordance with another aspect of the present disclosure;

5 FIG. 11 is a schematic diagram of a six transistor imager in accordance with
6 another aspect of the present disclosure;

7 FIG. 12 is a schematic diagram of an eleven transistor imager in accordance
8 with another aspect of the present disclosure;

9 FIG. 13 is a schematic view of a photosensitive array device in accordance
10 with yet a further aspect of the present disclosure;

11 FIG. 14 is a schematic view of a photosensitive array device in accordance
12 with another aspect of the present disclosure; and

13 FIG. 15 is a depiction of a method of increasing the speed of an optoelectronic
14 device in accordance with yet another aspect of the present disclosure.

15 16 **DETAILED DESCRIPTION**

17 Before the present disclosure is described herein, it is to be understood that
18 this disclosure is not limited to the particular structures, process steps, or materials
19 disclosed herein, but is extended to equivalents thereof as would be recognized by
20 those ordinarily skilled in the relevant arts. It should also be understood that
21 terminology employed herein is used for the purpose of describing particular
22 embodiments only and is not intended to be limiting.

23 **Definitions**

24 The following terminology will be used in accordance with the definitions set
25 forth below.

26 It should be noted that, as used in this specification and the appended claims,
27 the singular forms “a,” and, “the” can include plural referents unless the context
28 clearly dictates otherwise. Thus, for example, reference to “a dopant” can include one
29 or more of such dopants and reference to “the layer” can include reference to one or
30 more of such layers.

31 As used herein, “quantum efficiency” (QE) is defined as the percentage of
32 photons incident on an optoelectronic device that are converted into electrons.
33 External QE (EQE) is defined as the current obtained outside of the device per
34 incoming photon. As such, EQE therefore depends on both the absorption of photons

1 and the collection of charges. The EQE is lower than the QE due to recombination
2 effects and optical losses (e.g. transmission and reflection losses).

3 As used herein, “responsivity” is a measure of the input–output gain of a
4 detector system. In the case of a photodetector, responsivity is a measure of the
5 electrical output per optical input. Responsivity of a photodetector is expressed in
6 amperes per watt of incident radiant power. Additionally, responsivity is a function
7 of the wavelength of the incident radiation and of the properties of the device, such as
8 the bandgap of the material of which the device is made. One expression for
9 responsivity (R_λ) is shown in Equation I, where η is the external quantum efficiency
10 of the detector for a given wavelength (λ), q is the charge of an electron, h is Planks
11 constant, and ν is the frequency of light.

$$12 \quad R_\lambda = \frac{q}{h\nu} \times \eta \approx \frac{\lambda_{(\mu m)}}{1.23985} \times \eta \quad (I)$$

13
14
15
16 As used herein, the terms “electromagnetic radiation” and “light” can be used
17 interchangeably, and can represent wavelengths across a broad range, including
18 visible wavelengths (approximately 350nm to 800nm) and non-visible wavelengths
19 (longer than about 800nm or shorter than 350 nm). The infrared spectrum is often
20 described as including a near infrared portion of the spectrum including wavelengths
21 of approximately 800 to 1300 nm, a short wave infrared portion of the spectrum
22 including wavelengths of approximately 1300 nm to 3 micrometers, and a mid to long
23 wave infrared (or thermal infrared) portion of the spectrum including wavelengths
24 greater than about 3 micrometers up to about 30 micrometers. These are generally
25 and collectively referred to herein as “infrared” portions of the electromagnetic
26 spectrum unless otherwise noted.

27 As used herein, “response time” refers to the rise time or fall time of a detector
28 device. In one aspect, “rise time” is the time difference between the 10% point and the
29 90% point of the peak amplitude output on the leading edge of the electrical signal
30 generated by the interaction of light with the device. "Fall time" is measured as the
31 time difference between the 90% point and the 10% point of the trailing edge of the
32 electrical signal. In some aspects, fall time can be referred to as the decay time.

33 As used herein, the terms “disordered surface” and “textured surface” can be
34 used interchangeably, and refer to a surface having a topology with nano- to micron-

1 sized surface variations. Such a surface topology can be formed by the irradiation of
2 a laser pulse or laser pulses, chemical etching, lithographic patterning, interference of
3 multiple simultaneous laser pulses, or reactive ion etching. While the characteristics
4 of such a surface can be variable depending on the materials and techniques
5 employed, in one aspect such a surface can be several hundred nanometers thick and
6 made up of nanocrystallites (e.g. from about 10 to about 50 nanometers) and
7 nanopores. In another aspect, such a surface can include micron-sized structures (e.g.
8 about 1 μm to about 60 μm). In yet another aspect, the surface can include nano-sized
9 and/or micron-sized structures from about 5 nm and about 500 μm .

10 As used herein, the term “fluence” refers to the amount of energy from a
11 single pulse of laser radiation that passes through a unit area. In other words,
12 “fluence” can be described as the energy density of one laser pulse.

13 As used herein, the terms “surface modifying” and “surface modification”
14 refer to the altering of a surface of a semiconductor material using laser irradiation,
15 chemical etching, reactive ion etching, lithographic patterning, etc. In one specific
16 aspect, surface modification can include processes using primarily laser radiation or
17 laser radiation in combination with a dopant, whereby the laser radiation facilitates
18 the incorporation of the dopant into a surface of the semiconductor material.
19 Accordingly, in one aspect surface modification includes doping of a semiconductor
20 material.

21 As used herein, the term “target region” refers to an area of a semiconductor
22 material that is intended to be doped or surface modified. The target region of a
23 semiconductor material can vary as the surface modifying process progresses. For
24 example, after a first target region is doped or surface modified, a second target region
25 may be selected on the same semiconductor material.

26 As used herein, the term “detection” refers to the sensing, absorption, and/or
27 collection of electromagnetic radiation.

28 As used herein, the term “substantially” refers to the complete or nearly
29 complete extent or degree of an action, characteristic, property, state, structure, item,
30 or result. For example, an object that is “substantially” enclosed would mean that the
31 object is either completely enclosed or nearly completely enclosed. The
32 exact allowable degree of deviation from absolute completeness may in some cases
33 depend on the specific context. However, generally speaking the nearness of
34 completion will be so as to have the same overall result as if absolute and total

1 completion were obtained. The use of “substantially” is equally applicable when used
2 in a negative connotation to refer to the complete or near complete lack of an action,
3 characteristic, property, state, structure, item, or result. For example, a composition
4 that is “substantially free of” particles would either completely lack particles, or so
5 nearly completely lack particles that the effect would be the same as if it completely
6 lacked particles. In other words, a composition that is “substantially free of” an
7 ingredient or element may still actually contain such item as long as there is no
8 measurable effect thereof.

9 As used herein, the term “about” is used to provide flexibility to a numerical
10 range endpoint by providing that a given value may be “a little above” or “a little
11 below” the endpoint.

12 As used herein, a plurality of items, structural elements, compositional
13 elements, and/or materials may be presented in a common list for convenience.
14 However, these lists should be construed as though each member of the list is
15 individually identified as a separate and unique member. Thus, no individual member
16 of such list should be construed as a de facto equivalent of any other member of the
17 same list solely based on their presentation in a common group without indications to
18 the contrary.

19 Concentrations, amounts, and other numerical data may be expressed or
20 presented herein in a range format. It is to be understood that such a range format is
21 used merely for convenience and brevity and thus should be interpreted flexibly to
22 include not only the numerical values explicitly recited as the limits of the range, but
23 also to include all the individual numerical values or sub-ranges encompassed within
24 that range as if each numerical value and sub-range is explicitly recited. As an
25 illustration, a numerical range of “about 1 to about 5” should be interpreted to include
26 not only the explicitly recited values of about 1 to about 5, but also include individual
27 values and sub-ranges within the indicated range. Thus, included in this numerical
28 range are individual values such as 2, 3, and 4 and sub-ranges such as from 1-3, from
29 2-4, and from 3-5, etc., as well as 1, 2, 3, 4, and 5, individually.

30 This same principle applies to ranges reciting only one numerical value as a
31 minimum or a maximum. Furthermore, such an interpretation should apply regardless
32 of the breadth of the range or the characteristics being described.

The Disclosure

Many applications for optoelectronic devices can benefit from high speed operation. For example, a photodetector used in applications such as communicating data, laser range finding, laser marking, time of flight imaging, and the like, can be a limiting factor in how fast data can be transmitted. Thus, a photodetector having a faster responsivity can receive data at a correspondingly higher rate. The speed of many optoelectronic devices such as photodetectors is dependent, at least in part, on the speed with which charge carriers are swept from the photodetector. The speed at which carriers are swept from a photodetector can depend on the distance a carrier has to travel, whether the carriers are generated in a region of the device with an electric field, and the likelihood of a carrier being trapped or slowed in a defect within the device layer. In some cases, a bias can be applied to the photodetector to decrease the response time by increasing the drift velocity of the carriers. Additionally, many traditional data communication applications utilize electromagnetic radiation in the red and infrared spectrum as a data carrier. In a typical silicon device, electromagnetic radiation in the red and infrared spectrum generate carriers deep into the silicon device, thus increasing the distance the carrier has to travel to be collected. Thus it can be beneficial for a photodetector to absorb infrared radiation in a thin device in order to increase communication speeds and to reduce dark current.

Silicon is one material that can be used as a photodetector semiconductor. Thin silicon photodetectors are limited, however, in their ability to detect infrared wavelengths, particularly when functioning at higher data communication speeds. Traditional silicon materials require substantial absorption depths to detect photons having wavelengths longer than about 700 nm. While visible light can be absorbed at relatively shallow depths in silicon, absorption of longer wavelengths (e.g. 900 nm) in silicon of a thin wafer depth (e.g. approximately 100 μm) is poor if at all. Because short wave infrared light is mostly transparent to silicon-based photodetectors, other materials (e.g. InGaAs) have traditionally been used to detect infrared electromagnetic radiation having wavelengths greater than about 1100 nm. Using such other materials, however, is expensive, increases dark current relative to silicon devices, and limits the detection of electromagnetic radiation in the visible spectrum (i.e. visible light, 350 nm – 800 nm). As such, silicon is often used because it is relatively cheap to manufacture and can be used to detect wavelengths in the visible spectrum.

1 Accordingly, the present disclosure provides optoelectronic devices and
2 associated methods that increase the electromagnetic radiation absorption range of
3 thin silicon devices into the infrared region, thus allowing the absorption of visible
4 and infrared light by such devices. Additionally, such devices can be configured to
5 operate at much higher data rates and have increased external quantum efficiencies
6 and responsivities as compared to traditional thin silicon devices operating in the
7 infrared spectrum. In one aspect, for example, a silicon photodetector is provided that
8 includes a textured region to increase the absorption, external quantum efficiency, and
9 to decrease response times in the infrared wavelengths. Such unique and novel
10 devices can operate at high data rates in the visible and infrared spectrums. Such an
11 increased sensitivity in a silicon-based device can thus reduce processing cost of
12 photodetectors, reduce the power needed in light sources, increase the depth
13 resolution in 3D types imaging, increase the distance over which data can be
14 transmitted, improve laser range finding, and increases opportunities to use longer
15 wavelengths of electromagnetic radiation for communicating data.

16 In one aspect, for example, a high speed optoelectronic device is provided.
17 Such a device can include a silicon material having an incident light surface, a first
18 doped region and a second doped region forming a semiconductive junction in the
19 silicon material, and a textured region coupled to the silicon material and positioned
20 to interact with electromagnetic radiation. The optoelectronic device has a response
21 time of from about 1 picosecond to about 5 nanoseconds and a responsivity of greater
22 than or equal to about 0.4 A/W for electromagnetic radiation having at least one
23 wavelength from about 800 nm to about 1200 nm. For example, FIG. 1 shows an
24 absorption/responsivity graph where the dashed line 12 represents the absorption
25 characteristics of a photodetector device based on standard fast silicon device and the
26 solid line 14 represents the absorption characteristics of a photodetecting device based
27 on silicon but having a textured region. Notably, the absorption of a standard fast
28 silicon photodiode in the infrared, i.e. the 800nm to 1200nm region, results in
29 relatively low responsivity.

30 Additionally, in one aspect the response time of the optoelectronic device is
31 from about 1 picosecond to about 1 nanosecond. In another aspect, the response time
32 of the optoelectronic device is from about 1 picosecond to about 500 picoseconds.

33 In another aspect, the optoelectronic device has a responsivity of greater than
34 or equal to about 0.5 A/W for electromagnetic radiation having at least one

1 wavelength from about 800 nm to about 1200 nm. In yet another aspect, the
2 optoelectronic device has a responsivity of greater than or equal to about 0.45 A/W
3 for electromagnetic radiation having a wavelength of about 850 nm. In a further
4 aspect, the optoelectronic device has a responsivity of greater than or equal to about
5 0.3 A/W for electromagnetic radiation having a wavelength of about 940 nm. In yet a
6 further aspect, the optoelectronic device has a responsivity of greater than or equal to
7 about 0.05 A/W for electromagnetic radiation having a wavelength of about 1060 nm.

8 In some aspects, the thickness of the device can dictate the responsivity and
9 response time. However standard silicon devices need to be thick, i.e. greater than
10 100 μ m in order to detect wavelengths in the infrared spectrum, and such detection
11 with thick devices results in a slow response and high dark current. It has now been
12 discovered that a textured region positioned to interact with electromagnetic radiation
13 can increase the absorption of infrared light in a device, thereby improving the
14 infrared responsivity while allowing for fast operation. Diffuse scattering and
15 reflection can result in increased path lengths for absorption, particularly if combined
16 with total internal reflection, resulting in large improvements of responsivity in the
17 infrared for silicon photodiodes, photodetectors, photodiode arrays, and the like.
18 Because of the increased path lengths for absorption, thinner silicon materials can be
19 used to absorb electromagnetic radiation up into the infrared regions. One advantage
20 of thinner silicon material devices is that charge carriers are more quickly swept from
21 the device, thus decreasing the response time. Conversely, thick silicon material
22 devices sweep charge carriers therefrom more slowly, at least in part due to diffusion.

23 Thus, the devices of the present disclosure increase the absorption path length
24 of silicon materials by increasing the absorption path length for longer wavelengths as
25 compared to traditional silicon devices. The absorption depth in silicon
26 photodetectors is the depth into silicon at which the radiation intensity is reduced to
27 about 36% of the value at the surface of the silicon material. The increased
28 absorption path length results in an apparent reduction in the absorption depth, or a
29 reduced apparent or effective absorption depth. For example, the effective absorption
30 depth of silicon can be reduced such that longer wavelengths can be absorbed at
31 depths of less than or equal to about 100 μ m. By increasing the absorption path
32 length, such devices are able to absorb longer wavelengths (e.g. > 1000 nm for
33 silicon) within a thin semiconductor material. In addition to decreasing the effective
34

1 absorption depth, the response time can be decreased using thinner semiconductor
2 materials.

3 Accordingly, optoelectronic devices according to aspects of the present
4 disclosure provide, among other things, enhanced response in the infrared light
5 portion of the optical spectrum and improved response and quantum efficiency in
6 converting electromagnetic radiation to electrical signals. As such, high quantum
7 efficiencies and high speeds can be obtained in the infrared for devices thinner than
8 about 100 μm . In other words, the response is higher than that found in thicker
9 devices at infrared wavelengths.

10 In one aspect, as is shown in FIG. 2 for example, an optoelectronic device can
11 include a silicon material 22 having a first doped region 24 and a second doped region
12 26 associated therewith. The first and second doped regions thus form a
13 semiconductive junction. Numerous configurations are contemplated, and any type of
14 junction configuration is considered to be within the present scope. For example, the
15 first and second doped regions can be distinct from one another, contacting one
16 another, overlapping one another, etc. In some cases, an intrinsic region can be
17 located at least partially between the first and second doped regions.

18 The optoelectronic device can also include a textured region 28 coupled to the
19 silicon material 22 and positioned to interact with incoming electromagnetic radiation
20 29. In this case, the textured region is located on a side of the silicon material that is
21 opposite to the first doped region 24 and the second doped region 26.

22 Electromagnetic radiation that passes through the silicon material to contact the
23 textured region can be reflected back through the silicon material, thus effectively
24 increasing the absorption path length of the silicon material. The textured region can
25 be associated with an entire surface of the silicon material or only a portion thereof.
26 Additionally, in some aspects the textured region can be specifically positioned to
27 maximize the absorption path length of the silicon material. In other aspects, a third
28 doping can be included near the textured region to improve the collection of carriers
29 generated near the textured region.

30 The silicon material can be of any thickness that allows electromagnetic
31 radiation detection and conversion functionality, and thus any such thickness of
32 silicon material is considered to be within the present scope. Although any thickness
33 of the silicon material is considered to be within the present scope, thin silicon layer
34 materials can be particularly beneficial in decreasing the response time and/or the

1 capacitance of the device. As has been described, charge carriers can be more quickly
2 swept from thinner silicon material layers as compared to thicker silicon material
3 layers. The thinner the silicon, the less material the electron/holes have to traverse in
4 order to be collected, and the lower the probability of a generated charge carrier
5 encountering a defect that could trap or slow the collection of the carrier. Thus one
6 objective to implementing a fast photo response is to utilize a thin silicon material for
7 the body region of the photodiode. Such a device can be nearly depleted of charge
8 carriers by the built in potential of the photodiode and any applied bias to provide for
9 a fast collection of the photo generated carriers by drift in an electric field. Charge
10 carriers remaining in any undepleted region of the photodiode are collected by
11 diffusion transport, which is slower than drift transport. For this reason, it is desirable
12 to have the thickness of any region where diffusion may dominate to be much thinner
13 than the depleted drift regions. In silicon materials having the proper doping provides
14 a depletion region of about $10\mu\text{m}$ with no applied bias. As such, in some aspects it
15 can be useful to utilize a silicon material layer having a thickness less of less than
16 about $100\mu\text{m}$, or less than about $10\mu\text{m}$. In another aspect, the silicon material can
17 have a thickness and substrate doping concentration such that an applied bias
18 generates an electrical field sufficient for saturation velocity of the charge carriers. It
19 should be noted that operating a photodiode, as disclosed herein, at a zero bias can
20 result in low noise but at a longer response time. When bias is applied however, the
21 dark current is increased, resulting in higher noise, but with a decreased response
22 time. The increased dark current can be compensated if the incident radiation signal is
23 strong. The amount of dark current increase can be minimized, however, with a
24 thinner device layer.

25 Accordingly, in one aspect the silicon material has a thickness of from about 1
26 μm to about $100\mu\text{m}$. In another aspect, the silicon material has a thickness of from
27 about $1\mu\text{m}$ to about $50\mu\text{m}$. In yet another aspect, the silicon material has a thickness
28 of from about $5\mu\text{m}$ to about $10\mu\text{m}$. In a further aspect, the silicon material has a
29 thickness of from about $1\mu\text{m}$ to about $5\mu\text{m}$.

30 As has been described, the response time of an optoelectronic device is limited
31 by the transit time of the photo generated carriers across the thickness of the substrate.
32 The RC time constant of the load resistance, (R) and the capacitance (C) of the entire
33 electronic device structure can be kept less than this transit time value by using small
34 load resistors and keeping the capacitance of the photodiodes small by limiting the

1 doping density of the silicon material and area of the photodiodes. For example,
2 photodiodes doped at $10^{15}/\text{cm}^3$ can have a capacitance that may be $10\text{nF}/\text{cm}^2$ without
3 any applied bias. Small area photodiodes with 50 ohm load resistors can have very
4 fast RC time constants. A photodiode with an area of 0.01 cm^2 can have a RC time
5 constant of 0.5 nanoseconds. Given that the response time will be limited by the
6 maximum charge carrier transit time across the photodiode, then diffusion rates can
7 place an upper limit on the response time for photodiodes of different thickness. For
8 example, if the photodiodes have a thickness of less than $d = 100 \mu\text{m}$, then the
9 diffusion transit time can be calculated by Equation (II) below, where D is the
10 diffusion coefficient for electrons.

$$\frac{d^2}{2D} \quad (\text{II})$$

14
15 The response time is bound by an upper limit of $2 \mu\text{s}$. For light having a wavelength
16 of about 900 nm, only about 35% is absorbed in the first pass or a device thinner than
17 $100 \mu\text{m}$ and approximately 30% is reflected at the first surface, thereby giving a
18 responsivity on the order 10% or 0.1 A/W. The responsivity, R , can be increased at
19 least five fold by using multiple internal reflections to achieve a value of $R = 0.5$
20 A/W.

21 In one aspect, a photodiode can have a thickness of less than about $d = 10 \mu\text{m}$.
22 Using equation (I) above, the resultant upper response time limit is about 20 ns. For
23 light having a wavelength of about 700 nm with about 33% absorbed in the first pass
24 and about 30% being reflected at the first surface, the responsivity can be on the order
25 10% or 0.3 Ampere/Watt. The responsivity, R , can be increased at least two fold by
26 using multiple internal reflections as described herein to achieve a value of $R =$
27 $0.6\text{A}/\text{W}$.

28 In one aspect, for example, an optoelectronic device has a response time of
29 from about 100 picoseconds to about 1 nanosecond. In another aspect, an
30 optoelectronic device has a responsivity of from about 0.4 A/W to about 0.55 A/W for
31 at least one wavelength of from about 800 nm to about 1200 nm relative to standard
32 silicon. In yet another aspect, an optoelectronic device has a responsivity of from
33 about 0.1 A/W to about 0.55 A/W for at least one wavelength of from about 1000 nm
34 to about 1200 nm relative to standard silicon. In another aspect, the optoelectronic

1 device has an increased external quantum efficiency of at least 10% for at least one
2 wavelength of from about 550 nm to about 1200 nm relative to a silicon device with
3 comparable thickness and response time. In yet another aspect, an optoelectronic
4 device has a data rate greater than or equal to about 1 Gbs. In a further aspect, an
5 optoelectronic device has a data rate greater than or equal to about 2 Gbs.

6 As has been described, optoelectronic devices according to aspects of the
7 present disclosure can exhibit lower levels of dark current as compared to traditional
8 devices. Although a variety of reasons are possible, one exemplary reason may be
9 that a thinner silicon material layer can have fewer crystalline defects responsible for
10 the generation of dark current. In one aspect, for example, the dark current of an
11 optoelectronic device during operation is from about 100 pA/cm² to about 10 nA/cm².
12 In another aspect, the maximum dark current of an optoelectronic device during
13 operation is less than about 1 nA/cm².

14 Various types of silicon materials are contemplated, and any such material that
15 can be incorporated into an optoelectronic device is considered to be within the
16 present scope. In one aspect, for example, the silicon material is monocrystalline. In
17 another aspect, the silicon material is multicrystalline. In yet another aspect, the
18 silicon material is microcrystalline.

19 The silicon materials of the present disclosure can also be made using a
20 variety of manufacturing processes. In some cases the manufacturing procedures can
21 affect the efficiency of the device, and may be taken into account in achieving a
22 desired result. Exemplary manufacturing processes can include Czochralski (Cz)
23 processes, magnetic Czochralski (mCz) processes, Float Zone (FZ) processes,
24 epitaxial growth or deposition processes, and the like. In one aspect, the silicon
25 material is epitaxially grown.

26 As has been described, the textured region can function to diffuse
27 electromagnetic radiation, to redirect electromagnetic radiation, and to absorb
28 electromagnetic radiation, thus increasing the QE of the device. The textured region
29 can include surface features to increase the effective absorption length of the silicon
30 material. The surface features can be cones, pyramids, pillars, protrusions,
31 microlenses, quantum dots, inverted features and the like. Factors such as
32 manipulating the feature sizes, dimensions, material type, dopant profiles, texture
33 location, etc. can allow the diffusing region to be tunable for a specific wavelength.
34 In one aspect, tuning the device can allow specific wavelengths or ranges of

1 wavelengths to be absorbed. In another aspect, tuning the device can allow specific
2 wavelengths or ranges of wavelengths to be reduced or eliminated via filtering.

3 As has been described, a textured region according to aspects of the present
4 disclosure can allow a silicon material to experience multiple passes of incident
5 electromagnetic radiation within the device, particularly at longer wavelengths (i.e.
6 infrared). Such internal reflection increases the effective absorption length to be
7 greater than the thickness of the semiconductor substrate. This increase in absorption
8 length increases the quantum efficiency of the device, leading to an improved signal
9 to noise ratio. The textured region can be associated with the surface nearest the
10 impinging electromagnetic radiation, or the textured region can be associated with a
11 surface opposite in relation to impinging electromagnetic radiation, thereby allowing
12 the radiation to pass through the silicon material before it hits the textured region.
13 Additionally, the textured region can be doped. In one aspect, the textured region can
14 be doped to the same or similar doping polarity as the silicon substrate so as to
15 provide a doped contact region on the backside of the device.

16 The textured region can be formed by various techniques, including lasing,
17 chemical etching (e.g. anisotropic etching, isotropic etching), nanoimprinting,
18 additional material deposition, reactive ion etching, and the like. One effective
19 method of producing a textured region is through laser processing. Such laser
20 processing allows discrete locations of the semiconductor substrate to be textured. A
21 variety of techniques of laser processing to form a textured region are contemplated,
22 and any technique capable of forming such a region should be considered to be within
23 the present scope. Laser treatment or processing can allow, among other things,
24 enhanced absorption properties and thus increased electromagnetic radiation focusing
25 and detection.

26 In one aspect, for example, a target region of the silicon material can be
27 irradiated with laser radiation to form a textured region. Examples of such processing
28 have been described in further detail in U.S. Patents 7,057,256, 7,354,792 and
29 7,442,629, which are incorporated herein by reference in their entireties. Briefly, a
30 surface of a silicon material is irradiated with laser radiation to form a textured or
31 surface modified region. Such laser processing can occur with or without a dopant
32 material. In those aspects whereby a dopant is used, the laser can be directed through
33 a dopant carrier and onto the silicon surface. In this way, dopant from the dopant
34 carrier is introduced into the target region of the silicon material. Such a region

1 incorporated into a silicon material can have various benefits in accordance with
2 aspects of the present disclosure. For example, the target region typically has a
3 textured surface that increases the surface area of the laser treated region and
4 increases the probability of radiation absorption via the mechanisms described herein.
5 In one aspect, such a target region is a substantially textured surface including
6 micron-sized and/or nano-sized surface features that have been generated by the laser
7 texturing. In another aspect, irradiating the surface of the silicon material includes
8 exposing the laser radiation to a dopant such that irradiation incorporates the dopant
9 into the semiconductor. Various dopant materials are known in the art, and are
10 discussed in more detail herein. It is also understood that in some aspects such laser
11 processing can occur in an environment that does not substantially dope the silicon
12 material (e.g. an argon atmosphere).

13 Thus the surface of the silicon material that forms the textured region is
14 chemically and/or structurally altered by the laser treatment, which may, in some
15 aspects, result in the formation of surface features appearing as nanostructures,
16 microstructures, and/or patterned areas on the surface and, if a dopant is used, the
17 incorporation of such dopants into the semiconductor material. In some aspects, such
18 features can be on the order of 50 nm to 20 μm in size and can assist in the absorption
19 of electromagnetic radiation. In other words, the textured surface can increase the
20 probability of incident radiation being absorbed by the silicon material.

21 The type of laser radiation used to surface modify a silicon material can vary
22 depending on the material and the intended modification. Any laser radiation known
23 in the art can be used with the devices and methods of the present disclosure. There
24 are a number of laser characteristics, however, that can affect the surface modification
25 process and/or the resulting product including, but not limited to the wavelength of
26 the laser radiation, pulse width, pulse fluence, pulse frequency, polarization, laser
27 propagation direction relative to the silicon material, etc. In one aspect, a laser can be
28 configured to provide pulsatile lasing of a silicon material. A short-pulsed laser is one
29 capable of producing femtosecond, picosecond and/or nanosecond pulse durations.
30 Laser pulses can have a central wavelength in a range of about from about 10 nm to
31 about 12 μm , and more specifically from about 200 nm to about 1600 nm. The pulse
32 width of the laser radiation can be in a range of from about tens of femtoseconds to
33 about hundreds of nanoseconds. In one aspect, laser pulse widths can be in the range
34 of from about 50 femtoseconds to about 50 picoseconds. In another aspect, laser

1 pulse widths can be in the range of from about 50 picoseconds to 100 nanoseconds. In
2 another aspect, laser pulse widths are in the range of from about 50 to 500
3 femtoseconds.

4 The number of laser pulses irradiating a target region can be in a range of from
5 about 1 to about 5000. In one aspect, the number of laser pulses irradiating a target
6 region can be from about 2 to about 1000. Further, the repetition rate or frequency of
7 the pulses can be selected to be in a range of from about 10 Hz to about 10 MHz, or in
8 a range of from about 1 kHz to about 1 MHz, or in a range from about 10 Hz to about
9 10 kHz. Moreover, the fluence of each laser pulse can be in a range of from about 1
10 kJ/m^2 to about 20 kJ/m^2 , or in a range of from about 3 kJ/m^2 to about 8 kJ/m^2 .

11 A variety of dopants are contemplated, and any such material that can be used
12 in doping the first doped region, the second doped region, the textured region, or any
13 other doped portion of the optoelectronic device is considered to be within the present
14 scope. It should be noted that the particular dopant utilized can vary depending on the
15 silicon material being laser treated, as well as the intended uses of the resulting silicon
16 material.

17 A dopant can be either electron donating or hole donating. In one aspect, non-
18 limiting examples of dopants can include S, F, B, P, N, As, Se, Te, Ge, Ar, Ga, In, Sb,
19 and combinations thereof. It should be noted that the scope of dopants should
20 include, not only the dopants themselves, but also materials in forms that deliver such
21 dopants (i.e. dopant carriers). For example, S dopants includes not only S, but also
22 any material capable being used to dope S into the target region, such as, for example,
23 H_2S , SF_6 , SO_2 , and the like, including combinations thereof. In one specific aspect,
24 the dopant can be S. Sulfur can be present at an ion dosage level of between about $5 \times$
25 10^{14} and about 1×10^{16} ions/ cm^2 . Non-limiting examples of fluorine-containing
26 compounds can include ClF_3 , PF_5 , F_2 , SF_6 , BF_3 , GeF_4 , WF_6 , SiF_4 , HF , CF_4 , CHF_3 ,
27 CH_2F_2 , CH_3F , C_2F_6 , C_2HF_5 , C_3F_8 , C_4F_8 , NF_3 , and the like, including combinations
28 thereof. Non-limiting examples of boron-containing compounds can include
29 $\text{B}(\text{CH}_3)_3$, BF_3 , BCl_3 , BN , $\text{C}_2\text{B}_{10}\text{H}_{12}$, borosilica, B_2H_6 , and the like, including
30 combinations thereof. Non-limiting examples of phosphorous-containing compounds
31 can include PF_5 , PH_3 , and the like, including combinations thereof. Non-limiting
32 examples of chlorine-containing compounds can include Cl_2 , SiH_2Cl_2 , HCl , SiCl_4 , and
33 the like, including combinations thereof. Dopants can also include arsenic-containing
34 compounds such as AsH_3 and the like, as well as antimony-containing compounds.

1 Additionally, dopant materials can include mixtures or combinations across dopant
2 groups, i.e. a sulfur-containing compound mixed with a chlorine-containing
3 compound. In one aspect, the dopant material can have a density that is greater than
4 air. In one specific aspect, the dopant material can include Se, H₂S, SF₆, or mixtures
5 thereof. In yet another specific aspect, the dopant can be SF₆ and can have a
6 predetermined concentration range of about 5.0×10^{-8} mol/cm³ to about 5.0×10^{-4}
7 mol/cm³. SF₆ gas is a good carrier for the incorporation of sulfur into the
8 semiconductor material via a laser process without significant adverse effects on the
9 silicon material. Additionally, it is noted that dopants can also be liquid solutions of
10 n-type or p-type dopant materials dissolved in a solution such as water, alcohol, or an
11 acid or basic solution. Dopants can also be solid materials applied as a powder or as a
12 suspension dried onto the wafer.

13 Accordingly, the first doped region and the second doped region can be doped
14 with an electron donating or hole donating species to cause the regions to become
15 more positive or negative in polarity as compared to each other and/or the silicon
16 substrate. In one aspect, for example, either doped region can be p-doped. In another
17 aspect, either doped region can be n-doped. In one aspect, for example, the first
18 doped region can be negative in polarity and the second doped region can be positive
19 in polarity by doping with p⁺ and n⁻ dopants. In some aspects, variations of n(--), n(-
20), n(+), n(++), p(--), p(-), p(+), or p(++ type doping of the regions can be used.
21 Additionally, in some aspects the silicon material can be doped in addition to the first
22 and second doped regions. The silicon material can be doped to have a doping
23 polarity that is different from one or more of the first and second doped regions, of the
24 silicon material can be doped to have a doping polarity that is the same as one or more
25 of the first and second doped regions. In one specific aspect, the silicon material can
26 be doped to be p-type and one or more of the first and second doped regions can be n-
27 type. In another specific aspect, the silicon material can be doped to be n-type and
28 one or more of the first and second doped regions can be p-type. In one aspect, at
29 least one of the first or second doped regions has a surface area of from about 0.1 μm²
30 to about 32 μm².

31 In another aspect, at least a portion of the textured region and/or the silicon
32 material can be doped with a dopant to generate a back surface field. A back surface
33 field can function to repel generated charge carriers from the backside of the device
34 and toward the junction to improve collection efficiency and speed. The addition of a

1 back surface field can increase charge carrier collection and depletion. The presence
2 of a back surface field also acts to suppress dark current contribution from the surface
3 of a device.

4 In another aspect, as is shown in FIG. 3, an optoelectronic device can include
5 a silicon material 32 having a first doped region 34 and a second doped region 36
6 associated therewith, where the first and second doped regions form a semiconductive
7 photodiode junction. A textured region 38 is coupled to the silicon material, and is
8 positioned to interact with electromagnetic radiation. The optoelectronic device can
9 also include a first contact 37 to provide electrical contact to one side of the device,
10 and a second contact 39 to provide electrical contact with the other side of the device.
11 In one aspect, the first contact and the second contact are opposite in voltage polarity
12 from one another. Note that in some aspects, the first and second contacts can be on
13 the same side of the device (not shown). Additionally, a support substrate 35 can be
14 coupled to the device in order to provide structural stability thereto. In one aspect, the
15 one of the contacts can be a doped portion of the textured region. Either a portion of
16 the textured region or the entire textured region can be doped to create one of the
17 contacts.

18 While the optoelectronic devices according to aspects of the present disclosure
19 can operate in the absence of a bias at high speeds, in one aspect a reverse bias is
20 applied across the first and second contacts. Such a reverse bias can function to
21 decrease the response time of the device by more quickly sweeping charge carriers
22 from the silicon material. Accordingly, for those situations whereby a bias is used,
23 any bias voltage capable of sweeping charge carriers from the silicon material is
24 considered to be within the present scope. In one aspect, for example, the reverse bias
25 is from about 0.001 V to about 20 V. In another aspect, the reverse bias is from about
26 0.001 V to about 10 V. In yet another aspect, the reverse bias is from about 0.001 V
27 to about 5 V. In a further aspect, the reverse bias is from about 0.001 V to about 3 V.
28 In yet a further aspect, the reverse bias is from about 3 V to about 5 V. In some
29 aspects, the reverse bias can be absent, or in other words, 0 V is applied across the
30 first and second contacts. In such cases, the charge carriers can be depleted from the
31 silicon material by the junction potential created by the first and second doped
32 regions.

33 In some aspects, the first and second doped regions can be on opposite sides of
34 the silicon material. As is shown in FIG. 4, for example, a silicon material 42 can

1 include a first doped region 44 associated with one surface of the silicon material and
2 a second doped region 46 associated with the opposite side of the silicon material.
3 Furthermore, the textured region can be associated with either doped region. As is
4 shown in FIG. 5, for example, a silicon material 52 can include a first doped region 54
5 associated with one surface of the silicon material and a second doped region 56
6 associated with the opposite side of the silicon material, where a textured region 58 is
7 associated with the first doped region. In another aspect, the textured region is
8 associated with the second doped region (not shown). In a further aspect, a textured
9 region can be associated with each doped region (not shown).

10 In another aspect, as is shown in FIG. 6, a silicon material 62 can have a first
11 doped region 64 and a second doped region 66 on one surface, and a textured region 68
12 on an opposing surface. In this case, electromagnetic radiation 69 is incident on the
13 side of the silicon material having the textured surface. In another aspect, as is shown
14 in FIG. 7, a silicon material 72 can have a first doped region 74 and a second doped
15 region 76 on an opposing surface to a textured region 78. An antireflective layer 77
16 can be coupled to the silicon material on the opposite surface to the textured layer. In
17 some aspects, the antireflective layer can be on the same side of the silicon material as
18 the textured region (not shown). Furthermore, in some aspects a lens can be optically
19 coupled to the silicon material and positioned to focus incident electromagnetic
20 radiation into the silicon material.

21 In another aspect of the present disclosure, a photodiode array is provided.
22 Such an array can include a silicon material having an incident light surface, at least
23 two photodiodes in the silicon material, where each photodiode includes a first doped
24 region and a second doped region forming a junction, and a textured region coupled to
25 the silicon material and positioned to interact with electromagnetic radiation. The
26 textured region can be a single textured region or multiple textured regions.
27 Additionally, the photodiode array has a response time of from about 1 picosecond to
28 about 5 nanoseconds and a responsivity of greater than or equal to about 0.4 A/W for
29 electromagnetic radiation having at least one wavelength from about 800 nm to about
30 1200 nm.

31 As is shown in FIG. 8, for example, a silicon material 88 can include at least
32 two photodiodes 83 each having a first doped region 84 and a second doped region
33 86. A textured region 88 is positioned to interact with electromagnetic radiation.
34 FIG. 8 shows a separate textured region for each photodiode. In some aspects, a

1 single textured region can be used to increase the absorption path lengths of multiple
2 photodiodes in the array. Furthermore, an isolation structure 57 can be positioned
3 between the photodiodes to electrically and/or optically isolate the photodiodes from
4 one another. In another aspect, the photodiode array can be electronically coupled to
5 electronic circuitry to process the signals generated by each photodiode.

6 Various types of isolation structures are contemplated, and any such isolation
7 is considered to be within the present scope. The isolation structure can be shallow or
8 deep trench isolation. Furthermore, the isolation structure can include depths between
9 traditional shallow and deep isolation, depending on the device design. Isolation
10 structures can include dielectric materials, reflective materials, conductive materials,
11 and combinations thereof, including textured regions and other light diffusing
12 features. Thus the isolation structure can be configured to reflect incident
13 electromagnetic radiation, in some cases until it is absorbed, thereby increasing the
14 effective absorption length of the device.

15 Photodiode arrays can have a variety of uses. For example, in one aspect such
16 an array can be an imager. Numerous types of imagers are contemplated, and any
17 such imager or imaging application is considered to be within the present scope.
18 Non-limiting examples include 3D imaging, machine vision, night vision, security
19 and surveillance, various commercial applications, laser range finding and marking,
20 and the like. Thus, in the case of 3D imaging for example, the array is operable to
21 detect a phase delay between a reflected and an emitted optical signal.

22 As one example, various applications can benefit from depth information, such
23 as hands-free gesture control, video games, medical applications, machine vision, etc.
24 Time-of-flight (TOF) is a technique developed for use in radar and LIDAR (Light
25 Detection and Ranging) systems to provide depth information. The basic principle of
26 TOF involves sending a signal and measuring a property of the returned signal from a
27 target. The measured property is used to determine the TOF. Distance to the target is
28 therefore derived by multiplication of half the TOF and the velocity of the signal.

29 FIG. 9 illustrates a time of flight measurement with a target having multiple
30 surfaces that are separated spatially. Equation (III) can be used to measure the
31 distance to a target where d is the distance to the target and c is the speed of light.

$$32 \quad d = \frac{TOF * c}{2} \quad (III)$$

33
34

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34

By measuring the time (e.g. TOF) it takes for light to be emitted from a light source 92, travel to and from a target 94, the distance between the light source (e.g. a light emitting diode (LED)) and the surface of the target can be derived. For an imager, if each pixel can perform the above TOF measurement, a 3D image of the target can be achieved. The distance measurements become difficult with TOF methods when the target is relatively near the source due to the high speed of light. In one aspect, therefore, a TOF measurement can utilize a modulated LED light pulse and measure the phase delay between emitted light and received light. Based on the phase delay and the LED pulse width, the TOF can be derived.

TOF concept has been utilized in both CMOS and CCD sensor to obtain depth information from each pixel. In many traditional 3D TOF sensors, an infrared LED or laser emits a modulated light pulse to illuminate a target. The measured phase shift between emitted and received light can be used to derive the depth information. Such methods, however, can have various problematic issues. For example, ambiguity (e.g. aliasing) occurs if the TOF difference between two targets is equal to half period of light source modulation frequency. To solve the ambiguity issue, an often used approach is to measure the same scene with multiple modulation frequencies. In addition, due to the use of near infrared LED or laser, a good color image normally cannot be achieved by the same 3D TOF sensor since an infrared (IR) cut filter cannot be used. Further, many current 3D TOF sensors operate in a rolling shutter mode. In rolling shutter mode an image is captured by scanning across the frame either vertically or horizontally. Motion artifacts are known to accompany cameras that use the rolling shutter mode and can severely degrade the quality of the depth map.

Another issue occurs when ambient light creates an un-wanted offset in the signal output. The photon-shot noise related to the signal offset will degrade the signal-to-noise (SNR) ratio of the useful signal related to modulated near infrared (NIR) light emitting diode (LED). Therefore, many current 3D TOF imagers cannot operate outdoors (e.g. bright ambient light). In addition to the ambient light, any dark current will also contribute to the un-wanted offset, which is same as normal visible pixel.

As one example, a 3D pixel, such as a TOF 3D pixel with enhanced infrared response can improve depth accuracy. In one aspect, a photoimager array can include at least one 3D infrared detecting pixel and at least one visible light detecting pixel arranged monolithically in relation to each other. FIGs. 10a-c show non-limiting

1 example configurations of pixel arrangements of such arrays. FIG. 10a shows one
2 example of a pixel array arrangement having a red pixel 102, a blue pixel 104, and a
3 green pixel 106. Additionally, two 3D TOF pixels (108 and 109) having enhanced
4 responsivity or detectability in the infrared regions of the light spectrum are included.
5 The combination of two 3D pixels allows for better depth perception. In FIG. 10b,
6 the pixel arrangement shown includes an imager as described in FIG. 10a and three
7 arrays of a red pixel, a blue pixel, and two green pixels. Essentially, one TOF pixel
8 (108 and 109) replaces one quadrant of a RGGGB pixel design. In this configuration,
9 the addition of several green pixels allows for the capture of more green wavelengths
10 that is needed for green color sensitivity need for the human eye, while at the same
11 time capturing the infrared light for depth perception. It should be noted that the
12 present scope should not be limited by the number or arrangements of pixel arrays,
13 and that any number and/or arrangement is included in the present scope. FIG. 10c
14 shows another arrangement of pixels according to yet another aspect.

15 Various imager configurations and components are contemplated, and any
16 such should be considered to be within the present scope. Non-limiting examples of
17 such components can include a carrier wafer, an antireflective layer, a dielectric layer,
18 circuitry layer, a via(s), a transfer gate, an infrared filter, a color filter array (CFA), an
19 infrared cut filter, an isolation feature, and the like. Additionally, such devices can
20 have light absorbing properties and elements as has been disclosed in U.S. Patent
21 Application No. 12/885,158, filed on September 17, 2010 which is incorporated by
22 reference in its entirety.

23 As has been described, a TOF pixel can have an on-pixel optical narrow band
24 pass filter. The narrow band pass filter design can match the modulated light source
25 (either LED or laser) emission spectrum and may significantly reduce unwanted
26 ambient light that can further increase the signal to noise ratio of modulated infrared
27 light. Another benefit of increased infrared QE is the possibility of high frame rate
28 operation for high speed 3D image capture. An integrated infrared cut filter can allow
29 a high quality visible image with high fidelity color rendering. Integrating an infrared
30 cut filter onto the sensor chip can also reduce the total system cost of a camera
31 module (due to the removal of typical IR filter glass) and reduce module profile (good
32 for mobile applications).

33 The thickness and responsivity of a QE enhanced imager can have significant
34 impact on a TOF pixel operation, due to the increased speed and detection. The

1 increased QE will contribute to higher image signal to noise, which will greatly
2 reduce depth error. Further, increased QE on a silicon material having a thickness of
3 less than about 100 μm can allow the pixel to reduce the diffusion component of
4 signal so that the charge collection and transfer speed can be increased, which is good
5 for TOF pixel operation. In general, the photo-generated carrier created inside pixel
6 will depend on two mechanisms for collection: drift and diffusion. For light having
7 shorter wavelengths, most of the charge carriers will be generated in a shallow region
8 of the device and within the depletion region of the diode. Those carriers can be
9 collected relatively fast, via drift. For infrared light, the majority of photo carriers are
10 be generated deeper inside the silicon material. To achieve higher QE, normally thick
11 silicon layers are used. As such, most of the charge carriers carrier will be generated
12 outside the diode's depletion region and will depend on diffusion to be collected. For
13 a 3D TOF pixel, however, a fast sampling of photo generated charge is beneficial.

14 For the devices according to aspects of the present disclosure, a high QE can
15 be achieved within a thin (i.e. less than 100 μm) layer of silicon material. Therefore,
16 substantially all of the carriers generated can be collected via drift mechanism. This
17 allows a fast charge collection and transfer.

18 FIG. 11 shows an exemplary schematic for a six-transistor (6-T) architecture
19 which will allow global shutter operation according to one aspect of the present
20 disclosure. The pixel can include a photodiode (PD), a global reset (Global_RST), a
21 global transfer gate (Global_TX), a storage node, a transfer gate (TX1), reset (RST),
22 source follower (SF), floating diffusion (FD), row select transistor (RS), power supply
23 (V_{aapix}) and voltage out (V_{out}). Due to the use of extra transfer gate and storage
24 node, correlated-double-sampling (CDS) is allowed. Therefore, the read noise should
25 be able to match typical CMOS 4T pixels.

26 FIG. 12 shows an exemplary schematic of a 3D TOF pixel according to one
27 aspect of the present disclosure. The 3D TOF pixel can have 11 transistors for
28 accomplishing the depth measurement of the target. In this embodiment the 3D pixel
29 can comprise a photodiode (PD), a global reset (Global_RST), a first global transfer
30 gate (Global_TX1), a first storage node, a first transfer gate (TX1), a first reset
31 (RST1), a first source follower (SF1), a first floating diffusion (FD1), a first row
32 select transistor (RS1), a second global transfer gate (Global_TX2), a second storage
33 node, a second transfer gate (TX2), a second reset (RST2), a second source follower
34 (SF2), a second floating diffusion (FD2), a second row select transistor (RS2), power

1 supply (Vaapix) and voltage out (Vout). Other transistors can be included in the 3D
2 architecture and should be considered within the scope of the present invention. The
3 specific embodiment with 11 transistors can reduce motion artifacts due to the global
4 shutter operation, thereby giving more accurate measurements.

5 As has been described, a photodiode array can be used in various
6 communication applications. For example, the array can be used to detect pulsed
7 optical signals. Such pulsed signals can be used to carry data at high speeds. By
8 utilizing photodiodes having fast response times, very short pulse widths can be
9 detected, thus increasing the speed of data communication. In one aspect, for
10 example, the pulsed optical signals can have pulse widths from about 1 femtosecond
11 to about 1 microsecond. In another aspect, the at least two photodiodes are operable
12 to transmit data at a rate of at least 1 Gbps. In yet another aspect, the at least two
13 photodiodes are operable to transmit data at a rate of at least 2 Gbps.

14 In one aspect, an array of four photodiodes forming a quad photodiode array
15 (quad array) is provided. A quad array can be used in a variety of applications,
16 including communications, laser range finding, laser alignment, and the like. In some
17 aspects, the four photodiodes can have uniform photo response, or in other words, are
18 selective to the same wavelength range. It can also be beneficial to have little to no
19 electrical and/or optical cross talk between the photodiodes in the quad array. For this
20 reason, isolation structures can be disposed between the photodiodes can be
21 beneficial. Some application can also benefit from the high speed operation of the
22 photodiodes according to aspects of the present disclosure. FIGs. 13 and 14 show
23 exemplary configurations of quad arrays. FIG. 13 shows a quad array of four
24 photodiodes 130 including a silicon material 132 and a doped region 134. The doped
25 region is made up of multiple doped regions forming a junction. An isolation
26 structure 136 is located between the photodiodes to electrically and/or optically
27 isolate the photodiodes against undesirable cross talk. FIG. 14 shows a similar
28 arrangement in a circular configuration. This array includes four photodiodes 140
29 including a silicon material 142, a doped region 144, and an isolation structure 146.
30 In addition to those materials discussed herein, the isolation structure can include a
31 dielectric material for electrical isolation and a metal material for a high reflectivity to
32 the light incidence on the walls of the trench. In one aspect, the sides and surfaces of
33 the diode between the isolation regions can be more heavily doped than the silicon
34 material in order to pin the Fermi level at the band edge and reduce the dark current.

1 The photodiode can also include a buried layer of opposite conductivity type to the
2 silicon material. In some aspects, the doping of the silicon material can be kept low
3 and the thickness can be thinned to provide a fast response time to the optical signal.
4 A textured region can function to backside scatter light that passes through the silicon
5 material, thus improving near infrared responsivity.

6 In yet another aspect, a method of increasing the speed of an optoelectronic
7 device is provided. As is shown in FIG. 15, such a method can include doping at least
8 two regions in a silicon material to form at least one junction 152 and texturing the
9 silicon material to form a textured region positioned to interact with electromagnetic
10 radiation 154. The optoelectronic device has a response time of from about 1
11 picosecond to about 5 nanoseconds and a responsivity of greater than or equal to
12 about 0.4 A/W for electromagnetic radiation having at least one wavelength from
13 about 800 nm to about 1200 nm.

14 Of course, it is to be understood that the above-described arrangements are
15 only illustrative of the application of the principles of the present invention.
16 Numerous modifications and alternative arrangements may be devised by those
17 skilled in the art without departing from the spirit and scope of the present invention
18 and the appended claims are intended to cover such modifications and arrangements.
19 Thus, while the present invention has been described above with particularity and
20 detail in connection with what is presently deemed to be the most practical and
21 preferred embodiments of the invention, it will be apparent to those of ordinary skill
22 in the art that numerous modifications, including, but not limited to, variations in size,
23 materials, shape, form, function and manner of operation, assembly and use may be
24 made without departing from the principles and concepts set forth herein.

1 **CLAIMS**

2
3 What is claimed is:

- 4
- 5 1. A high speed optoelectronic device, comprising:
- 6 a silicon material having an incident light surface;
- 7 a first doped region and a second doped region forming a semiconductive
- 8 junction in the silicon material; and
- 9 a textured region coupled to the silicon material and positioned to interact with
- 10 electromagnetic radiation;
- 11 wherein the optoelectronic device has a response time of from about 1
- 12 picosecond to about 5 nanoseconds and a responsivity of greater than or equal to
- 13 about 0.4 A/W for electromagnetic radiation having at least one wavelength from
- 14 about 800 nm to about 1200 nm.
- 15
- 16 2. The device of claim 1, wherein the silicon material has a thickness of from about 1
- 17 μm to about 100 μm.
- 18
- 19 3. The device of claim 1, wherein the optoelectronic device has a responsivity of
- 20 greater than or equal to about 0.5 A/W for electromagnetic radiation having at least
- 21 one wavelength from about 800 nm to about 1200 nm.
- 22
- 23 4. The device of claim 1, wherein the optoelectronic device has a responsivity of
- 24 greater than or equal to about 0.45 A/W for electromagnetic radiation having a
- 25 wavelength of about 850 nm.
- 26
- 27 5. The device of claim 1, wherein the optoelectronic device has a response time of
- 28 from about 1 picosecond to about 1 nanosecond.
- 29
- 30 6. The device of claim 1, wherein the first doped region has a surface area of from
- 31 about 0.1 μm² to about 32 μm².
- 32
- 33 7. The device of claim 1, wherein the optoelectronic device has a data rate greater
- 34 than or equal to about 1 Gbs.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34

8. The device of claim 1, further comprising a first contact and a second contact, wherein the first contact is opposite in voltage polarity from the second contact.

9. The device of claim 8, wherein a reverse bias is applied across the first and second contacts.

10. The device of claim 9, wherein the reverse bias is from about 0.001 V to about 20 V.

11. The device of claim 8, wherein a bias is not applied across the first and second contacts during use.

12. The device of claim 1, wherein dark current of the device during operation is from about 100 pA/cm² to about 10 nA/cm².

13. The device of claim 1, wherein maximum dark current of the device during operation is less than about 1 nA/cm².

14. The device of claim 1, wherein the textured region is positioned on an opposite side of the silicon material from the incident light surface.

15. A high speed optoelectronic device, comprising:
a silicon material having an incident light surface;
a first doped region and a second doped region forming a semiconductive junction in the silicon material; and
a textured region coupled to the silicon material and positioned to interact with electromagnetic radiation;
wherein the optoelectronic device has a response time of from about 1 picosecond to about 5 nanoseconds and a responsivity of greater than or equal to about 0.3 A/W for electromagnetic radiation having a wavelength of about 940 nm.

16. A high speed optoelectronic device, comprising:
a silicon material having an incident light surface;

1 a first doped region and a second doped region forming a semiconductive
2 junction in the silicon material; and
3 a textured region coupled to the silicon material and positioned to interact with
4 electromagnetic radiation;
5 wherein the optoelectronic device has a response time of from about 1
6 picosecond to about 5 nanoseconds and a responsivity of greater than or equal to
7 about 0.05 A/W for electromagnetic radiation having a wavelength of about 1060 nm.

8
9 17. A photodiode array, comprising

10 a silicon material having an incident light surface;
11 at least two photodiodes in the silicon material, each photodiode including a
12 first doped region and a second doped region forming a junction; and
13 a textured region coupled to the silicon material and positioned to interact with
14 electromagnetic radiation;
15 wherein the photodiode array has a response time of from about 1 picosecond
16 to about 5 nanoseconds and a responsivity of greater than or equal to about 0.4 A/W
17 for electromagnetic radiation having at least one wavelength from about 800 nm to
18 about 1200 nm.

19
20 18. The array of claim `7, wherein the silicon material has a thickness of from about
21 1 μm to about 100 μm .

22
23 19. The array of claim `7, wherein the at least two photodiodes are four photodiodes
24 forming a quad array.

25
26 20. The array of claim `9, wherein the four photodiodes of the quad array are
27 selective to a single wavelength range.

28
29 21. The array of claim 17, wherein the array is an image sensor.

30
31 22. The array of claim 17, wherein the array is operable to detect a phase delay
32 between a reflected and an emitted optical signal.

- 1 23. The array of claim 17, wherein the array is operable to detect pulsed optical
2 signals.
- 3
- 4 24. The array of claim 17, wherein the at least two photodiodes are operable to
5 transmit data at a rate of at least 1 Gbps.
- 6
- 7 25. A method of increasing the speed of an optoelectronic device, comprising:
8 doping at least two regions in a silicon material to form at least one junction;
9 and
10 texturing the silicon material to form a textured region positioned to interact
11 with electromagnetic radiation;
12 wherein the optoelectronic device has a response time of from about 1
13 picosecond to about 5 nanoseconds and a responsivity of greater than or equal to
14 about 0.4 A/W for electromagnetic radiation having at least one wavelength from
15 about 800 nm to about 1200 nm.
- 16
- 17
- 18
- 19
- 20
- 21
- 22
- 23
- 24
- 25
- 26
- 27
- 28
- 29
- 30
- 31
- 32
- 33
- 34




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9

102	108	109
106	104	

FIG. 10a

102	106	108	109
106	104		
102	106	102	106
106	104	106	104

FIG. 10b

106	102	106	102
104	106	104	106
108	109	108	109
106	102	106	102
104	106	104	106
108	109	108	109

FIG. 10c




FIG. 11




FIG. 13




FIG. 14




FIG. 15