



UNITED STATES PATENT AND TRADEMARK OFFICE

UNITED STATES DEPARTMENT OF COMMERCE
United States Patent and Trademark Office
Address: COMMISSIONER FOR PATENTS
P.O. Box 1450
Alexandria, Virginia 22313-1450
www.uspto.gov

Table with 6 columns: APPLICATION NUMBER, FILING or 371(c) DATE, GRP ART UNIT, FIL FEE REC'D, ATTY. DOCKET NO, TOT CLAIMS, IND CLAIMS. Row 1: 62/365,329, 07/21/2016, 260, PW277E (83043.1061)

CONFIRMATION NO. 1021

FILING RECEIPT

109682
Holland & Hart LLP/Qualcomm
P.O. Box 11583
Salt Lake City, UT 84147



Date Mailed: 08/05/2016

Receipt is acknowledged of this provisional patent application. It will not be examined for patentability and will become abandoned not later than twelve months after its filing date. Any correspondence concerning the application must include the following identification information: the U.S. APPLICATION NUMBER, FILING DATE, NAME OF APPLICANT, and TITLE OF INVENTION. Fees transmitted by check or draft are subject to collection. Please verify the accuracy of the data presented on this receipt. If an error is noted on this Filing Receipt, please submit a written request for a Filing Receipt Correction. Please provide a copy of this Filing Receipt with the changes noted thereon. If you received a "Notice to File Missing Parts" for this application, please submit any corrections to this Filing Receipt with your reply to the Notice. When the USPTO processes the reply to the Notice, the USPTO will generate another Filing Receipt incorporating the requested corrections

Inventor(s)

Arjun Bharadwaj, Poway, CA;
Bin Tian, San Diego, CA;
Lochan Verma, San Diego, CA;
Sameer Vermani, San Diego, CA;

Applicant(s)

QUALCOMM Incorporated, San Diego, CA;

Power of Attorney: The patent practitioners associated with Customer Number 109682

Permission to Access Application via Priority Document Exchange: Yes

Permission to Access Search Results: Yes

Applicant may provide or rescind an authorization for access using Form PTO/SB/39 or Form PTO/SB/69 as appropriate.

If Required, Foreign Filing License Granted: 08/04/2016

The country code and number of your priority application, to be used for filing abroad under the Paris Convention, is US 62/365,329

Projected Publication Date: None, application is not eligible for pre-grant publication

Non-Publication Request: No

Early Publication Request: No

**Title**

PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

**Statement under 37 CFR 1.55 or 1.78 for AIA (First Inventor to File) Transition Applications: No**

**PROTECTING YOUR INVENTION OUTSIDE THE UNITED STATES**

Since the rights granted by a U.S. patent extend only throughout the territory of the United States and have no effect in a foreign country, an inventor who wishes patent protection in another country must apply for a patent in a specific country or in regional patent offices. Applicants may wish to consider the filing of an international application under the Patent Cooperation Treaty (PCT). An international (PCT) application generally has the same effect as a regular national patent application in each PCT-member country. The PCT process **simplifies** the filing of patent applications on the same invention in member countries, but **does not result** in a grant of "an international patent" and does not eliminate the need of applicants to file additional documents and fees in countries where patent protection is desired.

Almost every country has its own patent law, and a person desiring a patent in a particular country must make an application for patent in that country in accordance with its particular laws. Since the laws of many countries differ in various respects from the patent law of the United States, applicants are advised to seek guidance from specific foreign countries to ensure that patent rights are not lost prematurely.

Applicants also are advised that in the case of inventions made in the United States, the Director of the USPTO must issue a license before applicants can apply for a patent in a foreign country. The filing of a U.S. patent application serves as a request for a foreign filing license. The application's filing receipt contains further information and guidance as to the status of applicant's license for foreign filing.

Applicants may wish to consult the USPTO booklet, "General Information Concerning Patents" (specifically, the section entitled "Treaties and Foreign Patents") for more information on timeframes and deadlines for filing foreign patent applications. The guide is available either by contacting the USPTO Contact Center at 800-786-9199, or it can be viewed on the USPTO website at <http://www.uspto.gov/web/offices/pac/doc/general/index.html>.

For information on preventing theft of your intellectual property (patents, trademarks and copyrights), you may wish to consult the U.S. Government website, <http://www.stopfakes.gov>. Part of a Department of Commerce initiative, this website includes self-help "toolkits" giving innovators guidance on how to protect intellectual property in specific countries such as China, Korea and Mexico. For questions regarding patent enforcement issues, applicants may call the U.S. Government hotline at 1-866-999-HALT (1-866-999-4258).

**LICENSE FOR FOREIGN FILING UNDER**

**Title 35, United States Code, Section 184**

**Title 37, Code of Federal Regulations, 5.11 & 5.15**

**GRANTED**

The applicant has been granted a license under 35 U.S.C. 184, if the phrase "IF REQUIRED, FOREIGN FILING LICENSE GRANTED" followed by a date appears on this form. Such licenses are issued in all applications where the conditions for issuance of a license have been met, regardless of whether or not a license may be required as set forth in 37 CFR 5.15. The scope and limitations of this license are set forth in 37 CFR 5.15(a) unless an earlier

license has been issued under 37 CFR 5.15(b). The license is subject to revocation upon written notification. The date indicated is the effective date of the license, unless an earlier license of similar scope has been granted under 37 CFR 5.13 or 5.14.

This license is to be retained by the licensee and may be used at any time on or after the effective date thereof unless it is revoked. This license is automatically transferred to any related applications(s) filed under 37 CFR 1.53(d). This license is not retroactive.

The grant of a license does not in any way lessen the responsibility of a licensee for the security of the subject matter as imposed by any Government contract or the provisions of existing laws relating to espionage and the national security or the export of technical data. Licensees should apprise themselves of current regulations especially with respect to certain countries, of other agencies, particularly the Office of Defense Trade Controls, Department of State (with respect to Arms, Munitions and Implements of War (22 CFR 121-128)); the Bureau of Industry and Security, Department of Commerce (15 CFR parts 730-774); the Office of Foreign Assets Control, Department of Treasury (31 CFR Parts 500+) and the Department of Energy.

**NOT GRANTED**

No license under 35 U.S.C. 184 has been granted at this time, if the phrase "IF REQUIRED, FOREIGN FILING LICENSE GRANTED" DOES NOT appear on this form. Applicant may still petition for a license under 37 CFR 5.12, if a license is desired before the expiration of 6 months from the filing date of the application. If 6 months has lapsed from the filing date of this application and the licensee has not received any indication of a secrecy order under 35 U.S.C. 181, the licensee may foreign file the application pursuant to 37 CFR 5.15(b).

---

**SelectUSA**

The United States represents the largest, most dynamic marketplace in the world and is an unparalleled location for business investment, innovation, and commercialization of new technologies. The U.S. offers tremendous resources and advantages for those who invest and manufacture goods here. Through SelectUSA, our nation works to promote and facilitate business investment. SelectUSA provides information assistance to the international investor community; serves as an ombudsman for existing and potential investors; advocates on behalf of U.S. cities, states, and regions competing for global investment; and counsels U.S. economic development organizations on investment attraction best practices. To learn more about why the United States is the best country in the world to develop technology, manufacture products, deliver services, and grow your business, visit <http://www.SelectUSA.gov> or call +1-202-482-6800.

## **PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS**

### **BACKGROUND**

#### **FIELD OF THE DISCLOSURE**

**[0001]** The present disclosure, for example, relates to wireless communication systems, and more particularly to design aspects of high efficiency wireless local area networks (WLANs).

#### **DESCRIPTION OF RELATED ART**

**[0002]** Wireless communications systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be multiple-access systems capable of supporting communication with multiple users by sharing the available system resources (*e.g.*, time, frequency, and power). A wireless network, for example a Wireless Local Area Network (WLAN), such as a Wi-Fi network (IEEE 802.11) may include an access point (AP) that may communicate with one or more stations (STAs) or mobile devices. The AP may be coupled to a network, such as the Internet, and enable a mobile device to communicate via the network (and/or communicate with other devices coupled to the access point).

**[0003]** A first signaling field and/or a second signaling field of a preamble used for transmitting frames in high efficiency (HE) wireless local area networks (WLANs) can be modified to improve performance and efficiency of HE WLANs.

### **SUMMARY**

**[0004]** Methods, apparatuses, and computer readable media for supporting preamble design aspects of high efficiency wireless local area networks (WLANs) are disclosed.

**[0005]** According to aspects of a first method, a transmitter, for example an AP or station, identifies a resource unit (RU) configuration for a wireless local area network (WLAN) data field of a single user (SU) transmission frame that has a fixed bandwidth. The transmitter generates a RU indicator in a WLAN signaling field of a preamble of the SU transmission

frame, the RU indicator identifying a RU size and a RU location within the WLAN data field. The transmitter then transmits the SU transmission frame.

**[0006]** An apparatus for wireless communication is described. The apparatus may include means for identifying a resource unit (RU) configuration for a WLAN data field of a single user (SU) transmission frame that has a fixed bandwidth, means for generating a RU indicator in a WLAN signaling field of a preamble of the SU transmission frame, the RU indicator identifying a RU size and a RU location within the WLAN data field, and means for transmitting the SU transmission frame.

**[0007]** A further apparatus for wireless communication is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory and operable, when executed by the processor, to cause the apparatus to identify a resource unit (RU) configuration for a WLAN data field of a single user (SU) transmission frame that has a fixed bandwidth, generate a RU indicator in a WLAN signaling field of a preamble of the SU transmission frame, the RU indicator identifying a RU size and a RU location within the WLAN data field, and transmit the SU transmission frame.

**[0008]** A non-transitory computer-readable medium storing code for wireless communication is described. The code may include instructions executable to identify a resource unit (RU) configuration for a WLAN data field of a single user (SU) transmission frame that has a fixed bandwidth, generate a RU indicator in a WLAN signaling field of a preamble of the SU transmission frame, the RU indicator identifying a RU size and a RU location within the WLAN data field, and transmit the SU transmission frame.

**[0009]** According to aspects of a second method, an access point (AP) identifies a first indicator identifying a number of multi-user multiple input multiple output (MU-MIMO) stations associated with a first resource unit (RU) in a first content channel of a transmission frame. The AP also generates a first common portion of a wireless local area network (WLAN) signaling field in the first content channel of the transmission frame, wherein the first common portion includes the first indicator. The AP identifies a second indicator identifying an absence of MU-MIMO stations associated with a second resource unit (RU) in a second content channel of the transmission frame. The AP generates a second common portion of the WLAN signaling field in the second content channel of the transmission frame,

wherein the second common portion includes the second indicator. The AP then transmits the transmission frame that includes the WLAN signaling field.

**[0010]** An apparatus for wireless communication is described. The apparatus may include means for identifying a first indicator identifying a number of multi-user multiple input multiple output (MU-MIMO) stations associated with a first resource unit (RU) in a first content channel of a transmission frame, means for generating a first common portion of a WLAN signaling field in the first content channel of the transmission frame, wherein the first common portion includes the first indicator, means for identifying a second indicator identifying an absence of MU-MIMO stations associated with a second resource unit (RU) in a second content channel of the transmission frame, means for generating a second common portion of the WLAN signaling field in the second content channel of the transmission frame, wherein the second common portion includes the second indicator, and means for transmitting the transmission frame that includes the WLAN signaling field.

**[0011]** A further apparatus for wireless communication is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory and operable, when executed by the processor, to cause the apparatus to identify a first indicator identifying a number of multi-user multiple input multiple output (MU-MIMO) stations associated with a first resource unit (RU) in a first content channel of a transmission frame, generate a first common portion of a WLAN signaling field in the first content channel of the transmission frame, wherein the first common portion includes the first indicator, identify a second indicator identifying an absence of MU-MIMO stations associated with a second resource unit (RU) in a second content channel of the transmission frame, generate a second common portion of the WLAN signaling field in the second content channel of the transmission frame, wherein the second common portion includes the second indicator, and transmit the transmission frame that includes the WLAN signaling field.

**[0012]** A non-transitory computer-readable medium storing code for wireless communication is described. The code may include instructions executable to identify a first indicator identifying a number of multi-user multiple input multiple output (MU-MIMO) stations associated with a first resource unit (RU) in a first content channel of a transmission frame, generate a first common portion of a WLAN signaling field in the first content channel

of the transmission frame, wherein the first common portion includes the first indicator, identify a second indicator identifying an absence of MU-MIMO stations associated with a second resource unit (RU) in a second content channel of the transmission frame, generate a second common portion of the WLAN signaling field in the second content channel of the transmission frame, wherein the second common portion includes the second indicator, and transmit the transmission frame that includes the WLAN signaling field.

**[0013]** According to aspects of a third method, a first station receives a transmission frame that includes a wireless local area network (WLAN) signaling field decodable by a plurality of stations. The first station identifies, in a station-specific portion of the WLAN signaling field, an order for a plurality of station-specific information blocks associated with the plurality of stations. The station then determines a number of spatial streams allocated to the first station based at least in part on the identified order for the plurality of station-specific information blocks.

**[0014]** An apparatus for wireless communication is described. The apparatus may include means for receiving, at a first station, a transmission frame that includes a WLAN signaling field decodable by a plurality of stations, means for identifying, in a station-specific portion of the WLAN signaling field, an order for a plurality of station-specific information blocks associated with the plurality of stations, and means for determining a number of spatial streams allocated to the first station based at least in part on the identified order for the plurality of station-specific information blocks.

**[0015]** A further apparatus for wireless communication is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory and operable, when executed by the processor, to cause the apparatus to receive, at a first station, a transmission frame that includes a WLAN signaling field decodable by a plurality of stations, identify, in a station-specific portion of the WLAN signaling field, an order for a plurality of station-specific information blocks associated with the plurality of stations, and determine a number of spatial streams allocated to the first station based at least in part on the identified order for the plurality of station-specific information blocks.

**[0016]** A non-transitory computer-readable medium storing code for wireless communication is described. The code may include instructions executable to receive, at a

first station, a transmission frame that includes a WLAN signaling field decodable by a plurality of stations, identify, in a station-specific portion of the WLAN signaling field, an order for a plurality of station-specific information blocks associated with the plurality of stations, and determine a number of spatial streams allocated to the first station based at least in part on the identified order for the plurality of station-specific information blocks.

**[0017]** According to aspects of a fourth method, a transmitter, for example an AP or station, receives a transmission frame associated with a plurality of channels, the transmission frame including a wireless local area network (WLAN) signaling field. The transmitter identifies a first number of stations associated with the WLAN signaling field for a first channel of the plurality of channels. The transmitter identifies a second number of stations associated with the WLAN signaling field for a second channel of the plurality of channels. The transmitter then determines whether a data portion of the transmission frame contains multi-user multiple input multiple output (MU-MIMO) content based at least in part on the identified first number of stations and the identified second number of stations.

**[0018]** An apparatus for wireless communication is described. The apparatus may include means for receiving a transmission frame associated with a plurality of channels, the transmission frame including a WLAN signaling field, means for identifying a first number of stations associated with the WLAN signaling field for a first channel of the plurality of channels, means for identifying a second number of stations associated with the WLAN signaling field for a second channel of the plurality of channels, and means for determining whether a data portion of the transmission frame contains multi-user multiple input multiple output (MU-MIMO) content based at least in part on the identified first number of stations and the identified second number of stations.

**[0019]** A further apparatus for wireless communication is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory and operable, when executed by the processor, to cause the apparatus to receive a transmission frame associated with a plurality of channels, the transmission frame including a WLAN signaling field, identify a first number of stations associated with the WLAN signaling field for a first channel of the plurality of channels, identify a second number of stations associated with the WLAN signaling field for a second channel of the plurality of channels, and determine whether a data portion of the transmission

frame contains multi-user multiple input multiple output (MU-MIMO) content based at least in part on the identified first number of stations and the identified second number of stations.

**[0020]** A non-transitory computer-readable medium storing code for wireless communication is described. The code may include instructions executable to receive a transmission frame associated with a plurality of channels, the transmission frame including a WLAN signaling field, identify a first number of stations associated with the WLAN signaling field for a first channel of the plurality of channels, identify a second number of stations associated with the WLAN signaling field for a second channel of the plurality of channels, and determine whether a data portion of the transmission frame contains multi-user multiple input multiple output (MU-MIMO) content based at least in part on the identified first number of stations and the identified second number of stations.

**[0021]** According to aspects of a fifth method, a transmitter, for example an AP or station, generates an indication that a first channel of a plurality of channels associated with a transmission frame has been punctured, the transmission frame including a wireless local area network (WLAN) signaling field. The transmitter identifies information associated with the WLAN signaling field corresponding to the punctured first channel. The transmitter then transmits the indication that the first channel has been punctured and the information associated with the WLAN signaling field in a second channel of the plurality of channels.

**[0022]** An apparatus for wireless communication is described. The apparatus may include means for generating an indication that a first channel of a plurality of channels associated with a transmission frame has been punctured, the transmission frame including a WLAN signaling field, means for identifying information associated with the WLAN signaling field corresponding to the punctured first channel, and means for transmitting the indication that the first channel has been punctured and the information associated with the WLAN signaling field in a second channel of the plurality of channels.

**[0023]** A further apparatus for wireless communication is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory and operable, when executed by the processor, to cause the apparatus to generate an indication that a first channel of a plurality of channels associated with a transmission frame has been punctured, the transmission frame including a WLAN signaling field, identify information associated with the WLAN signaling field corresponding

to the punctured first channel, and transmit the indication that the first channel has been punctured and the information associated with the WLAN signaling field in a second channel of the plurality of channels.

**[0024]** A non-transitory computer-readable medium storing code for wireless communication is described. The code may include instructions executable to generate an indication that a first channel of a plurality of channels associated with a transmission frame has been punctured, the transmission frame including a WLAN signaling field, identify information associated with the WLAN signaling field corresponding to the punctured first channel, and transmit the indication that the first channel has been punctured and the information associated with the WLAN signaling field in a second channel of the plurality of channels.

**[0025]** In some examples of the method, apparatus, or non-transitory computer-readable medium described above, the second WLAN signaling field of the transmission frame comprises a bandwidth field indicating both a bandwidth associated with the transmission frame and a location of the second channel within the plurality of channels.

**[0026]** According to aspects of another method, the transmitter identifies a bandwidth associated with a transmission frame, identifies a location for one or more content channels within the bandwidth, and transmits the transmission frame including a WLAN signaling field indicating both the bandwidth and the location for the one or more content channels within the bandwidth of the transmission frame.

**[0027]** An apparatus for wireless communication is described. The apparatus may include means for identifying a bandwidth associated with a transmission frame, means for identifying a location for one or more content channels within the bandwidth, and means for transmitting the transmission frame including a WLAN signaling field indicating both the bandwidth and the location for the one or more content channels within the bandwidth of the transmission frame.

**[0028]** A further apparatus for wireless communication is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory and operable, when executed by the processor, to cause the apparatus to identify a bandwidth associated with a transmission frame, identify a location for

one or more content channels within the bandwidth, and transmit the transmission frame including a WLAN signaling field indicating both the bandwidth and the location for the one or more content channels within the bandwidth of the transmission frame.

**[0029]** A non-transitory computer-readable medium storing code for wireless communication is described. The code may include instructions executable to identify a bandwidth associated with a transmission frame, identify a location for one or more content channels within the bandwidth, and transmit the transmission frame including a WLAN signaling field indicating both the bandwidth and the location for the one or more content channels within the bandwidth of the transmission frame.

**[0030]** The foregoing has outlined rather broadly the features and technical advantages of examples according to the disclosure in order that the detailed description that follows may be better understood. Additional features and advantages will be described hereinafter. The conception and specific examples disclosed may be readily utilized as a basis for modifying or designing other structures for carrying out the same purposes of the present disclosure. Such equivalent constructions do not depart from the scope of the appended claims. Characteristics of the concepts disclosed herein, both their organization and method of operation, together with associated advantages will be better understood from the following description when considered in connection with the accompanying figures. Each of the figures is provided for the purpose of illustration and description only, and not as a definition of the limits of the claims.

#### BRIEF DESCRIPTION OF THE DRAWINGS

**[0031]** A further understanding of the nature and advantages of the present invention may be realized by reference to the following drawings. In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a dash and a second label that distinguishes among the similar components. If only the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label.

**[0032]** FIG. 1 illustrates an example of a wireless communications system that supports preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0033]** FIG. 2 shows an example of a WLAN protocol data unit (PDU) (*e.g.*, a physical layer convergence PDU (PPDU)) preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0034]** FIG. 3 illustrates an example of aspects of a WLAN protocol data unit for preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0035]** FIGS. 4A, 4B, and 4C illustrate examples of aspects of a WLAN protocol data unit for preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0036]** FIG. 5 illustrates an example of aspects of a WLAN protocol data unit for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0037]** FIG. 6 illustrates an example of aspects of a portion of a lookup table for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0038]** FIG. 7 illustrates an example of aspects of a spatial configuration lookup table for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0039]** FIG. 8 illustrates an example of user specific sub-fields split between two HE-SIG-B content channels, in accordance with various aspects of the present disclosure; and

**[0040]** FIGS. 9A through 9C show block diagrams 900-a through 900-c of example preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0041]** FIG. 10 illustrates an HE-SIG-B field for a primary HE-SIG-B content channel and an HE-SIG-B field for a secondary HE-SIG-B content channel in accordance with various aspects of the present disclosure;

**[0042] FIGS. 11A and 11B** illustrate HE-SIG-B transmission formats that support preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0043] FIGS. 11C and 11D** illustrates examples of channels for contiguous and non-contiguous channel bonding modes, in accordance with various aspects of the present disclosure;

**[0044] FIG. 12** illustrates RU allocation table entries for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0045] FIGS. 13A and 13B** show block diagrams of an example device for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0046] FIGS. 14A through 14D** show a first HE-SIG-A field contents for a HE SU PPDU and HE extended range SU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0047] FIGS. 15A through 15C** show a first HE-SIG-A field contents for a HE MU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0048] FIGS. 16A through 16B** show a first HE-SIG-A field contents for a HE trigger-based PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0049] FIGS. 17A through 17D** show a second HE-SIG-A field contents for a HE SU PPDU and HE extended range SU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0050] FIGS. 18A through 18C** show a second HE-SIG-A field contents for a HE MU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0051] FIGS. 19A through 19B** show a second HE-SIG-A field contents for a HE trigger-based PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0052]** FIGs. 20A through 20C show a HE-SIG-A field contents for a HE SU PPDU and HE Extended Range SU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure;

**[0053]** FIGs. 21A through 21C show a HE-SIG-A field contents for a HE MU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure; and

**[0054]** FIGs. 22A through 22B show a HE-SIG-A field contents for a HE Trigger-based PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure.

#### DETAILED DESCRIPTION

**[0055]** In accordance with various aspects of the present disclosure, a transmitter, for example an AP or station, identifies a resource unit (RU) configuration for a wireless local area network (WLAN) data field of a single user (SU) transmission frame that has a fixed bandwidth. The transmitter generates a RU indicator in a WLAN signaling field of a preamble of the SU transmission frame, the RU indicator identifying a RU size and a RU location within the WLAN data field. The transmitter then transmits the SU transmission frame.

**[0056]** In accordance with various aspects of the present disclosure, an access point (AP) identifies a first indicator identifying a number of multi-user multiple input multiple output (MU-MIMO) stations associated with a first resource unit (RU) in a first content channel of a transmission frame. The AP also generates a first common portion of a wireless local area network (WLAN) signaling field in the first content channel of the transmission frame, wherein the first common portion includes the first indicator. The AP identifies a second indicator identifying an absence of MU-MIMO stations associated with a second resource unit (RU) in a second content channel of the transmission frame. The AP generates a second common portion of the WLAN signaling field in the second content channel of the transmission frame, wherein the second common portion includes the second indicator. The AP then transmits the transmission frame that includes the WLAN signaling field.

**[0057]** In accordance with various aspects of the present disclosure, a first station receives a transmission frame that includes a wireless local area network (WLAN) signaling field decodable by a plurality of stations. The first station identifies, in a station-specific portion of the WLAN signaling field, an order for a plurality of station-specific information blocks associated with the plurality of stations. The station then determines a number of spatial streams allocated to the first station based at least in part on the identified order for the plurality of station-specific information blocks.

**[0058]** In accordance with various aspects of the present disclosure, a transmitter, for example an AP or station, receives a transmission frame associated with a plurality of channels, the transmission frame including a wireless local area network (WLAN) signaling field. The transmitter identifies a first number of stations associated with the WLAN signaling field for a first channel of the plurality of channels. The transmitter identifies a second number of stations associated with the WLAN signaling field for a second channel of the plurality of channels. The transmitter then determines whether a data portion of the transmission frame contains multi-user multiple input multiple output (MU-MIMO) content based at least in part on the identified first number of stations and the identified second number of stations.

**[0059]** In accordance with various aspects of the present disclosure, a transmitter, for example an AP or station, generates an indication that a first channel of a plurality of channels associated with a transmission frame has been punctured, the transmission frame including a wireless local area network (WLAN) signaling field. The transmitter identifies information associated with the WLAN signaling field corresponding to the punctured first channel. The transmitter then transmits the indication that the first channel has been punctured and the information associated with the WLAN signaling field in a second channel of the plurality of channels.

**[0060]** These and other aspects of the disclosure are further illustrated by and described with reference to apparatus diagrams, system diagrams, and flowcharts.

**[0061]** **FIG. 1** illustrates an example of a wireless communications system 100 that supports preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. For simplicity, the wireless communications system 100 is referred to as WLAN 100 in the following discussion.

**[0062]** The WLAN 100 includes an access point (AP) 105 and stations (STAs) 110 labeled as STA\_1 through STA\_7. The STAs 110 can be mobile handsets, tablet computers, personal digital assistants (PDAs), other handheld devices, netbooks, notebook computers, tablet computers, laptops, desktop computers, display devices (*e.g.*, TVs, computer monitors, *etc.*), printers, *etc.* While only one AP 105 is illustrated, the WLAN 100 can have multiple APs 105. STAs 110, can also be referred to as a mobile stations (MS), mobile devices, access terminals (ATs), user equipment (UEs), subscriber stations (SSs), or subscriber units. The STAs 110 associate and communicate with the AP 105 via a communication link 115. Each AP 105 has a coverage area 125 such that STAs 110 within that area are within range of the AP 105. The STAs 110 are dispersed throughout the coverage area 125. Each STA 110 is stationary, mobile, or a combination thereof.

**[0063]** Although not shown in FIG. 1, a STA 110 can be covered by more than one AP 105 and can therefore associate with multiple APs 105 at different times. A single AP 105 and an associated set of STAs 110 is referred to as a basic service set (BSS). An extended service set (ESS) is a set of connected BSSs. A distribution system (DS) (not shown) is used to connect APs 105 in an extended service set. A coverage area 125 for an AP 105 can be divided into sectors making up only a portion of the coverage area (not shown). The WLAN 100 includes APs 105 of different types (*e.g.*, metropolitan area, home network, *etc.*), with varying sizes of coverage areas and overlapping coverage areas for different technologies. Although not shown, other devices can communicate with the AP 105.

**[0064]** While the STAs 110 are capable of communicating with each other through the AP 105 using communication links 115, STAs 110 can also communicate directly with each other via direct wireless communication links 120. Direct wireless communication links can occur between STAs 110 regardless of whether any of the STAs is connected to an AP 105. Examples of direct wireless communication links 120 include Wi-Fi Direct connections, connections established by using a Wi-Fi Tunneled Direct Link Setup (TDLS) link, and other peer-to-peer (P2P) group connections.

**[0065]** The STAs 110 and APs 105 shown in FIG. 1 communicate according to the WLAN radio and baseband protocol including physical (PHY) and medium access control (MAC) layers from IEEE 802.11, and its various versions including, but not limited to, 802.11b, 802.11g, 802.11a, 802.11n, 802.11ac, 802.11ad, 802.11ah, 802.11z, 802.11ax, *etc.*

**[0066]** Transmissions to/from STAs 110 and APs 105 oftentimes include control information within a header that is transmitted prior to data transmissions. The information provided in a header is used by a device to decode the subsequent data. High efficiency (HE) WLAN preambles can be used to schedule multiple devices, such as STAs 110, for single-user simultaneous transmission (*e.g.*, single-user orthogonal frequency division multiple access (SU-OFDMA)) and/or MU-MIMO transmissions (*e.g.*, multiple input multiple output MU-MIMO). In one example an HE WLAN signaling field is used to signal a resource allocation pattern to multiple receiving STAs 110. The HE WLAN signaling field includes a common user field that is decodable by multiple STAs 110, the common user field including a resource allocation field. The resource allocation field indicates resource unit distributions to the multiple STAs 110 and indicates which resource units in a resource unit distribution correspond to MU-MIMO transmissions and which resource units correspond to OFDMA single-user transmissions. The HE WLAN signaling field also includes, subsequent to the common user field, dedicated user fields that are assigned to certain STAs 110. The order in which the dedicated user fields are generated corresponds to the allocated resource units (*e.g.*, the first dedicated user field corresponds to the first allocated resource unit). The HE WLAN signaling field is transmitted with a WLAN preamble to the multiple STAs 110.

**[0067]** FIG. 2 shows an example of a WLAN protocol data unit (PDU) 200 (*e.g.*, a physical layer convergence PDU (PPDU)) preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. WLAN PDU 200 illustrates aspects of a transmission between a STA 110 and an AP 105, as described above with reference to FIG. 1.

**[0068]** In this example, the WLAN protocol data unit 200 includes a physical (PHY) layer header 205 and a data field 220 (*e.g.*, a MAC protocol data unit (MPDU) or physical layer service data unit (PSDU)). The PHY layer header 205 includes a legacy WLAN preamble 210 and a high efficiency WLAN preamble 215. The preambles and data field are transmitted in the following order: legacy WLAN preamble 210, high efficiency WLAN preamble 215, data field 220.

**[0069]** The WLAN protocol data unit 200 is transmitted over a radio frequency spectrum band, which in some examples may include a plurality of sub-bands. In some examples, the radio frequency spectrum band may have a bandwidth of 80 MHz, and each of the sub-bands

may have a bandwidth of 20 MHz. The legacy WLAN preamble 210 includes legacy short training field (STF) (L-STF) information, legacy long training field (LTF) (L-LTF) information, and legacy signaling (L-SIG) information. When the radio frequency spectrum band includes multiple sub-bands, the L-STF, L-LTF, and L-SIG information is duplicated and transmitted in each of the plurality of sub-bands. The legacy preamble is used for packet detection, automatic gain control, channel estimation, *etc.* The legacy preamble is also used to maintain compatibility with legacy devices.

**[0070]** The high efficiency WLAN preamble 215 includes any of: a repeated legacy WLAN field (*e.g.*, an RL-SIG field), a first WLAN signaling field (*e.g.*, a first high efficiency WLAN signaling field such as HE-SIG-A), a second WLAN signaling field (*e.g.*, a second high efficiency WLAN signaling field such as HE-SIG-B), a WLAN STF (*e.g.*, a high efficiency WLAN STF), and at least one WLAN LTF (*e.g.*, at least one high efficiency WLAN LTF). The high efficiency WLAN preamble 215 enables an AP to simultaneously transmit to multiple stations (*e.g.*, MU-MIMO) and also enables an AP to allocate resources to multiple stations for uplink/downlink transmissions (*e.g.*, SU-OFDMA). The high efficiency WLAN preamble 215 uses a common signaling field and one or more dedicated (*e.g.*, station-specific) signaling fields to schedule resources and to indicate the scheduling to other WLAN devices. A device uses the scheduling to determine which resource units associated with the frequency spectrum utilized by data field 220 have been allocated to the device for forthcoming communications.

**[0071]** **FIG. 3** illustrates an example of aspects of a WLAN protocol data unit 300 for preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. WLAN protocol data unit 300 illustrates aspects of a transmission between a STA 110 and an AP 105, as described above with reference to FIGs. 1-2. WLAN protocol data unit 300 includes a first WLAN signaling field 305, a second WLAN signaling field 310, a high efficiency STF 315, a high efficiency LTF 320, and a data field 325. The first WLAN signaling field 305 includes an HE-SIG-A 330 that is repeated across multiple subbands. The data field 325 includes data portions 335 that have been allocated to different devices. For instance, data portion 335-a is allocated to a first device, data portion 335-b to a second device, data portion 335-c to a first group of devices, and data portion 335-d to a second group of devices.

**[0072]** The first WLAN signaling field 305 includes high efficiency WLAN signaling information usable by APs and stations other than a number of APs or stations identified to receive or transmit communications in the WLAN protocol data unit 300. The first WLAN signaling field 305 also includes information usable by the identified number of APs or stations to decode the second WLAN signaling field 310. When the radio frequency spectrum band includes a plurality of sub-bands, the information (*e.g.*, HE-SIG-A 330-a) included in the first WLAN signaling field 305 is duplicated and transmitted in each sub-band of the first WLAN signaling field 305, (*e.g.*, HE-SIG-A 330-b to 330-d).

**[0073]** The second WLAN signaling field 310 includes high efficiency WLAN signaling information usable by a number of APs or stations identified to transmit or receive communications in the WLAN protocol data unit 300. More specifically, the second WLAN signaling field 310 includes information usable by the number of APs or stations to transmit/encode or receive/decode data in the data field 220. The second WLAN signaling field 310 can be encoded separately from the first WLAN signaling field 305. The second WLAN signaling field 310 includes a common block field 340 that signals information to a group of devices, such as high efficiency STAs within range of an AP, and user blocks 345-a to 345-c that signal information specific to specific high efficiency STAs. The common block includes a resource allocation field 350 that signals to the high efficiency device how the data field 325 is partitioned amongst devices (*e.g.*, partitions the data field into resource units), which of the resource units are associated with SU-OFDMA and which are associated with MU-MIMO. Furthermore, the order of the user blocks 345 provides a link between the device associated with the user block 345 and the resource unit that has been allocated to the device. As an example, the resource allocation field 350 partitions the data field into nine regions (*e.g.*, 20MHz data region is partitioned into nine sub-regions that each span 26 tones). The STA addressed in the first user block corresponds to the first 26 tones, the second STA addressed in the second user block corresponds to the next 26 tones, *etc.* The common block may also include other fields, such as a LTF.

**[0074]** **FIGs. 4A** illustrates an example of aspects of a WLAN protocol data unit 400 for preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. WLAN protocol data unit 400 illustrates aspects of a transmission between a STA 110 and an AP 105, as described above with reference to FIGs. 1-2. WLAN protocol data

unit 400 includes a first WLAN signaling field 305-a, a high efficiency STF 315-a, a high efficiency LTF 320-a, and a data field 325-a. The first WLAN signaling field 305-a includes an HE-SIG-A 330 that is repeated across multiple subbands. The data field 325 may include data portions that have been allocated to different devices.

**[0075]** A transmission sent in the HE extended range PPDU format may be sent in environments where using a longer range transmission is desirable, *e.g.* this format may be used for communication with internet of thing (IoT) devices, sensors, *etc.* A HE extended range PPDU may also have a simpler structure and be more robust as compared to one or more other HE PPDU formats that may be used for SU transmissions. For example, a HE extended range PPDU format may use a repeated HE-SIG-A field in its preamble to provide for more robust reception. A HE extended range PPDU may also be configured to allow for the signaling of smaller resource units (RUs).

**[0076]** In contrast to a generic SU HE PPDU that may select among several different bandwidths or have a varying bandwidth (as signaled in the HE preamble), a HE extended range PPDU for SU transmissions may use a fixed bandwidth, *e.g.* 20 MHz, that may be smaller than the bandwidth available for the generic SU HE PPDU, *e.g.* where the SU HE PPDU bandwidth is 40 MHz, 80 MHz, or 160 MHz. Using a smaller, fixed bandwidth may allow for transmissions to be sent with a higher power than if the same amount of power were spread across a larger bandwidth, *e.g.* 40 MHz, 80 MHz, or 160 MHz, increasing range and robustness for the transmissions. For example, the power for the preamble of the HE extended range PPDU may be increased or boosted 3 dB above the transmission power of a generic SU HE PPDU. In some case, just the power of the preamble may be boosted by the transmitter to increase the likelihood of successful reception and decoding. In other examples, the entire PPDU may be boosted, *e.g.* by 3 dB. In other examples, the HE extended range PPDU may also boost the power of the transmitted preamble when using a larger bandwidth, such as a 40 MHz, 80 MHz, or 160 MHz bandwidth.

**[0077]** **FIG. 4B** illustrates an example 401 of aspects of a WLAN protocol data unit for preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. In the SU HE extended range PPDU in a 20 MHz band illustrated in FIG. 4B, transmissions to individual users may be allocated to one or more RUs within a tone unit of a PPDU. A size of a RU may be constrained to be one of 106 or 242 tones. In one example of

a PPDU, all 242 tones may be allocated to a user for a SU transmission as a single 242-tone RU 435. In another PPDU, 106 tones may be allocated as a first 106-tone RU 430 to a first user for SU transmission, which may be located in one of two positions. 106 tones may also be allocated as a second 106-tone RU 430 in this example. Thus, 3 different RU positions may be available for RU allocation, which may be indicated by a minimum of 2 bits of an RU allocation field 415.

**[0078]** FIG. 4C illustrates an example 402 of aspects of a WLAN protocol data unit for preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. In the SU HE extended range PPDU in a 20 MHz band illustrated in FIG. 4C, transmissions to individual users may be allocated to one or more RUs within a tone unit of a PPDU. A size of a RU may be constrained to be one of 52, 106, or 242 tones. In one example of a PPDU, all 242 tones may be allocated to a user for a SU transmission as a single 242-tone RU 450. In another PPDU, 106 tones may be allocated as a first 106-tone RU 445 to a first user for SU transmission, which may be located in one of two positions. 106 tones may also be allocated as a second 106-tone RU 445 in this example. In yet another PPDU, 52 tones may be allocated as a first 52-tone RU 440 to a first user for SU transmission, which may be located in one of four positions. 52 tones may also be allocated as a second 52-tone RU 440, as a third 52-tone RU 440, and as a fourth 52-tone RU 440 in this example, for up to 4 different users. Thus, 7 different RU positions may be available for RU allocation, which may be indicated by a minimum of 3 bits of an RU allocation field 415.

**[0079]** Thus, to maintain simplicity and reduce overhead, the number of combinations of RU sizes and locations may be limited to a maximum of 4 possibilities (for a 2 bit allocation as described above in reference to FIG. 4B) or a maximum of 8 possibilities (for a 3 bit allocation as described above in reference to FIG. 4C) for the HE extended range PPDU, meaning that 2 or 3 bits in the SIG-A field of the PPDU preamble may be used to identify, for a given RU, which of 3 or 7, respectively, possible RU sizes and locations are allocated. Where the bandwidth is fixed, for example to 20 MHz, additional bits are not needed in the SIG-A field of the PPDU preamble to identify the bandwidth used, simplifying the preamble.

**[0080]** In some examples, the RU allocation field 415 may only be used in an example where the bandwidth of PPDU is indicated by the BW field 410 to be 20 MHz. The 2 bits of the BW field 410 may be used to indicate that the PPDU uses one of four different

bandwidths. Where the BW field 410 indicates a bandwidth of 20 MHz (or another predetermined bandwidth according to other examples), the recipient of the PPDU may assume that the HE-SIG-A field 305-a contains the RU allocation field 415 following the BW field 410, and the RU allocation field 415 may be followed by an MCS field 420 and a Nsts field 425, as illustrated in FIG. 4A. Where the BW field 410 indicates a bandwidth other than 20 MHz (or the other predetermined bandwidth), for example 40 MHz, 80 MHz, or 160 MHz, then the recipient of the PPDU may assume that the HE-SIG-A field 305-a contains MCS field 420 following the BW field 410, and that the RU allocation field 415 has been omitted. Although the BW field 410, RU allocation field 415, MCS field 420, and Nsts field 425 are illustrated as falling one immediately after the other, intermediate fields may exist, or the fields may be rearranged to occur at differing positions.

**[0081]** In some instances, the HE-SIG-A field 305-a where the BW field 410 indicates a higher bandwidth, *e.g.* 40 MHz, 80 MHz, or 160 MHz, the HE-SIG-A field for the SU HE extended range PPDU may have the same format as for a non-extended range format PPDU, *e.g.* the HE-SIG-A field for the SU HE PPDU. Maintaining a similar format for the HE-SIG-A field for certain bandwidths of the SU extended range HE PPDU as the SU HE PPDU may increase simplicity of implementation.

**[0082]** Where an RU allocation field 415 in the HE-SIG-A field 305-a (*e.g.* in the case where BW field 410 indicates a 20 MHz bandwidth), then additional bits in the HE-SIG-A field may be needed. For example, the size of the HE-SIG-A field 305-a may be constrained, such that introducing bits in an RU allocation field 415 may push the size of the field over that constraint. As described above, the size of the RU allocation field 415 may be 2 bits in some examples. In such case, the size of the MCS field may be limited to 2 bits, for example where the size of the MCS field 420 in the absence of an RU allocation field 415 would otherwise be 4 bits. Thus, the MCS values indicated by the MCS field 420 may be MCS0, MCS1, MCS2, and MCS3. In an example the four MCSs may correspond to a BPSK 1/2 MCS, a QPSK 1/2 MCS, a QPSK 3/4 MCS, and a 16-QAM 1/2 MCS, respectively.

**[0083]** As also described above, the size of the RU allocation field 415 may be 3 bits in some examples. In such case, the size of the MCS field may be limited to 1 bit. Thus, in one example, the MCS values indicated by the MCS field 420 may be MCS0 and MCS1. In an example the two MCSs may correspond to a BPSK 1/2 MCS and a QPSK 1/2 MCS,

respectively. Thus, 1 bit may be used in the SIG-A field of the preamble to identify whether a first MCS or a second MCS is used to modulate and code the PPDU data; and 2 bits may be used in the SIG-A field of the preamble to identify whether a first, a second, a third, or a fourth MCS is used to modulate and code the PPDU data. In other examples, the MCS field may be omitted, such that MCS0 is used where the BW is indicated to be 20 MHz.

**[0084]** In other example, the number of spatial streams (Nsts) may also be limited so that the RU allocation field 415 may be used, or to provide further reserved bits to be used for other purposes. Thus, Nsts may be limited to two options, *e.g.* Nsts=0 or Nsts=1, and the SIG-A field may have a Nsts field 425 that may contain a single bit to indicate the number of spatial streams, Nsts. In other examples the Nsts field 425 may have 2 bits to indicate up to 4 spatial streams, or 3 bits to indicate up to 8 spatial streams. In other examples, the Nsts field 425 may be omitted, such that a single stream is used where the BW is indicated to be 20 MHz.

**[0085]** As described above, limiting the number of bits used for MCS field 420 and Nsts field 425 may also decrease the complexity that a receiver needs to handle and decoding, thus decreasing the power consumption at the receiver and decreasing the amount of testing that may need to be performed, even if the extra reserved bits created by limiting the size of such fields are not used for implementing other features.

**[0086]** FIG. 5 illustrates an example of aspects of a WLAN protocol data unit 500 for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. WLAN protocol data unit 400 illustrates aspects of a transmission between a STA 110 and an AP 105, as described above with reference to FIGs. 1-2. WLAN protocol data unit 400 includes an HE-SIG-B field 310-a, which is an example of a second WLAN signaling field 310. HE-SIG-B field 310-a includes two content channels 405-a and 405-b including control information. In one example, a device decodes both channels to acquire all of the content signaled in the HE-SIG-B field 310-a. Furthermore, a device that receives a user block within a frequency band associated with a stream 405 also received data within the same frequency band. The common portion (*e.g.* the information in common block fields 340-a and 340-b) and dedicated portion (*e.g.*, user blocks 345-d and 345-e) for every other 20 MHz channel are signaled together. User blocks 345-d and 345-e each include per user information for MU-MIMO users in user blocks and per-user information for SU users

in user blocks. The dedicated portion, which includes per user information, including user blocks 345-d and 345-e, may be dynamically allocated between channels during load balancing.

**[0087]** For example, 8 MU-MIMO users may be allocated RUs in channel 405-a and channel 405-b. RUs may be allocated by the common portion 340-a of the HE-SIG-B field 310-a to 5 MU-MIMO users of the 8 MU-MIMO users. The dedicated portion 345-d of the HE-SIG-B field 310-a may then provide information, once decoded by a station that is one of the 5 MU-MIMO users, that identifies where data for that station is found in the data portion associated with the channel 405-a of the transmission frame. Similarly, RUs may be allocated by the common portion 340-b of the HE-SIG-B field 310-a to 3 MU-MIMO users of the 8 MU-MIMO users. The dedicated portion 345-e of the HE-SIG-B field 310-a may then provide information, once decoded by a station that is one of the 3 MU-MIMO users, that identifies where data for that station is found in the data portion associated with the channel 405-b of the transmission frame (*e.g.* PPDU).

**[0088]** To perform load balancing, a transmitter, *e.g.* an AP or station, may split up a number of MU-MIMO users in different ways. For WLAN protocol data unit 500, 8 MU-MIMO users are split with 5 MU-MIMO users, which are allocated RUs of 484 tones associated with the first channel 405-a, and 3 MU-MIMO, which are allocated RUs of 484 tones associated with the second channel 405-b. In other examples, a user may be allocated RUs that are larger than the maximum RU size for a single channel. For example where the maximum RU size for a channel is 242 tones, an allocated RU for 1 or more MU-MIMO users may be 484 tones spanning two channels (*e.g.*, two 20 MHz channels making a 40 MHz allocation). For these larger allocations, *e.g.* where the RU size is 484 tones or larger, a number of MU-MIMO users may be split between a first channel and a second channel, for example from 1 to 8 MU-MIMO users. However, for purposes of load balancing, where it may be desirable to balance RU allocations between a first channel and a second channel, it may assist load balancing to provide the ability to allocate zero or no MU-MIMO users to a channel. For example, where a first channel already has a number of blocks allocated to SU transmissions for a number of users, and a second channel has no such blocks allocated to SU transmissions, for purposes of load balancing, the transmitter may then allocated zero or no

MU-MIMO blocks to the first channel, and each of the remaining MU-MIMO blocks for MU-MIMO users to the second channel.

**[0089]** FIG. 12 illustrates RU allocation table entries 1200 for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. In some examples for load balancing, a receiving station receive a downlink transmission including multiple channels, according to preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The downlink transmission may include WLAN signaling field 310. The signaling field may include a common portion in a first channel, *e.g.* channel 405-a for a first number of users, and a common portion in a second channel, *e.g.* channel 405-b for a second number of user. In some examples, the receiving station may need to successfully decode the common portions of both SIG-B content channels to determine the total number of users so that a total number of user blocks may be determined. So that a station may decode one of the channels, but not necessarily the second channel, a total number of users may be indicated in RU allocation table 1200.

**[0090]** RU allocation table 1200 includes a number of entries 1205, an RU size 1210, and a user indication 1215. A brief explanation 1220 is also included in RU allocation table 1200. In this example, the RU size 1210 is 484 tones, but additional RU sizes may also be accommodated, for example 996 tones. In addition, the RU allocation table may have additional entries that are not shown in the RU allocation table portion shown in FIG. 12.

**[0091]** In the example illustrated in FIG. 12, 8 entries 1225 may be provided to indicate the number of users where load balancing is not being performed. Additional entries 1230 may be added to indicate the distribution of users between channels for load balancing. For example a first entry 1230 may indicate that there are no user blocks transmitted. A second entry 1225 indicates a user indication of “1+1” where the primary channel contains a first user block and the secondary channel contains a second user block. A third entry 1230 indicates “2+1” where that the primary channel contains two user blocks and the secondary channel contains one user block. And so on to the user indication of “4+4” indicating that the primary channel contains four user blocks and the secondary channel contains four user blocks.

**[0092]** In other examples, additional combinations may be added to the RU allocation table to provide further load balancing capabilities, *e.g.* entries 1230 for a “7+1” combination for

the primary and secondary channels, or “2+4” for the primary and secondary channels, and so on. In other examples, each combination may be included in the RU allocation table. In addition, the RU allocation table may be needed for larger RU sizes, *e.g.* 996 tones, 996\*2 tones, and so on.

**[0093]** FIG. 6 illustrates an example of aspects of a portion of a lookup table 600 for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. Lookup table 600 is a portion of a lookup table, specifically rows that contain RU allocations of at least 102 tones, that may be used to signal RU allocation signaling in a common block field of a HE-SIG-B field of a HE PPDU as described above. Lookup table 600 may indicate the location of the SIG-B dedicated content for large SU allocations, and allows for load balancing in the case of large RU sizes, *e.g.* 484 tones or larger. To provide the ability to transmit no or zero MU-MIMO blocks for a RU size of 484 tones or larger, a lookup table that indicates a number of MU-MIMO users associated with a RU may be modified by adding rows to the table. In particular a row 605 may be added so that, in addition to signaling that there are 1 through 8 MU-MIMO user blocks transmitted in a particular SIG-B content channel associated with the 484 tone RU allocation, that an indication of an absence of a MU-MIMO user block transmitted in the said SIG-B content channel with the 484 tone allocation, *i.e.* there is no MU-MIMO user block transmitted with the 484 tone allocation for that channel. Similarly, a row 610 may be added so that, in addition to signaling that there are 1 through 8 MU-MIMO user blocks transmitted with a SIG-B content channel with the 996 tone RU allocation, that an indication of an absence of a MU-MIMO user block in the said SIG-B content channel associated with the 996 tone allocation, *i.e.* there is no MU-MIMO user block transmitted with the 996 tone allocation for that channel. In other examples, the RU size may vary, such that the additional rows may be used where a RU allocation span multiple channels and an indication of zero or an absence of MU-MIMO user blocks may be indicated for a large RU allocation. It should be noted that where the allocation size is less than 484 tones, according to this example, additional rows may not be needed in the lookup table 600 because only a single channel will be used, and load balancing between 2 or more channels will not take place.

**[0094]** FIG. 7 illustrates an example of aspects of a spatial configuration lookup table 700 for supporting preamble design aspects for HE WLANs in accordance with various aspects of

the present disclosure. A user field for an MU-MIMO allocation, *e.g.* in a HE-SIG-B field, may include a spatial configuration subfield of 4 bits indicating the number of spatial streams for each multiplexed STA, the index of the spatial stream, and the total number of spatial streams. Column Nuser indicates the number of users; Nuser may be indicated in the common portion (*e.g.* common block 340) of a HE-SIG-B field. Given Nuser, index of the spatial stream, the total number of spatial stream allocated, and an index of the user/station as determined by an order that the user/station appears in a dedicated portion of a second WLAN signaling field 310 (*e.g.* a HE-SIG-B field), the number of spatial stream associated with the particular user/station may be determined. The index of the spatial stream and total number of spatial streams allocated may be communicated explicitly. However, the index of the user/station needs to be determined based on the order in which it appears in the dedicated portion, as explained further below. Thus, the index may be implicitly determined based on the order, reducing overhead for explicit communication of the index.

**[0095]** In a transmission frame, *e.g.* a HE MU PPDU transmission frame using MU-MIMO RU allocations, the order of the dedicated portions 345 of a second WLAN signaling field 310 may be used to determine a number of spatial streams (Nsts) allocated to a particular user/station that has received the transmission frame. A station may receive a transmission frame that includes a second WLAN signaling field 310. The station may then decode the dedicated portions 345 of the second WLAN signaling field 310 and determine an order for the various stations or users in the MU-MIMO allocation along with the station that has received the transmission frame. The order may be predetermined for the station. For example, the station (when an AP is the transmitter) may determine that the order is based on the identity of the station according to the order that it appears in the dedicated portion 345 based on frequency, *e.g.* proceeding from the lowest subcarrier frequency to the highest subcarrier frequency (or vice-versa). In one example, the station may determine the order of stations appearing in the dedicated portion 345 without regard to whether a particular channel is dedicated as a primary channel (*e.g.* the primary 20 MHz channel) or a secondary channel (*e.g.* the secondary 20 MHz channel). In another example, the station may determine the order based on frequency, but first for the primary channel, followed by the secondary channel. For example, the station may proceed from the lowest subcarrier frequency to the highest subcarrier frequency (or vice-versa) for the primary channel, followed by the lowest subcarrier frequency to the highest subcarrier frequency (or vice-versa) for the secondary

channel. Thus, the station may determine the order of stations having data communicated in the dedicated portion 345.

**[0096]** Having determined the order for each station in the dedicated portion, a user/station may determine its own index based on where the station appears in the order. That index may then be used in conjunction with spatial configuration lookup table 700 to determine the number of spatial streams for that station. For example, if  $N_{user} = 3$ , there are a total number of spatial streams equal to 8, and the station has determined that its index is equal to 2, then the number of spatial streams associated with the user/station is 3, corresponding to entry 705.

**[0097]** In some examples for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure, a station may differentiate between SU and MU-MIMO allocations. Decoding and combining both SIG-B content channels may be used to distinguish between SU and MU-MIMO allocations. Due to load balancing as described above with reference to FIG. 5,  $N_{user}$  may be one as indicated by a common portion 340 in a HE-SIG-B field for a large MU-MIMO allocation. Because the content of the SU and MU dedicated portions of a HE-SIG-B field may be different,  $N_{user}$  indications in a first SIGB content channel need to be combined with the content in a second SIGB content channel. Through combining, if  $N_{user}$  for the first content channel plus  $N_{user}$  for the second content channel is greater than 1 (for the same RU), then the content is MU-MIMO dedicated content. If  $N_{user}$  for the first content channel plus  $N_{user}$  for the second content channel is not greater than 1 (for the same RU), the content is SU dedicated content.

**[0098]** In other examples for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure, HE-SIG-B compressed mode 800 may be used. The compressed mode may be used for MU-MIMO utilizing a full bandwidth. In such case, no RU signal information is transmitted in a HE\_SIG-B field. Instead, user specific sub-fields are split between the two HE-SIG-B content channels, as illustrated in **FIG. 8**. In the compressed mode, a number of MU-MIMO users needs to be indicated. To accomplish this, a field in the SIG-A field corresponding to the number of SIG-B symbols may be re-interpreted or repurposed, and the number of SIG-B symbols derived from the number of MU-MIMO users. The number of MU-MIMO users may be computed from the number of SIG-B symbols, which could lead to ambiguity in the case where a high MCS is

used. Thus, the number of MU-MIMO users may instead be indicated in a common portion of a HE-SIG-B field. This increases overhead because CRC and tail bits are also added to the common portion of the HE-SIG-B field.

**[0099]** In other examples for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure, an HE-SIG-B design may use channel bonding. According to an example, SIG-B may not be transmitted in a channel that has been punctured, for example a 20 MHz channel. This may be regardless of whether the preamble in the transmission frame prior to the SIG-B field has been transmitted or not. The SIG-B transmission format may be determined for secondary 20 MHz channels that are not transmitted, or other such channels that are not transmitted. When a second 20 MHz channel is not transmitted, there may be multiple options to transmit such information.

**[0100]** **FIGS. 11A and 11B** illustrate HE-SIG-B transmission formats 1100 that support preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. In these examples, the 2nd 20 MHz channel of an 80 MHz bandwidth has been punctured, either in whole or in part. For example, there may be excessive interference that causes the channel not to be received a station. In some examples, the SIG-B field may have been punctured, but the SIG-A field or other portions of the preamble for the channel has not been punctured. A common portion 1105 for a primary HE-SIG-B content channel is transmitted in the 1st 20 MHz channel and the 3rd 20 MHz channel in duplicate. A dedicated portion 1115 for the primary HE-SIG-B content channel is also transmitted in the 1st 20 MHz channel and the 3rd 20 MHz channel in duplicate. A common portion 1110 for a secondary HE-SIG-B content channel would otherwise be transmitted in the 2nd 20 MHz channel and the 4th 20 MHz channel in duplicate, but as shown, the 2nd 20 MHz channel has been punctured. Likewise, a dedicated portion 1120 for a secondary HE-SIG-B content channel would otherwise be transmitted in the 2nd 20 MHz channel and the 4th 20 MHz channel in duplicate, but the 2nd 20 MHz channel has been punctured. When the secondary 20 MHz channel is punctured, for example the 2nd 20 MHz channel, the information that would otherwise be contained in the SIG-B field 310-g may be determined from other channels or other mechanisms.

**[0101]** In a first example, illustrated in **FIG. 11B**, information/contents of the SIG-B that was found in the secondary 20 MHz channel may be transmitted on the primary 20 MHz

channel. In such case an indication of the puncturing of the 20 MHz channel may be signaled in the SIG-A field, for example by including an indicator, which in some examples may be a 1 bit indicator. This increases overhead on the primary channels, *e.g.* the 1st 20 MHz and the 3rd 20 MHz as illustrated in FIG. 11, since the SIG-B content from the secondary channels is transmitted on the primary channels, in addition to the SIG-B content on the primary channel. As illustrated for the primary HE-SIG-B content channel for both the 1st 20 MHz and the 3rd 20 MHz, common portion 1110 is followed by dedicated portion 1120 followed by common portion 1105 followed by dedicated portion 1115. In another example, for the primary HE-SIG-B content channel for both the 1st 20 MHz and the 3rd 20 MHz, common portion 1110 is followed by common portion 1105 followed by dedicated portion 1120 followed by dedicated portion 1115. Whether the common portion of the primary channel SIG-B content is transmitted first, as illustrated in FIG. 11B, or the secondary channel common portion is transmitted first, or whether another order of the common and dedicated portions may be transmitted, may be predetermined so that upon receiving an indication in the SIG-A field the receiving station may know the order to decode the SIG-B field in the primary channel.

**[0102]** As described above, an indicator (*e.g.*, a 1 bit indicator) in the SIG-A field may be used to indicate puncturing of a 20 MHz channel and the location of the SIG-B content channel (*e.g.*, the HE-SIG-B content channel in a particular 20 MHz channel of the bandwidth for a PPDU). In some examples, the BW field of the SIG-A field may include the indication (*e.g.*, the 1 bit indicator). In other examples, the BW field 410 described above with reference to FIG. 4, may be used to indicate a bandwidth used by a PPDU as well as a location of a SIG-B content channel. In some examples, various combinations of PPDU bandwidths and SIG-B content channel locations may be indicated by the BW field 410.

**[0103]** Table 1 below shows example values for a 3-bit BW field in a HE-SIG-A field of a HE MU PPDU. Where a BW field in a HE-SIG-A field has a value of 0 or 1, the BW field indicates a PPDU bandwidth of 20 MHz or 40 MHz, respectively. Where a BW field in a HE-SIG-A field has a value of 2, the BW field indicates that the bandwidth for the PPDU carrying the HE-SIG-A field has a bandwidth of 80 MHz, and that both a first (primary) 20 MHz HE-SIG-B content channel and a second (secondary) 20 MHz HE-SIG-B content channel are present in the primary 40 MHz. Where a BW field in a HE-SIG-A field has a value of 3, the BW field indicates that the bandwidth for the PPDU carrying the HE-SIG-A

field has a bandwidth of 160 MHz or 80+80 MHz, and that both a first (primary) 20 MHz HE-SIG-B content channel and a second (secondary) 20 MHz HE-SIG-B content channel are in the primary 40 MHz, respectively. Where a BW field in a HE-SIG-A field has a value of 4, the BW field indicates that the bandwidth for the PPDU carrying the HE-SIG-A field has a bandwidth of 80 MHz, and that the secondary 20 MHz HE-SIG-B content channel is absent from the primary 40 MHz, and the counterpart secondary 20 MHz HE-SIG-B content channel is absent from the secondary 40 MHz. Where a BW field in a HE-SIG-A field has a value of 5, the BW field indicates that the bandwidth for the PPDU carrying the HE-SIG-A field has a bandwidth of 80 MHz, and that there is a secondary 20 MHz HE-SIG-B content channel absent from the primary 40 MHz, and the counterpart secondary 20 MHz HE-SIG-B content channel is present in the secondary 40 MHz. Where a BW field in a HE-SIG-A field has a value of 6, the BW field indicates that the bandwidth for the PPDU carrying the HE-SIG-A field has a bandwidth of 160 MHz or 80+80 MHz, and that the secondary 20 MHz HE-SIG-B content channel is absent from the primary 40 MHz, and the counterpart secondary 20 MHz HE-SIG-B content channel is absent from the secondary 40 MHz. Where a BW field in a HE-SIG-A field has a value of 7, the BW field indicates that the bandwidth for the PPDU carrying the HE-SIG-A field has a bandwidth of 160 MHz or 80+80 MHz, and that there is a secondary 20 MHz HE-SIG-B content channel absent from the primary 40 MHz, and the counterpart secondary 20 MHz HE-SIG-B content channel is present in the secondary 40 MHz.

Table 1: Value of BW (3 bit) in HE-SIG-A field of HE MU PPDU

Value	Description
0	20 MHz
1	40 MHz
2	80 MHz with both primary and secondary 20 MHz HE-SIG-B content channels present in the primary 40 MHz
3	160/80+80 with both primary and secondary 20 MHz HE-SIG-B content channels present in the primary 40 MHz
4	80 MHz with the secondary 20 MHz HE-SIG-B content channel absent from the primary 40 MHz, and its HE-SIG-B counterpart absent from the secondary 40 MHz

5	80 MHz with the secondary 20 MHz HE-SIG-B content channel absent from the primary 40 MHz, and its HE-SIG-B counterpart present in the secondary 40 MHz
6	160/80+80 MHz with the secondary 20 MHz HE-SIG-B content channel absent from the primary 40 MHz, and its HE-SIG-B counterpart absent from the secondary 40 MHz
7	160/80+80 MHz with the secondary 20 MHz HE-SIG-B content channel absent from the primary 40 MHz, but its HE-SIG-B counterpart present in the secondary 40 MHz

**[0104]** In some examples, a 2-bit BW field in a SIG-A (*e.g.*, HE-SIG-A) field may be used to indicate a fewer number of combinations of bandwidth and SIG-B (*e.g.*, HE-SIG-B) content channel, or a 4-bit (or more) BW field in a HE-SIG-A field may be used to indicate a greater number of combinations. In other examples, the BW field may be used to indicate different combinations of bandwidth and SIG-B content channel locations.

**[0105]** FIG. 11C illustrates an example of channels 1100-c for a contiguous channel bonding mode, in accordance with various aspects of the present disclosure. Channels 1100-c include a primary 20 MHz channel, a secondary 20 MHz channel, a secondary 40 MHz channel, and a secondary 80 MHz channel for a 160 MHz bandwidth. Channels 1100-c include a primary 20 MHz channel, a secondary 20 MHz channel, and a secondary 40 MHz channel for a 80 MHz bandwidth. Channels 1100-c include a primary 20 MHz channel and a secondary 20 MHz channel for a 40 MHz bandwidth. Channels 1100-c may be examples of the corresponding channels described with reference to Table 1.

**[0106]** FIG. 11D illustrates an example of channels 1100-d for a non-contiguous channel bonding mode, in accordance with various aspects of the present disclosure. Channels 1100-d include a primary 20 MHz channel, a secondary 20 MHz channel, a secondary 40 MHz channel, and a secondary 80 MHz channel for a 80+80 MHz bandwidth configuration, where the secondary 80 MHz channel is not contiguous with the primary 20 MHz channel, secondary 20 MHz channel, and secondary 40 MHz channel. Channels 1100-d may be examples of the corresponding channels described with reference to Table 1 for a non-contiguous 80+80 MHz bandwidth, for example specifically with reference to BW values 3, 6, and/or 7.

**[0107]** In a second example, for example for an 80 MHz bandwidth as illustrated in **FIG. 11A**, or a 160 MHz bandwidth containing duplicated SIG-B content, information and/or contents of the SIG-B field that was found in the punctured secondary 20 MHz channel corresponding to the 2nd 20 MHz may be decoded from a 4th 20 MHz channel. In such case an indication of the SIG-B decoding may be signaled in the SIG-A field, for example by including an indicator in the SIG-A field. In this example, there may be a limitation that the 4th 20 MHz is not also punctured.

**[0108]** In other examples for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure, an HE-SIG-B design may be different when other 20 MHz channels are punctured. In such case, a common portion of a SIG-B field may be affected since one or more 20 MHz channels are absent.

**[0109]** In a first example, RU allocation for the punctured 20 MHz channels are not transmitted. A size of the common portion of the SIG-B field may be modified depending on the number and location of the punctured channels. In addition, a common portion size may be different between the two SIG-B content channels. An explicit indication of punctured channels may be indicated in the SIG-A field.

**[0110]** In a second example, a special or dedicated RU allocation bit sequence may be used to indicate that a 20 MHz channel is punctured. The indication may be made by adding an additional entry in a RU allocation table. A size of the common portion may be unchanged for either content channel. According to this example an explicit indication of the punctured 20 MHz channel may not be needed, though the additional RU allocation bit sequence may result in additional overhead in the common portion of the SIG-B field.

**[0111]** In these examples, the SIG-B dedicated portion, as opposed to the common portion, may be relatively unaffected. SIG-B duplicated structure may be maintained, while the dedicated content for punctured channels are not transmitted.

**[0112]** In other examples, other 20 MHz channels are punctured. For example, a data portion for a user may be punctured in a secondary channel corresponding to the 4th 20 MHz. SIG-B information for a 1st user and 2nd user may be transmitted in a primary channel, and SIG-B information for a 3rd user and 4th user may be transmitted in the secondary channel. If the channel carrying data for the 4th user is punctured, for example the 4th 20 MHz as

shown in FIG. 11A, then the receiving station may expect data for the 4th user because of the presence of an RU allocation in the SIG-B field for the 4th user. Two examples to address this situation are described below.

**[0113]** In a first example, the RU allocation for the punctured 20 MHz channel may be not transmitted. The size of the common portion, *e.g.* common portion 1105, may then be changed depending on the number and location of the punctured channels. The common portion size may also be different between the two SIG-B content channels. An explicit indication of which channels are punctured may then be communicated in the SIG-A field. In this example a number of channels that may be punctured may be limited by the number of bits allocated in the SIG-A field to communicate which, if any, of the channels are punctured to the receiving station. For example, 2 bits in the SIG-A field may allow for the indication of 4 possible combinations of punctured channels.

**[0114]** In a second example, an RU allocation bit sequence may be used to indicate that a 20 MHz channel is punctured. An additional entry in an RU allocation table, for example using an otherwise reserved entry in the RU allocation table, may be used to indicate that a RU is not allocated, *e.g.* because the 20 MHz channel is punctured. By inserting an additional entry in the RU allocation table, the size of the common portion may be unchanged in the content channel. Furthermore, an explicit indication of the punctured 20 MHz channel may not be needed. According to this second example, the dedicated portion may remain unchanged, while the SIG-B duplicated structure is maintained.

**[0115]** **FIGs. 9A through 9C** show block diagrams 900-a through 900-c of example preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure.

**[0116]** RU allocation signaling, *e.g.* using an RU allocation table, may be used to indicate the allocation plan for each 20MHz channel of a bandwidth. The size of each allocation and a number of users in each resource unit (RU) may be indicated in the RU allocation table. There may not be adequate numbers of entries available in an RU allocation table to indicate center tones (*e.g.* the above-described center 26 tones), for example, because the size of the RU allocation table is limited to minimize an amount of overhead. Such overhead may include the number or size of dedicated portions or blocks to be sent in the HE-SIG-B field 310-b.

**[0117]** An RU allocation table may provide for the allocation plan for channels. Such allocation plans may not provide a provision to account for all the tones in a bandwidth. In some examples, a tone plan may not provide the ability to allocate a 26 tone resource unit that falls in the center of the tone plan. For example, with reference to FIG. 4B, a 26 tone RU may fall between the 2 106 tone RUs in the allocation plan 430. Similarly, with reference to FIG. 4C, a 26 tone RU may fall between the 2 106 tone RUs in the allocation plan 445, and/or between the second and third 52 tone RUs in the allocation plan 440. In other allocation plans, the tones may not be indicated in the tone plan, but fall between 26 tone, 52 tone, or 106 tone RUs elsewhere within an allocation plan. Each such RU may be referred to herein as a center 26 tone RU.

**[0118]** According to some examples, that a center 26 RU is not allocated may be indicated in a station ID of a user block in the HE-SIG-B field. A certain sequence for the station ID may be used to indicate that center 26 tone RUs are not allocated, *e.g.* a station ID indicating an RU is unallocated, for example a sequence of 0's or a sequence of 1's for the station ID used to indicate that a corresponding center 26 tone RU is not allocated to any station.

**[0119]** In some examples, sending a station ID indicating that an RU is unallocated may require additional overhead. In some examples or implementations, certain of the RUs are more likely to be unallocated than other RUs. For example, the center 26 tone RUs may be the most likely to be unallocated. In some examples, the station ID indicating that an RU is unallocated may be transmitted if there is room in a pad field 925, but otherwise are not transmitted.

**[0120]** FIG. 9A illustrates the HE-SIG-B field 310-b, including a common block 905-a, user blocks for  $n$  users 910-a through 910-e, CRC+tail fields 915-a through 915-c, an RU allocation for the center 26 tone RU 920-a, and pad bits in a pad field 925-a. In this example, a single channel 930-a is shown. According to this example, that an RU is not allocated may be indicated in a station ID of a user block 910. A certain sequence for the station ID may be used to indicate that center 26 tone RUs are not allocated, for example a sequence of 0's or a sequence of 1's. The sequence of 0's or 1's may also be used to indicate for other of the RUs that they are unallocated in other examples. Thus, the station ID may be used to indicate that an RU is unallocated. For HE-SIG-B field 310-b, a center 26 tone RU is not allocated, and the indication is provided by block 920-a.

**[0121]** FIG. 9B illustrates the HE-SIG-B field 310-c, including a common block 905-b, user blocks for  $n$  users 910-f through 910-j, CRC+tail fields 915-d through 915-f, and pad bits in a pad field 925-b. In this example, a single channel 930-a is shown, where a center 26 tone RU is not allocated. In this example, there is not adequate space available in the pad field 925-b, and as a result, a block including the station ID (*e.g.* an AID) that indicates that the center 26 RU is unallocated is not transmitted in the HE-SIG-B field 310-c.

**[0122]** FIG. 9C illustrates the HE-SIG-B field 310-d, including a common block 905-c, user blocks for  $n$  users 910-k through 910-o, CRC+tail fields 915-g through 915-j, and pad bits in a pad field 925-c. In this example, the SIG-B field for a single channel 930-b is shown. In this example, there is adequate space available in the pad 925-b, and as a result, a blocks including the station ID that indicates that center 26 RUs are or are not allocated are transmitted in the HE-SIG-B field 310-c. In one example, the SIG-B field may relate to RU allocations for an 80MHz or 160MHz bandwidth, which there may be five center 26 RUs to be indicated. In this example, pad field 925 provide room for only three of the five center 26 RUs to be transmitted, center 26 RU [0] block 925-a for a first RU position, center 26 RU [1] block 925-b for a second RU position , and center 26 RU [2] block 925-c for a third RU position. Indications that the other two center 26 tone RUs are unallocated are not sent.

**[0123]** Upon receipt of the HE-SIG-B field 310-d by a station, the station may decode the center 26 RU blocks 925 and determine that the corresponding center 26 RUs are not allocated. The station may also determine that it has reached the end of the HE-SIG-B field 310-d, and thereby determine that the remaining two center 26 RUs are also not allocated.

**[0124]** In accordance with preamble design aspects described above, the order of dedicated (user) content of the user specific subfield of the SIG-B field may be ordered according to a number of possible combinations. In one example, the content may be ordered in the user specific subfield the same as the order used in the common portion of the SIG-B field. In some examples, the content of both the common portion and the user specific subfield (*e.g.* the dedicated portion) may be ordered in ascending or descending frequency allocated to the user. In other examples, the primary channel may be ordered first, followed by ascending frequency. In still other examples, the primary channel may be ordered first, followed by descending frequency.

**[0125]** FIG. 10 illustrates an HE-SIG-B field 310-f for a primary HE-SIG-B content channel and an HE-SIG-B field 310-e for a second HE-SIG-B content channel in accordance with various aspects of the present disclosure. In some examples, the location of the user specific field for the center 26 tone RUs may be at the end of the user block 1020 of the SIG-B field, despite the center 26 tone RUs themselves generally falling in the middle of a channel. The example shown in FIG. 10 includes user specific SIG-B content for the center 26 tone RU SIG-B content for the user specific portions of center 26 tone RUs. Specifically, the primary HE-SIG-B content channel 1005 includes center 26 tone RU content for the 1st 20 MHz at block 1065, for the 3rd 20 MHz at block 1070, for the 5th 20 MHz at block 1075, and for the 7th 20 MHz at block 1080, and also includes the center 26 tone RU content for the center 26 tones for the primary 80MHz channel. Specifically, the primary HE-SIG-B content channel 1010 includes center 26 tone RU content for the 2nd 20 MHz at block 1035, for the 4th 20 MHz at block 1040, for the 6th 20 MHz at block 1045, and for the 8th 20 MHz at block 1050. For the example of 160 MHz bandwidth, the HE-SIG-B content channel 1010 also includes the center 26 tone RU content for the center 26 tones for the secondary 80MHz channel in block 1055. For the example of 80 MHz bandwidth, the HE-SIG-B content channel 1010 may not include block 1055.

**[0126]** The center 26 tone RU content blocks of the HE-SIG-B field described above may indicate that the center 26 tone RUs are allocated. In other example fewer or none of the center 26 tone RUs may be allocated. In such example, the station ID (AID) described above with reference to FIGS. 9A-9C may be used to indicate that they are not allocated, or the user specific blocks for the center 26 tone RUs may not be transmitted due to a lack of padding, also as described with reference to FIGS. 9A-9C above.

**[0127]** In some example, overhead may be further reduced by reordering the transmission order of the center 26 tone RU blocks. For example, if only the 7th 20 MHz at block 1080 of the secondary HE-SIG-B content channel will indicate that a center 26 tone RU is allocated, and the remaining 26 tone RUs will be unallocated, then the scheduling that is done by the transmitting AP may performed such that, if any of the center 26 tone RUs are to be allocated, that they are allocated starting from the 1st 20 MHz, not starting with or for only the 7th 20 MHz. Thus, the transmitting AP may transmit user specific content in the SIG-B field for the allocated center 26 tone RU first, then cease transmitting, and not transmit

additional center 26 tone RUs. Similarly, the station may cease decoding the SIG-B once it encounters an AID value indicating that a center 26 tone RU is not allocated.

**[0128]** In other examples, the order of the center 26 tone RUs may be reordered according to a predetermined order that may be known to both a transmitting AP and a receiving station.

**[0129]** **FIGs. 14A through 14D** show a first HE-SIG-A field contents 1401-1404 for a HE SU PPDU and HE extended range SU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The HE-SIG-A field contents 1401 and HE-SIG-A field contents 1402 together represent a first part of a HE-SIG-A field, HE-SIG-A1, and the HE-SIG-A field contents 1403 and HE-SIG-A field contents 1404 together represent a second part of a HE-SIG-A field, HE-SIG-A2. One or more of HE-SIG-A field contents 1401-1404 may be part of HE WLAN preamble 215 with reference to FIG. 2, and/or HE-SIG-A field 305 with reference to FIGs. 3 and 4A. Where HE-SIG-A field contents 1401-1404 are implemented for a HE SU PPDU, the HE-SIG-A field contents 1401-1404, in aggregate, may be 8  $\mu$ s. Where HE-SIG-A field contents 1401-1404 are implemented for a HE extended range PPDU, the HE-SIG-A field contents 1401-1404, in aggregate, may be 16  $\mu$ s. In some examples, the HE-SIG-A field contents 1401-1404 in the HE extended range PPDU may be 8  $\mu$ s, but repeated twice making the total length 16  $\mu$ s.

**[0130]** **FIGs. 15A through 15C** show a first HE-SIG-A field contents 1501-1503 for a HE MU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The HE-SIG-A field contents 1501 represents a first part of a HE-SIG-A field, HE-SIG-A1, and the HE-SIG-A field contents 1502 and HE-SIG-A field contents 1503 together represent a second part of a HE-SIG-A field, HE-SIG-A2. One or more of HE-SIG-A field contents 1501-1503 may be part of HE WLAN preamble 215 with reference to FIG. 2, and/or HE-SIG-A field 305 with reference to FIGs. 3 and 4A. Where HE-SIG-A field contents 1501-1503 are implemented for a HE MU PPDU, the HE-SIG-A field contents 1501-1503, in aggregate, may be 8  $\mu$ s.

**[0131]** **FIGs. 16A through 16B** show a first HE-SIG-A field contents 1601-1602 for a HE trigger-based PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The HE-SIG-A field contents 1601 represents a first part of a HE-SIG-A field, HE-SIG-A1, and the HE-SIG-A field contents 1602

represents a second part of a HE-SIG-A field, HE-SIG-A2. One or more of HE-SIG-A field contents 1601-1602 may be part of HE WLAN preamble 215 with reference to FIG. 2, and/or HE-SIG-A field 305 with reference to FIGs. 3 and 4A. Where HE-SIG-A field contents 1601-1602 are implemented for a HE trigger-based PPDU, the HE-SIG-A field contents 1601-1602, in aggregate, may be 8  $\mu$ s.

**[0132] FIGs. 17A through 17D** show a second HE-SIG-A field contents 1701-1704 for a HE SU PPDU and HE extended range SU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The HE-SIG-A field contents 1701 and HE-SIG-A field contents 1702 together represent a first part of a HE-SIG-A field, HE-SIG-A1, and the HE-SIG-A field contents 1703 and HE-SIG-A field contents 1704 together represent a second part of a HE-SIG-A field, HE-SIG-A2. One or more of HE-SIG-A field contents 1701-1704 may be part of HE WLAN preamble 215 with reference to FIG. 2, and/or HE-SIG-A field 305 with reference to FIGs. 3 and 4A. Where HE-SIG-A field contents 1701-1704 are implemented for a HE SU PPDU, the HE-SIG-A field contents 1701-1704, in aggregate, may be 8  $\mu$ s. Where HE-SIG-A field contents 1701-1704 are implemented for a HE extended range PPDU, the HE-SIG-A field contents 1701-1704, in aggregate, may be 16  $\mu$ s. In some examples, the HE-SIG-A field contents 1701-1704 in the HE extended range PPDU may be 8  $\mu$ s, but repeated twice making the total length 16  $\mu$ s.

**[0133] FIGs. 18A through 18C** show a second HE-SIG-A field contents 1801-1803 for a HE MU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The HE-SIG-A field contents 1801 represents a first part of a HE-SIG-A field, HE-SIG-A1, and the HE-SIG-A field contents 1802 and HE-SIG-A field contents 1803 together represent a second part of a HE-SIG-A field, HE-SIG-A2. One or more of HE-SIG-A field contents 1801-1803 may be part of HE WLAN preamble 218 with reference to FIG. 2, and/or HE-SIG-A field 305 with reference to FIGs. 3 and 4A. Where HE-SIG-A field contents 1801-1803 are implemented for a HE MU PPDU, the HE-SIG-A field contents 1801-1803, in aggregate, may be 8  $\mu$ s.

**[0134] FIGs. 19A through 19B** show a second HE-SIG-A field contents 1901-1902 for a HE trigger-based PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The HE-SIG-A field contents

1901 represents a first part of a HE-SIG-A field, HE-SIG-A1, and the HE-SIG-A field contents 1902 represents a second part of a HE-SIG-A field, HE-SIG-A2. One or more of HE-SIG-A field contents 1901-1902 may be part of HE WLAN preamble 215 with reference to FIG. 2, and/or HE-SIG-A field 305 with reference to FIGs. 3 and 4A. Where HE-SIG-A field contents 1901-1902 are implemented for a HE trigger-based PPDU, the HE-SIG-A field contents 1901-1902, in aggregate, may be 8  $\mu$ s.

**[0135]** FIGs. 20A through 20C show an example of a HE-SIG-A field contents 2001-2003 for a HE SU PPDU and HE Extended Range SU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The HE-SIG-A1 field contents 2001-2002 represent a first part of a HE-SIG-A field, HE-SIG-A1, and HE-SIG-A2 field contents 2003 represent a second part of the HE-SIG-A field. The HE-SIG-A field contents 2001-2003 represents aspects of a re-ordering of various HE-SIG-A fields. One or more of HE-SIG-A field contents 2001-2003 may be part of HE WLAN preamble 218 with reference to FIG. 2, and/or HE-SIG-A field 305 with reference to FIGs. 3 and 4A.

**[0136]** The HE-SIG-A field contents 2001-2003 provide improved PAPR performance for HE-SIG-A. In certain aspects, the HE-SIG-A field contents 2001-2003 moves the beam change, MCS, DCM, LTE+CP, and Nsts fields to HE-SIG-A1 and moves the Txop duration to HE-SIG-A2. For the BSS color description, “0” may indicate public action frames; “63” may indicate IBSS/MBSS/TDLS frames (e.g., when the AP does not provide a color); and “1:62” may indicate HE BSS color. For the Txop duration description, “127” may indicate that the Txop duration is not set. For the Doppler description, “1” may indicate that Doppler procedure is used, and “0” may indicate otherwise.

**[0137]** In certain aspects, the format field may differentiate between HE SU PPDU and HE Trigger-based PPDU. Having this field first (e.g., “B0”) may support early detection and therefore may be beneficial. Having the Beam Change field as second field may be useful to determine better channel estimation, e.g., the receiver becomes aware of spatial mapping of pre-HE STF and HE LTF very early in reception. The MCS field in the beginning helps to determine MCS of the incoming data payload, e.g., early detect of 1024 QAM MCS enables receiver to enable special power save mode of reception. The DCM field follows MCS immediately, which may impacts the code rate used to calculate data rate for the MCS field.

**[0138]** In some aspects, the BSS Color field supports identifying to which BSS the packet belongs. The Spatial Reuse field conveys knowledge in conjunction with BSS Color field to help determine if STA can do spatial reuse transmission. In HE SU PPDU and HE Extended Range SU PPDU, the HE LTFs may follow the HE SIG-A2 format. Hence early knowledge of LTF + CP helps in HE SIG-A1 to prepare receiver better for channel estimation.

**[0139]** In some aspects, the benefits of HE-SIG-A field contents 2001-2003 studied by the PAPR performance of HE-SIG-A for various PPDU formats considering meaningful worst cases. For worst cases (e.g., all 0's and all 1's in HE SIG A) the sequence of the HE-SIG-A field contents 2001-2003 may support PAPR better than PAPR of MCS0 data.

**[0140]** **FIGs. 21A through 21C** show an example of a HE-SIG-A field contents 2101-2103 for a HE MU PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The HE-SIG-A field contents 2101-2102 represent a first part of a HE-SIG-A field, HE-SIG-A1, and the HE-SIG-A field contents 2103 represent a second part of the HE-SIG-A field, HE-SIG-A2. The HE-SIG-A field contents 2101-2103 represents aspects of a re-ordering of various HE-SIG-A fields. One or more of HE-SIG-A field contents 2101-2103 may be part of HE WLAN preamble 218 with reference to FIG. 2, and/or HE-SIG-A field 305 with reference to FIGs. 3 and 4A.

**[0141]** In certain aspects, the HE-SIG-A field contents 2101-2103 moves the MCS, DCM, LTE+CP, and SIGB # of symbols fields to HE-SIG-A1 and moves the Txop duration to HE-SIG-A2. For the BSS color description, "0" may indicate public action frames; "63" may indicate IBSS/MBSS/TDLS frames (e.g., when the AP does not provide a Color); and "1:62" may indicate HE BSS color. For the Txop duration description, "127" may indicate that the Txop duration is not set. For the Doppler description, "1" may indicate that Doppler procedure is used, and "0" may indicate otherwise.

**[0142]** **FIGs. 22A through 22B** show an example of a HE-SIG-A field contents 2201-2202 for a HE Trigger-based PPDU for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure. The HE-SIG-A field contents 2201 represents a first part of a HE-SIG-A field, HE-SIG-A1, and HE-SIG-A field contents 2202 represents a second part of the HE-SIG-A, HE-SIG-A2. The HE-SIG-A field contents 2201-2202 represents aspects of a re-ordering of various HE-SIG-A fields. One or more of

HE-SIG-A field contents 2201-2202 may be part of HE WLAN preamble 218 with reference to FIG. 2, and/or HE-SIG-A field 305 with reference to FIGs. 3 and 4A.

**[0143]** With reference to FIGs. 14A through 22B, one or more the HE-SIG-A field contents 1401-2202 may include one or more reserved fields. In some examples, these reserved fields are each set to “1”. Setting the reserved fields to “1”, for example instead of some or all to “0”, may ameliorate issues resulting from large peak-to-average-power (PAPR) ratios that may otherwise be present, and/or assist with binary convolutional code (BCC) encoder state setting.

**[0144]** In other examples, the reserved fields, for example bit B0 with reference to HE-SIG-A field contents 1401, 1501, and/or 1601, may be interpreted differently for a transmitter and a receiver. In one example, the reserved field may be set to “1” or “0” by the transmitter, and ignored by the receiver. In a second example, the reserved field may be set to “1” or “0” by the transmitter, and checked by the receiver for fidelity, such that the receiver may discard the associated PPDU if the field is set incorrectly. In a third example, the reserved field may be used to indicate a Wi-Fi version associated with the PPDU, such that the meaning of the HE-SIG-A bit fields may be different based on the indicated version of the field. For example, the reserved field, used as a version field, may be set to “0” to indicate IEEE 802.11ax is used, and may be set to “1” to indicate some future version of IEEE 802.11 is used.

**[0145]** In some examples, a bit associated with the “Format” field shown with reference to HE-SIG-A field contents 1401, 1601, 1701, 1901, 2001, 2101, and/or 2201 may be aligned to a B1 bit in a HE SU PPDU and HE trigger-based PPDU, and used to differentiate between a HE SU PPDU and HE trigger-based PPDU.

**[0146]** In some examples, the “BSS Color” field shown with reference to HE-SIG-A field contents 1401, 1601, 1701, 1901, 2001, 2101, and/or 2201 may contain six bits to identify a BSS. In some examples, the six bits of the BSS Color field are each set to “1” to indicate no BSS color. Setting the “BSS Color” field to all “1” to indicate no BSS color rather than all “0” to indicate no BSS color can avoid providing a trail of “0” bits.

**[0147]** In other examples, combinations of bit fields for the one or more the HE-SIG-A field contents 1401-2202 may be disallowed. These disallowed combinations of bit fields

may be used to indicate vendor-specific modes. For example, for a contention period (CP) of 0.4  $\mu$ s that is indicated to a receiver, a DCM value set to “1” and MCS greater than 4 may be a disallowed combination (*e.g.*, because in some circumstances DCM may be allowed to be applied only for HE-MCSs with indices of 0, 1, 3, or 4). This disallowed combination may still be indicated, but for the transmitter to indicate a vendor specific mode of operation to the receiver rather than for the receiver to operate in the otherwise disallowed combination.

**[0148]** In some examples, and with reference to FIGs. 14A through 22B, the bit fields may be arranged to avoid violating symbol boundaries. For example, each of the two reserved bits for a HE SU PPDU and HE extended range SU PPDU, “Reserved” field B25 shown in HE-SIG-A field contents 1702 and “LDPC extra symbol” field B3 shown in HE-SIG-A field contents 1703 may be arranged to be adjacent by swapping “Reserved” field B25 shown in HE-SIG-A field contents 1702 with “Coding” field B2 shown in HE-SIG-A field contents 1703. In still other examples, the HE trigger-based PPDU bit fields may be rearranged such that spatial reuse (SR) and transmit opportunity (TXOP) duration bit fields occur consecutively. For example, HE-SIG-A field contents 1901-1902 may be arranged as follows: “Format” field B0, “SR” field B1:B16, “TXOP” field B17:B23, and “Bandwidth” field B:24:B25 for the HE-SIG-A1 part of the HE-SIG-A field, followed by “BSS Color” field B0:B5, “Reserved” field B6:B15, CRC field B16:B19, and “Tail” field B20:B25 for the HE-SIG-A2 part of the HE-SIG-A field. Such arrangement may enable the extension of the TXOP duration bit field for improved resolution if SR is unused.

**[0149]** FIGs. 13A and 13B show block diagrams of an example device for supporting preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure.

**[0150]** FIG. 13A shows a block diagram 1300-a of an example wireless device 1390 that supports preamble design aspects for HE WLANs in accordance with various aspects of the present disclosure, and with respect to FIGs. 1-12 and 14A-22B. The wireless device 1390, which may be an example of a STA 110 or an AP 105, includes a resource unit signaling manager 1330, a MU-MIMO load balancer 1335, a spatial stream determiner 1340, a content type determiner 1345, and a punctured channel manager 1350. The processor 1305, memory 1310, transceiver(s) 1320, the resource unit signaling manager 1330, MU-MIMO load balancer 1335, spatial stream determiner 1340, content type determiner 1345, and punctured

channel manager 1350 are communicatively coupled with a bus 1355, which enables communication between these components. The antenna(s) 1325 are communicatively coupled with the transceiver(s) 1320.

**[0151]** The processor 1305 is an intelligent hardware device, such as a central processing unit (CPU), a microcontroller, an application-specific integrated circuit (ASIC), *etc.* The processor 1305 processes information received through the transceiver(s) 1320 and information to be sent to the transceiver(s) 1320 for transmission through the antenna(s) 1325.

**[0152]** The memory 1310 stores computer-readable, computer-executable software (SW) code 1315 containing instructions that, when executed, cause the processor 1305 or another one of the components of the wireless device 1390 to perform various functions described herein.

**[0153]** The transceiver(s) 1320 communicate bi-directionally with other wireless devices, such as APs 105, STAs 110, or other devices. The transceiver(s) 1320 include a modem to modulate packets and frames and provide the modulated packets to the antenna(s) 1325 for transmission. The modem is additionally used to demodulate packets received from the antenna(s) 1325.

**[0154]** The resource unit signaling manager 1330, MU-MIMO load balancer 1335, spatial stream determiner 1340, content type determiner 1345, and punctured channel manager 1350 implement the features described with reference to FIGs. 1-12 and 14A-22B, as further explained below.

**[0155]** The resource unit signaling manager 1330 can identify a resource unit (RU) configuration for a WLAN data field of a SU transmission frame that has a fixed bandwidth. The resource unit signaling manager 1330 can then generate a RU indicator in a WLAN signaling field of a preamble of the SU transmission frame, where the RU indicator identifies a RU size and a RU location within the WLAN data field. The resource unit signaling manager 1330 can, in some examples together with transceivers 1320 and/or antenna(s) 1325, transmit the SU transmission frame.

**[0156]** The MU-MIMO load balancer 1335 can identify a first indicator identifying a number of MU-MIMO stations associated with a first RU in a first content channel of a

transmission frame. The MU-MIMO load balancer 1335 can also identify a second indicator identifying an absence of MU-MIMO stations associated with a second RU in a second content channel of the transmission frame. The MU-MIMO load balancer 1335 may then generate a first common portion of a WLAN signaling field in the first content channel of the transmission frame, wherein the first common portion includes the first indicator, and generate a second common portion of the WLAN signaling field in the second content channel of the transmission frame, wherein the second common portion includes the second indicator. The MU-MIMO load balancer 1335 can, in some examples together with transceivers 1320 and/or antenna(s) 1325, transmit the SU transmission frame that includes the WLAN signaling field.

**[0157]** The spatial stream determiner 1340 can receive a transmission frame that includes a WLAN signaling field decodable by a plurality of stations. In some examples the spatial stream determiner 1340 receives the transmission frame together with transceivers 1320 and/or antenna(s) 1325. The spatial stream determiner 1340 may identify, in a station-specific portion of the WLAN signaling field, an order for a plurality of station-specific information blocks associated with the plurality of stations. The spatial stream determiner 1340 may then determine a number of spatial streams allocated to the first station based at least in part on the identified order for the plurality of station-specific information blocks.

**[0158]** The content type determiner 1345 may receive a transmission frame associated with a plurality of channels, the transmission frame including a WLAN signaling field. In some examples the content type determiner 1345 receives the transmission frame together with transceivers 1320 and/or antenna(s) 1325. The content type determiner 1345 can identify a first number of stations associated with the WLAN signaling field for a first channel of the plurality of channels, and identify a second number of stations associated with the WLAN signaling field for a second channel of the plurality of channels. The content type determiner 1345 may then determine whether a data portion of the transmission frame contains MU-MIMO content based at least in part on the identified first number of stations and the identified second number of stations.

**[0159]** The punctured channel manager 1350 can generate an indication that a first channel of a plurality of channels associated with a transmission frame has been punctured, the transmission frame including a WLAN signaling field. The punctured channel manager 1350

can identify information associated with the WLAN signaling field corresponding to the punctured first channel, then transmit the indication that the first channel has been punctured and the information associated with the WLAN signaling field in a second channel of the plurality of channels. In some examples, the punctured channel manager 1350 operates together with transceivers 1320 and/or antenna(s) 1325 to transmit the indication and the information associated with the WLAN signaling field in the second channel.

**[0160]** Again, FIG. 13A shows only one possible implementation of a device executing the features of FIGS. 1-12 and 14A-22B. While the components of FIG. 13A are shown as discrete hardware blocks (*e.g.*, ASICs, field programmable gate arrays (FPGAs), semi-custom integrated circuits, *etc.*) for purposes of clarity, it will be understood that each of the components may also be implemented by multiple hardware blocks adapted to execute some or all of the applicable features in hardware. Alternatively, features of two or more of the components of FIG. 13A may be implemented by a single, consolidated hardware block. For example, a single transceiver 1320 chip may implement the processor 1305, memory 1310, resource unit signaling manager 1330, MU-MIMO load balancer 1335, spatial stream determiner 1340, content type determiner 1345, and punctured channel manager 1350.

**[0161]** In still other examples, the features of each component may also be implemented, in whole or in part, with instructions embodied in a memory, formatted to be executed by one or more general or application-specific processors. For example, **FIG. 13B** shows a block diagram 1300-b of another example of a wireless device 1390-a in which the features of the resource unit signaling manager 1330-a, MU-MIMO load balancer 1335-a, spatial stream determiner 1340-a, content type determiner 1345-a, and punctured channel manager 1350-a are implemented as computer-readable code stored on memory 1310-a and executed by one or more processors 1305-a. Other combinations of hardware/software may be used to perform the features of one or more of the components of FIGS. 13A-13B.

**[0162]** The detailed description set forth above in connection with the appended drawings describes examples and does not represent the only examples that may be implemented or that are within the scope of the claims. The terms “example” and “exemplary,” when used in this description, mean “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other examples.” The detailed description includes specific details for the purpose of providing an understanding of the described techniques. These techniques,

however, may be practiced without these specific details. In some instances, well-known structures and apparatuses are shown in block diagram form in order to avoid obscuring the concepts of the described examples.

**[0163]** Information and signals may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the above description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

**[0164]** The various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed with a general-purpose processor, a digital signal processor (DSP), an ASIC, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices, *e.g.*, a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

**[0165]** The functions described herein may be implemented in hardware, software executed by a processor, firmware, or any combination thereof. If implemented in software executed by a processor, the functions may be stored on or transmitted over as one or more instructions or code on a computer-readable medium. Other examples and implementations are within the scope and spirit of the disclosure and appended claims. For example, due to the nature of software, functions described above can be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations. As used herein, including in the claims, the term “and/or,” when used in a list of two or more items, means that any one of the listed items can be employed by itself, or any combination of two or more of the listed items can be employed. For example, if a composition is described as containing components A, B, and/or C, the composition can

contain A alone; B alone; C alone; A and B in combination; A and C in combination; B and C in combination; or A, B, and C in combination. Also, as used herein, including in the claims, “or” as used in a list of items (for example, a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates a disjunctive list such that, for example, a list of “at least one of A, B, or C” means A or B or C or AB or AC or BC or ABC (*i.e.*, A and B and C).

**[0166]** Computer-readable media includes both computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A storage medium may be any available medium that can be accessed by a general purpose or special purpose computer. By way of example, and not limitation, computer-readable media can comprise RAM, ROM, EEPROM, flash memory, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other medium that can be used to carry or store desired program code means in the form of instructions or data structures and that can be accessed by a general-purpose or special-purpose computer, or a general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of medium. Disk and disc, as used herein, include compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers. Combinations of the above are also included within the scope of computer-readable media.

**[0167]** The previous description of the disclosure is provided to enable a person skilled in the art to make or use the disclosure. Various modifications to the disclosure will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not to be limited to the examples and designs described herein but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

## CLAIMS

**What is claimed is:**

1           1.       A method for wireless communication, comprising:  
2           identifying a resource unit (RU) configuration for a wireless local area  
3 network (WLAN) data field of a single user (SU) transmission frame that has a fixed  
4 bandwidth;  
5           generating a RU indicator in a WLAN signaling field of a preamble of the SU  
6 transmission frame, the RU indicator identifying a RU size and a RU location within the  
7 WLAN data field; and  
8           transmitting the SU transmission frame.

1           2.       A method for wireless communication, comprising:  
2           identifying a first indicator identifying a number of multi-user multiple input  
3 multiple output (MU-MIMO) stations associated with a first resource unit (RU) in a first  
4 content channel of a transmission frame;  
5           generating a first common portion of a wireless local area network (WLAN)  
6 signaling field in the first content channel of the transmission frame, wherein the first  
7 common portion includes the first indicator;  
8           identifying a second indicator identifying an absence of MU-MIMO stations  
9 associated with a second resource unit (RU) in a second content channel of the transmission  
10 frame;  
11          generating a second common portion of the WLAN signaling field in the  
12 second content channel of the transmission frame, wherein the second common portion  
13 includes the second indicator; and  
14          transmitting the transmission frame that includes the WLAN signaling field.

1           3.       A method for wireless communication, comprising:  
2           receiving, at a first station, a transmission frame that includes a wireless local  
3 area network (WLAN) signaling field decodable by a plurality of stations;  
4           identifying, in a station-specific portion of the WLAN signaling field, an order  
5 for a plurality of station-specific information blocks associated with the plurality of stations;  
6 and

7                   determining a number of spatial streams allocated to the first station based at  
8                   least in part on the identified order for the plurality of station-specific information blocks.

1                   4.        A method for wireless communication, comprising:  
2                   receiving a transmission frame associated with a plurality of channels, the  
3                   transmission frame including a wireless local area network (WLAN) signaling field;  
4                   identifying a first number of stations associated with the WLAN signaling  
5                   field for a first channel of the plurality of channels;  
6                   identifying a second number of stations associated with the WLAN signaling  
7                   field for a second channel of the plurality of channels; and  
8                   determining whether a data portion of the transmission frame contains multi-  
9                   user multiple input multiple output (MU-MIMO) content based at least in part on the  
10                  identified first number of stations and the identified second number of stations.

1                   5.        A method for wireless communication, comprising:  
2                   generating an indication that a first channel of a plurality of channels  
3                   associated with a transmission frame has been punctured, the transmission frame including a  
4                   wireless local area network (WLAN) signaling field;  
5                   identifying information associated with the WLAN signaling field  
6                   corresponding to the punctured first channel; and  
7                   transmitting the indication that the first channel has been punctured and the  
8                   information associated with the WLAN signaling field in a second channel of the plurality of  
9                   channels.

1                   6.        A method for wireless communication at an access point, comprising:  
2                   identifying a tone plan to be used for a transmission frame in a wireless local  
3                   area networks (WLAN);  
4                   allocating resource units (RUs) for a plurality of users for the transmission  
5                   frame;  
6                   determining that a resource unit (RU) of the tone plan is unallocated; and  
7                   generating, for the transmission frame, a station identification in a user  
8                   specific portion of a WLAN signaling field that indicates that the RU is unallocated.

1                   7.        A method for wireless communication at an access point, comprising:

2                   generating an indication that a first channel of a plurality of channels  
3 associated with a transmission frame has been punctured, the transmission frame including a  
4 first wireless local area network (WLAN) signaling field;  
5                   identifying information associated with the WLAN signaling field  
6 corresponding to the punctured first channel;  
7                   transmitting the indication that the first channel has been punctured in a  
8 second WLAN signaling field of the transmission frame; and  
9                   transmitting the information associated with the first WLAN signaling field in  
10 a second channel of the plurality of channels.

1                   8.       The method of claim 6, wherein the second WLAN signaling field of  
2 the transmission frame comprises a bandwidth field indicating both a bandwidth associated  
3 with the transmission frame and a location of the second channel within the plurality of  
4 channels.

1                   9.       A method for wireless communication at a transmitter, comprising:  
2 identifying a bandwidth associated with a transmission frame;  
3 identifying a location for one or more content channels within the bandwidth;  
4 and  
5                   transmitting the transmission frame including a WLAN signaling field  
6 indicating both the bandwidth and the location for the one or more content channels within  
7 the bandwidth of the transmission frame.

1                   10.     A method for wireless communication at a station, comprising:  
2 receiving a first content channel associated with a transmission frame, the first  
3 content channel including a wireless local area network (WLAN) signaling field; and  
4                   identifying, based on at least in part on an indication in the WLAN signaling  
5 field, a first number of users associated with the first content channel and a second number of  
6 users associated with the second content channel of the transmission frame.

1                   11.     An apparatus, comprising:  
2 a memory; and  
3 a processor coupled with the memory and configured to execute instructions  
4 stored on the memory to perform the steps recited in any of claims 1-10.

1                   12.     An apparatus, comprising:  
2                   means for performing the method steps recited in any of claims 1-10.

1                   13.     A computer program comprising executable instructions for causing at  
2 least one computer to perform a method according to any of claims 1-10 when executed.

1                   14.     A non-transitory computer-readable medium comprising instructions  
2 that, when executed, causes an apparatus to perform a method according to any of claims 1-  
3 10.

#### ABSTRACT OF THE DISCLOSURE

Methods, apparatuses, and computer readable media for resource allocation signaling in a high efficiency wireless local area network (WLAN) are disclosed. An access point (AP) may generate a resource unit (RU) size indicator in a first WLAN signaling field, the RU size indicator decodable by a set of stations. The AP may also generate a common user field in a second WLAN signaling field, such that a size of the common user field may be based on the RU size indicator of the first WLAN signaling field. The AP may generate, subsequent to the common user field in the second WLAN signaling field, a station-specific field, such that a position of the station-specific field corresponds to one or more RUs associated with the station-specific field. The AP may then transmit a WLAN preamble that includes the first WLAN signaling field followed by the second WLAN signaling field.




FIG. 1

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

2/43




FIG. 2





FIG. 3




400

FIG. 4A

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS


Inventors: BHARADWAJ et al.

5/43



401

FIG. 4B



402

FIG. 4C






FIG. 5

500

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

7/43

#1	#2	#3	#4	#5	#6	#7	#8	#9	Num of entries
26	26	26	26	26	106				8
26	26	52		26	106				8
52	26	26	26	26	106				8
52	52		26	26	106				8
106	106		26	26	26	26	26	26	8
106	106		26	26	26	26	52		8
106	106		26	26	52	26	26	26	8
106	106		26	26	52	52	52		8
106	106		26	26	106				64
				242					8
				484					8+1
				996					8+1
				2*996					8

605  
610

600

FIG. 6

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

Nuser	B0...B3	Nsts [1]	Nsts [2]	Nsts [3]	Nsts [4]	Nsts [5]	Nsts [6]	Nsts [7]	Nsts [8]	Number of Entries
2	0000~0011	1~4	1							10
	0100~0110	2~4	2							
	0111~1000	3~4	3							
	1001	4	4							
3	0000~0011	1~4	1	1						13
	0100~0110	2~4	2	1						
	0111~1000	3~4	3	1	705					
	1001~1011	2~4	2	2						
	1100	3	3	2						
4	0000~0011	1~4	1	1	1					11
	0100~0110	2~4	2	1	1					
	0111	3	3	1	1					
	1000~1001	2~3	2	2	1					
	1010	2	2	2	2					
5	0000~0011	1~4	1	1	1	1				6
	0100~0101	2~3	2	1	1	1				
6	0000~0010	1~3	1	1	1	1	1			4
	0011	2	2	1	1	1	1			
7	0000~0001	1~2	1	1	1	1	1	1		2
8	0000	1	1	1	1	1	1	1	1	1

700

FIG. 7

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

9/43




FIG. 8




FIG. 9A




FIG. 9B




FIG. 9C




FIG. 10

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

13/43




FIG. 11A




FIG. 11B

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.




FIG. 110D 1100-d




FIG. 110C 1100-c



Number of Entries	RU Size	User indication	Explanation
8		#users	Indicates user number (no load balancing)
1	484	0	Indicates that no user blocks are transmitted
1		1+1	
1		2+1	
1		2+2	
1		3+2	
1		3+3	
1		4+3	
1		4+4	

FIG. 12




FIG. 13A

1300-a






FIG. 13B

1300-b

## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

18/43

<b>Fields in HE-SIG-A for an HE SU PPDU and HE Extended range SU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A1	B0	Reserved	1	Reserved and set to 1
	B1	Format	1	Differentiate between an HE SU PPDU and an HE trigger-based PPDU. Set to 0 for HE trigger-based PPDU Set to 1 for HE SU PPDU This field is reserved for an HE extended range SU PPDU
	B2	UL/DL	1	Indicates whether the PPDU is sent UL or DL Set to 0 for DL Set to 1 for UL This field indicates DL for TDLS
	B3:B8	BSS Color	6	The BSS Color field is an identifier of the BSS Set to all "1" in-lieu of all "0" for no BSS color
	B9:B12	Spatial Reuse	4	
	B13:B19	TXOP Duration	7	Indicates the remaining time in the current TXOP
	B20:B21	Bandwidth	2	For HE SU PPDU Set to 0 for 20 MHz Set to 1 for 40 MHz Set to 2 for 80 MHz Set to 3 for 160/80+80 MHz For HE Extended Range PPDU Set to 0 for 20 MHz Set to 1 for first 106-tone RU in 20 MHz Set to 2 for second 106-tone RU in 20 MHz Value 3 is reserved NOTE- First and second 106-tone RU arranged in increasing order of absolute frequency

FIG. 14A

1401

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

19/43



<b>Fields in HE-SIG-A for an HE SU PPDU and HE Extended range SU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A1	B22:B25	MCS	4	For HE SU PPDU Set to 0 for MCS0 Set to 1 for MCS1 Set to 2 for MCS2 Set to 3 for MCS3 Set to 4 for MCS4 Set to 5 for MCS5 Set to 6 for MCS6 Set to 7 for MCS7 Set to 8 for MCS8 Set to 9 for MCS9 Set to 10 for MCS10 Set to 11 for MCS11 Values 12 - 15 are reserved For HE Extended Range PPDU Set to 0 for MCS0 Set to 1 for MCS1 Set to 2 for MCS2 Values 3 - 15 are reserved

FIG. 14B



1402



## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

20/43

<b>Fields in HE-SIG-A for an HE SU PPDU and HE Extended range SU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A2	B0:B1	CP and LTF Type	2	Set to 0 for 1x HE-LTF + 0.8 us Set to 1 for 2x HE-LTF + 0.8 us Set to 2 for 2x HE-LTF + 1.6 us Set to 3 for 4x HE-LTF + 3.2 us
	B2	Coding	1	Indicates whether BCC or LDPC is used. Set to 0 for BCC Set to 1 for LDPC
	B3	LDPC Extra Symbol	1	Indicates presence of extra OFDM symbol for LDPC Set to 0 for LDPC extra symbol not present Set to 1 for LDPC extra symbol present. NOTE- This field is reserved and set to 1 when Coding field is set to 0
	B4:B6	N_sts	3	Indicates the number of spatial streams. For HE SU PPDU Set to 0 for 1 space time stream Set to 1 for 2 space time stream Set to 2 for 3 space time stream Set to 3 for 4 space time stream Set to 4 for 5 space time stream Set to 5 for 6 space time stream Set to 6 for 7 space time stream Set to 7 for 8 space time stream For HE Extended Range PPDU Set to 0 for 1 space time stream Values 1 - 7 are reserved
	B7	STBC	1	Set to 1 if STBC is used Set to 0 otherwise
	B8	TxBF	1	Set to 1 if a Beamforming steering matrix is applied to the waveform in an SU transmission Set to 0 otherwise
	B9	DCM	1	Set to 1 to indicate that the payload of the SU PPDU is modulated with dual sub-carrier modulation for the MCS. Set to 0 indicates that the payload of the PPDU is not modulated with dual sub-carrier for the MCS.

FIG. 14C

1403

## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

21/43



<b>Fields in HE-SIG-A for an HE SU PPDU and HE Extended range SU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A2	B10:B12	Packet Extension	3	The first two bits (B10, B11) indicate the “a-factor”. The third bit (B12) indicates the “PE-Disambiguity”
	B13	Beam Change	1	Set to 1 indicates that the pre-HE STF portion of the SU PPDU is spatially mapped differently from HE-LTF1. Set to 0 indicates that the pre-HE STF portion of SU PPDU is spatially mapped the same way as HE-LTF1 on each tone.
	B14	Doppler	1	
	B15	Reserved	1	Reserved and set to 1
	B16:B19	CRC	4	CRC of bits 0 - 41 in HE-SIG-A. See 22.3.9.7.1 (CRC calculation for HE-SIG-A). The first bit to be transmitted is bit C3 as explained in 20.3.9.7.1 (CRC calculation for HE-SIG).
	B20:B25	Tail	6	Used to terminate the trellis of the convolution decoder. Set to 0.

FIG. 14D



1404



## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

22/43

<b>Fields in HE-SIG-A for an HE MU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A1	B0	Reserved	1	Reserved and set to 1
	B1	UL/DL	1	Indicates whether the PPDU is sent UL or DL. Set to 0 for DL Set to 1 for UL. This field indicates DL for TDLS. NOTE- The TDLS peer can identify the TDLS frame by ToDS and FromDS fields in the MAC header of the MPDU
	B2:B7	BSS Color	6	The BSS Color field is an identifier of the BSS Set to all "1" in-lieu of all "0" for no BSS color
	B8:B11	Spatial Reuse	4	
	B12:B18	TXOP Duration	7	Indicates the remaining time in the current TXOP
	B19:B21	Bandwidth	3	
	B22:B24	SIGB MCS	3	Indicates MCS of HE-SIG-B Set to 0 for MCS0 Set to 1 for MCS1 Set to 2 for MCS2 Set to 3 for MCS3 Set to 4 for MCS4 Set to 5 for MCS5 Values 6 - 7 are reserved
	B25	SIGB DCM	1	Set to 1 indicates that the HE-SIG-B is modulated with dual sub-carrier modulation for the MCS. Set to 0 indicates that the HE-SIB-B is not modulated with dual sub-carrier modulation for the MCS.

FIG. 15A

1501

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

23/43



<b>Fields in HE-SIG-A for an HE MU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A2	B0:B3	SIGB Number of Symbols/ Number of MU-MIMO users	4	When SIGB compression field=0, indicates the number of HE-SIG-B symbols. Set to 0 for 1 HE-SIG-B symbol Set to 1 for 2 HE-SIG-B symbol Set to 2 for 3 HE-SIG-B symbol Set to 3 for 4 HE-SIG-B symbol Set to 4 for 5 HE-SIG-B symbol Set to 5 for 6 HE-SIG-B symbol Set to 6 for 7 HE-SIG-B symbol Set to 7 for 8 HE-SIG-B symbol Set to 8 for 9 HE-SIG-B symbol Set to 9 for 10 HE-SIG-B symbol Set to 10 for 11 HE-SIG-B symbol Set to 11 for 12 HE-SIG-B symbol Set to 12 for 13 HE-SIG-B symbol Set to 13 for 14 HE-SIG-B symbol Set to 14 for 15 HE-SIG-B symbol Set to 15 for 16 HE-SIG-B symbol When SIGB compression field=1, indicates the number of MU-MIMO users - 1.
	B4	SIGB Compression field	1	Set to 1 for full BW MU-MIMO. Set to 0 otherwise.
	B5:B7	Number of HE-LTF symbols	3	Indicates the number of HE-LTF symbols. Set to 0 for 1 HE-LTF symbol Set to 1 for 2 HE-LTF symbols Set to 2 for 3 HE-LTF symbols Set to 3 for 4 HE-LTF symbols Set to 4 for 5 HE-LTF symbols Set to 5 for 6 HE-LTF symbols Set to 6 for 7 HE-LTF symbols Set to 7 for 8 HE-LTF symbols

FIG. 15B



1502



## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

24/43

Fields in HE-SIG-A for an HE MU PPDU				
Two parts of HE-SIG-A	Bits	Field	# of Bits	Description
HE-SIG-A2	B8:B9	CP+LTF Size	2	Set to 0 for 1x HE-LTF + 0.8 us Set to 1 for 2x HE-LTF + 0.8 us Set to 2 for 2x HE-LTF + 1.6 us Set to 3 for 4x HE-LTF + 3.2 us NOTE - 1x + 0.8 us CP+LTF Type only applicable for full BW MU-MIMO or MU PPDU targeted to single user.
	B10	LDPC Extra Symbol	1	Indicates presence of extra OFDM symbol for LDPC Set to 0 for LDPC extra symbol not present Set to 1 for LDPC extra symbol present.
	B11:B13	Packet Extension	3	The first two bits (B11, B12) indicate the "a-factor". The third bit (B13) indicates the "PE-Disambiguity"
	B14	STBC	1	Set to 1 indicates STBC for all users in the payload and does not apply to SIGB. Set to 0 indicates no STBC for all users in the payload and does not apply to SIGB
	B15	Doppler	1	
	B16:B19	CRC	4	CRC of bits 0 - 41 in HE-SIG-A. See 22.3.9.7.1 (CRC calculation for HE-SIG-A). The first bit to be transmitted is bit C3 as explained in 20.3.9.7.1 (CRC calculation for HE-SIG).
	B20:B25	Tail	6	Used to terminate the trellis of the convolution decoder. Set to 0.

FIG. 15C

1503

## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

25/43

<b>Fields in HE-SIG-A for an HE trigger-based PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A1	B0	Reserved	1	Reserved and set to 1
	B1	Format	1	Differentiate between an HE SU PPDU and an HE trigger-based PPDU. Set to 0 for HE trigger-based PPDU Set to 1 for HE SU PPDU This field is reserved for an HE extended range SU PPDU
	B2:B7	BSS Color	6	The BSS Color field is an identifier of the BSS Set to all "1" in-lieu of all "0" for no BSS color
	B8:B23	Spatial Reuse	16	For 20 MHz bandwidth SR bits B0:B3 corresponding to entire 20 MHz. Each of the SR bits B4:B7, B8:11, and B12:B15 have identical values as B0:B3. For 40 MHz bandwidth SR bits B0:B3 corresponding to first 20 MHz and SR bits B4:B7 corresponding to second 20 MHz. SR Bits B8:B11 and B12:B15 have identical values as B0:B3 and B4:B7, respectively. For 80 MHz bandwidth SR bits B0:B3, B4:B7, B8:B11, and B12:B15 corresponding to first, second, third, and fourth 20 MHz, respectively. For 160 MHz bandwidth SR bits B0:B3, B4:B7, B8:B11, and B12:B15 corresponding to first, second, third, and fourth 40 MHz, respectively. NOTE- First, second, third, and fourth channel arranged in increasing order of absolute frequency
	B24:B25	Bandwidth	2	Set to 0 for 20 MHz Set to 1 for 40 MHz Set to 2 for 80 MHz Set to 3 for 160/80+80 MHz

FIG. 16A

1601

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

26/43



<b>Fields in HE-SIG-A for an HE trigger-based PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A2	B0:B6	TXOP Duration	7	Indicates the remaining time in the current TXOP
	B7:B15	Reserved	9	Reserved and set to 1
	B16:B19	CRC	4	CRC of bits 0 - 41 in HE-SIG-A. See 22.3.9.7.1 (CRC calculation for HE-SIG-A). The first bit to be transmitted is bit C3 as explained in 20.3.9.7.1 (CRC calculation for HE-SIG).
	B20:B25	Tail	6	Used to terminate the trellis of the convolution decoder. Set to 0.

FIG. 16B



1602



## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

27/43

<b>Fields in HE-SIG-A for an HE SU PPDU and HE Extended range SU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A1	B0	Format	1	Differentiate between an HE SU PPDU and an HE trigger-based PPDU. Set to 0 for HE trigger-based PPDU Set to 1 for HE SU PPDU This field is reserved for an HE extended range SU PPDU
	B1	UL/DL	1	Indicates whether the PPDU is sent UL or DL. Set to 0 for DL Set to 1 for UL. This field indicates DL for TDLS.
	B2:B7	BSS Color	6	The BSS Color field is an identifier of the BSS Set to all "1" in-lieu of all"0" for no BSS color
	B8:B11	Spatial Reuse	4	
	B12:B18	TXOP Duration	7	Indicates the remaining time in the current TXOP
	B19:B20	Bandwidth	2	For HE SU PPDU Set to 0 for 20 MHz Set to 1 for 40 MHz Set to 2 for 80 MHz Set to 3 for 160/80+80 MHz For HE Extended Range PPDU Set to 0 for 20 MHz Set to 1 for first 106-tone RU in 20 MHz Set to 2 for second 106-tone RU in 20 MHz Value 3 is reserved NOTE- First and second 106-tone RU arranged in increasing order of absolute frequency.

FIG. 17A

1701

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

28/43



<b>Fields in HE-SIG-A for an HE SU PPDU and HE Extended range SU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A1	B21:B24	MCS	4	For HE SU PPDU Set to 0 for MCS0 Set to 1 for MCS1 Set to 2 for MCS2 Set to 3 for MCS3 Set to 4 for MCS4 Set to 5 for MCS5 Set to 6 for MCS6 Set to 7 for MCS7 Set to 8 for MCS8 Set to 9 for MCS9 Set to 10 for MCS10 Set to 11 for MCS11 Values 12 - 15 are reserved For HE Extended Range PPDU Set to 0 for MCS0 Set to 1 for MCS1 Set to 2 for MCS2 Values 3 - 15 are reserved
	B25	Reserved	1	Reserved and set to 1

FIG. 17B

1702



## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

29/43

<b>Fields in HE-SIG-A for an HE SU PPDU and HE Extended range SU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A2	B0:B1	CP and LTF Type	2	Set to 0 for 1x HE-LTF + 0.8 us Set to 1 for 2x HE-LTF + 0.8 us Set to 2 for 2x HE-LTF + 1.6 us Set to 3 for 4x HE-LTF + 3.2 us
	B2	Coding	1	Indicates whether BCC or LDPC is used. Set to 0 for BCC Set to 1 for LDPC
	B3	LDPC Extra Symbol	1	Indicates presence of extra OFDM symbol for LDPC Set to 0 for LDPC extra symbol not present Set to 1 for LDPC extra symbol present. NOTE- This field is reserved and set to 1 when Coding field is set to 0
	B4:B6	N_sts	3	Indicates the number of spatial streams. For HE SU PPDU Set to 0 for 1 space time stream Set to 1 for 2 space time stream Set to 2 for 3 space time stream Set to 3 for 4 space time stream Set to 4 for 5 space time stream Set to 5 for 6 space time stream Set to 6 for 7 space time stream Set to 7 for 8 space time stream For HE Extended Range PPDU Set to 0 for 1 space time stream Values 1 - 7 are reserved
	B7	STBC	1	Set to 1 if STBC is used Set to 0 otherwise
	B8	TxBF	1	Set to 1 if a Beamforming steering matrix is applied to the waveform in an SU transmission Set to 0 otherwise
	B9	DCM	1	Set to 1 to indicate that the payload of the SU PPDU is modulated with dual sub-carrier modulation for the MCS. Set to 0 indicates that the payload of the PPDU is not modulated with dual sub-carrier for the MCS.

FIG. 17C

1703

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

30/43



<b>Fields in HE-SIG-A for an HE SU PPDU and HE Extended range SU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A2	B10:B12	Packet Extension	3	The first two bits (B10, B11) indicate the “a-factor”. The third bit (B12) indicates the “PE-Disambiguity”
	B13	Beam Change	1	Set to 1 indicates that the pre-HE STF portion of the SU PPDU is spatially mapped differently from HE-LTF1. Set to 0 indicates that the pre-HE STF portion of SU PPDU is spatially mapped the same way as HE-LTF1 on each tone.
	B14	Doppler	1	
	B15	Reserved	1	Reserved and set to 1
	B16:B19	CRC	4	CRC of bits 0 - 41 in HE-SIG-A. See 22.3.9.7.1 (CRC calculation for HE-SIG-A). The first bit to be transmitted is bit C3 as explained in 20.3.9.7.1 (CRC calculation for HE-SIG).
	B20:B25	Tail	6	Used to terminate the trellis of the convolution decoder. Set to 0.

FIG. 17D



1704



## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

31/43

<b>Fields in HE-SIG-A for an HE MU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A1	B0	UL/DL	1	Indicates whether the PPDU is sent UL or DL. Set to 0 for DL Set to 1 for UL. This field indicates DL for TDLS. NOTE- The TDLS peer can identify the TDLS frame by ToDS and FromDS fields in the MAC header of the MPDU
	B1:B6	BSS Color	6	The BSS Color field is an identifier of the BSS Set to all "1" in-lieu of all "0" for no BSS color
	B7:B10	Spatial Reuse	4	
	B11:B17	TXOP Duration	7	Indicates the remaining time in the current TXOP
	B18:B20	Bandwidth	3	
	B21:B23	SIGB MCS	3	Indicates MCS of HE-SIG-B Set to 0 for MCS0 Set to 1 for MCS1 Set to 2 for MCS2 Set to 3 for MCS3 Set to 4 for MCS4 Set to 5 for MCS5 Values 6 - 7 are reserved
	B24	SIGB DCM	1	Set to 1 indicates that the HE-SIG-B is modulated with dual sub-carrier modulation for the MCS. Set to 0 indicates that the HE-SIB-B is not modulated with dual sub-carrier modulation for the MCS.
	B25	Reserved	1	Reserved and set to 1

FIG. 18A

1801

## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

32/43

<b>Fields in HE-SIG-A for an HE MU PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A2	B0:B3	SIGB Number of Symbols/ Number of MU-MIMO users	4	When SIGB compression field=0, indicates the number of HE-SIG-B symbols. Set to 0 for 1 HE-SIG-B symbol Set to 1 for 2 HE-SIG-B symbol Set to 2 for 3 HE-SIG-B symbol Set to 3 for 4 HE-SIG-B symbol Set to 4 for 5 HE-SIG-B symbol Set to 5 for 6 HE-SIG-B symbol Set to 6 for 7 HE-SIG-B symbol Set to 7 for 8 HE-SIG-B symbol Set to 8 for 9 HE-SIG-B symbol Set to 9 for 10 HE-SIG-B symbol Set to 10 for 11 HE-SIG-B symbol Set to 11 for 12 HE-SIG-B symbol Set to 12 for 13 HE-SIG-B symbol Set to 13 for 14 HE-SIG-B symbol Set to 14 for 15 HE-SIG-B symbol Set to 15 for 16 HE-SIG-B symbol When SIGB compression field=1, indicates the number of MU-MIMO users - 1.
	B4	SIGB Compression field	1	Set to 1 for full BW MU-MIMO. Set to 0 otherwise.
	B5:B7	Number of HE-LTF symbols	3	Indicates the number of HE-LTF symbols. Set to 0 for 1 HE-LTF symbol Set to 1 for 2 HE-LTF symbols Set to 2 for 3 HE-LTF symbols Set to 3 for 4 HE-LTF symbols Set to 4 for 5 HE-LTF symbols Set to 5 for 6 HE-LTF symbols Set to 6 for 7 HE-LTF symbols Set to 7 for 8 HE-LTF symbols
	B8:B9	CP+LTF Size	2	Set to 0 for 1x HE-LTF + 0.8 us Set to 1 for 2x HE-LTF + 0.8 us Set to 2 for 2x HE-LTF + 1.6 us Set to 3 for 4x HE-LTF + 3.2 us NOTE - 1x + 0.8 us CP+LTF Type only applicable for full BW MU-MIMO or MU PPDU targeted to single user.

FIG. 18B

1802

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

33/43



<b>Fields in HE-SIG-A for an HE MU PDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A2	B10	LDPC Extra Symbol	1	Indicates presence of extra OFDM symbol for LDPC Set to 0 for LDPC extra symbol not present Set to 1 for LDPC extra symbol present.
	B11:B13	Packet Extension	3	The first two bits (B11, B12) indicate the "a-factor". The third bit (B13) indicates the "PE-Disambiguity"
	B14	STBC	1	Set to 1 indicates STBC for all users in the payload and does not apply to SIGB. Set to 0 indicates no STBC for all users in the payload and does not apply to SIGB
	B15	Doppler	1	
	B16:B19	CRC	4	CRC of bits 0 - 41 in HE-SIG-A. See 22.3.9.7.1 (CRC calculation for HE-SIG-A). The first bit to be transmitted is bit C3 as explained in 20.3.9.7.1 (CRC calculation for HE-SIG).
	B20:B25	Tail	6	Used to terminate the trellis of the convolution decoder. Set to 0.

FIG. 18C



1803



## Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

34/43

Fields in HE-SIG-A for an HE trigger-based PPDU				
Two parts of HE-SIG-A	Bits	Field	# of Bits	Description
HE-SIG-A1	B0	Format	1	Differentiate between an HE SU PPDU and an HE trigger-based PPDU. Set to 0 for HE trigger-based PPDU Set to 1 for HE SU PPDU This field is reserved for an HE extended range SU PPDU
	B1:B6	BSS Color	6	The BSS Color field is an identifier of the BSS Set to all "1" in-lieu of all "0" for no BSS color
	B7:B22	Spatial Reuse	16	For 20 MHz bandwidth SR bits B0:B3 corresponding to entire 20 MHz. Each of the SR bits B4:B7, B8:11, and B12:B15 have identical values as B0:B3. For 40 MHz bandwidth SR bits B0:B3 corresponding to first 20 MHz and SR bits B4:B7 corresponding to second 20 MHz. SR Bits B8:B11 and B12:B15 have identical values as B0:B3 and B4:B7, respectively. For 80 MHz bandwidth SR bits B0:B3, B4:B7, B8:B11, and B12:B15 corresponding to first, second, third, and fourth 20 MHz, respectively. For 160 MHz bandwidth SR bits B0:B3, B4:B7, B8:B11, and B12:B15 corresponding to first, second, third, and fourth 40 MHz, respectively. NOTE- First, second, third, and fourth channel arranged in increasing order of absolute frequency
	B23:B24	Bandwidth	2	Set to 0 for 20 MHz Set to 1 for 40 MHz Set to 2 for 80 MHz Set to 3 for 160/80+80 MHz
	B25	Reserved	1	Reserved and set to 1

FIG. 19A

1901



<b>Fields in HE-SIG-A for an HE trigger-based PPDU</b>				
<b>Two parts of HE-SIG-A</b>	<b>Bits</b>	<b>Field</b>	<b># of Bits</b>	<b>Description</b>
HE-SIG-A2	B0:B6	TXOP Duration	7	Indicates the remaining time in the current TXOP
	B7:B15	Reserved	9	Reserved and set to 1
	B16:B19	CRC	4	CRC of bits 0 - 41 in HE-SIG-A. See 22.3.9.7.1 (CRC calculation for HE-SIG-A). The first bit to be transmitted is bit C3 as explained in 20.3.9.7.1 (CRC calculation for HE-SIG).
	B20:B25	Tail	6	Used to terminate the trellis of the convolution decoder. Set to 0.

FIG. 19B

1902



Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

36/43

Two parts of HE-SIG-A	Bits	Field	# of bits	Description
HE-SIG-A1	B0	Format	1	Differentiate between an HE SU PPDU and HE trigger-based PPDU. Set to 0 for HE trigger-based PPDU Set to 1 for HE SU PPDU. This field is reserved for an HE Extended range SU PPDU.
	B1	Beam Change	1	Set to 1 to indicate that the pre-HE STF portion of the SU PPDU is spatially mapped differently from HE-LTF1. Set to 0 to indicate that the pre-HE STF portion of SU PPDU is spatially mapped the same way as HE-LTF1 on each tone.
	B2	UL/DL	1	Indicates whether the PPDU is sent UL or DL. Set to 0 for DL. This field indicates DL for TDLS. Set to 1 for UL.
	B3:B6	MCS	4	For HE SU PPDU Set to n for MCSn, where n = 0, 1, 2, ..., 11. Values 12 - 15 are reserved For HE Extended Range PPDU Set to n for MCSn where n = 0, 1, 2. Values 3 - 15 are reserved
	B7	DCM	1	Set to 1 to indicate that the payload of the SU PPDU is modulated with dual sub-carrier modulation for the MCS. Set to 0 indicates that the payload of the PPDU is not modulated with dual sub-carrier for the MCS. DCM is only applicable to MCS0, MCS1, MCS3, and MCS4. DCM is only applicable to 1 and 2 spatial streams. DCM is not applicable to STBC.
	B8:B13	BSS Color	6	Set to 1 to 62 to indicate BSS Color of the HE BSS. Set to 0 to indicate BSS Color for public action frames. Set to 63 for MBSS, IBSS, and TDLS, when AP does not provide a BSS Color.
	B14	Reserved	1	Reserved and set to 1
	B15:B18	Spatial Reuse	4	

FIG. 20A

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

37/43



Two parts of HE-SIG-A	Bits	Field	# of bits	Description
HE-SIG-A1	B19; B20	Bandwidth	2	For HE SU PPDU Set to 0 for 20 MHz Set to 1 for 40 MHz Set to 2 for 80 MHz Set to 3 for 160/80+80 MHz
	B21; B22	LTF + CP	2	Set to 0 for 1x HE-LTF + 0.8 us Set to 2 for 2x HE-LTF + 1.6 us
	B23; B25	Nsts	3	Indicates the number of spatial streams. For HE SU PPDU Set to n for n+1 space time stream, where n = 0, 1, 2, ..., 7. For HE Extended Range PPDU Set to 0 for 1 space time stream Value of 1 is TBD Values 2 - 7 are reserved

FIG. 20B



Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

38/43

Two parts of HE-SIG-A	Bits	Field	# of bits	Description
HE-SIG-A2	B0:B6	TXOP Duration	7	Set to 0 to 126 to indicate Txop duration. Duration is not set. Set to 127 to indicate that Txop
	B7	Coding	1	Indicates whether BCC or LDPC is used. Set to 0 for BCC Set to 1 for LDPC
	B8	LDPC Extra Symbol Segment	1	Indicates presence of extra OFDM symbol segment for LDPC Set to 0 for LDPC extra symbol not present Set to 1 for LDPC extra symbol present. NOTE- This field is reserved and set to 1 when Coding field is set to 0
	B9	STBC	1	Set to 1 if STBC is used Set to 0 otherwise
	B10	Tx BF	1	Set to 1 if a Beamforming steering matrix is applied to the waveform in an SU transmission Set to 0 otherwise
	B11:B13	Packet Extension	3	The first two bits (B11, B12) indicate the "a-factor". The third bit (B13) indicates the "PE-Disambiguity"
	B14	Reserved	1	Reserved and set to 1
	B15	Doppler	1	Set to 1 to indicate Doppler procedure is used Set to 0 otherwise
	B16:B19	CRC	4	CRC of bits 0 - 41 in HE-SIG-A. See 22.3.9.7.1 (CRC calculation for HE-SIG-A). The first bit to be transmitted is bit C3 as explained in 20.3.9.7.1 (CRC calculation for HE-SIG).
	B20:B25	Tail	6	Used to terminate the trellis of the convolution decoder. Set to 0.

FIG. 20C

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

39/43

Two parts of HE-SIG-A	Bits	Field	# of bits	Description
HE-SIG-A1	B0	UL/DL	1	Indicates whether the PPDU is sent UL or DL. Set to 0 for DL This field indicates DL for TDLS.
	B1:B3	MCS	3	Indicates MCS of HE-SIG-B Set to n for MCSn, where n = 0, 1, 2, ..., 5 Values 6 - 7 are reserved
	B4	DCM	1	Set to 1 indicates that the HE-SIG-B is modulated with dual sub-carrier modulation for the MCS. Set to 0 indicates that the HE-SIG-B is not modulated with dual sub-carrier modulation for the MCS. DCM is only applicable to MCS0, MCS1, MCS3, and MCS4.
	B5:B10	BSS Color	6	Set to 1 to 62 to indicate BSS Color of the HE BSS. Set to 0 to indicate BSS Color for public action frames. Set to 63 for MBSS, IBSS, and TDLS, when AP does not provide a BSS Color.
	B11:B14	Spatial Reuse	4	
	B15:B17	Bandwidth	3	
	B18:B21	SIGB Number of Symbols/ Number of MU-MIMO Users	4	When SIGB compression field=0, indicates the number of HE-SIG-B symbols. Set to n for n+1 HE-SIG-B symbol, where n = 0, 1, 2, ..., 15 When SIGB compression field=1, indicates the number of MU-MIMO users minus 1.

FIG. 21A

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

40/43

Two parts of HE-SIG-A	Bits	Field	# of bits	Description
HE-SIG-A1	B22	SIGB Compression	1	Set to 1 for full BW MU-MIMO. Set to 0 otherwise.
	B23: B24	LTF and CP	2	Set to 0 for 1x HE-LTF + 0.8 us Set to 2 for 2x HE-LTF + 1.6 us Set to 3 for 4x HE-LTF + 3.2 us NOTE - 1x + 0.8 us CP+LTF Type only applicable for full BW MU-MIMO or MU PPDU targeted to single user.
	B25	Doppler	1	Set to 1 to indicate Doppler procedure is used Set to 0 otherwise

FIG. 21B

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

41/43

Two parts of HE-SIG-A	Bits	Field	# of bits	Description
HE-SIG-A2	B0:B6	Txop Duration	7	Set to 0 to 126 to indicate Txop duration. Set to 127 to indicate that Txop Duration is not set.
	B7	Reserved	1	Reserved and set to 1
	B8:B10	Number of HE-LTF symbols	3	Indicates the number of HE-LTF symbols. Set to n for n+1 HE-LTF symbol, where n = 0, 1, 2,.....7
	B11	LDPC Extra Symbol Segment	1	Indicates presence of extra OFDM symbol segment for LDPC. Set to 0 for LDPC extra symbol not present. Set to 1 for LDPC extra symbol present.
	B12	STBC	1	Set to 1 if STBC is used. Set to 0 otherwise
	B13:B15	Packet Extension	3	The first two bits (B12, B13) indicate the "a-factor". The third bit (B14) indicates the "PE-Disambiguity"
	B16:B19	CRC	4	CRC of bits 0 - 41 in HE-SIG-A. See 22.3.9.7.1 (CRC calculation for HE-SIG-A). The first bit to be transmitted is bit C3 as explained in 20.3.9.7.1 (CRC calculation for HE-SIG).
	B20:B25	Tail	6	Used to terminate the trellis of the convolution decoder. Set to 0.

FIG. 21C

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.  
42/43

Two parts of HE-SIG-A	Bits	Field	# of bits	Description
HE-SIG-A1	B0	Format	1	Differentiate between an HE SU PPDU and an HE trigger-based PPDU. Set to 0 for HE trigger-based PPDU Set to 1 for HE SU PPDU This field is reserved for an HE extended range SU PPDU
	B1:B6	BSS Color	6	Set to 1 to 62 to indicate BSS Color of the HE BSS. Set to 0 to indicate BSS Color of public action frames. Set to 63 for MBSS, IBSS, and TDLS, when AP does not provide a BSS Color.
	B7:B22	Spatial Reuse	16	For 20 MHz bandwidth SR bits B8:B11 corresponding to entire 20 MHz. Each of the SR bits B12:B15, B16:19, and B20:B23 have identical values as B8:B11.  For 40 MHz bandwidth SR bits B8:B11 corresponding to first 20 MHz and SR bits B12:B15 corresponding to second 20 MHz. SR Bits B16:B19 and B20:B23 have identical values as B8:B11 and B12:B15, respectively.  For 80 MHz bandwidth SR bits B8:B11, B12:B15, B16:B19, and B20:B23 corresponding to first, second, third, and fourth 20 MHz, respectively.  For 160 MHz bandwidth SR bits B8:B11, B12:B15, B16:B19, and B20:B23 corresponding to first, second, third, and fourth 40 MHz, respectively. NOTE- First, second, third, and fourth channel arranged in increasing order of absolute frequency
	B23	Reserved	1	Reserved and set to value indicated in the Trigger frame
	B24: B25	Bandwidth	2	Set to 0 for 20 MHz Set to 2 for 80 MHz  Set to 1 for 40 MHz Set to 3 for 160/80+80 MHz

FIG. 22A

Title: PREAMBLE DESIGN ASPECTS FOR HIGH EFFICIENCY WIRELESS LOCAL AREA NETWORKS

Inventors: BHARADWAJ et al.

43/43



Two parts of HE-SIG-A	Bits	Field	# of bits	Description
HE-SIG-A2	B0:B6	Txop Duration	7	Set to 0 to 126 to indicate Txop duration. Set to 127 to indicate that Txop Duration is not set.
	B7:B15	Reserved	9	Reserved and set to value indicated in the Trigger frame
	B16:B19	CRC	4	CRC of bits 0 - 41 in HE-SIG-A. See 22.3.9.7.1 (CRC calculation for HE-SIG-A). The first bit to be transmitted is bit C3 as explained in 20.3.9.7.1 (CRC calculation for HE-SIG).
	B20:B25	Tail	6	Used to terminate the trellis of the convolution decoder. Set to 0.

FIG. 22B

