

3GPP TS 36.101 V8.4.0 (2008-12)

Technical Specification

3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) radio transmission and reception (Release 8)



The present document has been developed within the 3rd Generation Partnership Project (3GPPTM) and may be further elaborated for the purposes of 3GPP.

The present document has not been subject to any approval process by the 3GPP Organizational Partners and shall not be implemented.
This Specification is provided for future development work within 3GPP only. The Organizational Partners accept no liability for any use of this Specification.
Specifications and reports for implementation of the 3GPPTM system should be obtained via the 3GPP Organizational Partners' Publications Offices.

Keywords

radio

3GPP

Postal address

3GPP support office address

650 Route des Lucioles - Sophia Antipolis
Valbonne - FRANCE
Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Internet

<http://www.3gpp.org>

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© 2008, 3GPP Organizational Partners (ARIB, ATIS, CCSA, ETSI, TTA, TTC).
All rights reserved.

UMTS™ is a Trade Mark of ETSI registered for the benefit of its members

3GPP™ is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners

LTE™ is a Trade Mark of ETSI currently being registered for the benefit of its Members and of the 3GPP Organizational Partners

GSM® and the GSM logo are registered and owned by the GSM Association

Contents

| | |
|--|----|
| Foreword..... | 8 |
| 1 Scope..... | 9 |
| 2 References..... | 9 |
| 3 Definitions, symbols and abbreviations..... | 9 |
| 3.1 Definitions..... | 9 |
| 3.2 Symbols..... | 10 |
| 3.3 Abbreviations..... | 11 |
| 4 General..... | 12 |
| 4.1 Relationship between minimum requirements and test requirements..... | 12 |
| 4.2 Applicability of minimum requirements..... | 12 |
| 5 Operating bands and channel arrangement..... | 12 |
| 5.1 General..... | 12 |
| 5.2 Void..... | 12 |
| 5.3 Void..... | 12 |
| 5.4 Void..... | 12 |
| 5.5 Operating bands..... | 12 |
| 5.6 Channel bandwidth..... | 13 |
| 5.6.1 Channel bandwidths per operating band..... | 14 |
| 5.7 Channel arrangement..... | 15 |
| 5.7.1 Channel spacing..... | 15 |
| 5.7.2 Channel raster..... | 15 |
| 5.7.3 Carrier frequency and EARFCN..... | 16 |
| 5.7.4 TX–RX frequency separation..... | 16 |
| 6 Transmitter characteristics..... | 18 |
| 6.1 General..... | 18 |
| 6.2 Transmit power..... | 18 |
| 6.2.1 Void..... | 18 |
| 6.2.2 UE Maximum Output Power..... | 18 |
| 6.2.3 UE Maximum Output power for modulation / channel bandwidth..... | 19 |
| 6.2.4 UE Maximum Output Power with additional requirements..... | 19 |
| 6.2.5 Configured transmitted Power..... | 20 |
| 6.3 Output power dynamics..... | 20 |
| 6.3.1 (Void)..... | 20 |
| 6.3.2 Minimum output power..... | 20 |
| 6.3.2.1 Minimum requirement..... | 20 |
| 6.3.3 Transmit OFF power..... | 21 |
| 6.3.3.1 Minimum requirement..... | 21 |
| 6.3.4 ON/OFF time mask..... | 21 |
| 6.3.4.1 General ON/OFF time mask..... | 21 |
| 6.3.4.2 PRACH and SRS time mask..... | 22 |
| 6.3.5 Power Control..... | 23 |
| 6.3.5.2 Relative Power tolerance..... | 23 |
| 6.4 Control and monitoring functions..... | 24 |
| 6.4.1 Out-of-synchronization handling of output power..... | 24 |
| 6.5 Transmit signal quality..... | 24 |
| 6.5.1 Frequency error..... | 24 |
| 6.5.2 Transmit modulation..... | 24 |
| 6.5.2.1 Error Vector Magnitude..... | 24 |
| 6.5.2.1.1 Minimum requirement..... | 25 |
| 6.5.2.2 IQ-component..... | 25 |
| 6.5.2.2.1 Minimum requirements..... | 25 |
| 6.5.2.3 In-band emissions..... | 25 |
| 6.5.2.3.1 Minimum requirements..... | 25 |

| | | |
|-----------|---|----|
| 6.5.2.4 | Spectrum flatness..... | 26 |
| 6.5.2.4.1 | Minimum requirements..... | 26 |
| 6.6 | Output RF spectrum emissions | 27 |
| 6.6.1 | Occupied bandwidth..... | 27 |
| 6.6.2 | Out of band emission..... | 28 |
| 6.6.2.1 | Spectrum emission mask | 28 |
| 6.6.2.1.1 | Minimum requirement | 28 |
| 6.6.2.2 | Additional Spectrum Emission Mask | 28 |
| 6.6.2.2.1 | Minimum requirement (network signalled value "NS_03") | 28 |
| 6.6.2.2.2 | Minimum requirement (network signalled value "NS_04") | 29 |
| 6.6.2.2.3 | Minimum requirement (network signalled value "NS_06" or "NS_07")..... | 29 |
| 6.6.2.3 | Adjacent Channel Leakage Ratio | 30 |
| 6.6.2.3.1 | Minimum requirement E-UTRA..... | 30 |
| 6.6.2.3.2 | Minimum requirements UTRA..... | 31 |
| 6.6.2.4 | Additional ACLR requirements..... | 31 |
| 6.6.2.4.1 | Minimum requirements (network signalled value "NS_02")..... | 31 |
| 6.6.3 | Spurious emissions..... | 32 |
| 6.6.3.1 | Minimum requirements | 32 |
| 6.6.3.2 | Spurious emission band UE co-existence..... | 32 |
| 6.6.3.3 | Additional spurious emissions..... | 34 |
| 6.6.3.3.1 | Minimum requirement (network signalled value "NS_02" or "NS_05")..... | 34 |
| 6.6.3.3.2 | Minimum requirement (network signalled value "NS_07")..... | 34 |
| 6.7 | Transmit intermodulation | 35 |
| 6.7.1 | Minimum requirement..... | 35 |
| 7 | Receiver characteristics..... | 35 |
| 7.1 | General..... | 35 |
| 7.2 | Diversity characteristics..... | 36 |
| 7.3 | Reference sensitivity power level | 36 |
| 7.3.1 | Minimum requirements (QPSK) | 36 |
| 7.3.2 | Requirement for large transmission configurations..... | 37 |
| 7.4 | Maximum input level..... | 38 |
| 7.4.1 | Minimum requirements | 38 |
| 7.5 | Adjacent Channel Selectivity (ACS) | 38 |
| 7.5.1 | Minimum requirements | 38 |
| 7.6 | Blocking characteristics..... | 39 |
| 7.6.1 | In-band blocking | 40 |
| 7.6.1.1 | Minimum requirements | 40 |
| 7.6.2 | Out of-band blocking | 41 |
| 7.6.2.1 | Minimum requirements | 41 |
| 7.6.3 | Narrow band blocking..... | 41 |
| 7.6.3.1 | Minimum requirements | 41 |
| 7.7 | Spurious response | 42 |
| 7.7.1 | Minimum requirements | 42 |
| 7.8 | Intermodulation characteristics..... | 42 |
| 7.8.1 | Wide band intermodulation..... | 42 |
| 7.8.1.1 | Minimum requirements | 43 |
| 7.8.2 | Void..... | 43 |
| 7.9 | Spurious emissions | 43 |
| 7.9.1 | Minimum requirements | 43 |
| 8.1 | General..... | 44 |
| 8.1.1 | Dual-antenna receiver capability..... | 44 |
| 8.1.1.1 | Simultaneous unicast and MBMS operations..... | 44 |
| 8.1.1.2 | Dual-antenna receiver capability in idle mode | 44 |
| 8.2 | Demodulation of PDSCH (Cell-Specific Reference Symbols)..... | 44 |
| 8.2.1 | FDD (Fixed Reference Channel)..... | 44 |
| 8.2.1.1 | Single-antenna port performance..... | 45 |
| 8.2.1.1.1 | Minimum Requirement QPSK..... | 45 |
| 8.2.1.1.2 | Minimum Requirement 16QAM..... | 45 |
| 8.2.1.1.3 | Minimum Requirement 64QAM..... | 46 |
| 8.2.1.1.4 | Minimum Requirement 1 PRB allocation..... | 46 |
| 8.2.1.2 | Transmit diversity performance..... | 47 |

| | | |
|-----------------------------|--|-----------|
| 8.2.1.3 | Open-loop spatial multiplexing performance | 48 |
| 8.2.1.4 | Closed-loop spatial multiplexing performance | 48 |
| 8.2.1.4.1 | Minimum Requirement Single-Layer Spatial Multiplexing | 48 |
| 8.2.1.4.2 | Minimum Requirement Multi-Layer Spatial Multiplexing | 49 |
| 8.2.1.5 | MU-MIMO | 50 |
| 8.2.1.6 | [Control channel performance: D-BCH and PCH] | 50 |
| 8.2.2 | TDD (Fixed Reference Channel) | 50 |
| 8.2.2.1 | Single-antenna port performance | 50 |
| 8.2.2.1.1 | Minimum Requirement QPSK | 50 |
| 8.2.2.1.2 | Minimum Requirement 16QAM | 51 |
| 8.2.2.1.3 | Minimum Requirement 64QAM | 51 |
| 8.2.2.1.4 | Minimum Requirement 1 PRB allocation | 52 |
| 8.2.2.2 | Transmit diversity performance | 53 |
| 8.2.2.3 | Open-loop spatial multiplexing performance | 53 |
| 8.2.2.4 | Closed-loop spatial multiplexing performance | 53 |
| 8.2.2.5 | MU-MIMO | 53 |
| 8.2.2.6 | [Control channel performance: D-BCH and PCH] | 53 |
| 8.3 | Demodulation of PDSCH (User-Specific Reference Symbols) | 53 |
| 8.4 | Demodulation of PDCCH/PCFICH | 53 |
| 8.4.1 | FDD | 53 |
| 8.4.1.1 | Single-antenna port performance | 54 |
| 8.4.1.2 | Transmit diversity performance | 54 |
| 8.4.2 | TDD | 54 |
| 8.4.2.1 | Single-antenna port performance | 54 |
| 8.4.2.2 | Transmit diversity performance | 54 |
| 8.5 | Demodulation of PHICH | 55 |
| 8.6 | Demodulation of PBCH | 55 |
| 9 | Reporting of Channel State Information | 55 |
| 9.1 | General | 55 |
| 9.2 | CQI definition under AWGN conditions | 55 |
| 9.2.1 | Minimum requirement PUCCH 1-0 | 55 |
| Annex A (normative): | Measurement channels | 56 |
| A.1 | General | 56 |
| A.2 | UL reference measurement channels | 56 |
| A.2.1 | General | 56 |
| A.2.1.1 | Applicability and common parameters | 56 |
| A.2.1.2 | Determination of payload size | 56 |
| A.2.2 | Reference measurement channels for FDD | 57 |
| A.2.2.1 | Full RB allocation | 57 |
| A.2.2.1.1 | QPSK | 57 |
| A.2.2.1.2 | 16-QAM | 57 |
| A.2.2.1.3 | 64-QAM | 57 |
| A.2.2.2 | Partial RB allocation | 57 |
| A.2.2.2.1 | QPSK | 58 |
| A.2.2.2.2 | 16-QAM | 59 |
| A.2.2.2.3 | 64-QAM | 61 |
| A.2.3 | Reference measurement channels for TDD | 61 |
| A.2.3.1 | Full RB allocation | 61 |
| A.2.3.1.1 | QPSK | 61 |
| A.2.3.1.2 | 16-QAM | 61 |
| A.2.3.1.3 | 64-QAM | 61 |
| A.2.3.2 | Partial RB allocation | 61 |
| A.2.3.2.1 | QPSK | 61 |
| A.2.3.2.2 | 16-QAM | 61 |
| A.2.3.2.3 | 64-QAM | 61 |
| A.3 | DL reference measurement channels | 61 |
| A.3.1 | General | 61 |
| A.3.2 | Reference measurement channel for receiver characteristics | 62 |

| | | |
|-----------------------------|--|-----------|
| A.3.3 | Reference measurement channels for PDSCH performance requirements (FDD) | 65 |
| A.3.3.1 | Single-antenna transmission (Common Reference Symbols) | 65 |
| A.3.3.2 | Multi-antenna transmission (Common Reference Symbols)..... | 67 |
| A.3.3.2.1 | Two antenna ports | 67 |
| A.3.3.2.2 | Four antenna ports | 67 |
| A.3.3.3 | [RMC for UE-Specific Reference Symbols]..... | 68 |
| A.3.4 | Reference measurement channels for PDSCH performance requirements (TDD) | 68 |
| A.3.4.1 | Single-antenna transmission (Common Reference Symbols) | 68 |
| A.3.4.2 | Multi-antenna transmission (Common Reference Signals)..... | 70 |
| A.3.4.2.1 | Two antenna ports | 70 |
| A.3.4.2.2 | Four antenna ports | 71 |
| A.3.4.3 | [RMC for UE-Specific Reference Symbols]..... | 72 |
| A.3.5 | Reference measurement channels for PDCCH/PCFICH performance requirements | 72 |
| A.3.5.1 | FDD..... | 72 |
| A.3.5.2 | TDD | 72 |
| Annex B (normative): | Propagation conditions..... | 73 |
| B.1 | Static propagation condition..... | 73 |
| B.2 | Multi-path fading propagation conditions..... | 73 |
| B.2.1 | Delay profiles..... | 73 |
| B.2.2 | Combinations of channel model parameters | 74 |
| B.2.3 | MIMO Channel Correlation Matrices..... | 74 |
| B.2.3.1 | Definition of MIMO Correlation Matrices..... | 74 |
| B.2.3.2 | MIMO Correlation Matrices at High, Medium and Low Level | 76 |
| B.3 | High speed train scenario | 78 |
| Annex C (normative): | Downlink Physical Channels | 80 |
| C.1 | General | 80 |
| C.2 | Set-up | 80 |
| C.3 | Connection | 80 |
| C.3.1 | Measurement of Receiver Characteristics..... | 80 |
| C.3.2 | Measurement of Performance requirements | 81 |
| Annex D (normative): | Characteristics of the interfering signal | 82 |
| D.1 | General | 82 |
| D.2 | Interference signals | 82 |
| Annex E (normative): | Environmental conditions | 83 |
| E.1 | General | 83 |
| E.2 | Environmental | 83 |
| E.2.1 | Temperature..... | 83 |
| E.2.2 | Voltage..... | 83 |
| E.2.3 | Vibration..... | 84 |
| Annex F (normative): | Transmit modulation..... | 85 |
| F.1 | Measurement Point..... | 85 |
| F.2 | Basic Error Vector Magnitude measurement | 85 |
| F.3 | Basic in-band emissions measurement..... | 85 |
| F.4 | Modified signal under test..... | 86 |
| F.5 | Window length..... | 88 |
| F.5.1 | Timing offset | 88 |
| F.5.2 | Window length..... | 88 |
| F.5.3 | Window length for normal CP | 88 |

| | | |
|-------------------------------|-------------------------------------|-----------|
| F.5.4 | Window length for Extended CP | 88 |
| F.6 | Averaged EVM | 89 |
| F.7 | Spectrum Flatness | 89 |
| Annex G (informative): | Change history | 90 |

Foreword

This Technical Specification (TS) has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

Where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

1 Scope

. The present document establishes the minimum RF characteristics and minimum performance requirements for E-UTRA User Equipment (UE).

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] ITU-R Recommendation SM.329-10, "Unwanted emissions in the spurious domain"
- [3] ITU-R Recommendation M.1545: "Measurement uncertainty as it applies to test limits for the terrestrial component of International Mobile Telecommunications-2000".
- [4] 3GPP TS 36.211: "Physical Channels and Modulation".
- [5] 3GPP TS 36.212: "Multiplexing and channel coding".
- [6] 3GPP TS 36.213: "Physical layer procedures".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

Channel edge: The lowest and highest frequency of the carrier, separated by the channel bandwidth.

Channel bandwidth: The RF bandwidth supporting a single E-UTRA RF carrier with the transmission bandwidth configured in the uplink or downlink of a cell. The channel bandwidth is measured in MHz and is used as a reference for transmitter and receiver RF requirements.

Maximum Output Power: The mean power level per carrier of UE measured at the antenna connector in a specified reference condition.

Mean power: When applied to E-UTRA transmission this is the power measured in the operating system bandwidth of the carrier. The period of measurement shall be at least one subframe (1ms) unless otherwise stated.

Occupied bandwidth: The width of a frequency band such that, below the lower and above the upper frequency limits, the mean powers emitted are each equal to a specified percentage $\beta/2$ of the total mean power of a given emission.

Output power: The mean power of one carrier of the UE, delivered to a load with resistance equal to the nominal load impedance of the transmitter.

Reference bandwidth: The bandwidth in which an emission level is specified.

Transmission bandwidth: Bandwidth of an instantaneous transmission from a UE or BS, measured in Resource Block units.

Transmission bandwidth configuration: The highest transmission bandwidth allowed for uplink or downlink in a given channel bandwidth, measured in Resource Block units.

3.2 Symbols

For the purposes of the present document, the following symbols apply:

| | |
|--|---|
| BW_{Channel} | Channel bandwidth |
| E_{RS} | Transmitted energy per RE for reference symbols during the useful part of the symbol, i.e. excluding the cyclic prefix, (average power normalized to the subcarrier spacing) at the eNode B transmit antenna connector |
| \hat{E}_s | The received energy per RE during the useful part of the symbol, i.e. excluding the cyclic prefix, averaged across the allocated RB(s) (average power within the allocated RB(s), divided by the number of RE within this allocation, and normalized to the subcarrier spacing) at the UE antenna connector |
| F | Frequency |
| $F_{\text{Interferer}} \text{ (offset)}$ | Frequency offset of the interferer |
| $F_{\text{Interferer}}$ | Frequency of the interferer |
| F_C | Frequency of the carrier centre frequency |
| $F_{\text{DL_low}}$ | The lowest frequency of the downlink operating band |
| $F_{\text{DL_high}}$ | The highest frequency of the downlink operating band |
| $F_{\text{UL_low}}$ | The lowest frequency of the uplink operating band |
| $F_{\text{UL_high}}$ | The highest frequency of the uplink operating band |

Editor's note : one of the two following definitions for I_o will be used (TBD)

| | |
|----------------------|--|
| I_o | The power spectral density of the total input signal (power averaged over the useful part of the symbols within the transmission bandwidth configuration, divided by the total number of RE for this configuration and normalised to the subcarrier spacing) at the UE antenna connector, including the own-cell downlink signal |
| I_o | The power spectral density of the total input signal at the UE antenna connector (power averaged over the useful part of the symbols within a given bandwidth and normalised to the said bandwidth), including the own-cell downlink signal |
| I_{or} | The total transmitted power spectral density of the own-cell downlink signal (power averaged over the useful part of the symbols within the transmission bandwidth configuration, divided by the total number of RE for this configuration and normalised to the subcarrier spacing) at the eNode B transmit antenna connector |
| \hat{I}_{or} | The total received power spectral density of the own-cell downlink signal (power averaged over the useful part of the symbols within the transmission bandwidth configuration, divided by the total number of RE for this configuration and normalised to the subcarrier spacing) at the UE antenna connector |
| I_{ot} | The received power spectral density of the total noise and interference for a certain RE (average power obtained within the RE and normalized to the subcarrier spacing) as measured at the UE antenna connector |
| N_{cp} | Cyclic prefix length |
| N_{DL} | Downlink EARFCN |
| N_{oc} | The power spectral density of a white noise source (average power per RE normalised to the subcarrier spacing), simulating interference from cells that are not defined in a test procedure, as measured at the UE antenna connector |
| $N_{\text{offs-DL}}$ | Offset used for calculating downlink EARFCN |
| $N_{\text{offs-UL}}$ | Offset used for calculating uplink EARFCN |

| | |
|------------------|---|
| N_{otx} | The power spectral density of a white noise source (average power per RE normalised to the subcarrier spacing) simulating eNode B transmitter impairments as measured at the eNode B transmit antenna connector |
| N_{RB} | Transmission bandwidth configuration, expressed in units of resource blocks |
| N_{UL} | Uplink EARFCN |
| R_{av} | Minimum average throughput per RB |
| $P_{Interferer}$ | Modulated mean power of the interferer |
| ΔF_{OOB} | Δ Frequency of Out Of Band emission |

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

| | |
|---------|--|
| ACLR | Adjacent Channel Leakage Ratio |
| ACS | Adjacent Channel Selectivity |
| A-MPR | Additional Maximum Power Reduction |
| AWGN | Additive White Gaussian Noise |
| BS | Base Station |
| CW | Continuous Wave |
| DL | Downlink |
| EARFCN | E-UTRA Absolute Radio Frequency Channel Number |
| EPRE | Energy Per Resource Element |
| E-UTRA | Evolved UMTS Terrestrial Radio Access |
| EUTRAN | Evolved UMTS Terrestrial Radio Access Network |
| EVM | Error Vector Magnitude |
| FDD | Frequency Division Duplex |
| FRC | Fixed Reference Channel |
| HD-FDD | Half- Duplex FDD |
| MCS | Modulation and Coding Scheme |
| MOP | Maximum Output Power |
| MPR | Maximum Power Reduction |
| MSR | Maximum Sensitivity Reduction |
| OOB | Out-of-band |
| PA | Power Amplifier |
| PSS | Primary Synchronization Signal |
| PSS_RA | PSS-to-RS EPRE ratio for the channel PSS |
| RE | Resource Element |
| REFSENS | Reference Sensitivity power level |
| r.m.s | Root Mean Square |
| SNR | Signal-to-Noise Ratio |
| SSS | Secondary Synchronization Signal |
| SSS_RA | SSS-to-RS EPRE ratio for the channel SSS |
| TDD | Time Division Duplex |
| UE | User Equipment |
| UL | Uplink |
| UMTS | Universal Mobile Telecommunications System |
| UTRA | UMTS Terrestrial Radio Access |
| UTRAN | UMTS Terrestrial Radio Access Network |
| xCH_RA | xCH-to-RS EPRE ratio for the channel xCH in all transmitted OFDM symbols not containing RS |
| xCH_RB | xCH-to-RS EPRE ratio for the channel xCH in all transmitted OFDM symbols containing RS |

4 General

4.1 Relationship between minimum requirements and test requirements

The Minimum Requirements given in this specification make no allowance for measurement uncertainty. The test specification TS 36.xxx section y defines Test Tolerances. These Test Tolerances are individually calculated for each test. The Test Tolerances are used to relax the Minimum Requirements in this specification to create Test Requirements.

The measurement results returned by the Test System are compared - without any modification - against the Test Requirements as defined by the shared risk principle.

The Shared Risk principle is defined in ITU-R M.1545 [3].

4.2 Applicability of minimum requirements

In this specification the Minimum Requirements are specified as general requirements and additional requirements. Where the Requirement is specified as a general requirement, the requirement is mandated to be met in all scenarios

For specific scenarios for which an additional requirement is specified, in addition to meeting the general requirement, the UE is mandated to meet the additional requirements.

5 Operating bands and channel arrangement

5.1 General

The channel arrangements presented in this clause are based on the operating bands and channel bandwidths defined in the present release of specifications.

NOTE: Other operating bands and channel bandwidths may be considered in future releases.

5.2 Void

5.3 Void

5.4 Void

5.5 Operating bands

E-UTRA is designed to operate in the operating bands defined in Table 5.5-1.

Table 5.5-1 E-UTRA operating bands

| E-UTRA Operating Band | Uplink (UL) operating band BS receive UE transmit | Downlink (DL) operating band BS transmit UE receive | Duplex Mode |
|-----------------------------|---|---|----------------|
| | F_{UL_low} – F_{UL_high} | F_{DL_low} – F_{DL_high} | |
| 1 | 1920 MHz – 1980 MHz | 2110 MHz – 2170 MHz | FDD |
| 2 | 1850 MHz – 1910 MHz | 1930 MHz – 1990 MHz | FDD |
| 3 | 1710 MHz – 1785 MHz | 1805 MHz – 1880 MHz | FDD |
| 4 | 1710 MHz – 1755 MHz | 2110 MHz – 2155 MHz | FDD |
| 5 | 824 MHz – 849 MHz | 869 MHz – 894 MHz | FDD |
| 6 | 830 MHz – 840 MHz | 875 MHz – 885 MHz | FDD |
| 7 | 2500 MHz – 2570 MHz | 2620 MHz – 2690 MHz | FDD |
| 8 | 880 MHz – 915 MHz | 925 MHz – 960 MHz | FDD |
| 9 | 1749.9 MHz – 1784.9 MHz | 1844.9 MHz – 1879.9 MHz | FDD |
| 10 | 1710 MHz – 1770 MHz | 2110 MHz – 2170 MHz | FDD |
| 11 | 1427.9 MHz – 1452.9 MHz | 1475.9 MHz – 1500.9 MHz | FDD |
| 12 | 698 MHz – 716 MHz | 728 MHz – 746 MHz | FDD |
| 13 | 777 MHz – 787 MHz | 746 MHz – 756 MHz | FDD |
| 14 | 788 MHz – 798 MHz | 758 MHz – 768 MHz | FDD |
| ... | | | |
| 17 | 704 MHz – 716 MHz | 734 MHz – 746 MHz | FDD |
| ... | | | |
| 33 | 1900 MHz – 1920 MHz | 1900 MHz – 1920 MHz | TDD |
| 34 | 2010 MHz – 2025 MHz | 2010 MHz – 2025 MHz | TDD |
| 35 | 1850 MHz – 1910 MHz | 1850 MHz – 1910 MHz | TDD |
| 36 | 1930 MHz – 1990 MHz | 1930 MHz – 1990 MHz | TDD |
| 37 | 1910 MHz – 1930 MHz | 1910 MHz – 1930 MHz | TDD |
| 38 | 2570 MHz – 2620 MHz | 2570 MHz – 2620 MHz | TDD |
| 39 | 1880 MHz – 1920 MHz | 1880 MHz – 1920 MHz | TDD |
| 40 | 2300 MHz – 2400 MHz | 2300 MHz – 2400 MHz | TDD |

5.6 Channel bandwidth

Requirements in present document are specified for the channel bandwidths listed in Table 5.6-1.

Table 5.6-1 Transmission bandwidth configuration N_{RB} in E-UTRA channel bandwidths

| Channel bandwidth $BW_{Channel}$ [MHz] | 1.4 | 3 | 5 | 10 | 15 | 20 |
|--|-----|----|----|----|----|-----|
| Transmission bandwidth configuration N_{RB} | 6 | 15 | 25 | 50 | 75 | 100 |

Figure 5.6-1 shows the relation between the Channel bandwidth ($BW_{Channel}$) and the Transmission bandwidth configuration (N_{RB}). The channel edges are defined as the lowest and highest frequencies of the carrier separated by the channel bandwidth, i.e. at $F_C \pm BW_{Channel}/2$.




Figure 5.6-1 Definition of Channel Bandwidth and Transmission Bandwidth Configuration for one E-UTRA carrier.

5.6.1 Channel bandwidths per operating band

- a) The requirements in this specification apply to the combination of channel bandwidths and operating bands shown in Table 5.6.1-1. The transmission bandwidth configuration in Table 5.6.1-1 shall be supported for each of the specified channel bandwidths. The same (symmetrical) channel bandwidth is specified for both the TX and RX path.

Table 5.6.1-1: E-UTRA channel bandwidth

| E-UTRA band / channel bandwidth | | | | | | |
|--|---------|-------|--------------------|--------------------|--------------------|--------------------|
| E-UTRA Band | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| 1 | | | Yes | Yes | Yes | Yes |
| 2 | Yes | Yes | Yes | Yes | Yes ^[1] | Yes ^[1] |
| 3 | Yes | Yes | Yes | Yes | Yes ^[1] | Yes ^[1] |
| 4 | Yes | Yes | Yes | Yes | Yes | Yes |
| 5 | Yes | Yes | Yes | Yes ^[1] | | |
| 6 | | | Yes | Yes ^[1] | | |
| 7 | | | Yes | Yes | Yes | Yes ^[1] |
| 8 | Yes | Yes | Yes | Yes ^[1] | | |
| 9 | | | Yes | Yes | Yes ^[1] | Yes ^[1] |
| 10 | | | Yes | Yes | Yes | Yes |
| 11 | | | Yes | Yes ^[1] | Yes ^[1] | Yes ^[1] |
| 12 | Yes | Yes | Yes ^[1] | Yes ^[1] | | |
| 13 | Yes | Yes | Yes ^[1] | Yes ^[1] | | |
| 14 | Yes | Yes | Yes ^[1] | Yes ^[1] | | |
| ... | | | | | | |
| 17 | Yes | Yes | Yes ^[1] | Yes ^[1] | | |
| ... | | | | | | |
| 33 | | | Yes | Yes | Yes | Yes |
| 34 | | | Yes | Yes | Yes | |
| 35 | Yes | Yes | Yes | Yes | Yes | Yes |
| 36 | Yes | Yes | Yes | Yes | Yes | Yes |
| 37 | | | Yes | Yes | Yes | Yes |
| 38 | | | Yes | Yes | | |
| 39 | | | Yes | Yes | Yes | Yes |
| 40 | | | | Yes | Yes | Yes |
| NOTE 1: bandwidth for which a relaxation of the specified UE receiver sensitivity requirement (Clause 7.3) is allowed. | | | | | | |

- b) The use of different (asymmetrical)) channel bandwidth for the TX and RX is not precluded and is intended to form part of a later release.

5.7 Channel arrangement

5.7.1 Channel spacing

The spacing between carriers will depend on the deployment scenario, the size of the frequency block available and the channel bandwidths. The nominal channel spacing between two adjacent E-UTRA carriers is defined as following:

$$\text{Nominal Channel spacing} = (\text{BW}_{\text{Channel}(1)} + \text{BW}_{\text{Channel}(2)})/2$$

where $\text{BW}_{\text{Channel}(1)}$ and $\text{BW}_{\text{Channel}(2)}$ are the channel bandwidths of the two respective E-UTRA carriers. The channel spacing can be adjusted to optimize performance in a particular deployment scenario.

5.7.2 Channel raster

The channel raster is 100 kHz for all bands, which means that the carrier centre frequency must be an integer multiple of 100 kHz.

5.7.3 Carrier frequency and EARFCN

The carrier frequency in the uplink and downlink is designated by the E-UTRA Absolute Radio Frequency Channel Number (EARFCN) in the range 0 - 65535. The relation between EARFCN and the carrier frequency in MHz for the downlink is given by the following equation, where F_{DL_low} and $N_{Offs-DL}$ are given in table 5.7.3-1 and N_{DL} is the downlink EARFCN.

$$F_{DL} = F_{DL_low} + 0.1(N_{DL} - N_{Offs-DL})$$

The relation between EARFCN and the carrier frequency in MHz for the uplink is given by the following equation where F_{UL_low} and $N_{Offs-UL}$ are given in table 5.7.3-1 and N_{UL} is the uplink EARFCN.

$$F_{UL} = F_{UL_low} + 0.1(N_{UL} - N_{Offs-UL})$$

Table 5.7.3-1 E-UTRA channel numbers

| E-UTRA Operating Band | Downlink | | | Uplink | | |
|-----------------------------|---------------------|---------------|-------------------|---------------------|---------------|-------------------|
| | F_{DL_low} (MHz) | $N_{Offs-DL}$ | Range of N_{DL} | F_{UL_low} (MHz) | $N_{Offs-UL}$ | Range of N_{UL} |
| 1 | 2110 | 0 | 0 – 599 | 1920 | 18000 | 18000 – 18599 |
| 2 | 1930 | 600 | 600 – 1199 | 1850 | 18600 | 18600 – 19199 |
| 3 | 1805 | 1200 | 1200 – 1949 | 1710 | 19200 | 19200 – 19949 |
| 4 | 2110 | 1950 | 1950 – 2399 | 1710 | 19950 | 19950 – 20399 |
| 5 | 869 | 2400 | 2400 – 2649 | 824 | 20400 | 20400 – 20649 |
| 6 | 875 | 2650 | 2650 – 2749 | 830 | 20650 | 20650 – 20749 |
| 7 | 2620 | 2750 | 2750 – 3449 | 2500 | 20750 | 20750 – 21449 |
| 8 | 925 | 3450 | 3450 – 3799 | 880 | 21450 | 21450 – 21799 |
| 9 | 1844.9 | 3800 | 3800 – 4149 | 1749.9 | 21800 | 21800 – 22149 |
| 10 | 2110 | 4150 | 4150 – 4749 | 1710 | 22150 | 22150 – 22749 |
| 11 | 1475.9 | 4750 | 4750 – 4999 | 1427.9 | 22750 | 22750 – 22999 |
| 12 | 728 | 5000 | 5000 - 5179 | 698 | 23000 | 23000 - 23179 |
| 13 | 746 | 5180 | 5180 – 5279 | 777 | 23180 | 23180 – 23279 |
| 14 | 758 | 5280 | 5280 – 5379 | 788 | 23280 | 23280 – 23379 |
| ... | | | | | | |
| 17 | 734 | 5730 | 5730 – 5849 | 704 | 23730 | 23730 - 23849 |
| ... | | | | | | |
| 33 | 1900 | 26000 | 36000 – 36199 | 1900 | 36000 | 36000 – 36199 |
| 34 | 2010 | 26200 | 36200 – 36349 | 2010 | 36200 | 36200 – 36349 |
| 35 | 1850 | 26350 | 36350 – 36949 | 1850 | 36350 | 36350 – 36949 |
| 36 | 1930 | 26950 | 36950 – 37549 | 1930 | 36950 | 36950 – 37549 |
| 37 | 1910 | 27550 | 37550 – 37749 | 1910 | 37550 | 37550 – 37749 |
| 38 | 2570 | 27750 | 37750 – 38249 | 2570 | 37750 | 37750 – 38249 |
| 39 | 1880 | 28250 | 38250-38649 | 1880 | 38250 | 38250-38649 |
| 40 | 2300 | 28650 | 38650-39649 | 2300 | 38650 | 38650-39649 |

5.7.4 TX–RX frequency separation

- a) The default E-UTRA TX channel (carrier centre frequency) to RX channel (carrier centre frequency) separation is specified in Table 5.7.4-1 for the TX and RX channel bandwidths defined in Table 5.6.1-1

Table 5.7.4-1: Default UE TX-RX frequency separation

| Frequency Band | TX - RX carrier centre frequency separation |
|----------------|---|
| 1 | 190 MHz |
| 2 | 80 MHz. |
| 3 | 95 MHz. |
| 4 | 400 MHz |
| 5 | 45 MHz |
| 6 | 45 MHz |
| 7 | 120 MHz |
| 8 | 45 MHz |
| 9 | 95 MHz |
| 10 | 400 MHz |
| 11 | 48 MHz |
| 12 | 30 MHz |
| 13 | -31 MHz |
| 14 | -30 MHz |
| 17 | 30 MHz |

- b) The use of other TX channel to RX channel carrier centre frequency separation is not precluded and is intended to form part of a later release.

6 Transmitter characteristics

6.1 General

Unless otherwise stated, the transmitter characteristics are specified at the antenna connector of the UE with a single transmit antenna. For UE with integral antenna only, a reference antenna with a gain of 0 dBi is assumed.

6.2 Transmit power

6.2.1 Void

6.2.2 UE Maximum Output Power

The following UE Power Classes define the maximum output power. The power is the broadband transmit power of the UE, i.e. the power in the channel bandwidth (clause 5.2) of the radio access mode. The period of measurement shall be at least one sub frame (1ms).

Table 6.2.2-1: UE Power Class

| E-UTRA Band | Class 1 (dBm) | Tolerance (dB) | Class 2 (dBm) | Tolerance (dB) | Class 3 (dBm) | Tolerance (dB) | Class 4 (dBm) | Tolerance (dB) |
|--|------------------|-------------------|------------------|-------------------|------------------|-------------------|------------------|-------------------|
| 1 | | | | | 23 | ± 2 | | |
| 2 | | | | | 23 | ± 2 | | |
| 3 | | | | | 23 | ± 2 | | |
| 4 | | | | | 23 | ± 2 | | |
| 5 | | | | | 23 | ± 2 | | |
| 6 | | | | | 23 | ± 2 | | |
| 7 | | | | | 23 | ± 2 | | |
| 8 | | | | | 23 | ± 2 | | |
| 9 | | | | | 23 | ± 2 | | |
| 10 | | | | | 23 | ± 2 | | |
| 11 | | | | | 23 | ± 2 | | |
| 12 | | | | | 23 | ± 2 | | |
| 13 | | | | | 23 | ± 2 | | |
| 14 | | | | | 23 | ± 2 | | |
| ... | | | | | | | | |
| 17 | | | | | 23 | ± 2 | | |
| ... | | | | | | | | |
| 33 | | | | | 23 | ± 2 | | |
| 34 | | | | | 23 | ± 2 | | |
| 35 | | | | | 23 | ± 2 | | |
| 36 | | | | | 23 | ± 2 | | |
| 37 | | | | | 23 | ± 2 | | |
| 38 | | | | | 23 | ± 2 | | |
| 39 | | | | | 23 | ± 2 | | |
| 40 | | | | | 23 | ± 2 | | |
| Note 1. The above tolerances are applicable for UE(s) that support up to 4 E-UTRA operating bands. For UE(s) that support 5 or more E-UTRA bands the maximum output power is expected to decrease with each additional band and is FFS | | | | | | | | |

6.2.3 UE Maximum Output power for modulation / channel bandwidth

For UE Power Class 3, the allowed Maximum Power Reduction (MPR) for the maximum output power in Table 6.2.2-1 due to higher order modulation and transmit bandwidth configuration (resource blocks) is specified in Table 6.2.3-1.

Table 6.2.3-1: Maximum Power Reduction (MPR) for Power Class 3

| Modulation | Channel bandwidth / Transmission bandwidth configuration (RB) | | | | | | MPR (dB) |
|------------|---|---------|-------|--------|--------|--------|----------|
| | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz | |
| QPSK | > 5 | > 4 | > 8 | > 12 | > 16 | > 18 | ≤ 1 |
| 16 QAM | ≤ 5 | ≤ 4 | ≤ 8 | ≤ 12 | ≤ 16 | ≤ 18 | ≤ 1 |
| 16 QAM | > 5 | > 4 | > 8 | > 12 | > 16 | > 18 | ≤ 2 |

6.2.4 UE Maximum Output Power with additional requirements

Additional ACLR and spectrum emission requirements can be signalled by the network to indicate that the UE shall meet also additional requirements in a specific deployment scenario. To meet these additional requirements the concept of Additional Maximum Power Reduction A-MPR is introduced for the output power in Table 6.2.2-1

For UE Power Class 3 the specific requirements and identified sub-clauses are specified in table 6.2.4-1 along with the allowed A-MPR values that may be used to meet these requirements. The allowed A-MPR values specified below in Table 6.2.4-1 are in addition to the allowed MPR requirements specified in clause 6.2.3.

Table 6.2.4-1: Additional Maximum Power Reduction (A-MPR) / Spectrum Emission requirements

| Network Signalling value | Requirements (sub-clause) | E-UTRA Band | Channel bandwidth (MHz) | Resources Blocks | A-MPR (dB) |
|------------------------------------|---------------------------|------------------|-------------------------|------------------|---------------|
| NS_01 | - | - | - | | |
| NS_02 | 6.6.2.4.1 6.6.3.3.1 | 1, 6, 9, 11 | 10 | > 42 | ≤ 1 |
| | | | 15 | > 44 | ≤ 1 |
| | | | 20 | > 48 | ≤ 1 |
| NS_03 | 6.6.2.2.1 | 2, 4, 10, 35, 36 | 3 | >5 | ≤ 1 |
| | 6.6.2.2.1 | 2, 4, 10, 35, 36 | 5 | >6 | ≤ 1 |
| | 6.6.2.2.1 | 2, 4, 10, 35, 36 | 10 | >6 | ≤ 1 |
| | 6.6.2.2.1 | 2, 4, 10, 35, 36 | 15 | >8 | ≤ 1 |
| | 6.6.2.2.1 | 2, 4, 10, 35, 36 | 20 | >10 | ≤ 1 |
| NS_04 | 6.6.2.2.2 | TBD | TBD | TBD | |
| NS_05 | 6.6.3.3.1 | 1 | 10, 15, 20 | ≥ 50 for QPSK | ≤ 1 |
| NS_06 | 6.6.2.2.3 | 12, 13, 14, 17 | 1.4, 3, 5, 10 | n/a | n/a |
| NS_07 | 6.6.2.2.3 6.6.3.3.2 | 13 | 10 | Table 6.2.4-2 | Table 6.2.4-2 |
| .. | | | | | |
| NS_32 | - | - | - | - | - |
| Note: $0 \leq \text{A-MPR} \leq 3$ | | | | | |

Table 6.2.4-2: A-MPR for “NS07”

| | Region A | Region B | Region C |
|---------------|----------|----------|----------|
| [RB_start] | TBD | TBD | TBD |
| [Max. L_CRBs] | TBD | TBD | TBD |
| A-MPR (dB) | TBD | TBD | TBD |

6.2.5 Configured transmitted Power

P_{CMAX} is the configured UE transmitted power defined as follows;

$$P_{\text{CMAX}} = \text{MIN} \{P_{\text{EMAX}}, P_{\text{UMAX}}\}$$

Where

- P_{EMAX} is the maximum allowed power configured by higher layers and defined in [TS36.331]
- P_{UMAX} is the maximum UE power for the UE power class specified in section 6.2.2 modified by section 6.2.3 and section 6.2.4

The UE shall not exceed P_{CMAX} with the tolerances defined in sub-clause 6.2.5-1

Table 6.2.5-1: PCMAX tolerance

| P_{CMAX} (dBm) | Tolerance (dB) | |
|--------------------------------|----------------|-----------|
| | (Normal) | (Extreme) |
| 23 | [± 2.0] | [± 2.0] |
| 22 | [± 2.5] | [± TBD] |
| 21 | [± 3.0] | [± TBD] |
| 20 | [± TBD] | [± TBD] |
| $14 \leq P_{\text{CMAX}} < 20$ | [± TBD] | [± TBD] |
| $9 \leq P_{\text{CMAX}} < 14$ | [± TBD] | [± TBD] |
| $-40 \leq P_{\text{CMAX}} < 9$ | [± TBD] | [± TBD] |

6.3 Output power dynamics

6.3.1 (Void)

6.3.2 Minimum output power

The minimum controlled output power of the UE is defined as the broadband transmit power of the UE, i.e. the power in the channel bandwidth for all transmit bandwidth configurations (resource blocks), when the power is set to a minimum value.

6.3.2.1 Minimum requirement

The minimum output power is defined as the mean power in one sub-frame (1ms). The minimum output power shall not exceed the values specified in Table 6.3.2.1-1.

Table 6.3.2.1-1: Minimum output power

| | Channel bandwidth / Minimum output power / measurement bandwidth | | | | | |
|-----------------------|--|---------|---------|---------|----------|--------|
| | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Minimum output power | -40 dBm | | | | | |
| Measurement bandwidth | 1.08 MHz | 2.7 MHz | 4.5 MHz | 9.0 MHz | 13.5 MHz | 18 MHz |

6.3.3 Transmit OFF power

Transmit OFF power is defined as the mean power when the transmitter is OFF. The transmitter is considered to be OFF when the UE is not allowed to transmit or during periods when the UE is not transmitting a sub-frame. During measurements gaps, the UE is not considered to be OFF.

6.3.3.1. Minimum requirement

The transmit OFF power is defined as the mean power in a duration of at least one sub-frame (1ms) excluding any transient periods. The transmit OFF power shall not exceed the values specified in Table 6.3.3.1-1.

Table 6.3.3.1-1: Transmit OFF power

| | Channel bandwidth / Minimum output power / measurement bandwidth | | | | | |
|-----------------------|--|---------|---------|---------|----------|--------|
| | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Transmit OFF power | -50 dBm | | | | | |
| Measurement bandwidth | 1.08 MHz | 2.7 MHz | 4.5 MHz | 9.0 MHz | 13.5 MHz | 18 MHz |

6.3.4 ON/OFF time mask

6.3.4.1 General ON/OFF time mask

The General ON/OFF time mask defines the observation period between Transmit OFF and ON power and between Transmit ON and OFF power. ON/OFF scenarios include; the beginning or end of DTX, measurement gap, contiguous, and non contiguous transmission

The OFF power measurement period is defined in a duration of at least one sub-frame excluding any transient periods. The ON power measurement period is defined as the mean power over one sub-frame excluding any transient period.

There are no additional requirements on UE transmit power beyond that which is required in clause 6.3.1 and clause 6.6.2.3




Figure 6.3.4.1-1: General ON/OFF time mask

6.3.4.2 PRACH and SRS time mask

In the case a single SRS transmission, the ON measurement period is defined as the mean power over the entire symbol duration

For the PRACH Power / Time mask defines the observation period between PRACH transmissions. The PRACH ON power is specified as the mean power over the PRACH measurement period excluding any transient periods. The measurement period for different PRACH preamble format is specified in table 6.3.4.2-1.

There are no additional requirements on UE transmit power beyond that which is required in clause 6.3.1 and clause 6.6.2.3

Table 6.3.4.2-1: PRACH ON power measurement period

| PRACH preamble format | Measurement period (ms) |
|-----------------------|-------------------------|
| 0 | 0.9031 |
| 1 | 1.4844 |
| 2 | 1.8031 |
| 3 | 2.2844 |
| 4 | 0.1479 |




Figure 6.3.4.2-1: PRACH and SRS ON/OFF time mask

6.3.5 Power Control

6.3.5.1 Absolute Power Tolerance

Absolute power tolerance is the ability of the UE transmitter to set its initial output power to a specific value for the first sub-frame at the start of a contiguous transmission or non-contiguous transmission with a transmission gap larger than 20ms. This tolerance includes the channel estimation error (the absolute RSRP accuracy requirement specified in clause 9.1 of TS 36.133)

In the case of a PRACH transmission, the absolute tolerance is specified for the first preamble. The absolute power tolerance includes the channel estimation error (the absolute RSRP accuracy requirement specified in clause 9.1 of TS 36.133).

6.3.5.1.1 Minimum requirements

The minimum requirement for absolute power tolerance is given in Table 6.3.5.1.1-1 over the power range bounded by the Maximum output power as defined in sub clause 6.3.1 and the Minimum output power as defined in sub clause 6.2

Table 6.3.5.1.1-1: Absolute power tolerance

| Conditions | Tolerance |
|------------|-------------|
| Normal | [± 10.5] dB |
| Extreme | [± 13.5] dB |

6.3.5.2 Relative Power tolerance

Relative power tolerance is the ability of the UE transmitter to set its output power to a specific value for the 2nd and subsequent sub-frame after the start of a contiguous transmission or non-contiguous transmission with a transmission gap ≤20ms.

In the case of a PRACH transmission, the relative tolerance is the ability of the UE transmitter to set its output power to a specific value for the 2nd and subsequent preambles. The measurement period for the PRACH preamble is specified in Table 6.3.4.2-1.

6.3.5.2.1 Minimum requirements

The UE shall meet the requirements specified in Table 6.3.5.2.1-1 and. Table 6.3.5.2.1-2

To account for RF Power amplifier mode changes a number of exception are allowed. The number of exceptions allowed where the power tolerance limit is a maximum of [±6.0dB] in Table 6.3.5.3.1-1 and Table 6.3.5.3.1-2 is TBD

Table 6.3.5.2.1-1 Relative Power Tolerance for Transmission (normal conditions)

| power step size (Up or down) ΔP [dB] | PUSCH/ PUCCH [dB] | SRS [dB] | PRACH [dB] |
|---|-----------------------------------|-------------|------------------------------|
| 0 $\leq \Delta P \leq$ 4 | [± MAX {2.0, $\Delta P/2+2$ }] | | [± MAX {0.5, $\Delta P/2$ }] |
| 4 $< \Delta P \leq$ 10 | [± 4.0] | | [± 3.0] ¹ |
| 10 $< \Delta P \leq$ 15 | [± 5.0] | | n/a |
| 15 $< \Delta P \leq$ 20 | [± 6.0] | | n/a |
| 20 $< \Delta P$ | [± 6.0] | | n/a |
| Note | | | |
| 1. For PRACH maximum power step is 6 dB | | | |

Table 6.3.5.2.1-2 Relative Power Tolerance for Transmission (extreme conditions)

| power step size (Up or down) ΔP [dB] | | | PUSCH/ PUCCH [dB] | SRS [dB] | PRACH [dB] |
|---|----------------------|----|---|-------------|---|
| 0 | $\leq \Delta P \leq$ | 4 | $[\pm \text{MAX}\{4.0, \Delta P/2+4\}]$ | | $[\pm \text{MAX}\{4.0, \Delta P/2+4\}]$ |
| 4 | $< \Delta P \leq$ | 10 | $[\pm 6.0]$ | | $[\pm 5.0]$ |
| 10 | $< \Delta P \leq$ | 15 | $[\pm 7.0]$ | | n/a |
| 15 | $< \Delta P \leq$ | 20 | $[\pm 8.0]$ | | n/a |
| 20 | $< \Delta P$ | | $[\pm 8.0]$ | | n/a |
| Note 1. For PRACH maximum power step is 6 dB | | | | | |

For a sub-frame excluding a SRS symbol, the power change is defined as the relative power difference between the mean power of the original (reference) sub-frame and the mean power of the target subframe, not including the transient duration. . The mean power of successive sub-frames shall be calculated according to Figure 6.3.5.2.1-1

The observation period for a power step tolerance for a sub-frame which includes SRS symbol is FFS and requirements for handling PUCCH and SRS symbols power steps in the same sub-frame to be progressed.

During the transient period there are no additional requirements on UE transmit power beyond what is required in sub – clause 6.3.1 and clause 6.6.2.3

Figure 6.3.5.2.1-1: Power step template (TBD)

6.4 Control and monitoring functions

6.4.1 Out-of-synchronization handling of output power

6.5 Transmit signal quality

6.5.1 Frequency error

The UE modulated carrier frequency shall be accurate to within ± 0.1 PPM observed over a period of one time slot (0.5 ms) compared to the carrier frequency received from the E-UTRA Node B

6.5.2 Transmit modulation

Transmit modulation defines the modulation quality for expected in-channel RF transmissions from the UE. This transmit modulation limit is specified in terms of; an Error Vector Magnitude (EVM) for the allocated resources blocks (RB), an I/Q component and an in-band emissions for the non-allocated RB.

All the parameters defined in clause 6.5.2 are defined using the measurement methodology specified in Annex F.

6.5.2.1 Error Vector Magnitude

The Error Vector Magnitude is a measure of the difference between the reference waveform and the measured waveform. This difference is called the error vector. Before calculating the EVM the measured waveform is corrected by the sample timing offset and RF frequency offset. Then the IQ origin offset shall be removed from the measured waveform before calculating the EVM.

The measured waveform is further modified by selecting the absolute phase and absolute amplitude of the Tx chain. The EVM result is defined after the front-end IDFT as the square root of the ratio of the mean error vector power to the mean reference power expressed as a %. The basic EVM measurement interval is one slot in the time domain.

6.5.2.1.1 Minimum requirement

The RMS average of the basic EVM measurements for 10 consecutive sub-frames for the different modulations schemes shall not exceed the values specified in Table 6.5.2.1.1-1 for the parameters defined in Table 6.5.2.1.1-2.

Table 6.5.2.1.1-1: Minimum requirements for Error Vector Magnitude

| Parameter | Unit | Level |
|-----------|------|-------|
| QPSK | % | 17.5 |
| 16QAM | % | 12.5 |
| 64QAM | % | [tbd] |

Table 6.5.2.1.1-2: Parameters for Error Vector Magnitude

| Parameter | Unit | Level |
|--------------------------|------|-------------------|
| UE Output Power | dBm | ≥ -40 |
| Operating conditions | | Normal conditions |
| Basic measurement period | | slot |

6.5.2.2 IQ-component

The IQ origin offset is the phase and amplitude of an additive sinusoid waveform that has the same frequency as the reference waveform carrier frequency. The measurement interval is one time.

6.5.2.2.1 Minimum requirements

The relative carrier leakage power (IQ origin offset power) shall not exceed the values specified in Table 6.5.2.2.1-1.

Table 6.5.2.2.1-1: Minimum requirements for Relative Carrier Leakage Power

| LO Leakage | Parameters | Relative Limit (dBc) |
|------------|--|----------------------|
| | Output power > 0 dBm | -25 |
| | -30 dBm \leq Output power ≤ 0 dBm | -20 |
| | -40 dBm \leq Output power < -30 dBm | -10 |

6.5.2.3 In-band emissions

The in-band emission is defined as the average across 12 sub-carrier and as a function of the RB offset from the edge of the allocated UL transmission bandwidth. The in-band emission is measured as the ratio of the UE output power in a non-allocated RB to the UE output power in an allocated RB. The basic in-band emissions measurement interval is defined over one slot in the time domain.

6.5.2.3.1 Minimum requirements

The relative in-band emission shall not exceed the values specified in Table 6.5.2.3.1-1.

Table 6.5.2.3.1-1: Minimum requirements for in-band emissions

| Parameter Description | Unit | Limit (Note 1) | Applicable Frequencies |
|-----------------------|------|----------------|------------------------|
|-----------------------|------|----------------|------------------------|

| | | | | |
|----------|-----|--|----------------------------------|--------------------------------|
| General | dB | $\max\{-30, -25-10\cdot\log_{10}(N_{RB}/L_{CRBs}),$ $20\cdot\log_{10}EVM-3-5\cdot(\Delta_{RB}-1)/L_{CRBs},$ $-57\text{ dBm}/180\text{ kHz}-P_{RB}\}$ | | Any non-allocated (Note 2) |
| IQ Image | dB | -25 | | Image frequencies (Notes 2, 3) |
| DC | dBc | -25 | Output power > 0 dBm | LO frequency (Notes 4, 5) |
| | | -20 | -30 dBm ≤ Output power ≤ 0 dBm | |
| | | -10 | -40 dBm ≤ Output power < -30 dBm | |
| | | | | |

Note 1: The minimum requirement is calculated from any of the listed requirements, whichever is the highest power.

Note 2: The measurement bandwidth is 1 RB and the limit is expressed as a ratio of measured power in one non-allocated RB to the measured average power per allocated RB, where the averaging is done across all allocated RBs.

Note 3: The applicable frequencies for this limit are those that are enclosed in the reflection of the allocated bandwidth, based on symmetry with respect to the centre carrier frequency, but excluding any allocated RBs.

Note 4: The measurement bandwidth is 1 RB and the limit is expressed as a ratio of measured power in one non-allocated RB to the measured total power in all allocated RBs.

Note 5: The applicable frequencies for this limit are those that are enclosed in the RBs containing the DC frequency if N_{RB} is odd, or in the two RBs immediately adjacent to the DC frequency if N_{RB} is even, but excluding any allocated RB.

Note 6: L_{CRBs} is the Transmission Bandwidth (see Figure 5.4.2-1).

Note 7: N_{RB} is the Transmission Bandwidth Configuration (see Figure 5.4.2-1).

Note 8: Δ_{RB} is the starting frequency offset between the allocated RB and the measured non-allocated RB (e.g. $\Delta_{RB} = 1$ or $\Delta_{RB} = -1$ for the first adjacent RB outside of the allocated bandwidth).

Note 9: P_{RB} is the transmitted power per 180 kHz in allocated RBs, measured in dBm.

6.5.2.4 Spectrum flatness

The spectrum flatness is defined as a relative power variation across the subcarriers of all RB of the allocated UL block. The spectrum flatness is measured as a dB value comparing the output power of a subcarrier and the average power per subcarrier. The measurement interval is one time.

6.5.2.4.1 Minimum requirements

The spectrum flatness shall not exceed the values specified in Table 6.5.2.4.1-1 for normal conditions and Table 6.5.2.4.1-2 for extreme conditions.

Table 6.5.2.4.1-1: Minimum requirements for spectrum flatness (normal conditions)


| Spectrum Flatness | Relative Limit (dB) |
|---|---------------------|
| If $F_{UL_measurement} - F_{UL_low} \geq 3\text{MHz}$ and If $F_{UL_high} - F_{UL_measurement} \geq 3\text{ MHz}$ | +2/-2 |
| If $F_{UL_measurement} - F_{UL_low} < 3\text{ MHz}$ or If $F_{UL_high} - F_{UL_measurement} < 3\text{ MHz}$ | +3/-5 |
| Note 1. F_{UL_low} and F_{UL_high} refers to each E-UTRA frequency band specified in Table 5.2-1 2. $F_{UL_measurement}$ refers to frequency tone being evaluated | |

Table 6.5.2.4.1-2: Minimum requirements for spectrum flatness (extreme conditions)

| Spectrum Flatness | Relative Limit (dB) |
|--|---------------------|
| If $F_{UL_measurement} - F_{UL_low} \geq 5\text{MHz}$ and If $F_{UL_high} - F_{UL_measurement} \geq 5\text{ MHz}$ | +2/-2 |
| If $F_{UL_measurement} - F_{UL_low} < 5\text{ MHz}$ and If $F_{UL_high} - F_{UL_measurement} < 5\text{ MHz}$ | +4/-8 |
| Note 3. F_{UL_low} and F_{UL_high} refers to each E-UTRA frequency band specified in Table 5.2-1 4. $F_{UL_measurement}$ refers to frequency tone being evaluated | |

6.6 Output RF spectrum emissions

The output UE transmitter spectrum consists of the three components; the emission within the occupied bandwidth (channel bandwidth), the Out Of Band (OOB) emissions and the far out spurious emission domain.

**Figure 6.6-1: Transmitter RF spectrum**

6.6.1 Occupied bandwidth

Occupied bandwidth is defined as the bandwidth containing 99 % of the total integrated mean power of the transmitted spectrum on the assigned channel. The occupied bandwidth for all transmission bandwidth configurations (Resources Blocks) shall be less than the channel bandwidth specified in Table 6.6.1-1

Table 6.6.1-1: Occupied channel bandwidth

| | Occupied channel bandwidth / channel bandwidth | | | | | |
|-------------------------|--|---------|-------|--------|--------|--------|
| | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Channel bandwidth (MHz) | 1.4 | 3 | 5 | 10 | 15 | 20 |

6.6.2 Out of band emission

The Out of band emissions are unwanted emissions immediately outside the assigned channel bandwidth resulting from the modulation process and non-linearity in the transmitter but excluding spurious emissions. This out of band emission limit is specified in terms of a spectrum emission mask and an Adjacent Channel Leakage power Ratio.

6.6.2.1 Spectrum emission mask

The spectrum emission mask of the UE applies to frequencies (Δf_{OOB}) starting from the \pm edge of the assigned E-UTRA channel bandwidth. For frequencies greater than (Δf_{OOB}) as specified in Table 6.6.2.1.1-1 the spurious requirements in clause 6.6.3 are applicable.

6.6.2.1.1 Minimum requirement

The power of any UE emission shall not exceed the levels specified in Table 6.6.2.1.1-1 for the specified channel bandwidth.

Table 6.6.2.1.1-1: General E-UTRA spectrum emission mask

| Δf_{OOB} (MHz) | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz | Measurement bandwidth |
|----------------------------------|------------|------------|----------|-----------|-----------|-----------|--------------------------|
| $\pm 0-1$ | [TBD] | [TBD] | -15 | -18 | -20 | -21 | 30 kHz |
| $\pm 1-2.5$ | -10 | -10 | -10 | -10 | -10 | -10 | 1 MHz |
| $\pm 2.5-5$ | -25 | -10 | -10 | -10 | -10 | -10 | 1 MHz |
| $\pm 5-6$ | | -25 | -13 | -13 | -13 | -13 | 1 MHz |
| $\pm 6-10$ | | | -25 | -13 | -13 | -13 | 1 MHz |
| $\pm 10-15$ | | | | -25 | -13 | -13 | 1 MHz |
| $\pm 15-20$ | | | | | -25 | -13 | 1 MHz |
| $\pm 20-25$ | | | | | | -25 | 1 MHz |

Note: As a general rule, the resolution bandwidth of the measuring equipment should be equal to the measurement bandwidth. However, to improve measurement accuracy, sensitivity and efficiency, the resolution bandwidth may be smaller than the measurement bandwidth. When the resolution bandwidth is smaller than the measurement bandwidth, the result should be integrated over the measurement bandwidth in order to obtain the equivalent noise bandwidth of the measurement bandwidth.

6.6.2.2 Additional Spectrum Emission Mask

This requirement is specified in terms of an "additional spectrum emission" requirement.

6.6.2.2.1 Minimum requirement (network signalled value "NS_03")

Additional spectrum emission requirements are signalled by the network to indicate that the UE shall meet an additional requirement for a specific deployment scenario as part of the cell handover/broadcast message.

When "NS_03" is indicated in the cell, the power of any UE emission shall not exceed the levels specified in Table 6.6.2.2.1-1.

Table 6.6.2.2.1-1: Additional requirements

| | Spectrum emission limit (dBm)/ Channel bandwidth | | | | | | |
|----------------------------------|--|------------|----------|-----------|-----------|-----------|--------------------------|
| Δf_{OoB} (MHz) | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz | Measurement bandwidth |
| $\pm 0-1$ | [TBD] | [TBD] | -15 | -18 | -20 | -21 | 30 kHz |
| $\pm 1-2.5$ | [TBD] | [TBD] | -13 | -13 | -13 | -13 | 1 MHz |
| $\pm 2.5-5$ | [TBD] | [TBD] | -13 | -13 | -13 | -13 | 1 MHz |
| $\pm 5-6$ | [TBD] | [TBD] | -13 | -13 | -13 | -13 | 1 MHz |
| $\pm 6-10$ | [TBD] | [TBD] | -25 | -13 | -13 | -13 | 1 MHz |
| $\pm 10-15$ | [TBD] | [TBD] | | -25 | -13 | -13 | 1 MHz |
| $\pm 15-20$ | [TBD] | [TBD] | | | -25 | -13 | 1 MHz |
| $\pm 10-25$ | [TBD] | [TBD] | | | | -25 | 1 MHz |

Note: As a general rule, the resolution bandwidth of the measuring equipment should be equal to the measurement bandwidth. However, to improve measurement accuracy, sensitivity and efficiency, the resolution bandwidth may be smaller than the measurement bandwidth. When the resolution bandwidth is smaller than the measurement bandwidth, the result should be integrated over the measurement bandwidth in order to obtain the equivalent noise bandwidth of the measurement bandwidth.

6.6.2.2.2 Minimum requirement (network signalled value "NS_04")

Additional spectrum emission requirements are signalled by the network to indicate that the UE shall meet an additional requirement for a specific deployment scenario as part of the cell handover/broadcast message.

When "NS_04" is indicated in the cell, the power of any UE emission shall not exceed the levels specified in Table 6.6.2.2.2-1.

Table 6.6.2.2.2-1: Additional requirements

| | Spectrum emission limit (dBm)/ Channel bandwidth | | | | | | |
|----------------------------------|--|------------|----------|-----------|-----------|-----------|--------------------------|
| Δf_{OoB} (MHz) | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz | Measurement bandwidth |
| $\pm 0-1$ | [TBD] | [TBD] | -15 | -18 | -20 | -21 | 30 kHz |
| $\pm 1-2.5$ | [TBD] | [TBD] | -13 | -13 | -13 | -13 | 1 MHz |
| $\pm 2.5-5$ | [TBD] | [TBD] | -13 | -13 | -13 | -13 | 1 MHz |
| $\pm 5-6$ | [TBD] | [TBD] | -25 | -25 | -25 | -25 | 1 MHz |
| $\pm 6-10$ | [TBD] | [TBD] | -25 | -25 | -25 | -25 | 1 MHz |
| $\pm 10-15$ | [TBD] | [TBD] | | -25 | -25 | -25 | 1 MHz |
| $\pm 15-20$ | [TBD] | [TBD] | | | -25 | -25 | 1 MHz |
| $\pm 10-25$ | [TBD] | [TBD] | | | | -25 | 1 MHz |

Note: As a general rule, the resolution bandwidth of the measuring equipment should be equal to the measurement bandwidth. However, to improve measurement accuracy, sensitivity and efficiency, the resolution bandwidth may be smaller than the measurement bandwidth. When the resolution bandwidth is smaller than the measurement bandwidth, the result should be integrated over the measurement bandwidth in order to obtain the equivalent noise bandwidth of the measurement bandwidth.

6.6.2.2.3 Minimum requirement (network signalled value "NS_06" or "NS_07")

Additional spectrum emission requirements are signalled by the network to indicate that the UE shall meet an additional requirement for a specific deployment scenario as part of the cell handover/broadcast message.

When "NS_06" or "NS_07" is indicated in the cell, the power of any UE emission shall not exceed the levels specified in Table 6.6.2.2.3-1.


Table 6.6.2.3-1: Additional requirements

| | Spectrum emission limit (dBm)/ Channel bandwidth | | | | |
|----------------------------------|--|------------|----------|-----------|--------------------------|
| Δf_{OoB} (MHz) | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | Measurement bandwidth |
| $\pm 0-0.1$ | [TBD] | [TBD] | -15 | -18 | 30 kHz |
| $\pm 0.1-1$ | -13 | -13 | -13 | -13 | 100 kHz |
| $\pm 1-2.5$ | [TBD] | [TBD] | -13 | -13 | 1 MHz |
| $\pm 2.5-5$ | [TBD] | [TBD] | -13 | -13 | 1 MHz |
| $\pm 5-6$ | | [TBD] | -13 | -13 | 1 MHz |
| $\pm 6-10$ | | | -25 | -13 | 1 MHz |
| $\pm 10-15$ | | | | -25 | 1 MHz |

Note: As a general rule, the resolution bandwidth of the measuring equipment should be equal to the measurement bandwidth. However, to improve measurement accuracy, sensitivity and efficiency, the resolution bandwidth may be smaller than the measurement bandwidth. When the resolution bandwidth is smaller than the measurement bandwidth, the result should be integrated over the measurement bandwidth in order to obtain the equivalent noise bandwidth of the measurement bandwidth.

6.6.2.3 Adjacent Channel Leakage Ratio

Adjacent Channel Leakage power Ratio (ACLR) is the ratio of the filtered mean power centred on the assigned channel frequency to the filtered mean power centred on an adjacent channel frequency. ACLR requirements are specified for two scenarios for an adjacent E-UTRA and /or UTRA channel as shown in Figure 6.6.2.3 -1.

**Figure 6.6.2.3-1: Adjacent Channel Leakage requirements**

6.6.2.3.1 Minimum requirement E-UTRA

E-UTRA Adjacent Channel Leakage power Ratio ($E\text{-UTRA}_{\text{ACLR}}$) is the ratio of the filtered mean power centred on the assigned channel frequency to the filtered mean power centred on an adjacent channel frequency. The assigned E-UTRA channel power and adjacent E-UTRA channel power are measured with rectangular filters with measurement bandwidths specified in Table 6.6.2.3.1-1. If the measured adjacent channel power is greater than -50dBm then the $E\text{-UTRA}_{\text{ACLR}}$ shall be higher than the value specified in Table 6.6.2.3.1-1.

Table 6.6.2.3.1-1: General requirements for $E\text{-UTRA}_{\text{ACLR}}$

| | Channel bandwidth / $E\text{-UTRA}_{\text{ACLR1}}$ / measurement bandwidth | | | | | |
|--|--|------------|----------|-----------|-----------|-----------|
| | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| $E\text{-UTRA}_{\text{ACLR1}}$ | 30 dB | 30 dB | 30 dB | 30 dB | 30 dB | 30 dB |
| E-UTRA channel Measurement bandwidth | | | 4.5 MHz | 9.0 MHz | 13.5 MHz | 18 MHz |

6.6.2.3.2 Minimum requirements UTRA

UTRA Adjacent Channel Leakage power Ratio ($UTRA_{ACLR}$) is the ratio of the filtered mean power centred on the assigned E-UTRA channel frequency to the filtered mean power centred on an adjacent(s) UTRA channel frequency.

UTRA Adjacent Channel Leakage power Ratio is specified for both the first UTRA adjacent channel ($UTRA_{ACLR1}$) and the 2nd UTRA adjacent channel ($UTRA_{ACLR2}$). The UTRA channel power is measured with a RRC bandwidth filter with roll-off factor $\alpha = 0.22$. The assigned E-UTRA channel power is measured with a rectangular filter with measurement bandwidth specified in Table 6.6.2.3.2-1. If the measured UTRA channel power is greater than -50dBm then the $UTRA_{ACLR}$ shall be higher than the value specified in Table 6.6.2.3.2-1.

Table 6.6.2.3.2-1: Additional requirements

| | Channel bandwidth / $UTRA_{ACLR1/2}$ / measurement bandwidth | | | | | |
|---|--|---------|---------------------|-------------------|---------------------|--------------------|
| | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| $UTRA_{ACLR1}$ | 33 dB | 33 dB | 33 dB | 33 dB | 33 dB | 33 dB |
| Adjacent channel centre frequency offset (in MHz) | - | - | $2.5+BW_{UTRA}/2$ | $5+BW_{UTRA}/2$ | $7.5+BW_{UTRA}/2$ | $10+BW_{UTRA}/2$ |
| $UTRA_{ACLR2}$ | - | - | 36 dB | 36 dB | 36 dB | 36 dB |
| Adjacent channel centre frequency offset (in MHz) | - | - | $2.5+3*BW_{UTRA}/2$ | $5+3*BW_{UTRA}/2$ | $7.5+3*BW_{UTRA}/2$ | $10+3*BW_{UTRA}/2$ |
| E-UTRA channel Measurement bandwidth | - | - | 4.5 MHz | 9.0 MHz | 13.5 MHz | 18 MHz |
| UTRA 5MHz channel Measurement bandwidth* | - | - | 3.84 MHz | 3.84 MHz | 3.84 MHz | 3.84 MHz |
| UTRA 1.6MHz channel measurement bandwidth** | - | - | 1.28 MHz | 1.28MHz | 1.28MHz | 1.28MHz |
| * Note: Applicable for E-UTRA FDD co-existence with UTRA FDD in paired spectrum. | | | | | | |
| ** Note: Applicable for E-UTRA TDD co-existence with UTRA TDD in unpaired spectrum. | | | | | | |

6.6.2.4 Additional ACLR requirements

This requirement is specified in terms of an additional $UTRA_{ACLR2}$ requirement.

6.6.2.4.1 Minimum requirements (network signalled value "NS_02")

"NS_02" is signalled by the network to indicate that the UE shall meet this additional requirement for a specific deployment scenario as part of the cell handover/broadcast message.

The Additional ACLR requirement is specified for the 2nd UTRA 5MHz adjacent channel ($UTRA_{ACLR2}$). The UTRA channel power is measured with a 3.84 MHz RRC bandwidth filter with roll-off factor $\alpha = 0.22$. The assigned E-UTRA channel power is measured with a rectangular filter with measurement bandwidth specified in Table 6.6.2.3.2-1. If the UTRA 2nd adjacent channel power is greater than -50dBm then the $UTRA_{ACLR2}$ shall be higher than the value specified in Table 6.6.2.4.1-1.

Table 6.6.2.4.1-1: Additional requirements (UTRA_{ACLR2})

| | Channel bandwidth / UTRA _{ACLR2} / measurement bandwidth | | | | | |
|--------------------------------------|---|---------|----------|----------|--------|--------|
| | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| UTRA _{ACLR2bis} | - | - | 43 dB | 43 dB | - | - |
| E-UTRA channel Measurement bandwidth | - | - | 4.5 MHz | 9.0 MHz | - | - |
| UTRA channel Measurement bandwidth | - | - | 3.84 MHz | 3.84 MHz | - | - |

6.6.3 Spurious emissions

Spurious emissions are emissions which are caused by unwanted transmitter effects such as harmonics emission, parasitic emissions, intermodulation products and frequency conversion products, but exclude out of band emissions. The spurious emission limits are specified in terms of general requirements inline with SM.329 [2] and E-UTRA operating band requirement to address UE co-existence.

Unless otherwise stated, the spurious emission limits apply for the frequency ranges that are more than Δf_{OOB} (MHz) in Table 6.6.3.1-1 from the edge of the channel bandwidth.

6.6.3.1 Minimum requirements

Table 6.6.3.1-1: Boundary between E-UTRA Δf_{OOB} and spurious emission domain

| Channel bandwidth | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
|-------------------------------|---------|---------|-------|--------|--------|--------|
| Δf_{OOB} (MHz) | [tbd] | [tbd] | 10 | 15 | 20 | 25 |

The spurious emission limits in Table 6.6.3.1-2 apply for all transmitter band configurations (RB) and channel bandwidths.

Table 6.6.3.1-2: Spurious emissions limits

| Frequency Range | Maximum Level | Measurement Bandwidth |
|--|---------------|-----------------------|
| $9 \text{ kHz} \leq f < 150 \text{ kHz}$ | -36 dBm | 1 kHz |
| $150 \text{ kHz} \leq f < 30 \text{ MHz}$ | -36 dBm | 10 kHz |
| $30 \text{ MHz} \leq f < 1000 \text{ MHz}$ | -36 dBm | 100 kHz |
| $1 \text{ GHz} \leq f < 12.75 \text{ GHz}$ | -30 dBm | 1 MHz |

6.6.3.2 Spurious emission band UE co-existence

This clause specifies the requirements for the specified E-UTRA band

Table 6.6.3.2-1: Requirements

| E-UTRA Band | Spurious emission | | | | | |
|-------------|---|-----------------------|---|-------------|-----------------|---------|
| | Protected band | Frequency range (MHz) | | Level (dBm) | Bandwidth (MHz) | Comment |
| 1 | E-UTRA Band 1, 3, 7, 8, 9, 11, 34, 38, 40 | FDL_low | - | FDL_high | -50 | 1 |
| | Frequency range | 860 | - | 895 | -50 | 1 |

| | | | | | | | |
|----|---|---------|---|----------|-----|---------|---------------------|
| | Frequency range | 1884.5 | - | 1919.6 | -41 | 0.3 | Note ⁶ |
| | E-UTRA band 33 | 1900 | - | 1920 | -50 | 1 | Note ³ |
| | E-UTRA band 39 | 1880 | - | 1920 | -50 | 1 | Note ³ |
| 2 | E-UTRA Band 2, 4, 5, 10, 12, 13, 14, 17 | FDL_low | - | FDL_high | -50 | 1 | |
| 3 | E-UTRA Band 1, 3, 7, 8, 9, 11, 33, 34, 38 | FDL_low | - | FDL_high | -50 | 1 | |
| 4 | E-UTRA Band 2, 4, 5, 10, 12, 13, 14, 17 | FDL_low | - | FDL_high | -50 | 1 | |
| 5 | E-UTRA Band 2, 4, 5, 10, 12, 13, 14, 17 | FDL_low | - | FDL_high | -50 | 1 | |
| 6 | E-UTRA Band 1, 9, 11, 34 | FDL_low | - | FDL_high | -50 | 1 | |
| | Frequency range | 860 | - | 875 | -37 | 1 | |
| | Frequency range | 875 | - | 895 | -50 | 1 | |
| | Frequency range | 1884.5 | - | 1919.6 | -41 | 0.3 | |
| 7 | E-UTRA Band 1, 3, 7, 8, 33, 34 | FDL_low | - | FDL_high | -50 | 1 | |
| | E-UTRA Band 38 | 2570 | - | 2620 | -50 | 1 | Note ³ |
| 8 | E-UTRA Band 1, 8, 7, 33, 34, 38, 39, 40 | FDL_low | - | FDL_high | -50 | 1 | |
| | E-UTRA band 3 | 1805 | - | 1830 | -50 | 1 | Note ⁴ |
| | E-UTRA band 3 | 1805 | - | 1880 | -36 | 0.1 | Note ^{2,4} |
| | E-UTRA band 3 | 1830 | - | 1880 | -50 | 1 | Note ⁴ |
| | E-UTRA band 7 | 2640 | - | 2690 | -50 | 1 | Note ⁴ |
| | E-UTRA band 7 | 2640 | - | 2690 | -36 | 0.1 | Note ^{2,4} |
| 9 | E-UTRA Band 1, 9, 11, 34 | FDL_low | - | FDL_high | -50 | 1 | |
| | Frequency range | 860 | - | 895 | -50 | 1 | |
| | Frequency range | 1884.5 | - | 1919.6 | -41 | 0.3 | |
| 10 | E-UTRA Band 2, 4, 5, 10, 12, 13, 14, 17 | FDL_low | - | FDL_high | -50 | 1 | |
| 11 | E-UTRA Band 1, 9, 11, 34 | FDL_low | - | FDL_high | -50 | 1 | |
| | Frequency range | 860 | - | 895 | -50 | 1 | |
| | Frequency range | 1884.5 | - | 1919.6 | -41 | 0.3 | |
| 12 | E-UTRA Band 2, 4, 5, 10, 12, 13, 14, 17 | FDL_low | - | FDL_high | -50 | 1 | |
| 13 | E-UTRA Band 2, 4, 5, 10, 12, 13, 14, 17 | FDL_low | - | FDL_high | -50 | 1 | |
| | Frequency range | 763 | - | 775 | -35 | 0.00625 | |
| 14 | E-UTRA Band 2, 4, 5, 10, 12, 13, 14, 17 | FDL_low | - | FDL_high | -50 | 1 | |
| | Frequency range | 763 | - | 775 | -35 | 0.00625 | |
| 17 | E-UTRA Band 2, 4, 5, 10, 12, 13, 14, 17 | FDL_low | - | FDL_high | -50 | 1 | |
| | | | | | | | |
| 33 | E-UTRA Band 1, 3, 8, 34, 38, 39, 40 | FDL_low | - | FDL_high | -50 | 1 | Note ⁵ |
| 34 | E-UTRA Band 1, 3, 7, 8, 9, 11, 33, 38, 39, 40 | FDL_low | - | FDL_high | -50 | 1 | Note ⁵ |
| | Frequency range | 860 | - | 895 | -50 | 1 | |
| | Frequency range | 1884.5 | - | 1919.6 | -41 | 0.3 | |

| | | | | | | | |
|--|------------------------------|---------|---|----------|-----|---|--|
| 35 | | | | | | | |
| 36 | | | | | | | |
| 37 | | | - | | | | |
| 38 | E-UTRA Band 1,3, 33, 34 | FDL_low | - | FDL_high | -50 | 1 | |
| 39 | E-UTRA Band 34, 40 | FDL_low | - | FDL_high | -50 | 1 | |
| 40 | E-UTRA Band 1, 3, 33, 34, 39 | FDL_low | - | FDL_high | -50 | 1 | |
| Note 1 FDL_low and FDL_high refer to each E-UTRA frequency band specified in Table 5.2-1 2 As exceptions, measurements with a level up to the applicable requirements defined in Table 6.6.3.1-2 are permitted for each assigned E-UTRA carrier used in the measurement due to 2nd or 3rd harmonic spurious emissions. An exception is allowed if there is at least one individual RE within the transmission bandwidth (see Figure 5.4.2-1) for which the 2nd or 3rd harmonic, i.e. the frequency equal to two or three times the frequency of that RE, is within the measurement bandwidth. 3 To meet these requirements some restriction will be needed for either the operating band or protected band 4 Requirements are specified in terms of E-UTRA sub-bands 5 For non synchronised TDD operation to meet these requirements some restriction will be needed for either the operating band or protected band 6 Applicable when NS_02 or NS_05 in section 6.6.3.3.1 is signalled by the network. | | | | | | | |

6.6.3.3 Additional spurious emissions

These requirements are specified in terms of an additional spectrum emission requirement. Additional spurious emission requirements are signalled by the network to indicate that the UE shall meet an additional requirement for a specific deployment scenario as part of the cell handover/broadcast message.

6.6.3.3.1 Minimum requirement (network signalled value "NS_02" or "NS_05")

When "NS_02" or "NS_05" is indicated in the cell, the power of any UE emission shall not exceed the levels specified in Table 6.6.3.3.1-1. This requirement also applies for the frequency ranges that are less than Δf_{OoB} (MHz) in Table 6.6.3.1-1 from the edge of the channel bandwidth.

Table 6.6.3.3.1-1: Additional requirements (PHS)

| Frequency band (MHz) | Channel bandwidth / Spectrum emission limit (dBm) | | | | | | Measurement bandwidth |
|--|---|---------|-------|--------|--------|--------|-----------------------|
| | 1.4 MHz | 3.0 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz | |
| $1884.5 \leq f \leq 1919.6$ | -41 | -41 | -41 | -41 | -41 | -41 | 300 KHz |
| Note 1. The requirements are applicable when the edge of the assigned E-UTRA UL channel bandwidth frequency is larger than or equal to the upper edge of PHS band (1919.6 MHz) + 4 MHz + the Channel BW assigned. Operations below this point are for further study. | | | | | | | |

6.6.3.3.2 Minimum requirement (network signalled value "NS_07")

When "NS_07" is indicated in the cell, the power of any UE emission shall not exceed the levels specified in Table 6.6.3.3.2-1.

Table 6.6.3.3.2-1: Additional requirements

| Frequency band (MHz) | Channel bandwidth / Spectrum emission limit (dBm) | Measurement bandwidth |
|-------------------------|--|--------------------------|
| | 10 MHz | |
| $763 \leq f \leq 775$ | [-60] | 6.25 kHz |

6.7 Transmit intermodulation

The transmit intermodulation performance is a measure of the capability of the transmitter to inhibit the generation of signals in its non linear elements caused by presence of the wanted signal and an interfering signal reaching the transmitter via the antenna.

6.7.1 Minimum requirement

User Equipment(s) transmitting in close vicinity of each other can produce intermodulation products, which can fall into the UE, or eNode B receive band as an unwanted interfering signal. The UE intermodulation attenuation is defined by the ratio of the mean power of the wanted signal to the mean power of the intermodulation product when an interfering CW signal is added at a level below the wanted signal at each of the transmitter antenna port with the other antenna port(s) if any is terminated. Both the wanted signal power and the intermodulation product power are measured through E-UTRA rectangular filter with measurement bandwidth shown in Table 6.7.1-1.

The requirement of transmitting intermodulation is prescribed in Table 6.7.1-1.

Table 6.7.1-1: Transmit Intermodulation

| BW Channel (UL) | 5MHz | | 10MHz | | 15MHz | | 20MHz | |
|---|----------|----------|----------|----------|----------|----------|----------|----------|
| Interference Signal Frequency Offset | 5MHz | 10MHz | 10MHz | 20MHz | 15MHz | 30MHz | 20MHz | 40MHz |
| Interference CW Signal Level | -40dBc | | | | | | | |
| Intermodulation Product | [-29dBc] | [-35dBc] | [-29dBc] | [-35dBc] | [-29dBc] | [-35dBc] | [-29dBc] | [-35dBc] |
| Measurement bandwidth | 4.5MHz | 4.5MHz | 9.0MHz | 9.0MHz | 13.5MHz | 13.5MHz | 18MHz | 18MHz |

7 Receiver characteristics

7.1 General

Unless otherwise stated the receiver characteristics are specified at the antenna connector(s) of the UE. For UE(s) with an integral antenna only, a reference antenna(s) with a gain of 0 dBi is assumed for each antenna port(s). UE with an integral antenna(s) may be taken into account by converting these power levels into field strength requirements, assuming a 0 dBi gain antenna. . For UEs with more than one receiver antenna connector, identical interfering signals shall be applied to each receiver antenna port if more than one of these is used (diversity).

The levels of the test signal applied to each of the antenna connectors shall be as defined in the respective sections below.

All the parameters in clause 7 are defined using the DL reference measurement channel specified in Annex A.3.2 and using the set-up specified in Annex C.3.1

7.2 Diversity characteristics

The requirements in Section 7 assume that the receiver is equipped with two Rx port as a baseline. Requirements for 4 ports are FFS. With the exception of clause 7.9 all requirements shall be verified by using both (all) antenna ports simultaneously.

7.3 Reference sensitivity power level

The reference sensitivity power level REFSSENS is the minimum mean power applied to both the UE antenna ports at which the throughput shall meet or exceed the requirements for the specified reference measurement channel.

7.3.1 Minimum requirements (QPSK)

The throughput shall be $\geq 95\%$ of the maximum throughput of the reference measurement channel as specified in Annex A.3.2 with parameters specified in Table 7.3.1-1 and table 7.3.1-2

Table 7.3.1-1: Reference sensitivity QPSK P_{REFSENS}

| E-UTRA Band | Channel bandwidth | | | | | | Duplex Mode |
|--|-------------------|-------------|-------------|--------------|--------------|--------------|-------------|
| | 1.4 MHz (dBm) | 3 MHz (dBm) | 5 MHz (dBm) | 10 MHz (dBm) | 15 MHz (dBm) | 20 MHz (dBm) | |
| 1 | - | - | -100 | -97 | -95.2 | -94 | FDD |
| 2 | -104.2 | -100.2 | -98 | -95 | -93.2 | -92 | FDD |
| 3 | -103.2 | -99.2 | -97 | -94 | -92.2 | -91 | FDD |
| 4 | -106.2 | -102.2 | -100 | -97 | -95.2 | -94 | FDD |
| 5 | -104.2 | -100.2 | -98 | -95 | | | FDD |
| 6 | - | - | -100 | -97 | | | FDD |
| 7 | - | - | -98 | -95 | -93.2 | -92 | FDD |
| 8 | -103.2 | -99.2 | -97 | -94 | | | FDD |
| 9 | - | - | -99 | -96 | -94 | -93 | FDD |
| 10 | - | - | -100 | -97 | -95.2 | -94 | FDD |
| 11 | - | - | -98 | -95 | -93.2 | -92 | FDD |
| 12 | -103.2 | -99.2 | -97 | -94 | | | FDD |
| 13 | -103.2 | -99.2 | -97 | -94 | | | FDD |
| 14 | | | | | | | FDD |
| ... | | | | | | | |
| 17 | [-104.2] | [-100.2] | [-98] | [-95] | | | FDD |
| ... | | | | | | | |
| 33 | - | - | -100 | -97 | -95.2 | -94 | TDD |
| 34 | - | - | -100 | -97 | -95.2 | -94 | TDD |
| 35 | -106.2 | -102.2 | -100 | -97 | -95.2 | -94 | TDD |
| 36 | -106.2 | -102.2 | -100 | -97 | -95.2 | -94 | TDD |
| 37 | - | - | -100 | -97 | -95.2 | -94 | TDD |
| 38 | - | - | -100 | -97 | | | TDD |
| 39 | - | - | -100 | -97 | -95.2 | -94 | TDD |
| 40 | - | - | -100 | -97 | -95.2 | -94 | TDD |
| Note 1: The transmitter shall be set to maximum output power level (Table 7.3.1-2) | | | | | | | |
| Note 2: Reference measurement channel is A.3.2 | | | | | | | |
| Note 3: The signal power is specified per port | | | | | | | |
| Note 4: For the UE which supports both Band 3 and Band 9 the reference sensitivity level of Band 3 + 0.5 dB is applicable for band 9 | | | | | | | |

Note 1: The relation to the received PSD is $\langle \text{REF } \hat{I}_{or} \rangle = P_{\text{REFSENS}} (N_{sc}^{RB} N_{RB} \Delta f)^{-1}$ with N_{RB} is the maximum transmission configuration according to Table 5.6-1.

Table 7.3.1-2 specifies the minimum number of allocated uplink resource blocks for which the reference receive sensitivity requirement must be met.

Table 7.3.1-2: Maximum uplink configuration for reference sensitivity

| E-UTRA Band / Channel bandwidth / NRB / Duplex mode | | | | | | | |
|--|---------|-------|-----------------|-----------------|-----------------|-----------------|-------------|
| E-UTRA Band | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz | Duplex Mode |
| 1 | - | - | 25 | 50 | 75 | 100 | FDD |
| 2 | 6 | 15 | 25 | 50 | 50 ¹ | 50 ¹ | FDD |
| 3 | 6 | 15 | 25 | 50 | 50 ¹ | 50 ¹ | FDD |
| 4 | 6 | 15 | 25 | 50 | 75 | 100 | FDD |
| 5 | 6 | 15 | 25 | 25 ¹ | - | - | FDD |
| 6 | - | - | 25 | 25 ¹ | - | - | FDD |
| 7 | - | - | 25 | 50 | 75 ¹ | 75 ¹ | FDD |
| 8 | 6 | 15 | 25 | 25 ¹ | - | - | FDD |
| 9 | - | - | 25 | 50 | 50 ¹ | 50 ¹ | FDD |
| 10 | - | - | 25 | 50 | 75 | 100 | FDD |
| 11 | - | - | 25 | 25 ¹ | 25 ¹ | 25 ¹ | FDD |
| 12 | 6 | 15 | 20 ¹ | 20 ¹ | | | FDD |
| 13 | 6 | 15 | 20 ¹ | 20 ¹ | | | FDD |
| 14 | | | | | | | FDD |
| ... | | | | | | | |
| 17 | 6 | 15 | 20 ¹ | 20 ¹ | | | FDD |
| ... | | | | | | | |
| 33 | - | - | 25 | 50 | 75 | 100 | TDD |
| 34 | - | - | 25 | 50 | 75 | - | TDD |
| 35 | 6 | 15 | 25 | 50 | 75 | 100 | TDD |
| 36 | 6 | 15 | 25 | 50 | 75 | 100 | TDD |
| 37 | - | - | 25 | 50 | 75 | 100 | TDD |
| 38 | - | - | 25 | 50 | - | - | TDD |
| 39 | | | 25 | 50 | 75 | 100 | TDD |
| 40 | | | | 50 | 75 | 100 | TDD |
| Note 1: Maximum number of UL resources blocks allocated is less than the total resources blocks supported by the channel bandwidth | | | | | | | |

7.3.2 Requirement for large transmission configurations

For some combinations of bandwidths and operating bands, a certain relaxation of the UE performance is allowed when the transmission configuration is larger than that in Table 7.3.1-2. Table 7.3.2-1 specifies the allowed maximum sensitivity degradation (MSD) when the UL resource block allocation is the total resource blocks (Table 5.4.2-1) supported by the channel bandwidth.

Table 7.3.2-1: Maximum Sensitivity Degradation

| E-UTRA Band | Channel bandwidth | | | | | | Duplex Mode |
|---|-------------------|------------|------------|-------------|-------------|-------------|-------------|
| | 1.4 MHz (dB) | 3 MHz (dB) | 5 MHz (dB) | 10 MHz (dB) | 15 MHz (dB) | 20 MHz (dB) | |
| 1 | | | n/a | n/a | n/a | n/a | FDD |
| 2 | n/a | n/a | n/a | n/a | TBD | TBD | FDD |
| 3 | n/a | n/a | n/a | n/a | TBD | TBD | FDD |
| 4 | n/a | n/a | n/a | n/a | n/a | n/a | FDD |
| 5 | n/a | n/a | n/a | TBD | | | FDD |
| 6 | | | n/a | TBD | | | FDD |
| 7 | | | n/a | n/a | TBD | TBD | FDD |
| 8 | n/a | n/a | n/a | TBD | | | FDD |
| 9 | | | n/a | n/a | TBD | TBD | FDD |
| 10 | | | n/a | n/a | n/a | n/a | FDD |
| 11 | | | n/a | TBD | TBD | TBD | FDD |
| 12 | | | TBD | TBD | | | FDD |
| 13 | n/a | n/a | TBD | TBD | | | FDD |
| 14 | | | | | | | FDD |
| 17 | | | TBD | TBD | | | FDD |
| Note: 1. The transmitter shall be set to maximum output power level with MPR applied and with the maximum transmission configuration (Table 5.2.1-1) allocated | | | | | | | |

7.4 Maximum input level

This is defined as the maximum mean power received at the UE antenna port, at which the specified relative throughput shall meet or exceed the minimum requirements for the specified reference measurement channel.

7.4.1 Minimum requirements

The throughput shall be $\geq 95\%$ of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 with parameters specified in Table 7.4.1.

Table 7.4.1-1: Maximum input level

| Rx Parameter | Units | Channel bandwidth | | | | | |
|---|-------|-------------------|-------|-------|--------|--------|--------|
| | | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Wanted signal mean power | dBm | -25 | | | | | |
| Note: 1. The transmitter shall be set to 4dB below the supported maximum output power. 2. Reference measurement channel is Annex A.3.2: 64QAM, R=3/4 variant. | | | | | | | |

7.5 Adjacent Channel Selectivity (ACS)

7.5.1 Minimum requirements

Adjacent Channel Selectivity (ACS) is a measure of a receiver's ability to receive a E-UTRA signal at its assigned channel frequency in the presence of an adjacent channel signal at a given frequency offset from the centre frequency of the assigned channel. ACS is the ratio of the receive filter attenuation on the assigned channel frequency to the receive filter attenuation on the adjacent channel(s).

The UE shall fulfil the minimum requirement specified in Table 7.5.1-1 for all values of an adjacent channel interferer up to -25 dBm. However it is not possible to directly measure the ACS, instead the lower and upper range of test parameters are chosen in Table 7.5.1-2 and Table 7.5.1-3 where the throughput shall be $\geq 95\%$ of the maximum throughput of the reference measurement channels as specified in Annex A.3.2.

Table 7.5.1-1: Adjacent channel selectivity

| Rx Parameter | Units | Channel bandwidth | | | | | |
|--------------|-------|-------------------|-------|-------|--------|--------|--------|
| | | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| ACS | dB | 33.0 | 33.0 | 33.0 | 33.0 | 30 | 27 |

Table 7.5.1-2: Test parameters for Adjacent channel selectivity, Case 1

| Rx Parameter | Units | Channel bandwidth | | | | | |
|--|-------|-------------------|-----------------|------------------|------------------|-----------------|-------------------|
| | | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Wanted signal mean power | dBm | REFSENS + 14 dB | | | | | |
| $P_{\text{Interferer}}$ | dBm | REFSENS +45.5dB | REFSENS +45.5dB | REFSENS +45.5dB* | REFSENS +45.5dB | REFSENS +42.5dB | REFSENS +39.5dB |
| $BW_{\text{Interferer}}$ | MHz | 1.4 | 3 | 5 | 5 | 5 | 5 |
| $F_{\text{Interferer (offset)}}$ | MHz | 1.4[+0.0025] | 3[+0.0075] | 5[+0.0025] | 7.5[+0.007 5] | 10[+0.0125] | 12.5[+0.00 25] |
| Note: 1. The transmitter shall be set to 4dB below the supported maximum output power. 2. The interferer consists of the Reference measurement channel specified in Annex A.3.2 with set-up according to Annex C.3.1 | | | | | | | |

Table 7.5.1-3: Test parameters for Adjacent channel selectivity, Case 2

| Rx Parameter | Units | Channel bandwidth | | | | | |
|---|-------|-------------------|------------|------------|------------------|-----------------|-------------------|
| | | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Wanted signal mean power | dBm | -56.5 | -56.5 | -56.5 | -56.5 | -53.5 | -50.5 |
| $P_{\text{Interferer}}$ | dBm | -25 | | | | | |
| $BW_{\text{Interferer}}$ | MHz | 1.4 | 3 | 5 | 5 | 5 | 5 |
| $F_{\text{Interferer (offset)}}$ | MHz | 1.4[+0.002 5] | 3[+0.0075] | 5[+0.0025] | 7.5[+0.007 5] | 10[+0.0125] | 12.5[+0.00 25] |
| Note: 1. The transmitter shall be set to 24dB below the supported maximum output power. 2. The interferer consists of the Reference measurement channel specified in Annex 3.2 with set-up according to Annex C.3.1 | | | | | | | |

7.6 Blocking characteristics

The blocking characteristic is a measure of the receiver's ability to receive a wanted signal at its assigned channel frequency in the presence of an unwanted interferer on frequencies other than those of the spurious response or the adjacent channels, without this unwanted input signal causing a degradation of the performance of the receiver beyond a specified limit. The blocking performance shall apply at all frequencies except those at which a spurious response occur.

7.6.1 In-band blocking

In-band blocking is defined for an unwanted interfering signal falling into the UE receive band or into the first 15 MHz below or above the UE receive band at which the relative throughput shall meet or exceed the minimum requirement for the specified measurement channels..

7.6.1.1 Minimum requirements

The throughput shall be $\geq 95\%$ of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 with parameters specified in Tables 7.6.1.1-1 and 7.6.1.1-2.

Table 7.6.1.1-1: In band blocking parameters

| Rx Parameter | Units | Channel bandwidth | | | | | |
|--|-------|--|--------------|---------------|---------------|---------------|---------------|
| | | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Wanted signal mean power | dBm | REFSENS + channel bandwidth specific value below | | | | | |
| | | 6 | 6 | 6 | 6 | 7 | 9 |
| $BW_{\text{interferer}}$ | MHz | 1.4 | 3 | 5 | 5 | 5 | 5 |
| $F_{\text{offset, case 1}}$ | MHz | 2.1[+0.0125] | 4.5[+0.0075] | 7.5[+0.0125] | 7.5[+0.0025] | 7.5[+0.0075] | 7.5[+0.0125] |
| $F_{\text{offset, case 2}}$ | MHz | 3.5[+0.0075] | 7.5[+0.0075] | 12.5[+0.0075] | 12.5[+0.0125] | 12.5[+0.0025] | 12.5[+0.0075] |
| Note: 1. The transmitter shall be set to 4dB below the supported maximum output power. 2. The interferer consists of the Reference measurement channel specified in Annex A.3.2 with set-up according to Annex C.3.1 | | | | | | | |

Table 7.6.1.1-2: In-band blocking

| E-UTRA band | Parameter | Units | Case 1 | Case 2 | Case 3 |
|--|----------------------------------|-------|---|---|---|
| | $P_{\text{interferer}}$ | dBm | -56 | -44 | [T.B.D] |
| | $F_{\text{interferer}}$ (Offset) | MHz | $= -BW/2 - F_{\text{offset, case 1}}$ & $= +BW/2 + F_{\text{offset, case 1}}$ | $\leq -BW/2 - F_{\text{offset, case 2}}$ & $\geq +BW/2 + F_{\text{offset, case 2}}$ | |
| 1, 2, 3, 4, 5, 7, 8, 9, 10, 11, 12 33, 34, 35, 36, 37, 38, 39, 40 | $F_{\text{interferer}}$ | MHz | $F_{\text{DL_low}} - 7.5$ to $F_{\text{DL_high}} + 7.5$ (Note 1) | $F_{\text{DL_low}} - 15$ to $F_{\text{DL_high}} + 15$ | |
| 6, 13 | $F_{\text{interferer}}$ | MHz | $F_{\text{DL_low}} - 7.5$ to $F_{\text{DL_high}} + 7.5$ (Note 1 & 2) | $F_{\text{DL_low}} - 15$ to $F_{\text{DL_high}} + 15$ (Note 2) | |
| 17 | $F_{\text{interferer}}$ | MHz | $F_{\text{DL_low}} - 7.5$ to $F_{\text{DL_high}} + 7.5$ (Note 1 & 2) | $F_{\text{DL_low}} - 9.0$ to $F_{\text{DL_high}} + 15$ (Note 2) | $F_{\text{DL_low}} - 15$ to $F_{\text{DL_low}} - 9.0$ (Note 3) |
| Note 1. For each carrier frequency the requirement is valid for two frequencies: a. the carrier frequency $-BW/2 - F_{\text{offset, case 1}}$ and b. the carrier frequency $+BW/2 + F_{\text{offset, case 1}}$. 2. For Bands 6 and 13 and 17 the unwanted modulated interfering signal does not fall inside the UE receive band, but within the first 15 MHz below or above the UE receive band 3. For Band 17 additional unwanted modulated interfering signals fall from 6 to 18 MHz from the lower band edge. | | | | | |

7.6.2 Out of-band blocking

Out-of-band band blocking is defined for an unwanted CW interfering signal falling more than 15 MHz below or above the UE receive band. For the first 15 MHz below or above the UE receive band the appropriate in-band blocking or adjacent channel selectivity in sub-clause 7.5.1 and sub-clause 7.6.1 shall be applied.

7.6.2.1 Minimum requirements

. The throughput shall be $\geq 95\%$ of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 with parameters specified in Tables 7.6.2.1-1 and 7.6.2.1-2.

For Table 7.6.2.1-2 in frequency range 1, 2 and 3, up to [TBD] exceptions are allowed for spurious response frequencies in each assigned frequency channel when measured using a 1MHz step size. For these exceptions the requirements of clause 7.7 Spurious response are applicable.

For Table 7.6.2.1-2 in frequency range 4, up to [TBD] exceptions are allowed for spurious response frequencies in each assigned frequency channel when measured using a 1MHz step size. For these exceptions the requirements of clause 7.7 Spurious response are applicable.

Table 7.6.2.1-1: Out-of-band blocking parameters

| Rx Parameter | Units | Channel bandwidth | | | | | |
|--|-------|--|-------|-------|--------|--------|--------|
| | | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Wanted signal mean power | dBm | REFSENS + channel bandwidth specific value below | | | | | |
| | | 6 | 6 | 6 | 6 | 7 | 9 |
| Note: | | | | | | | |
| 1. The transmitter shall be set to 4dB below the supported maximum output power. | | | | | | | |
| 2. Reference measurement channel is specified in Annex A.3.2. | | | | | | | |

Table 7.6.2.1-2: Out of band blocking

| E-UTRA band | Parameter | Units | Frequency | | | |
|---|---------------------------------|-------|--|---|--|--|
| | | | range 1 | range 2 | range 3 | range 4 |
| | $P_{\text{Interferer}}$ | dBm | -44 | -30 | -15 | -15 |
| 1, 2, 3, 4, 5 6, 7, 8, 9, 10,11,12, 13, 17,33,34, 35, 36, 37, 38, 39, 40 | $F_{\text{Interferer}}$ (CW) | MHz | $F_{\text{DL_low}} -15$ to $F_{\text{DL_low}} -60$ | $F_{\text{DL_low}} -60$ to $F_{\text{DL_low}} -85$ | $F_{\text{DL_low}} -85$ to 1 MHz | - |
| | | | $F_{\text{DL_high}} +15$ to $F_{\text{DL_high}} + 60$ | $F_{\text{DL_high}} +60$ to $F_{\text{DL_high}} +85$ | $F_{\text{DL_high}} +85$ to +12750 MHz | - |
| 2, 5, 12, 17 | $F_{\text{Interferer}}$ | MHz | - | - | - | $F_{\text{UL_low}} - F_{\text{UL_high}}$ |
| Note: | | | | | | |

7.6.3 Narrow band blocking

This requirement is measure of a receiver's ability to receive a E-UTRA signal at its assigned channel frequency in the presence of an unwanted narrow band CW interferer at a frequency, which is less than the nominal channel spacing.

7.6.3.1 Minimum requirements

. The relative throughput shall be $\geq 95\%$ of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 with parameters specified in Table 7.6.3.1-1

Table 7.6.3.1-1: Narrow-band blocking

| Parameter | Unit | Channel Bandwidth | | | | | |
|--|------|---|--------|--------|--------|--------|---------|
| | | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| P_w | dBm | P_{REFSENS} + channel-bandwidth specific value below | | | | | |
| | | 22 | 18 | 16 | 13 | 14 | 16 |
| P_{uw} (CW) | dBm | -55 | -55 | -55 | -55 | -55 | -55 |
| F_{uw} (offset for $\Delta f = 15$ kHz) | MHz | 0.9075 | 1.7025 | 2.7075 | 5.2125 | 7.7025 | 10.2075 |
| F_{uw} (offset for $\Delta f = 7.5$ kHz) | MHz | | | | | | |
| Note 1: The transmitter shall be set a 4 dB below the supported maximum power. | | | | | | | |
| Note 2: Reference measurement channel is specified in Annex A.3.2. | | | | | | | |

7.7 Spurious response

Spurious response is a measure of the receiver's ability to receive a wanted signal on its assigned channel frequency without exceeding a given degradation due to the presence of an unwanted CW interfering signal at any other frequency at which a response is obtained i.e. for which the out of band blocking limit as specified in sub-clause 7.6.2 is not met.

7.7.1 Minimum requirements

The throughput shall be $\geq 95\%$ of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 with parameters specified in Tables 7.7.1-1 and 7.7.1-2.

Table 7.7.1-1: Spurious response parameters

| Rx Parameter | Units | Channel bandwidth | | | | | |
|--|-------|--|-------|-------|--------|--------|--------|
| | | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Wanted signal mean power | dBm | REFSENS + channel bandwidth specific value below | | | | | |
| | | 6 | 6 | 6 | 6 | 7 | 9 |
| Note: | | | | | | | |
| 1. The transmitter shall be set to 4dB below the supported maximum output power. | | | | | | | |
| 2. Reference measurement channel is specified in Annex A.3.2. | | | | | | | |

Table 7.7.1-2: Spurious Response

| Parameter | Unit | Level |
|------------------------------|------|-------------------------------|
| $P_{\text{Interferer}}$ (CW) | dBm | -44 |
| $F_{\text{Interferer}}$ | MHz | Spurious response frequencies |

7.8 Intermodulation characteristics

Intermodulation response rejection is a measure of the capability of the receiver to receive a wanted signal on its assigned channel frequency in the presence of two or more interfering signals which have a specific frequency relationship to the wanted signal.

7.8.1 Wide band intermodulation

The wide band intermodulation requirement is defined following the same principles using modulated E-UTRA carrier and CW signal as interferer.

7.8.1.1 Minimum requirements

The throughput shall be $\geq 95\%$ of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 with parameters specified in Table 7.8.1.1 for the specified wanted signal mean power in the presence of two interfering signals

Table 7.8.1.1-1: Wide band intermodulation

| Rx Parameter | Units | Channel bandwidth | | | | | |
|---|-------|--|--------------------------------|---------------------------------|--------|--------|--------|
| | | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| Wanted signal mean power | dBm | REFSENS + channel bandwidth specific value below | | | | | |
| | | 12 | 8 | 6 | 6 | 7 | 9 |
| P _{Interferer 1} (CW) | dBm | -46 | | | | | |
| P _{Interferer 2} (Modulated) | dBm | -46 | | | | | |
| BW _{Interferer 2} | | 1.4 | 3 | 5 | | | |
| F _{Interferer 1} (Offset) | MHz | -BW/2 -2.1 / +BW/2+ 2.1 | -BW/2 -4.5 / +BW/2 + 4.5 | -BW/2 - 7.5 / +BW/2 + 7.5 | | | |
| F _{Interferer 2} (Offset) | MHz | 2*F _{Interferer 1} | | | | | |
| R _{av} | kbps | | | | | | |
| Note: | | | | | | | |
| 1. The transmitter shall be set to 4dB below the supported maximum output power. | | | | | | | |
| 2. Reference measurement channel is specified in Annex Annex A.3.2. | | | | | | | |
| 3. The modulated interferer consists of the Reference measurement channel specified in Annex A.3.2 with set-up according to Annex C.3.1The interfering modulated signal is 5MHz E-UTRA signal as described in Annex D for channel bandwidth ≥5MHz | | | | | | | |

7.8.2 Void

7.9 Spurious emissions

The spurious emissions power is the power of emissions generated or amplified in a receiver that appear at the UE antenna connector.

7.9.1 Minimum requirements

The power of any narrow band CW spurious emission shall not exceed the maximum level specified in Table 7.9.1-1

Table 7.9.1-1: General receiver spurious emission requirements

| Frequency Band | Measurement Bandwidth | Maximum level | Note |
|---|-----------------------|---------------|------|
| $30\text{MHz} \leq f < 1\text{GHz}$ | 100 kHz | -57 dBm | |
| $1\text{GHz} \leq f \leq 12.75\text{GHz}$ | 1 MHz | -47 dBm | |

8 Performance requirement

This clause contains performance requirements for the physical channels specified in [TS 36.211]. The performance requirements for the UE in this clause are specified for the measurement channels specified in Annex A.3, the propagation conditions in Annex B and the downlink channels in Annex C.3.2.

8.1 General

8.1.1 Dual-antenna receiver capability

The performance requirements are based on UE(s) that utilize a dual-antenna receiver.

8.1.1.1 Simultaneous unicast and MBMS operations

8.1.1.2 Dual-antenna receiver capability in idle mode

8.2 Demodulation of PDSCH (Cell-Specific Reference Symbols)

8.2.1 FDD (Fixed Reference Channel)

The parameters specified in Table 8.2.1-1 are valid for all FDD tests unless otherwise stated.

Table 8.2.1-1: Common Test Parameters (FDD)

| Parameter | Unit | Value |
|-------------------------------------|--------------|--|
| Inter-TTI Distance | | 1 |
| Number of HARQ processes | Processes | 8 |
| Maximum number of HARQ transmission | | 4 |
| Redundancy version coding sequence | | {0,1,2,3} for QPSK and 16QAM {0,0,1,2} for 64QAM |
| Number of OFDM symbols for PDCCH | OFDM symbols | 4 for 1.4 MHz bandwidth, 3 for 3 MHz and 5 MHz bandwidths, 2 for 10 MHz, 15 MHz and 20 MHz bandwidths |
| Cyclic Prefix | | Normal |
| Note: | | |

For all test cases, the SNR is defined as

$$, SNR = \frac{\hat{E}_s^{(1)} + \hat{E}_s^{(2)}}{N_{oc}^{(1)} + N_{oc}^{(2)}}$$

where the superscript indicates the receiver antenna connector. The SNR requirement applies for the UE categories given for each test.

8.2.1.1 Single-antenna port performance

The single-antenna performance in a given multi-path fading environments is determined by the SNR for which a certain relative information bit throughput of the reference measurement channels in Annex A.3.2 is achieved. The purpose of these tests is to verify the single-antenna performance with different channel models and MCS. The QPSK and 64QAM cases are also used to verify the performance for all bandwidths specified in Table 5.6.1-1.

8.2.1.1.1 Minimum Requirement QPSK

The requirements are specified in Table 8.2.1.1.1-2, with the addition of the parameters in Table 8.2.1.1.1-1 and the downlink physical channel setup according to table [in Annex C.3.2].

Table 8.2.1.1.1-1: Test Parameters for Testing QPSK

| Parameter | | Unit | Test [1.1-1.4,2.1] |
|---------------------------|----------|-----------|--------------------|
| Downlink power allocation | ρ_A | dB | 0 |
| | ρ_B | dB | 0 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Note 1: $P_B = 0$ | | | |
| Parameter | | Unit | Test [1.1-1.4,2.1] |
| Downlink power allocation | ρ_A | dB | 0 |
| | ρ_B | dB | 0 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Note 1: $P_B = 0$ | | | |

Table 8.2.1.1.1-2: Minimum performance QPSK (FRC)

| Test number | Bandwidth | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|-----------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [1.1] | 10 MHz | [R.2 FDD] | EVA5 | 1x2 Low | 70 | -1.0 | |
| [1.2] | 10 MHz | [R.2 FDD] | ETU70 | 1x2 Low | 70 | -0.4 | |
| [1.3] | 10 MHz | [R.2 FDD] | ETU300 | 1x2 Low | 70 | 0.0 | |
| [1.4] | 10 MHz | [R.2 FDD] | HST | 1x2 Low | 70 | TBD | |
| [2.1] | 1.4 MHz | [R.4 FDD] | EVA5 | 1x2 Low | 70 | -0.5 | |

8.2.1.1.2 Minimum Requirement 16QAM

The requirements are specified in Table 8.2.1.1.2-1, with the addition of the parameters in Table 8.2.1.1.2-2 and the downlink physical channel setup according to table [in Annex C.3.2].

Table 8.2.1.1.2-1: Test Parameters for Testing 16QAM

| Parameter | | Unit | Test [1.5-1.7] |
|---------------------------|----------|-----------|----------------|
| Downlink power allocation | ρ_A | dB | 0 |
| | ρ_B | dB | 0 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Note 1: $P_B = 0$ | | | |

Table 8.2.1.1.2-2: Minimum performance 16QAM (FRC)

| Test number | Bandwidth | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|-----------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [1.5] | 10 MHz | [R.3 FDD] | EVA5 | 1x2 Low | 70 | 6.7 | |
| [1.6] | 10 MHz | [R.3 FDD] | ETU70 | 1x2 Low | 30 | 1.4 | |
| [1.7] | 10 MHz | [R.3 FDD] | ETU300 | 1x2 High | 70 | 9.4 | |

8.2.1.1.3 Minimum Requirement 64QAM

The requirements are specified in Table 8.2.1.1.3-2, with the addition of the parameters in Table 8.2.1.1.3-1 and the downlink physical channel setup according to table [in Annex C.3.2].

Table 8.2.1.1.3-1: Test Parameters for Testing 64QAM

| Parameter | | Unit | Test [1.8-1.10,2.2-2.5] |
|---------------------------|----------|-----------|-------------------------|
| Downlink power allocation | ρ_A | dB | 0 |
| | ρ_B | dB | 0 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Note 1: $P_B = 0$ | | | |

Table 8.2.1.1.3-2: Minimum performance 64QAM (FRC)

| Test number | Bandwidth | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|-----------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [2.2] | 3 MHz | [R.5 FDD] | EVA5 | 1x2 Low | 70 | 17.6 | |
| [2.3] | 5 MHz | [R.6 FDD] | EVA5 | 1x2 Low | 70 | 17.4 | |
| [1.8] | 10 MHz | [R.7 FDD] | EVA5 | 1x2 Low | 70 | 17.7 | |
| [1.9] | 10 MHz | [R.7 FDD] | ETU70 | 1x2 Low | 70 | 19.0 | |
| [1.10] | 10 MHz | [R.7 FDD] | EVA5 | 1x2 High | 70 | 19.1 | |
| [2.4] | 15 MHz | [R.8 FDD] | EVA5 | 1x2 Low | 70 | 17.7 | |
| [2.5] | 20 MHz | [R.9 FDD] | EVA5 | 1x2 Low | 70 | 17.6 | |

8.2.1.1.4 Minimum Requirement 1 PRB allocation

The requirements are specified in Table 8.2.1.1.4-2, with the addition of the parameters in Table 8.2.1.1.4-1 and the downlink physical channel setup according to table [in Annex C.3.2]. The purpose of these tests is to verify the single-antenna performance with a single PRB allocated at the lower band edge.

Table 8.2.1.1.4-1: Test Parameters for Testing 1 PRB allocation

| Parameter | | Unit | Test [3.1-3.3] |
|--------------------------------|----------|-----------|---------------------------|
| Downlink power allocation | ρ_A | dB | 0 |
| | ρ_B | dB | 0 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Cell ID | | | 0 |
| OCNG [Symbols for unused PRBs] | | | [Zeros shall be inserted] |
| Note 1: $P_B = 0$ | | | |

Table 8.2.1.1.4-2: Minimum performance 1PRB (FRC)

| Test number | Bandwidth and MCS | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|---------------------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [3.1] | 3 MHz 16QAM 1/2 | [R.0 FDD] | ETU70 | 1x2 Low | 30 | 1.9 | |
| [3.2] | 10 MHz 16QAM 1/2 | [R.1 FDD] | ETU70 | 1x2 Low | 30 | 1.9 | |
| [3.3] | 20 MHz 16QAM 1/2 | [R.1 FDD] | ETU70 | 1x2 Low | 30 | 1.9 | |

8.2.1.2 Transmit diversity performance

The requirements are specified in Table 8.2.1.2-2, with the addition of the parameters in Table 8.2.1.2-1 and the downlink physical channel setup according to table [in Annex C.3.2]. The purpose is to verify the performance of transmit diversity (SFBC) with 2 and 4 transmitter antennas.

Table 8.2.1.2-1: Test Parameters for Transmit diversity Performance (FRC)

| Parameter | | Unit | Test [7.1-7-3] |
|---------------------------|----------|-----------|----------------|
| Downlink power allocation | ρ_A | dB | -3 |
| | ρ_B | dB | -3 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Note 1: $P_B = 1$ | | | |

Table 8.2.1.2-2: Minimum performance Transmit Diversity (FRC)

| Test number | Bandwidth and MCS | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|---------------------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [7.1] | 10 MHz 16QAM 1/2 | [R.11 FDD] | EVA5 | 2x2 Medium | 70 | 6.8 | |
| [7.2] | 10 MHz QPSK 1/3 | [R.10 FDD] | HST | 2x2 Low | 70 | TBD | |
| [7.3] | 1.4 MHz QPSK 1/3 | [R.12 FDD] | EPA5 | 4x2 Medium | 70 | TBD | |

8.2.1.3 Open-loop spatial multiplexing performance

The requirements are specified in Table 8.2.1.3-2, with the addition of the parameters in Table 8.2.1.3-1 and the downlink physical channel setup according to table [in Annex C.3.2]. The purpose is to verify the performance of large delay CDD with 2 and 4 transmitter antennas.

Table 8.2.1.3-1: Test Parameters for Large Delay CDD (FRC)

| Parameter | | Unit | Test [6.1] | Test [6.2] | |
|---------------------------|----------|-----------|-------------|-------------|--|
| Downlink power allocation | ρ_A | dB | -3 | -6 | |
| | ρ_B | dB | -3 (Note 1) | -6 (Note 1) | |
| N_{oc} at antenna port | | dBm/15kHz | TBD | TBD | |
| Note 1: $P_B = 1$ | | | | | |

Table 8.2.1.3-2: Minimum performance Large Delay CDD (FRC)

| Test number | Bandwidth and MCS | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|---------------------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [6.1] | 10 MHz 16QAM 1/2 | [R.11 FDD] | EVA70 | 2x2 Low | 70 | 13.0 | |
| [6.2] | 10 MHz 16QAM 1/2 | [R.14 FDD] | EVA70 | 4x2 Low | 70 | 14.3 | |

8.2.1.4 Closed-loop spatial multiplexing performance

8.2.1.4.1 Minimum Requirement Single-Layer Spatial Multiplexing

The requirements are specified in Table 8.2.1.4.1-2, with the addition of the parameters in Table 8.2.1.4.1-1 and the downlink physical channel setup according to table [in Annex C.3.2]. The purpose of these tests is to verify the closed loop rank-one performance with wideband and frequency selective precoding.

Table 8.2.1.4.1-1: Test Parameters for Single-Layer Spatial Multiplexing (FRC)

| Parameter | | Unit | Test [4.1] | Test [4.2] | Test [4.3] |
|--|----------|-----------|-------------|-------------|-------------|
| Downlink power allocation | ρ_A | dB | -3 | -3 | -6 |
| | ρ_B | dB | -3 (Note 1) | -3 (Note 1) | -6 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD | TBD | TBD |
| Precoding granularity | | PRB | 6 | 50 | 6 |
| PMI delay (Note 2) | | ms | 6 | 6 | 6 |
| Note 1: $P_B = 1$ | | | | | |
| Note 2: If the UE reports in an available uplink reporting instance at subframe SF#n based on PMI estimation at a downlink SF not later than SF#(n-4), this reported PMI cannot be applied at the eNB downlink before SF#(n+2) | | | | | |

Table 8.2.1.4.1-2: Minimum performance Single-Layer Spatial Multiplexing (FRC)

| Test number | Bandwidth and MCS | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|-------------------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [4.1] | 10 MHz QPSK 1/3 | [R.10] | EVA5 | 2x2 Low | 70 | -2.5 | |
| [4.2] | 10 MHz QPSK 1/3 | [R.10] | EPA5 | 2x2 High | 70 | -2.8 | |
| [4.3] | 10 MHz QPSK 1/3 | [R.13] | EVA5 | 4x2 Low | 70 | -3.4 | |

8.2.1.4.2 Minimum Requirement Multi-Layer Spatial Multiplexing

The requirements are specified in Table 8.2.1.4.2-2, with the addition of the parameters in Table 8.2.1.4.2-1 and the downlink physical channel setup according to table [in Annex C.3.2]. The purpose of these tests is to verify the closed loop rank-two performance with wideband and frequency selective precoding.

Table 8.2.1.4.2-1: Test Parameters for Multi-Layer Spatial Multiplexing (FRC)

| Parameter | | Unit | Test [5.1] | Test [5.2] | Test [5.3] |
|--|----------|-----------|-------------|-------------|-------------|
| Downlink power allocation | ρ_A | dB | -3 | -3 | -6 |
| | ρ_B | dB | -3 (Note 1) | -3 (Note 1) | -6 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD | TBD | TBD |
| Precoding granularity | | PRB | 50 | 50 | 6 |
| PMI delay (Note 2) | | ms | 6 | 6 | 6 |
| Note 1: $P_B = 1$ | | | | | |
| Note 2: If the UE reports in an available uplink reporting instance at subframe SF#n based on PMI estimation at a downlink SF not later than SF#(n-4), this reported PMI cannot be applied at the eNB downlink before SF#(n+2) | | | | | |

Table 8.2.1.4.2-2: Minimum performance Multi-Layer Spatial Multiplexing (FRC)

| Test number | Bandwidth and MCS | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|---------------------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [5.1] | 10 MHz 16QAM 1/2 | [R.11 FDD] | EVA5 | 2x2 Low | 70 | 12.9 | |
| [5.2] | 10 MHz 16QAM 1/2 | [R.11 FDD] | ETU70 | 2x2 Low | 70 | 14.3 | |
| [5.3] | 10 MHz 16QAM 1/2 | [R.14 FDD] | EVA5 | 4x2 Low | 70 | 10.5 | |

8.2.1.5 MU-MIMO

8.2.1.6 [Control channel performance: D-BCH and PCH]

8.2.2 TDD (Fixed Reference Channel)

The parameters specified in Table 8.2.2-1 are valid for all TDD tests unless otherwise stated.

Table 8.2.2-1: Common Test Parameters (TDD)

| Parameter | | Value |
|--|--------------|--|
| Uplink downlink configuration (Note 1) | | 1 |
| Special subframe configuration (Note 2) | | 4 |
| Cyclic prefix | | Normal |
| Inter-TTI Distance | | 1 |
| Number of HARQ processes | Processes | 7 |
| Maximum number of HARQ transmission | | 4 |
| Redundancy version coding sequence | | {0,1,2,3} for QPSK and 16QAM {0,0,1,2} for 64QAM |
| Number of OFDM symbols for PDCCH | OFDM symbols | 4 for 1.4 MHz bandwidth, 3 for 3 MHz and 5 MHz bandwidths, 2 for 10 MHz, 15 MHz and 20 MHz bandwidths |
| Cyclic Prefix | | Normal |
| Note 1: as specified in Table 4.2-2 in [TS 36.211] | | |
| Note 2: as specified in Table 4.2-1 in [TS 36.211] | | |

8.2.2.1 Single-antenna port performance

The single-antenna performance in a given multi-path fading environments is determined by the SNR for which a certain relative information bit throughput of the reference measurement channels in Annex A.3.2 is achieved. The purpose of these tests is to verify the single-antenna performance with different channel models and MCS. The QPSK and 64QAM cases are also used to verify the performance for all bandwidths specified in Table 5.6.1-1.

8.2.2.1.1 Minimum Requirement QPSK

The requirements are specified in Table 8.2.2.1.1-2, with the addition of the parameters in Table 8.2.2.1.1-1 and the downlink physical channel setup according to table [in Annex C.3.2].

Table 8.2.2.1.1-1: Test Parameters for Testing QPSK

| Parameter | | Unit | Test [1.1-1.4,2.1] |
|---------------------------|----------|-----------|--------------------|
| Downlink power allocation | ρ_A | dB | 0 |
| | ρ_B | dB | 0 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Note 1: $P_B = 0$ | | | |

Table 8.2.2.1.1-2: Minimum performance QPSK (FRC)

| Test number | Bandwidth | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|-----------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [1.1] | 10 MHz | [R.2 TDD] | EVA5 | 1x2 Low | 70 | -1.2 | |
| [1.2] | 10 MHz | [R.2 TDD] | ETU70 | 1x2 Low | 70 | -0.6 | |
| [1.3] | 10 MHz | [R.2 TDD] | ETU300 | 1x2 Low | 70 | -0.2 | |
| [1.4] | 10 MHz | [R.2 TDD] | HST | 1x2 Low | 70 | TBD | |
| [2.1] | 1.4 MHz | [R.4 TDD] | EVA5 | 1x2 Low | 70 | TBD | |

8.2.2.1.2 Minimum Requirement 16QAM

The requirements are specified in Table 8.2.2.1.2-1, with the addition of the parameters in Table 8.2.2.1.2-2 and the downlink physical channel setup according to table [in Annex C.3.2].

Table 8.2.2.1.2-1: Test Parameters for Testing 16QAM

| Parameter | | Unit | Test [1.5-1.7] |
|---------------------------|----------|-----------|----------------|
| Downlink power allocation | ρ_A | dB | 0 |
| | ρ_B | dB | 0 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Note 1: $P_B = 0$ | | | |

Table 8.2.2.1.2-2: Minimum performance 16QAM (FRC)

| Test number | Bandwidth | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|-----------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [1.5] | 10 MHz | [R.3 TDD] | EVA5 | 1x2 Low | 70 | 6.7 | |
| [1.6] | 10 MHz | [R.3 TDD] | ETU70 | 1x2 Low | 30 | 1.4 | |
| [1.7] | 10 MHz | [R.3 TDD] | ETU300 | 1x2 High | 70 | 9.3 | |
| | | | | | | | |

8.2.2.1.3 Minimum Requirement 64QAM

The requirements are specified in Table 8.2.2.1.3-2, with the addition of the parameters in Table 8.2.2.1.3-1 and the downlink physical channel setup according to table [in Annex C.3.2].

Table 8.2.2.1.3-1: Test Parameters for Testing 64QAM

| Parameter | | Unit | Test [1.8-1.10,2.2-2.5] |
|---------------------------|----------|-----------|-------------------------|
| Downlink power allocation | ρ_A | dB | 0 |
| | ρ_B | dB | 0 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Note 1: $P_B = 0$ | | | |

Table 8.2.2.1.3-2: Minimum performance 64QAM (FRC)

| Test number | Bandwidth | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|-----------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [2.2] | 3 MHz | [R.5 TDD] | EVA5 | 1x2 Low | 70 | TBD | |
| [2.3] | 5 MHz | [R.6 TDD] | EVA5 | 1x2 Low | 70 | TBD | |
| [1.8] | 10 MHz | [R.7 TDD] | EVA5 | 1x2 Low | 70 | 17.6 | |
| [1.9] | 10 MHz | [R.7 TDD] | ETU70 | 1x2 Low | 70 | 19.1 | |
| [1.10] | 10 MHz | [R.7 TDD] | EVA5 | 1x2 High | 70 | 19.1 | |
| [2.4] | 15 MHz | [R.8 TDD] | EVA5 | 1x2 Low | 70 | TBD | |
| [2.5] | 20 MHz | [R.9 TDD] | EVA5 | 1x2 Low | 70 | TBD | |

8.2.2.1.4 Minimum Requirement 1 PRB allocation

The requirements are specified in Table 8.2.2.1.4-2, with the addition of the parameters in Table 8.2.2.1.1.4-1 and the downlink physical channel setup according to table [in Annex C.3.2]. The purpose of these tests is to verify the single-antenna performance with a single PRB allocated at the lower band edge.

Table 8.2.2.1.4-1: Test Parameters for Testing 1 PRB allocation

| Parameter | | Unit | Test [3.1-3.3] |
|--------------------------------|----------|-----------|---------------------------|
| Downlink power allocation | ρ_A | dB | 0 |
| | ρ_B | dB | 0 (Note 1) |
| N_{oc} at antenna port | | dBm/15kHz | TBD |
| Cell ID | | | 0 |
| OCNG [Symbols for unused PRBs] | | | [Zeros shall be inserted] |
| Note 1: $P_B = 0$ | | | |

Table 8.2.2.1.4-2: Minimum performance 1PRB (FRC)

| Test number | Bandwidth and MCS | Reference Channel | Propagation Condition | Correlation Matrix and Antenna Configuration | Reference value | | UE Category |
|-------------|---------------------|-------------------|-----------------------|--|------------------------------------|----------|-------------|
| | | | | | Fraction of Maximum Throughput (%) | SNR (dB) | |
| [3.1] | 3 MHz 16QAM 1/2 | [R.0 TDD] | ETU70 | 1x2 Low | 30 | TBD | |
| [3.2] | 10 MHz 16QAM 1/2 | [R.1 TDD] | ETU70 | 1x2 Low | 30 | TBD | |
| [3.3] | 20 MHz 16QAM 1/2 | [R.1 TDD] | ETU70 | 1x2 Low | 30 | TBD | |

8.2.2.2 Transmit diversity performance

8.2.2.3 Open-loop spatial multiplexing performance

8.2.2.4 Closed-loop spatial multiplexing performance

8.2.2.5 MU-MIMO

8.2.2.6 [Control channel performance: D-BCH and PCH]

8.3 Demodulation of PDSCH (User-Specific Reference Symbols)

8.4 Demodulation of PDCCH/PCFICH

The receiver characteristics of the PDCCH/PCFICH are determined by the probability of miss-detection of the Downlink Scheduling Grant (Pm-dsg). PDCCH and PCFICH are tested jointly, i.e. a miss detection of PCFICH implies a miss detection of PDCCH.

8.4.1 FDD

Table 8.4.1-1: Test Parameters for PDCCH/PCFICH

| Parameter | | Unit | Test [8.1] | | |
|---|----------|-----------|------------|--|--|
| Number of PDCCH symbols | | symbols | 2 | | |
| Number of PHICH groups (N_g) | | | 1 | | |
| PHICH duration | | | Normal | | |
| Cell ID | | | 0 | | |
| Downlink power allocation | PDCCH RA | dB | 0 | | |
| | PDCCH RB | dB | 0 | | |
| Power difference between PCFICH and PDCCH | | dB | 0 | | |
| N_{oc} at antenna port | | dBm/15kHz | | | |
| Cyclic prefix | | | Normal | | |

8.4.1.1 Single-antenna port performance

For the parameters specified in Table 8.4.1-1 the average probability of a missed downlink scheduling grant (Pm-dsg) shall be below the specified value in Table 8.4.1.1-1 [The downlink physical setup is in accordance with Annex C.3.2.]

Table 8.4.1.1-1: Minimum performance PDCCH/PCFICH

| Test number | Bandwidth | Aggregation level | Reference Channel | Propagation Condition | Correlation Matrix | Reference value | |
|-------------|-----------|-------------------|-------------------|-----------------------|--------------------|-----------------|----------|
| | | | | | | Pm-dsg (%) | SNR (dB) |
| [8.1] | 10 MHz | 8 CCE | [R.15 FDD] | ETU70 | Low | 1 | -1.7 |

8.4.1.2 Transmit diversity performance

8.4.2 TDD

Table 8.4.2-1: Test Parameters for PDCCH/PCFICH

| Parameter | | Unit | Test [8.1] | | |
|--|----------|-----------|------------|--|--|
| Uplink downlink configuration (Note 1) | | | 1 | | |
| Special subframe configuration (Note 2) | | | 4 | | |
| Number of PDCCH symbols | | symbols | 2 | | |
| Number of PHICH groups (N_g) | | | 1 | | |
| PHICH duration | | | Normal | | |
| Cell ID | | | 0 | | |
| Downlink power allocation | PDCCH_RA | dB | 0 | | |
| | PDCCH_RB | dB | 0 | | |
| Power difference between PCFICH and PDCCH | | dB | 0 | | |
| N_{oc} at antenna port | | dBm/15kHz | | | |
| Cyclic prefix | | | Normal | | |
| Note 1: as specified in Table 4.2-2 in [TS 36.211] | | | | | |
| Note 2: as specified in Table 4.2-1 in [TS 36.211] | | | | | |

8.4.2.1 Single-antenna port performance

For the parameters specified in Table 8.4.2-1 the average probability of a missed downlink scheduling grant (Pm-dsg) shall be below the specified value in Table 8.4.2.1-1 [The downlink physical setup is in accordance with Annex C.3.2.]

Table 8.4.2.1-1: Minimum performance PDCCH/PCFICH

| Test number | Bandwidth | Aggregation level | Reference Channel | Propagation Condition | Correlation Matrix | Reference value | |
|-------------|-----------|-------------------|-------------------|-----------------------|--------------------|-----------------|------------|
| | | | | | | Pm-dsg (%) | SNR (dB) |
| [8.1] | 10 MHz | 8 CCE | [R.15 TDD] | ETU70 | Low | 1 | [-1.6 + m] |

Editor's note: the margin "m" is TBD.

8.4.2.2 Transmit diversity performance

8.5 Demodulation of PHICH

8.6 Demodulation of PBCH

9 Reporting of Channel State Information

9.1 General

This section includes requirements for the reporting of channel state information (CSI).

9.2 CQI definition under AWGN conditions

The reporting accuracy of the channel quality indicator (CQI) under frequency non-selective conditions is determined by the reporting variance and the BLER performance using the transport format indicated by the reported CQI median. The purpose is to verify that the reported CQI values are in accordance with the CQI definition given in [TS 36.211].

9.2.1 Minimum requirement PUCCH 1-0

For the parameters specified in Table 9.2.1-1, and using the downlink physical channels specified in tables C.3.2-1 and C.3.2-2, the reported CQI value shall be in the range of +/-[1] of the reported median more than [90%] of the time. If the PDSCH BLER using the transport format indicated by median CQI is less than or equal to 0.1, the BLER using the transport format indicated by the (median CQI +[1]) shall be greater than 0.1. If the PDSCH BLER using the transport format indicated by the median CQI is greater than 0.1, the BLER using transport format indicated by (median CQI – [1]) shall be less than or equal to 0.1.

Table 9.2.1-1: PUCCH 1-0 static test

| Parameter | Unit | Test 1 | Test 2 |
|--|--------------|-----------|--------|
| Bandwidth | MHz | 10 | |
| PDSCH transmission mode | | [2] | |
| Reference signal power E_{RS} / I_{or} | dB | 3 | |
| SNR | dB | [0] | [6] |
| $N_{oc}^{(j)}$ | dB[mW/15kHz] | [-102] | [-102] |
| $\hat{I}_{or}^{(j)}$ | dB[mW/15kHz] | [-102] | [-96] |
| Reporting period | ms | [2-20 ms] | |
| NOTE: Reference measurement channel as per TS 36.213 Section 7.2.3 | | | |

Annex A (normative): Measurement channels

A.1 General

A.2 UL reference measurement channels

A.2.1 General

A.2.1.1 Applicability and common parameters

The following sections define the UL signal applicable to the Transmitter Characteristics (clause 6) and for the Receiver Characteristics (clause 7) where the UL signal is relevant.

The Reference channels in this section assume transmission of PUSCH and Demodulation Reference signal only. The following conditions apply:

- 1 HARQ transmission
- Cyclic Prefix normal
- PUSCH hopping off
- Link adaptation off
- Demodulation Reference signal as per TS 36.211 [4] subclause 5.5.2.1.2.

Where ACK/NACK is transmitted, it is assumed to be multiplexed on PUSCH as per TS 36.212 [5] subclause 5.2.2.6.

- ACK/NACK 1 bit
- ACK/NACK mapping adjacent to Demodulation Reference symbol
- ACK/NACK resources punctured into data
- Max number of resources for ACK/NACK: 4 SC-FDMA symbols per sub-carrier
- No CQI transmitted, no RI transmitted

A.2.1.2 Determination of payload size

The algorithm for determining the payload size A is as follows; given a desired coding rate R and radio block allocation N_{RB}

1. Calculate the number of channel bits N_{ch} that can be transmitted during the first transmission of a given sub-frame.
2. Find A such that the resulting coding rate is as close to R as possible, that is,

$$\min |R - (A + 24) / N_{ch}|,$$

subject to

- a) A is a valid TB size according to section 7.1.7 of TS 36.213 [6] assuming an allocation of N_{RB} resource blocks.

3. If there is more than one A that minimises the equation above, then the larger value is chosen per default.

A.2.2 Reference measurement channels for FDD

A.2.2.1 Full RB allocation

A.2.2.1.1 QPSK

Table A.2.2.1.1-1 Reference Channels for QPSK with full RB allocation

| Parameter | Unit | Value | | | | | |
|------------------------------------|------|-------|------|------|-------|-------|-------|
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | 6 | 15 | 25 | 50 | 75 | 100 |
| DFT-OFDM Symbols per subframe | | 12 | 12 | 12 | 12 | 12 | 12 |
| Modulation | | QPSK | QPSK | QPSK | QPSK | QPSK | QPSK |
| Target Coding rate | | 1/3 | 1/3 | 1/3 | 1/3 | 1/3 | 1/3 |
| Payload size | Bits | 600 | 1544 | 2216 | 5160 | 6712 | 10296 |
| Transport block CRC | Bits | 24 | 24 | 24 | 24 | 24 | 24 |
| Number of code blocks - C | | 1 | 1 | 1 | 1 | 2 | 2 |
| Code block CRC size | Bits | 0 | 0 | 0 | 0 | 24 | 24 |
| Total number of bits per sub-frame | Bits | 1728 | 4320 | 7200 | 14400 | 21600 | 28800 |
| Total symbols per sub-frame | | 864 | 2160 | 3600 | 7200 | 10800 | 14400 |

A.2.2.1.2 16-QAM

Table A.2.2.1.2-1 Reference Channels for 16-QAM with full RB allocation

| Parameter | Unit | Value | | | | | |
|------------------------------------|------|-------|-------|-------|-------|-------|-------|
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | 6 | 15 | 25 | 50 | 75 | 100 |
| DFT-OFDM Symbols per subframe | | 12 | 12 | 12 | 12 | 12 | 12 |
| Modulation | | 16QAM | 16QAM | 16QAM | 16QAM | 16QAM | 16QAM |
| Target Coding rate | | 3/4 | 3/4 | 3/4 | 3/4 | 3/4 | 3/4 |
| Payload size | Bits | 2600 | 6456 | 10680 | 21384 | 32856 | 43816 |
| Transport block CRC | Bits | 24 | 24 | 24 | 24 | 24 | 24 |
| Number of code blocks - C | | 1 | 2 | 2 | 4 | 6 | 7 |
| Code block CRC size | Bits | 0 | 24 | 24 | 24 | 24 | 24 |
| Total number of bits per sub-frame | Bits | 3456 | 8640 | 14400 | 28800 | 43200 | 57600 |
| Total symbols per sub-frame | | 864 | 2160 | 3600 | 7200 | 10800 | 14400 |

A.2.2.1.3 64-QAM

[FFS]

A.2.2.2 Partial RB allocation

For each channel bandwidth, various partial RB allocations are specified. The number of allocated RBs is chosen according to values specified in the Tx and Rx requirements. The single allocated RB case is included.

The allocated RBs are contiguous and start from one end of the channel bandwidth. A single allocated RB is at one end of the channel bandwidth.

A.2.2.2.1 QPSK

Table A.2.2.2.1-1 Reference Channels for 1.4MHz QPSK with partial RB allocation

| Parameter | Unit | Value | Value |
|------------------------------------|------|-------|-------|
| Channel bandwidth | MHz | 1.4 | 1.4 |
| Allocated resource blocks | | 1 | 5 |
| DFT-OFDM Symbols per subframe | | 12 | 12 |
| Modulation | | QPSK | QPSK |
| Target Coding rate | | 1/3 | 1/3 |
| Payload size | Bits | 72 | 424 |
| Transport block CRC | Bits | 24 | 24 |
| Number of code blocks - C | | 1 | 1 |
| Code block CRC size | Bits | 0 | 0 |
| Total number of bits per sub-frame | Bits | 288 | 1440 |
| Total symbols per sub-frame | | 144 | 720 |

Table A.2.2.2.1-2 Reference Channels for 3MHz QPSK with partial RB allocation

| Parameter | Unit | Value | Value |
|------------------------------------|------|-------|-------|
| Channel bandwidth | MHz | 3 | 3 |
| Allocated resource blocks | | 1 | 4 |
| DFT-OFDM Symbols per subframe | | 12 | 12 |
| Modulation | | QPSK | QPSK |
| Target Coding rate | | 1/3 | 1/3 |
| Payload size | Bits | 72 | 392 |
| Transport block CRC | Bits | 24 | 24 |
| Number of code blocks - C | | 1 | 1 |
| Code block CRC size | Bits | 0 | 0 |
| Total number of bits per sub-frame | Bits | 288 | 1152 |
| Total symbols per sub-frame | | 144 | 576 |

Table A.2.2.2.1-3 Reference Channels for 5MHz QPSK with partial RB allocation

| Parameter | Unit | Value | Value | Value |
|------------------------------------|------|-------|-------|-------|
| Channel bandwidth | MHz | 5 | 5 | 5 |
| Allocated resource blocks | | 1 | 8 | 20 |
| DFT-OFDM Symbols per subframe | | 12 | 12 | 12 |
| Modulation | | QPSK | QPSK | QPSK |
| Target Coding rate | | 1/3 | 1/3 | 1/3 |
| Payload size | Bits | 72 | 808 | 1736 |
| Transport block CRC | Bits | 24 | 24 | 24 |
| Number of code blocks - C | | 1 | 1 | 1 |
| Code block CRC size | Bits | 0 | 0 | 0 |
| Total number of bits per sub-frame | Bits | 288 | 2304 | 5760 |
| Total symbols per sub-frame | | 144 | 1152 | 2880 |

Table A.2.2.2.1-4 Reference Channels for 10MHz QPSK with partial RB allocation

| Parameter | Unit | Value | Value | Value | Value |
|------------------------------------|------|-------|-------|-------|-------|
| Channel bandwidth | MHz | 10 | 10 | 10 | 10 |
| Allocated resource blocks | | 1 | 12 | 20 | 25 |
| DFT-OFDM Symbols per subframe | | 12 | 12 | 12 | 12 |
| Modulation | | QPSK | QPSK | QPSK | QPSK |
| Target Coding rate | | 1/3 | 1/3 | 1/3 | 1/3 |
| Payload size | Bits | 72 | 1224 | 1736 | 2216 |
| Transport block CRC | Bits | 24 | 24 | 24 | 24 |
| Number of code blocks - C | | 1 | 1 | 1 | 1 |
| Code block CRC size | Bits | 0 | 0 | 0 | 0 |
| Total number of bits per sub-frame | Bits | 288 | 3456 | 5760 | 7200 |
| Total symbols per sub-frame | | 144 | 1728 | 2880 | 3600 |

Table A.2.2.2.1-5 Reference Channels for 15MHz QPSK with partial RB allocation

| Parameter | Unit | Value | Value | Value |
|------------------------------------|------|-------|-------|-------|
| Channel bandwidth | MHz | 15 | 15 | 15 |
| Allocated resource blocks | | 1 | 16 | 50 |
| DFT-OFDM Symbols per subframe | | 12 | 12 | 12 |
| Modulation | | QPSK | QPSK | QPSK |
| Target Coding rate | | 1/3 | 1/3 | 1/3 |
| Payload size | Bits | 72 | 1384 | 5160 |
| Transport block CRC | Bits | 24 | 24 | 24 |
| Number of code blocks - C | | 1 | 1 | 1 |
| Code block CRC size | Bits | 0 | 0 | 0 |
| Total number of bits per sub-frame | Bits | 288 | 4608 | 14400 |
| Total symbols per sub-frame | | 144 | 2304 | 7200 |

Table A.2.2.2.1-6 Reference Channels for 20MHz QPSK with partial RB allocation

| Parameter | Unit | Value | Value | Value | Value | Value |
|------------------------------------|------|-------|-------|-------|-------|-------|
| Channel bandwidth | MHz | 20 | 20 | 20 | 20 | 20 |
| Allocated resource blocks | | 1 | 18 | 25 | 50 | 75 |
| DFT-OFDM Symbols per subframe | | 12 | 12 | 12 | 12 | 12 |
| Modulation | | QPSK | QPSK | QPSK | QPSK | QPSK |
| Target Coding rate | | 1/3 | 1/3 | 1/3 | 1/3 | 1/3 |
| Payload size | Bits | 72 | 1864 | 2216 | 5160 | 6712 |
| Transport block CRC | Bits | 24 | 24 | 24 | 24 | 24 |
| Number of code blocks - C | | 1 | 1 | 1 | 1 | 2 |
| Code block CRC size | Bits | 0 | 0 | 0 | 0 | 24 |
| Total number of bits per sub-frame | Bits | 288 | 5184 | 7200 | 14400 | 21600 |
| Total symbols per sub-frame | | 144 | 2592 | 3600 | 7200 | 10800 |

A.2.2.2.2 16-QAM

Table A.2.2.2.2-1 Reference Channels for 1.4MHz 16-QAM with partial RB allocation

| Parameter | Unit | Value | Value |
|------------------------------------|------|-------|-------|
| Channel bandwidth | MHz | 1.4 | 1.4 |
| Allocated resource blocks | | 1 | 5 |
| DFT-OFDM Symbols per subframe | | 12 | 12 |
| Modulation | | 16QAM | 16QAM |
| Target Coding rate | | 3/4 | 3/4 |
| Payload size | Bits | 408 | 2152 |
| Transport block CRC | Bits | 24 | 24 |
| Number of code blocks - C | | 1 | 1 |
| Code block CRC size | Bits | 0 | 0 |
| Total number of bits per sub-frame | Bits | 576 | 2880 |
| Total symbols per sub-frame | | 144 | 720 |

Table A.2.2.2.2-2 Reference Channels for 3MHz 16-QAM with partial RB allocation

| Parameter | Unit | Value | Value |
|------------------------------------|------|-------|-------|
| Channel bandwidth | MHz | 3 | 3 |
| Allocated resource blocks | | 1 | 4 |
| DFT-OFDM Symbols per subframe | | 12 | 12 |
| Modulation | | 16QAM | 16QAM |
| Target Coding rate | | 3/4 | 3/4 |
| Payload size | Bits | 408 | 1736 |
| Transport block CRC | Bits | 24 | 24 |
| Number of code blocks – C | | 1 | 1 |
| Code block CRC size | Bits | 0 | 0 |
| Total number of bits per sub-frame | Bits | 576 | 2304 |
| Total symbols per sub-frame | | 144 | 576 |

Table A.2.2.2.2-3 Reference Channels for 5MHz 16-QAM with partial RB allocation

| Parameter | Unit | Value | Value |
|------------------------------------|------|-------|-------|
| Channel bandwidth | MHz | 5 | 5 |
| Allocated resource blocks | | 1 | 8 |
| DFT-OFDM Symbols per subframe | | 12 | 12 |
| Modulation | | 16QAM | 16QAM |
| Target Coding rate | | 3/4 | 3/4 |
| Payload size | Bits | 408 | 3496 |
| Transport block CRC | Bits | 24 | 24 |
| Number of code blocks - C | | 1 | 1 |
| Code block CRC size | Bits | 0 | 0 |
| Total number of bits per sub-frame | Bits | 576 | 4608 |
| Total symbols per sub-frame | | 144 | 1152 |

Table A.2.2.2.2-4 Reference Channels for 10MHz 16-QAM with partial RB allocation

| Parameter | Unit | Value | Value |
|------------------------------------|------|-------|-------|
| Channel bandwidth | MHz | 10 | 10 |
| Allocated resource blocks | | 1 | 12 |
| DFT-OFDM Symbols per subframe | | 12 | 12 |
| Modulation | | 16QAM | 16QAM |
| Target Coding rate | | 3/4 | 3/4 |
| Payload size | Bits | 408 | 5160 |
| Transport block CRC | Bits | 24 | 24 |
| Number of code blocks - C | | 1 | 1 |
| Code block CRC size | Bits | 0 | 0 |
| Total number of bits per sub-frame | Bits | 576 | 6912 |
| Total symbols per sub-frame | | 144 | 1728 |

Table A.2.2.2.2-5 Reference Channels for 15MHz 16-QAM with partial RB allocation

| Parameter | Unit | Value | Value |
|------------------------------------|------|-------|-------|
| Channel bandwidth | MHz | 15 | 15 |
| Allocated resource blocks | | 1 | 16 |
| DFT-OFDM Symbols per subframe | | 12 | 12 |
| Modulation | | 16QAM | 16QAM |
| Target Coding rate | | 3/4 | 3/4 |
| Payload size | Bits | 408 | 6968 |
| Transport block CRC | Bits | 24 | 24 |
| Number of code blocks - C | | 1 | 2 |
| Code block CRC size | Bits | 0 | 24 |
| Total number of bits per sub-frame | Bits | 576 | 9216 |
| Total symbols per sub-frame | | 144 | 2304 |

Table A.2.2.2.2-6 Reference Channels for 20MHz 16-QAM with partial RB allocation

| Parameter | Unit | Value | Value |
|------------------------------------|------|-------|-------|
| Channel bandwidth | MHz | 20 | 20 |
| Allocated resource blocks | | 1 | 18 |
| DFT-OFDM Symbols per subframe | | 12 | 12 |
| Modulation | | 16QAM | 16QAM |
| Target Coding rate | | 3/4 | 3/4 |
| Payload size | Bits | 408 | 7736 |
| Transport block CRC | Bits | 24 | 24 |
| Number of code blocks - C | | 1 | 2 |
| Code block CRC size | Bits | 0 | 24 |
| Total number of bits per sub-frame | Bits | 576 | 10368 |
| Total symbols per sub-frame | | 144 | 2592 |

A.2.2.2.3 64-QAM

[FFS]

A.2.3 Reference measurement channels for TDD

[FFS]

A.2.3.1 Full RB allocation

[FFS]

A.2.3.1.1 QPSK

[FFS]

A.2.3.1.2 16-QAM

[FFS]

A.2.3.1.3 64-QAM

[FFS]

A.2.3.2 Partial RB allocation

[FFS]

A.2.3.2.1 QPSK

[FFS]

A.2.3.2.2 16-QAM

[FFS]

A.2.3.2.3 64-QAM

[FFS]

A.3 DL reference measurement channels

A.3.1 General

The number of available channel bits varies across the sub-frames due to PBCH and PSS/SSS overhead. The payload size per sub-frame is varied in order to keep the code rate constant throughout a frame.

The algorithm for determining the payload size A is as follows; given a desired coding rate R and radio block allocation N_{RB}

1. Calculate the number of channel bits N_{ch} that can be transmitted during the first transmission of a given sub-frame.
2. Find A such that the resulting coding rate is as close to R as possible, that is,

$$\min |R - (A + 24) / N_{ch}|,$$

subject to

- a) A is a valid TB size according to section 7.1.7 of TS 36.213 [6] assuming an allocation of N_{RB} resource blocks.
- 3. If there is more than one A that minimizes the equation above, then the larger value is chosen per default.
- 4. For TDD, the measurement channel is based on DL/UL configuration ratio of 2DL+DwPTS (12 OFDM symbol):
2UL

A.3.2 Reference measurement channel for receiver characteristics

Tables A.3.2-1 and A.3.2-2 are applicable for measurements on the Receiver Characteristics (clause 7) with the exception of sub-clause 7.4 (Maximum input level).

Tables A.3.2-3 and A.3.2-4 are applicable for sub-clause 7.4 (Maximum input level).

Tables A.3.2-1 and A.3.2-2 also apply for the modulated interferer used in Clauses 7.5, 7.6 and 7.8 with test specific bandwidths.

Table A.3.2-1 Fixed Reference Channel for Receiver Requirements (FDD)

| Parameter | Unit | Value | | | | | |
|---|-----------|-------|--------|--------|-------|-------|-------|
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | 6 | 15 | 25 | 50 | 75 | 100 |
| Subcarriers per resource block | | 12 | 12 | 12 | 12 | 12 | 12 |
| Allocated subframes per Radio Frame | | 10 | 10 | 10 | 10 | 10 | 10 |
| Modulation | | QPSK | QPSK | QPSK | QPSK | QPSK | QPSK |
| Target Coding Rate | | 1/3 | 1/3 | 1/3 | 1/3 | 1/3 | 1/3 |
| Number of HARQ Processes | Processes | 8 | 8 | 8 | 8 | 8 | 8 |
| Maximum number of HARQ transmissions | | 1 | 1 | 1 | 1 | 1 | 1 |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | 408 | 1320 | 2216 | 4392 | 6712 | 8760 |
| For Sub-Frame 5 | Bits | 328 | 1064 | 1800 | 4392 | 6712 | 8760 |
| For Sub-Frame 0 | Bits | 152 | 872 | 1800 | 4392 | 6712 | 8760 |
| Transport block CRC | Bits | 24 | 24 | 24 | 24 | 24 | 24 |
| Number of Code Blocks per subframe | | 1 | 1 | 1 | 1 | 2 | 2 |
| Code block CRC size | Bits | 0 | 0 | 0 | 0 | 24 | 24 |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | 1368 | 3780 | 6300 | 13800 | 20700 | 27600 |
| For Sub-Frame 5 | Bits | 1080 | 3492 | 6012 | 13512 | 20412 | 27312 |
| For Sub-Frame 0 | Bits | 528 | 2940 | 5460 | 12960 | 19860 | 26760 |
| Max. Throughput averaged over 1 frame | kbps | 374.4 | 1249.6 | 2132.8 | 4392 | 6712 | 8760 |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 15 MHz and 10MHz channel BW. 3 symbols allocated to PDCCH for 5 MHz and 3 MHz. 4 symbols allocated to PDCCH for 1.4 MHz | | | | | | | |
| Note 2: Reference signal, Synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |
| Note 3: The RLC should be configured to Unacknowledged Mode | | | | | | | |

Table A.3.2-2 Fixed Reference Channel for Receiver Requirements (TDD)

| Parameter | Unit | Value | | | | | |
|---|-----------|-------|-------|--------|--------|--------|--------|
| Channel Bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | 6 | 15 | 25 | 50 | 75 | 100 |
| Uplink-Downlink Configuration | | 1 | 1 | 1 | 1 | 1 | 1 |
| Allocated subframes per Radio Frame (D+S) | | 4 | 4+2 | 4+2 | 4+2 | 4+2 | 4+2 |
| Number of HARQ Processes | Processes | 8 | 8 | 8 | 8 | 8 | 8 |
| Maximum number of HARQ transmission | | 1 | 1 | 1 | 1 | 1 | 1 |
| Modulation | | QPSK | QPSK | QPSK | QPSK | QPSK | QPSK |
| Target coding rate | | 1/3 | 1/3 | 1/3 | 1/3 | 1/3 | 1/3 |
| Information Bit Payload per Sub-Frame | Bits | | | | | | |
| For Sub-Frame 4, 9 | | 408 | 1320 | 2216 | 4392 | 6712 | 8760 |
| For Sub-Frame 1, 6 | | n/a | 1064 | 1800 | 3624 | 5352 | 7224 |
| For Sub-Frame 0 | | 208 | 1064 | 1800 | 4392 | 6712 | 8760 |
| For Sub-Frame 5 | | 408 | 1064 | 2216 | 4392 | 6712 | 8760 |
| Transport block CRC | Bits | 24 | 24 | 24 | 24 | 24 | 24 |
| Number of Code Blocks | | 1 | 1 | 1 | 1 | 2 | 2 |
| Code block CRC size | | 0 | 0 | 0 | 0 | 24 | 24 |
| Binary Channel Bits Per Sub-Frame | Bits | | | | | | |
| For Sub-Frame 4, 9 | | 1368 | 3780 | 6300 | 13800 | 20700 | 27600 |
| For Sub-Frame 1, 6 | | n/a | 3276 | 5556 | 11256 | 16956 | 22656 |
| For Sub-Frame 5 | | 1224 | 3636 | 6156 | 13656 | 20556 | 27456 |
| Max. Throughput averaged over one frame | kbps | 143.2 | 689.6 | 1204.8 | 2481.6 | 3755.2 | 4948.8 |
| Note 1: For normal subframes(0,4,5,9), 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 10 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz. For special subframe (1&6), only 2 OFDM symbols are allocated to PDCCH for all BWs. | | | | | | | |
| Note 2: For 1.4MHz, no data shall be scheduled on special subframes(1&6) to avoid problems with insufficient PDCCH performance | | | | | | | |
| Note 3: Reference signal, Synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |
| Note 4: The RLC should be configured to Unacknowledged Mode | | | | | | | |

Table A.3.2-3 Fixed Reference Channel for Maximum input level (FDD)

| Parameter | Unit | Value | | | | | |
|---|-----------|--------|-------|--------|-------|-------|-------|
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | 6 | 15 | 25 | 50 | 75 | 100 |
| Subcarriers per resource block | | 12 | 12 | 12 | 12 | 12 | 12 |
| Allocated subframes per Radio Frame | | 10 | 10 | 10 | 10 | 10 | 10 |
| Modulation | | 64QAM | 64QAM | 64QAM | 64QAM | 64QAM | 64QAM |
| Target Coding Rate | | 3/4 | 3/4 | 3/4 | 3/4 | 3/4 | 3/4 |
| Number of HARQ Processes | Processes | 8 | 8 | 8 | 8 | 8 | 8 |
| Maximum number of HARQ transmissions | | 1 | 1 | 1 | 1 | 1 | 1 |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | 2984 | 8504 | 14112 | 30576 | 46888 | 61664 |
| For Sub-Frame 5 | Bits | 2344 | 7992 | 13536 | 30576 | 45352 | 61664 |
| For Sub-Frame 0 | Bits | 1192 | 6456 | 12576 | 28336 | 45352 | 61664 |
| Transport block CRC | Bits | 24 | 24 | 24 | 24 | 24 | 24 |
| Number of Code Blocks per subframe | | 1 | 2 | 3 | 5 | 8 | 11 |
| Code block CRC size | Bits | 0 | 24 | 24 | 24 | 24 | 24 |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | 4104 | 11340 | 18900 | 41400 | 62100 | 82800 |
| For Sub-Frame 5 | Bits | 3240 | 10476 | 18036 | 40536 | 61236 | 81936 |
| For Sub-Frame 0 | Bits | 1584 | 8820 | 16380 | 38880 | 59580 | 80280 |
| Max. Throughput averaged over 1 frame | kbps | 2470.8 | 8248 | 13901. | 30352 | 46581 | 61664 |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 15 MHz channel BW. 3 symbols allocated to PDCCH for 5 MHz and 3 MHz. 4 symbols allocated to PDCCH for 1.4 MHz | | | | | | | |
| Note 2: Reference signal, Synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |
| Note 3: The RLC should be configured to Unacknowledged Mode | | | | | | | |

Table A.3.2-4 Fixed Reference Channel for Maximum input level (TDD)

[FFS]

A.3.3 Reference measurement channels for PDSCH performance requirements (FDD)

A.3.3.1 Single-antenna transmission (Common Reference Symbols)

Table A.3.3.1-1: Fixed Reference Channel QPSK R=1/3

| Parameter | Unit | Value | | | | | |
|---|------|-----------|---|---|-----------|----|----|
| Reference channel | | [R.4 FDD] | | | [R.2 FDD] | | |
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | 6 | | | 50 | | |
| Allocated subframes per Radio Frame | | 10 | | | 10 | | |
| Modulation | | QPSK | | | QPSK | | |
| Target Coding Rate | | 1/3 | | | 1/3 | | |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | 408 | | | 4392 | | |
| For Sub-Frame 5 | Bits | 328 | | | 4392 | | |
| For Sub-Frame 0 | Bits | 152 | | | 4392 | | |
| Number of Code Blocks per subframe | | 1 | | | 1 | | |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | 1368 | | | 13800 | | |
| For Sub-Frame 5 | Bits | 1080 | | | 13512 | | |
| For Sub-Frame 0 | Bits | 528 | | | 12960 | | |
| Max. Throughput averaged over 1 frame | Mbps | 0.374 | | | 4.39 | | |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 15 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz | | | | | | | |
| Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |

Table A.3.3.1-2: Fixed Reference Channel 16QAM R=1/2

| Parameter | Unit | Value | | | | | |
|---|------|-------|---|---|-----------|----|----|
| Reference channel | | | | | [R.3 FDD] | | |
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | | | | 50 | | |
| Allocated subframes per Radio Frame | | | | | 10 | | |
| Modulation | | | | | 16QAM | | |
| Target Coding Rate | | | | | 1/2 | | |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | | | 14112 | | |
| For Sub-Frame 5 | Bits | | | | 12960 | | |
| For Sub-Frame 0 | Bits | | | | 12960 | | |
| Number of Code Blocks per subframe | | | | | 3 | | |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | | | 27600 | | |
| For Sub-Frame 5 | Bits | | | | 27024 | | |
| For Sub-Frame 0 | Bits | | | | 25920 | | |
| Max. Throughput averaged over 1 frame | Mbps | | | | 13.9 | | |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 15 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz | | | | | | | |
| Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |

Table A.3.3.1-3: Fixed Reference Channel 64QAM R=3/4

| Parameter | Unit | Value | | | | | |
|-------------------|------|-------|-----------|-----------|-----------|-----------|-----------|
| Reference channel | | | [R.5 FDD] | [R.6 FDD] | [R.7 FDD] | [R.8 FDD] | [R.9 FDD] |
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |

| | | | | | | | |
|---|------|-------|-------|-------|-------|-------|-------|
| Allocated resource blocks | | | 15 | 25 | 50 | 75 | 100 |
| Allocated subframes per Radio Frame | | | 10 | 10 | 10 | 10 | 10 |
| Modulation | | 64QAM | 64QAM | 64QAM | 64QAM | 64QAM | 64QAM |
| Target Coding Rate | | 3/4 | 3/4 | 3/4 | 3/4 | 3/4 | 3/4 |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | 8504 | 14112 | 30576 | 46888 | 61664 |
| For Sub-Frame 5 | Bits | | 7992 | 13536 | 30576 | 45352 | 61664 |
| For Sub-Frame 0 | Bits | | 6456 | 12576 | 28336 | 45352 | 61664 |
| Number of Code Blocks per subframe | | | 2 | 3 | 5 | 8 | 11 |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | 11340 | 18900 | 41400 | 62100 | 82800 |
| For Sub-Frame 5 | Bits | | 10476 | 18036 | 40536 | 61236 | 81936 |
| For Sub-Frame 0 | Bits | | 8820 | 16380 | 38880 | 59580 | 80280 |
| Max. Throughput averaged over 1 frame | Mbps | | 8.25 | 13.9 | 30.4 | 46.6 | 61.7 |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 15 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz | | | | | | | |
| Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |

Table A.3.3.1-4: Fixed Reference Channel Single PRB (Channel Edge)

| Parameter | Unit | Value | | | | | |
|---|------|-------|--------------|---|--------------|----|----|
| Reference channel | | | [R.0 FDD] | | [R.1 FDD] | | |
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10/20 | 15 | 20 |
| Allocated resource blocks | | | 1 | | 1 | | |
| Allocated subframes per Radio Frame | | | 10 | | 10 | | |
| Modulation | | | 16QAM | | 16QAM | | |
| Target Coding Rate | | | 1/2 | | 1/2 | | |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | 224 | | 256 | | |
| For Sub-Frame 5 | Bits | | 224 | | 256 | | |
| For Sub-Frame 0 | Bits | | 224 | | 256 | | |
| Number of Code Blocks per subframe | | | 1 | | 1 | | |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | 504 | | 552 | | |
| For Sub-Frame 5 | Bits | | 504 | | 552 | | |
| For Sub-Frame 0 | Bits | | 504 | | 552 | | |
| Max. Throughput averaged over 1 frame | Mbps | | 0.224 | | 0.256 | | |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 15 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz | | | | | | | |
| Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |

A.3.3.2 Multi-antenna transmission (Common Reference Symbols)

A.3.3.2.1 Two antenna ports

Table A.3.3.2.1-1: Fixed Reference Channel two antenna ports

| Parameter | Unit | Value | | | | | |
|---|------|-------|---------------|---------------|--|--|--|
| Reference channel | | | [R.10 FDD] | [R.11 FDD] | | | |
| Channel bandwidth | MHz | | 10 | 10 | | | |
| Allocated resource blocks | | | 50 | 50 | | | |
| Allocated subframes per Radio Frame | | | 10 | 10 | | | |
| Modulation | | | QPSK | 16QAM | | | |
| Target Coding Rate | | | 1/3 | 1/2 | | | |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | 4392 | 12960 | | | |
| For Sub-Frame 5 | Bits | | 4392 | 12960 | | | |
| For Sub-Frame 0 | Bits | | 4392 | 12960 | | | |
| Number of Code Blocks per subframe | | | 1 | 3 | | | |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | 13200 | 26400 | | | |
| For Sub-Frame 5 | Bits | | 12912 | 25824 | | | |
| For Sub-Frame 0 | Bits | | 12384 | 24768 | | | |
| Max. Throughput averaged over 1 frame | Mbps | | 4.39 | 13.0 | | | |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 15 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz | | | | | | | |
| Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |

A.3.3.2.2 Four antenna ports

Table A.3.3.2.2-1: Fixed Reference Channel four antenna ports

| Parameter | Unit | Value | | | | | |
|---|------|-------|---------------|---------------|---------------|--|--|
| Reference channel | | | [R.12 FDD] | [R.13 FDD] | [R.14 FDD] | | |
| Channel bandwidth | MHz | | 1.4 | 10 | 10 | | |
| Allocated resource blocks | | | 6 | 50 | 50 | | |
| Allocated subframes per Radio Frame | | | 10 | 10 | 10 | | |
| Modulation | | | QPSK | QPSK | 16QAM | | |
| Target Coding Rate | | | 1/3 | 1/3 | 1/2 | | |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | 408 | 4392 | 12960 | | |
| For Sub-Frame 5 | Bits | | 328 | 4392 | 12960 | | |
| For Sub-Frame 0 | Bits | | 152 | 3624 | 11448 | | |
| Number of Code Blocks per subframe | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | | | 1 | 1 | 3 | | |
| For Sub-Frame 5 | | | 1 | 1 | 3 | | |
| For Sub-Frame 0 | | | 1 | 1 | 2 | | |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 1,2,3,4,6,7,8,9 | Bits | | 1248 | 12800 | 25600 | | |
| For Sub-Frame 5 | Bits | | 960 | 12512 | 25024 | | |
| | Bits | | 480 | 12032 | 24064 | | |
| Max. Throughput averaged over 1 frame | Mbps | | 0.374 | 4.32 | 12.8 | | |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 15 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz | | | | | | | |
| Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |

A.3.3.3 [RMC for UE-Specific Reference Symbols]

A.3.4 Reference measurement channels for PDSCH performance requirements (TDD)

A.3.4.1 Single-antenna transmission (Common Reference Symbols)

Table A.3.4.1-1: Fixed Reference Channel QPSK R=1/3

| Parameter | Unit | Value | | | | | |
|--|------|--------------|---|---|--------------|----|----|
| Reference channel | | [R.4 TDD] | | | [R.2 TDD] | | |
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | 6 | | | 50 | | |
| Uplink-Downlink Configuration (Note 3) | | 1 | | | 1 | | |
| Allocated subframes per Radio Frame (D+S) | | 4+2 | | | 4+2 | | |
| Modulation | | QPSK | | | QPSK | | |
| Target Coding Rate | | 1/3 | | | 1/3 | | |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 4,9 | Bits | 408 | | | 4392 | | |
| For Sub-Frames 1,6 | Bits | n/a | | | 3624 | | |
| For Sub-Frame 5 | Bits | 408 | | | 4392 | | |
| For Sub-Frame 0 | Bits | 208 | | | 4392 | | |
| Number of Code Blocks per subframe | | 1 | | | 1 | | |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 4,9 | Bits | 1368 | | | 13800 | | |
| For Sub-Frames 1,6 | Bits | n/a | | | 11256 | | |
| For Sub-Frame 5 | Bits | 1224 | | | 13656 | | |
| For Sub-Frame 0 | Bits | 672 | | | 13104 | | |
| Max. Throughput averaged over 1 frame | Mbps | 0.143 | | | 2.48 | | |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 10 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz. For subframe 1&6, only 2 OFDM symbols are allocated to PDCCH. Note 2: For BW=1.4 MHz, the information bit payloads of special subframes are set to zero (no scheduling) to avoid problems with insufficient PDCCH performance at the test point. Note 3: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] Note 4: as per Table 4.2-2 in TS 36.211 [4] | | | | | | | |

Table A.3.4.1-2: Fixed Reference Channel 16QAM R=1/2

| Parameter | Unit | Value | | | | | |
|---|------|-------|---|---|--------------|----|----|
| Reference channel | | | | | [R.3 TDD] | | |
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | | | | 50 | | |
| Uplink-Downlink Configuration (Note 3) | | | | | 1 | | |
| Allocated subframes per Radio Frame (D+S) | | | | | 4+2 | | |
| Modulation | | | | | 16QAM | | |
| Target Coding Rate | | | | | 1/2 | | |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 4,9 | Bits | | | | 14112 | | |
| For Sub-Frames 1,6 | Bits | | | | 11448 | | |
| For Sub-Frame 5 | Bits | | | | 14112 | | |
| For Sub-Frame 0 | Bits | | | | 12960 | | |
| Number of Code Blocks per subframe | | | | | | | |
| For Sub-Frames 4,9 | | | | | 3 | | |
| For Sub-Frames 1,6 | | | | | 2 | | |
| For Sub-Frame 5 | | | | | 3 | | |

| | | | | | | | |
|--|------|--|--|--|-------|--|--|
| For Sub-Frame 0 | | | | | 3 | | |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 4,9 | Bits | | | | 27600 | | |
| For Sub-Frames 1,6 | Bits | | | | 22512 | | |
| For Sub-Frame 5 | Bits | | | | 27312 | | |
| For Sub-Frame 0 | Bits | | | | 26208 | | |
| Max. Throughput averaged over 1 frame | Mbps | | | | 7.82 | | |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 10 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz. For subframe 1&6, only 2 OFDM symbols are allocated to PDCCH. | | | | | | | |
| Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |
| Note 3: as per Table 4.2-2 in TS 36.211 [4] | | | | | | | |

Table A.3.4.1-3: Fixed Reference Channel 64QAM R=3/4

| Parameter | Unit | Value | | | | | |
|--|------|-------|--------------|--------------|--------------|--------------|--------------|
| Reference channel | | | [R.5 TDD] | [R.6 TDD] | [R.7 TDD] | [R.8 TDD] | [R.9 TDD] |
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10 | 15 | 20 |
| Allocated resource blocks | | | 15 | 25 | 50 | 75 | 100 |
| Uplink-Downlink Configuration (Note 3) | | | 1 | 1 | 1 | 1 | 1 |
| Allocated subframes per Radio Frame (D+S) | | | 4+2 | 4+2 | 4+2 | 4+2 | 4+2 |
| Modulation | | 64QAM | 64QAM | 64QAM | 64QAM | 64QAM | 64QAM |
| Target Coding Rate | | | 3/4 | 3/4 | 3/4 | 3/4 | 3/4 |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 4,9 | Bits | | 8504 | 14112 | 30576 | 46888 | 61664 |
| For Sub-Frames 1,6 | Bits | | 7480 | 12576 | 25456 | 37888 | 51024 |
| For Sub-Frame 5 | Bits | | 7992 | 14112 | 30576 | 46888 | 61664 |
| For Sub-Frame 0 | Bits | | 6968 | 12576 | 30576 | 45352 | 61664 |
| Number of Code Blocks per subframe | | | | | | | |
| For Sub-Frames 4,9 | | | 2 | 3 | 41400 | 62100 | 82800 |
| For Sub-Frames 1,6 | | | 2 | 3 | 33768 | 50868 | 67968 |
| For Sub-Frame 5 | | | 2 | 3 | 40968 | 61668 | 82368 |
| For Sub-Frame 0 | | | 2 | 3 | 39312 | 60012 | 80712 |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 4,9 | Bits | | 11340 | 18900 | 5 | 8 | 11 |
| For Sub-Frames 1,6 | Bits | | 9828 | 16668 | 5 | 7 | 9 |
| For Sub-Frame 5 | Bits | | 10908 | 18468 | 5 | 8 | 11 |
| For Sub-Frame 0 | Bits | | 9252 | 16812 | 5 | 8 | 11 |
| Max. Throughput averaged over 1 frame | Mbps | | 4.69 | 8.01 | 17.3 | 26.2 | 34.9 |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 10 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz. For subframe 1&6, only 2 OFDM symbols are allocated to PDCCH. | | | | | | | |
| Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |
| Note 3: as per Table 4.2-2 TS 36.211 [4] | | | | | | | |

Table A.3.4.1-4: Fixed Reference Channel Single PRB

| Parameter | Unit | Value | | | | | |
|---|------|-------|--------------|---|--------------|----|----|
| Reference channel | | | [R.0 TDD] | | [R.1 TDD] | | |
| Channel bandwidth | MHz | 1.4 | 3 | 5 | 10/20 | 15 | 20 |
| Allocated resource blocks | | | 1 | | 1 | | |
| Uplink-Downlink Configuration (Note 3) | | | 1 | | 1 | | |
| Allocated subframes per Radio Frame (D+S) | | | 4+2 | | 4+2 | | |
| Modulation | | | 16QAM | | 16QAM | | |
| Target Coding Rate | | | 1/2 | | 1/2 | | |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 4,9 | Bits | | 224 | | 256 | | |
| For Sub-Frames 1,6 | Bits | | 208 | | 208 | | |
| For Sub-Frame 5 | Bits | | 224 | | 256 | | |

| | | | |
|--|------|-------|-------|
| For Sub-Frame 0 | Bits | 224 | 256 |
| Number of Code Blocks per subframe | | 1 | 1 |
| Binary Channel Bits Per Sub-Frame | | | |
| For Sub-Frames 4,9 | Bits | 504 | 552 |
| For Sub-Frames 1,6 | Bits | 456 | 456 |
| For Sub-Frame 5 | Bits | 504 | 552 |
| For Sub-Frame 0 | Bits | 504 | 552 |
| Max. Throughput averaged over 1 frame | Mbps | 0.131 | 0.144 |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 10 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz. For subframe 1&6, only 2 OFDM symbols are allocated to PDCCH. Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] Note 3: as per Table 4.2-2 in TS 36.211 [4] | | | |

A.3.4.2 Multi-antenna transmission (Common Reference Signals)

A.3.4.2.1 Two antenna ports

Table A.3.4.2.1-1: Fixed Reference Channel two antenna ports

| Parameter | Unit | Value | |
|--|------|------------|------------|
| Reference channel | | [R.10 TDD] | [R.11 TDD] |
| Channel bandwidth | MHz | 10 | 10 |
| Allocated resource blocks | | 50 | 50 |
| Uplink-Downlink Configuration (Note 3) | | 1 | 1 |
| Allocated subframes per Radio Frame (D+S) | | 4+2 | 4+2 |
| Modulation | | QPSK | 16QAM |
| Target Coding Rate | | 1/3 | 1/2 |
| Information Bit Payload | | | |
| For Sub-Frames 4,9 | Bits | 4392 | 12960 |
| For Sub-Frames 1,6 | | 3624 | 9912 |
| For Sub-Frame 5 | Bits | 4392 | 12960 |
| For Sub-Frame 0 | Bits | 4392 | 12960 |
| Number of Code Blocks per subframe | | | |
| For Sub-Frames 4,9 | | 1 | 3 |
| For Sub-Frames 1,6 | | 1 | 2 |
| For Sub-Frame 5 | | 1 | 3 |
| For Sub-Frame 0 | | 1 | 3 |
| Binary Channel Bits Per Sub-Frame | | | |
| For Sub-Frames 4,9 | Bits | 13200 | 26400 |
| For Sub-Frames 1,6 | | 10656 | 21312 |
| For Sub-Frame 5 | Bits | 13056 | 26112 |
| For Sub-Frame 0 | Bits | 12528 | 25056 |
| Max. Throughput averaged over 1 frame | Mbps | 2.48 | 7.17 |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 10 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz. For subframe 1&6, only 2 OFDM symbols are allocated to PDCCH. Note 2: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] Note 3: as per Table 4.2-2 in TS 36.211 [4] | | | |

A.3.4.2.2 Four antenna ports

Table A.3.4.2.2-1: Fixed Reference Channel four antenna ports

| Parameter | Unit | Value | | | | | |
|--|------|---------------|---------------|---------------|--|--|--|
| Reference channel | | [R.12 TDD] | [R.13 TDD] | [R.14 TDD] | | | |
| Channel bandwidth | MHz | 1.4 | 10 | 10 | | | |
| Allocated resource blocks | | 6 | 50 | 50 | | | |
| Uplink-Downlink Configuration (Note 4) | | 1 | 1 | 1 | | | |
| Allocated subframes per Radio Frame (D+S) | | 4+2 | 4+2 | 4+2 | | | |
| Modulation | | QPSK | QPSK | 16QAM | | | |
| Target Coding Rate | | 1/3 | 1/3 | 1/2 | | | |
| Information Bit Payload | | | | | | | |
| For Sub-Frames 4,9 | Bits | 408 | 4392 | 12960 | | | |
| For Sub-Frames 1,6 | Bits | n/a | 3624 | 9912 | | | |
| For Sub-Frame 5 | Bits | 328 | 4392 | 12960 | | | |
| For Sub-Frame 0 | Bits | 208 | 4392 | 11448 | | | |
| Number of Code Blocks per subframe | | | | | | | |
| For Sub-Frames 4,9 | | 1 | 1 | 3 | | | |
| For Sub-Frames 1,6 | | 1 | 1 | 2 | | | |
| For Sub-Frame 5 | | 1 | 1 | 3 | | | |
| For Sub-Frame 0 | | 1 | 1 | 2 | | | |
| Binary Channel Bits Per Sub-Frame | | | | | | | |
| For Sub-Frames 4,9 | Bits | 1248 | 12800 | 25600 | | | |
| For Sub-Frames 1,6 | | n/a | 10256 | 20512 | | | |
| For Sub-Frame 5 | Bits | 1104 | 12656 | 25312 | | | |
| For Sub-Frame 0 | Bits | 624 | 12176 | 24352 | | | |
| Max. Throughput averaged over 1 frame | Mbps | 0.135 | 2.48 | 7.02 | | | |
| Note 1: 2 symbols allocated to PDCCH for 20 MHz, 15 MHz and 10 MHz channel BW; 3 symbols allocated to PDCCH for 5 MHz and 3 MHz; 4 symbols allocated to PDCCH for 1.4 MHz. For subframe 1&6, only 2 OFDM symbols are allocated to PDCCH. | | | | | | | |
| Note 2: For BW=1.4 MHz, the information bit payloads of special subframes are set to zero (no scheduling) to avoid problems with insufficient PDCCH performance at the test point. | | | | | | | |
| Note 3: Reference signal, synchronization signals and PBCH allocated as per TS 36.211 [4] | | | | | | | |
| Note 4: as per Table 4.2-2 in TS 36.211 [4] | | | | | | | |

A.3.4.3 [RMC for UE-Specific Reference Symbols]

A.3.5 Reference measurement channels for PDCCH/PCFICH performance requirements

A.3.5.1 FDD

Table A.3.5.1-1: Reference Channel FDD

| Parameter | Unit | Value | | |
|----------------------------------|---------|------------|------------|------------|
| Reference channel | | [R.15 FDD] | [R.16 FDD] | [R.17 FDD] |
| Number of transmitter antennas | | 1 | 2 | 4 |
| Channel bandwidth | MHz | 10 | 1.4 | 10 |
| Number of OFDM symbols for PDCCH | symbols | 2 | 2 | 2 |
| Aggregation level | CCE | 8 | 2 | 4 |
| DCI Format | | Format 1 | Format 1 | Format 2 |
| Cell ID | | 0 | 0 | 0 |
| Payload (without CRC) | Bits | 31 | 32+1 | 46 |
| | | | | |

A.3.5.2 TDD

Table A.3.5.1-1: Reference Channel TDD

| Parameter | Unit | Value | | |
|----------------------------------|---------|------------|------------|------------|
| Reference channel | | [R.15 TDD] | [R.16 TDD] | [R.17 TDD] |
| Number of transmitter antennas | | 1 | 2 | 4 |
| Channel bandwidth | MHz | 10 | 1.4 | 10 |
| Number of OFDM symbols for PDCCH | symbols | 2 | 2 | 2 |
| Aggregation level | CCE | 8 | 2 | 4 |
| DCI Format | | Format 1 | Format 1 | Format 2 |
| Cell ID | | 0 | 0 | 0 |
| Payload (without CRC) | Bits | 34 | 35 | 49 |
| | | | | |

Annex B (normative): Propagation conditions

B.1 Static propagation condition

B.2 Multi-path fading propagation conditions

The multipath propagation conditions consist of several parts:

- A delay profile in the form of a "tapped delay-line", characterized by a number of taps at fixed positions on a sampling grid. The profile can be further characterized by the r.m.s. delay spread and the maximum delay spanned by the taps.
- A combination of channel model parameters that include the Delay profile and the Doppler spectrum, that is characterized by a classical spectrum shape and a maximum Doppler frequency
- A set of correlation matrices defining the correlation between the UE and eNodeB antennas in case of multi-antenna systems.

B.2.1 Delay profiles

The delay profiles are selected to be representative of low, medium and high delay spread environments. The resulting model parameters are defined in Table B.2.1-1 and the tapped delay line models are defined in Tables B.2.1-2, B.2.1-3 and B.2.1-4.

Table B.2.1-1 Delay profiles for E-UTRA channel models

| Model | Number of channel taps | Delay spread (r.m.s.) | Maximum excess tap delay (span) |
|------------------------------------|------------------------|-----------------------|---------------------------------|
| Extended Pedestrian A (EPA) | 7 | 45 ns | 410 ns |
| Extended Vehicular A model (EVA) | 9 | 357 ns | 2510 ns |
| Extended Typical Urban model (ETU) | 9 | 991 ns | 5000 ns |

Table B.2.1-2 Extended Pedestrian A model (EPA)

| Excess tap delay [ns] | Relative power [dB] |
|-----------------------|---------------------|
| 0 | 0.0 |
| 30 | -1.0 |
| 70 | -2.0 |
| 90 | -3.0 |
| 110 | -8.0 |
| 190 | -17.2 |
| 410 | -20.8 |

Table B.2.1-3 Extended Vehicular A model (EVA)

| Excess tap delay [ns] | Relative power [dB] |
|--------------------------|------------------------|
| 0 | 0.0 |
| 30 | -1.5 |
| 150 | -1.4 |
| 310 | -3.6 |
| 370 | -0.6 |
| 710 | -9.1 |
| 1090 | -7.0 |
| 1730 | -12.0 |
| 2510 | -16.9 |

Table B.2.1-4 Extended Typical Urban model (ETU)

| Excess tap delay [ns] | Relative power [dB] |
|--------------------------|------------------------|
| 0 | -1.0 |
| 50 | -1.0 |
| 120 | -1.0 |
| 200 | 0.0 |
| 230 | 0.0 |
| 500 | 0.0 |
| 1600 | -3.0 |
| 2300 | -5.0 |
| 5000 | -7.0 |

B.2.2 Combinations of channel model parameters

Table B.2.2-1 shows propagation conditions that are used for the performance measurements in multi-path fading environment for low, medium and high Doppler frequencies

Table B.2.2-1 Channel model parameters

| Model | Maximum Doppler frequency |
|-----------|---------------------------|
| EPA 5Hz | 5 Hz |
| EVA 5Hz | 5 Hz |
| EVA 70Hz | 70 Hz |
| ETU 70Hz | 70 Hz |
| ETU 300Hz | 300 Hz |

B.2.3 MIMO Channel Correlation Matrices

B.2.3.1 Definition of MIMO Correlation Matrices

Table B.2.3.1-1 defines the correlation matrix for the eNodeB

Table B.2.3.1-1 eNodeB correlation matrix

| | One antenna | Two antennas | Four antennas |
|----------------------------|---------------|--|---|
| eNode B Correlation | $R_{eNB} = 1$ | $R_{eNB} = \begin{pmatrix} 1 & \alpha \\ \alpha^* & 1 \end{pmatrix}$ | $R_{eNB} = \begin{pmatrix} 1 & \alpha^{1/9} & \alpha^{4/9} & \alpha \\ \alpha^{1/9*} & 1 & \alpha^{1/9} & \alpha^{4/9} \\ \alpha^{4/9*} & \alpha^{1/9*} & 1 & \alpha^{1/9} \\ \alpha^* & \alpha^{4/9*} & \alpha^{1/9*} & 1 \end{pmatrix}$ |

Table B.2.3.1-2 defines the correlation matrix for the UE:

Table B.2.3.1-2 UE correlation matrix

| | One antenna | Two antennas | Four antennas |
|-----------------------|--------------|---|--|
| UE Correlation | $R_{UE} = 1$ | $R_{UE} = \begin{pmatrix} 1 & \beta \\ \beta^* & 1 \end{pmatrix}$ | $R_{UE} = \begin{pmatrix} 1 & \beta^{1/9} & \beta^{4/9} & \beta \\ \beta^{1/9*} & 1 & \beta^{1/9} & \beta^{4/9} \\ \beta^{4/9*} & \beta^{1/9*} & 1 & \beta^{1/9} \\ \beta^* & \beta^{4/9*} & \beta^{1/9*} & 1 \end{pmatrix}$ |

Table B.2.3.1-3 defines the channel spatial correlation matrix R_{spat} . The parameters, α and β in Table B.2.3.1-3 defines the spatial correlation between the antennas at the eNodeB and UE.

Table B.2.3.1-3: R_{spat} correlation matrices

| | |
|-----------------|--|
| 1x2 case | $R_{spat} = R_{UE} = \begin{bmatrix} 1 & \beta \\ \beta^* & 1 \end{bmatrix}$ |
| 2x2 case | $R_{spat} = R_{eNB} \otimes R_{UE} = \begin{bmatrix} 1 & \alpha \\ \alpha^* & 1 \end{bmatrix} \otimes \begin{bmatrix} 1 & \beta \\ \beta^* & 1 \end{bmatrix} = \begin{bmatrix} 1 & \beta & \alpha & \alpha\beta \\ \beta^* & 1 & \alpha\beta^* & \alpha \\ \alpha^* & \alpha^*\beta & 1 & \beta \\ \alpha^*\beta^* & \alpha^* & \beta^* & 1 \end{bmatrix}$ |
| 4x2 case | $R_{spat} = R_{eNB} \otimes R_{UE} = \begin{bmatrix} 1 & \alpha^{1/9} & \alpha^{4/9} & \alpha \\ \alpha^{1/9*} & 1 & \alpha^{1/9} & \alpha^{4/9} \\ \alpha^{4/9*} & \alpha^{1/9*} & 1 & \alpha^{1/9} \\ \alpha^* & \alpha^{4/9*} & \alpha^{1/9*} & 1 \end{bmatrix} \otimes \begin{bmatrix} 1 & \beta \\ \beta^* & 1 \end{bmatrix}$ |

| | |
|-----------------|---|
| 4x4 case | $R_{spat} = R_{eNB} \otimes R_{UE} = \begin{bmatrix} 1 & \alpha^{1/9} & \alpha^{4/9} & \alpha \\ \alpha^{1/9*} & 1 & \alpha^{1/9} & \alpha^{4/9} \\ \alpha^{4/9*} & \alpha^{1/9*} & 1 & \alpha^{1/9} \\ \alpha^* & \alpha^{4/9*} & \alpha^{1/9*} & 1 \end{bmatrix} \otimes \begin{bmatrix} 1 & \beta^{1/9} & \beta^{4/9} & \beta \\ \beta^{1/9*} & 1 & \beta^{1/9} & \beta^{4/9} \\ \beta^{4/9*} & \beta^{1/9*} & 1 & \beta^{1/9} \\ \beta^* & \beta^{4/9*} & \beta^{1/9*} & 1 \end{bmatrix}$ |
|-----------------|---|

For cases with more antennas at either eNodeB or UE or both, the channel spatial correlation matrix can still be expressed as the Kronecker product of R_{eNB} and R_{UE} according to $R_{spat} = R_{eNB} \otimes R_{UE}$.

B.2.3.2 MIMO Correlation Matrices at High, Medium and Low Level

The α and β for different correlation types are given in Table B.2.3.2-1.

Table B.2.3.2-1

| Low correlation | | Medium Correlation | | High Correlation | |
|-----------------|---------|--------------------|---------|------------------|---------|
| α | β | α | β | α | β |
| 0 | 0 | 0.3 | 0.9 | 0.9 | 0.9 |

The correlation matrices for high, medium and low correlation are defined in Table B.2.3.1-2, B.2.3.2-3 and B.2.3.2-4, as below.

The values in the table have been adjusted for the 4x2 and 4x4 high correlation cases to insure the correlation matrix is positive semi-definite after round-off to 4 digit precision. This is done using the equation:

$$\mathbf{R}_{high} = [\mathbf{R}_{spatial} + a\mathbf{I}_n] / (1 + a)$$

Where the value “a” is a scaling factor such that the smallest value is used to obtain a positive semi-definite result. For the 4x2 high correlation case, a=0.00010. For the 4x4 high correlation case, a=0.00012.

Table B.2.3.2-2: MIMO correlation matrices for high correlation

| | |
|-----------------|---|
| 1x2 case | $R_{high} = \begin{pmatrix} 1 & 0.9 \\ 0.9 & 1 \end{pmatrix}$ |
| 2x2 case | $R_{high} = \begin{pmatrix} 1 & 0.9 & 0.9 & 0.81 \\ 0.9 & 1 & 0.81 & 0.9 \\ 0.9 & 0.81 & 1 & 0.9 \\ 0.81 & 0.9 & 0.9 & 1 \end{pmatrix}$ |
| 4x2 case | $R_{high} = \begin{bmatrix} 1.0000 & 0.8999 & 0.9883 & 0.8894 & 0.9542 & 0.8587 & 0.8999 & 0.8099 \\ 0.8999 & 1.0000 & 0.8894 & 0.9883 & 0.8587 & 0.9542 & 0.8099 & 0.8999 \\ 0.9883 & 0.8894 & 1.0000 & 0.8999 & 0.9883 & 0.8894 & 0.9542 & 0.8587 \\ 0.8894 & 0.9883 & 0.8999 & 1.0000 & 0.8894 & 0.9883 & 0.8587 & 0.9542 \\ 0.9542 & 0.8587 & 0.9883 & 0.8894 & 1.0000 & 0.8999 & 0.9883 & 0.8894 \\ 0.8587 & 0.9542 & 0.8894 & 0.9883 & 0.8999 & 1.0000 & 0.8894 & 0.9883 \\ 0.8999 & 0.8099 & 0.9542 & 0.8587 & 0.9883 & 0.8894 & 1.0000 & 0.8999 \\ 0.8099 & 0.8999 & 0.8587 & 0.9542 & 0.8894 & 0.9883 & 0.8999 & 1.0000 \end{bmatrix}$ |

| | | |
|-----------------|--------------|---|
| 4x4 case | $R_{high} =$ | 1.0000 0.9882 0.9541 0.8999 0.9882 0.9767 0.9430 0.8894 0.9541 0.9430 0.9105 0.8587 0.8999 0.8894 0.8587 0.8099 |
| | | 0.9882 1.0000 0.9882 0.9541 0.9767 0.9882 0.9767 0.9430 0.9430 0.9541 0.9430 0.9105 0.8894 0.8999 0.8894 0.8587 |
| | | 0.9541 0.9882 1.0000 0.9882 0.9430 0.9767 0.9882 0.9767 0.9105 0.9430 0.9541 0.9430 0.8587 0.8894 0.8999 0.8894 |
| | | 0.8999 0.9541 0.9882 1.0000 0.8894 0.9430 0.9767 0.9882 0.8587 0.9105 0.9430 0.9541 0.8099 0.8587 0.8894 0.8999 |
| | | 0.9882 0.9767 0.9430 0.8894 1.0000 0.9882 0.9541 0.8999 0.9882 0.9767 0.9430 0.8894 0.9541 0.9430 0.9105 0.8587 |
| | | 0.9767 0.9882 0.9767 0.9430 0.9882 1.0000 0.9882 0.9541 0.9767 0.9882 0.9767 0.9430 0.9430 0.9541 0.9430 0.9105 |
| | | 0.9430 0.9767 0.9882 0.9767 0.9541 0.9882 1.0000 0.9882 0.9430 0.9767 0.9882 0.9767 0.9105 0.9430 0.9541 0.9430 |
| | | 0.8894 0.9430 0.9767 0.9882 0.8999 0.9541 0.9882 1.0000 0.8894 0.9430 0.9767 0.9882 0.8587 0.9105 0.9430 0.9541 |
| | | 0.9541 0.9430 0.9105 0.8587 0.9882 0.9767 0.9430 0.8894 1.0000 0.9882 0.9541 0.8999 0.9882 0.9767 0.9430 0.8894 |
| | | 0.9430 0.9541 0.9430 0.9105 0.9767 0.9882 0.9767 0.9430 0.9882 1.0000 0.9882 0.9541 0.9767 0.9882 0.9767 0.9430 |
| | | 0.9105 0.9430 0.9541 0.9430 0.9430 0.9767 0.9882 0.9767 0.9541 0.9882 1.0000 0.9882 0.9430 0.9767 0.9882 0.9767 |
| | | 0.8587 0.9105 0.9430 0.9541 0.8894 0.9430 0.9767 0.9882 0.8999 0.9541 0.9882 1.0000 0.8894 0.9430 0.9767 0.9882 |
| | | 0.8999 0.8894 0.8587 0.8099 0.9541 0.9430 0.9105 0.8587 0.9882 0.9767 0.9430 0.8894 1.0000 0.9882 0.9541 0.8999 |
| | | 0.8894 0.8999 0.8894 0.8587 0.9430 0.9541 0.9430 0.9105 0.9767 0.9882 0.9767 0.9430 0.9882 1.0000 0.9882 0.9541 |
| | | 0.8587 0.8894 0.8999 0.8894 0.9105 0.9430 0.9541 0.9430 0.9430 0.9767 0.9882 0.9767 0.9541 0.9882 1.0000 0.9882 |
| | | 0.8099 0.8587 0.8894 0.8999 0.8587 0.9105 0.9430 0.9541 0.8894 0.9430 0.9767 0.9882 0.8999 0.9541 0.9882 1.0000 |

Table B.2.3.2-3: MIMO correlation matrices for medium correlation

| | |
|-----------------|---|
| 1x2 case | N/A |
| 2x2 case | $R_{medium} = \begin{pmatrix} 1 & 0.9 & 0.3 & 0.27 \\ 0.9 & 1 & 0.27 & 0.3 \\ 0.3 & 0.27 & 1 & 0.9 \\ 0.27 & 0.3 & 0.9 & 1 \end{pmatrix}$ |
| 4x2 case | $R_{medium} = \begin{pmatrix} 1.0000 & 0.9000 & 0.8748 & 0.7873 & 0.5856 & 0.5271 & 0.3000 & 0.2700 \\ 0.9000 & 1.0000 & 0.7873 & 0.8748 & 0.5271 & 0.5856 & 0.2700 & 0.3000 \\ 0.8748 & 0.7873 & 1.0000 & 0.9000 & 0.8748 & 0.7873 & 0.5856 & 0.5271 \\ 0.7873 & 0.8748 & 0.9000 & 1.0000 & 0.7873 & 0.8748 & 0.5271 & 0.5856 \\ 0.5856 & 0.5271 & 0.8748 & 0.7873 & 1.0000 & 0.9000 & 0.8748 & 0.7873 \\ 0.5271 & 0.5856 & 0.7873 & 0.8748 & 0.9000 & 1.0000 & 0.7873 & 0.8748 \\ 0.3000 & 0.2700 & 0.5856 & 0.5271 & 0.8748 & 0.7873 & 1.0000 & 0.9000 \\ 0.2700 & 0.3000 & 0.5271 & 0.5856 & 0.7873 & 0.8748 & 0.9000 & 1.0000 \end{pmatrix}$ |
| 4x4 case | TBD |

Table B.2.3.2-4: MIMO correlation matrices for low correlation

| | |
|-----------------|-----------------------------|
| 1x2 case | $R_{low} = \mathbf{I}_2$ |
| 2x2 case | $R_{low} = \mathbf{I}_4$ |
| 4x2 case | $R_{low} = \mathbf{I}_8$ |
| 4x4 case | $R_{low} = \mathbf{I}_{16}$ |

In Table B.2.3.2-4, \mathbf{I}_d is the $d \times d$ identity matrix.

B.3 High speed train scenario

The high speed train condition for the test of the baseband performance is a non fading propagation channel with one tap. Doppler shift is given by

$$f_s(t) = f_d \cos \theta(t) \quad (\text{B.3.1})$$

where $f_s(t)$ is the Doppler shift and f_d is the maximum Doppler frequency. The cosine of angle $\theta(t)$ is given by

$$\cos \theta(t) = \frac{D_s/2 - vt}{\sqrt{D_{\min}^2 + (D_s/2 - vt)^2}}, \quad 0 \leq t \leq D_s/v \quad (\text{B.3.2})$$

$$\cos \theta(t) = \frac{-1.5D_s + vt}{\sqrt{D_{\min}^2 + (-1.5D_s + vt)^2}}, \quad D_s/v < t \leq 2D_s/v \quad (\text{B.3.3})$$

$$\cos \theta(t) = \cos \theta(t \bmod (2D_s/v)), \quad t > 2D_s/v \quad (\text{B.3.4})$$

where $D_s/2$ is the initial distance of the train from eNodeB, and D_{\min} is eNodeB Railway track distance, both in meters; v is the velocity of the train in m/s, t is time in seconds.

Doppler shift and cosine angle are given by equation B.3.1 and B.3.2-B.3.4 respectively, where the required input parameters listed in table B.3-1 and the resulting Doppler shift shown in Figure B.3-1 are applied for all frequency bands.

Table B.3-1: High speed train scenario

| Parameter | Value |
|------------|----------|
| D_s | 300 m |
| D_{\min} | 2 m |
| v | 300 km/h |
| f_d | 750 Hz |

NOTE 1: Parameters for HST conditions in table B.3-1 including f_d and Doppler shift trajectories presented on figure B.3-1 were derived for Band 7.




Figure B.3-1: Doppler shift trajectory

Annex C (normative): Downlink Physical Channels

C.1 General

This annex specifies the downlink physical channels that are needed for setting a connection and channels that are needed during a connection.

C.2 Set-up

Table C.2-1 describes the downlink Physical Channels that are required for connection set up.

**Table C.2-1: Downlink Physical Channels required
for connection set-up**

| Physical Channel |
|------------------|
| PBCH |
| SSS |
| PSS |
| PCFICH |
| PDCCH |
| PHICH |
| PDSCH |

C.3 Connection

The following clauses, describes the downlink Physical Channels that are transmitted during a connection i.e., when measurements are done.

C.3.1 Measurement of Receiver Characteristics

Table C.3.1-1 is applicable for measurements on the Receiver Characteristics (clause 7).

Table C.3.1-1: Downlink Physical Channels transmitted during a connection (FDD and TDD)

| Physical Channel | EPRE Ratio | |
|------------------|------------------|--|
| PBCH | PBCH RA = 0 dB | |
| | PBCH RB = 0 dB | |
| PSS | PSS RA = 0 dB | |
| SSS | SSS RA = 0 dB | |
| PCFICH | PCFICH RB = 0 dB | |
| PDCCH | PDCCH RA = 0 dB | |
| | PDCCH RB = 0 dB | |
| PDSCH | PDSCH RA = 0 dB | |
| | PDSCH RB = 0 dB | |
| | | |

NOTE 1: No boosting is applied.

Table C.3.1-2: Power allocation for OFDM symbols and reference signals

| Parameter | Unit | Value | Note |
|--|------------|---------------|--|
| Transmitted power spectral density I_{or} | dBm/15 kHz | Test specific | 1. I_{or} shall be kept constant throughout all OFDM symbols |
| Cell-specific reference signal power ratio E_{RS} / I_{or} | | 0 dB | |
| | | | |
| | | | |

C.3.2 Measurement of Performance requirements

Table C.3.2-1 is applicable for measurements in which uniform RS-to-EPRE boosting for all downlink physical channels.

Table C.3.2-1: Downlink Physical Channels transmitted during a connection (FDD and TDD)

| Physical Channel | EPRE Ratio | |
|------------------|-----------------|--|
| PBCH | PBCH ρ_A | |
| | PBCH ρ_B | |
| PSS | PSS ρ_A | |
| SSS | SSS ρ_A | |
| PCFICH | PCFICH ρ_B | |
| PDCCH | PDCCH ρ_A | |
| | PDCCH ρ_B | |
| PDSCH | PDSCH ρ_A | |
| | PDSCH ρ_B | |
| | | |

NOTE 1: $\rho_A = \rho_B = 0$ dB means no RS boosting.

Table C.3.2-2: Power allocation for OFDM symbols and reference signals

| Parameter | Unit | Value | Note |
|--|------------|---------------|--|
| Total transmitted power spectral density I_{or} | dBm/15 kHz | Test specific | 1. I_{or} shall be kept constant throughout all OFDM symbols |
| Cell-specific reference signal power ratio E_{RS} / I_{or} | | Test specific | 1. Applies for antenna port p |

Annex D (normative): Characteristics of the interfering signal

D.1 General

When the channel band width is wider or equal to 5MHz, a modulated 5MHz full band width E-UTRA down link signal and CW signal are used as interfering signals when RF performance requirements for E-UTRA UE receiver are defined. For channel band widths below 5MHz, the band width of modulated interferer should be equal to band width of the received signal.

D.2 Interference signals

Table D.2-1 describes the modulated interferer for different channel band width options.

Table D.2-1: Description of modulated E-UTRA interferer

| | Channel bandwidth | | | | | |
|--------------------------|-------------------|-------|-------|--------|--------|--------|
| | 1.4 MHz | 3 MHz | 5 MHz | 10 MHz | 15 MHz | 20 MHz |
| RB | 6 | 15 | 25 | 50 | 75 | 100 |
| BW _{Interferer} | 1.4 MHz | 3 MHz | 5 MHz | 5 MHz | 5 MHz | 5 MHz |

Annex E (normative): Environmental conditions

E.1 General

This normative annex specifies the environmental requirements of the UE. Within these limits the requirements of the present documents shall be fulfilled.

E.2 Environmental

The requirements in this clause apply to all types of UE(s).

E.2.1 Temperature

The UE shall fulfil all the requirements in the full temperature range of:

Table E.2.1-1

| | |
|----------------|---|
| +15°C to +35°C | for normal conditions (with relative humidity of 25 % to 75 %) |
| -10°C to +55°C | for extreme conditions (see IEC publications 68-2-1 and 68-2-2) |

Outside this temperature range the UE, if powered on, shall not make ineffective use of the radio frequency spectrum. In no case shall the UE exceed the transmitted levels as defined in clause 6.2 for extreme operation.

E.2.2 Voltage

The UE shall fulfil all the requirements in the full voltage range, i.e. the voltage range between the extreme voltages.

The manufacturer shall declare the lower and higher extreme voltages and the approximate shutdown voltage. For the equipment that can be operated from one or more of the power sources listed below, the lower extreme voltage shall not be higher, and the higher extreme voltage shall not be lower than that specified below.

Table E.2.2-1

| Power source | Lower extreme voltage | Higher extreme voltage | Normal conditions voltage |
|-----------------------------|-----------------------|------------------------|---------------------------|
| AC mains | 0,9 * nominal | 1,1 * nominal | nominal |
| Regulated lead acid battery | 0,9 * nominal | 1,3 * nominal | 1,1 * nominal |
| Non regulated batteries: | | | |
| Leclanché | 0,85 * nominal | Nominal | Nominal |
| Lithium | 0,95 * nominal | 1,1 * Nominal | 1,1 * Nominal |
| Mercury/nickel & cadmium | 0,90 * nominal | | Nominal |

Outside this voltage range the UE if powered on, shall not make ineffective use of the radio frequency spectrum. In no case shall the UE exceed the transmitted levels as defined in clause 6.2 for extreme operation. In particular, the UE shall inhibit all RF transmissions when the power supply voltage is below the manufacturer declared shutdown voltage.

E.2.3 Vibration

The UE shall fulfil all the requirements when vibrated at the following frequency/amplitudes.

Table E.2.3-1

| Frequency | ASD (Acceleration Spectral Density) random vibration |
|------------------|---|
| 5 Hz to 20 Hz | 0,96 m ² /s ³ |
| 20 Hz to 500 Hz | 0,96 m ² /s ³ at 20 Hz, thereafter –3 dB/Octave |

Outside the specified frequency range the UE, if powered on, shall not make ineffective use of the radio frequency spectrum. In no case shall the UE exceed the transmitted levels as defined in TS 36.101 for extreme operation.

Annex F (normative): Transmit modulation

F.1 Measurement Point

Figure F.1-1 shows the measurement point for the unwanted emission falling into non-allocated RB(s) and the EVM for the allocated RB(s).




Figure F.1-1: EVM measurement points

F.2 Basic Error Vector Magnitude measurement

The EVM is the difference between the ideal waveform and the measured waveform for the allocated RB(s)

$$EVM = \sqrt{\frac{\sum_{v \in T_m} |z'(v) - i(v)|^2}{|T_m| \cdot P_0}},$$

where

T_m is a set of $|T_m|$ modulation symbols with the considered modulation scheme being active within the measurement period,

$z'(v)$ are the samples of the signal evaluated for the EVM,

$i(v)$ is the ideal signal reconstructed by the measurement equipment, and

P_0 is the average power of the ideal signal. For normalized modulation symbols P_0 is equal to 1.

The basic EVM measurement interval is defined over one slot in the time domain.

F.3 Basic in-band emissions measurement

The in-band emissions are a measure of the interference falling into the non-allocated resources blocks

For the non-allocated RBs below the allocated frequency block the in-band emissions would be measured as follows

$$Emissions_{absolute}(\Delta_{RB}) = \frac{1}{|T_s|} \sum_{t \in T_s} \sum_{\substack{\min(f_{\min}, c-12 \cdot \Delta_{RB}) \\ \max(f_{\min}, c-12 \cdot \Delta_{RB})}}^{\min(f_{\max}, c-12 \cdot \Delta_{RB} + 11)} |Y(t, f)|^2,$$

where

T_s is a set of $|T_s|$ SC-FDMA symbols with the considered modulation scheme being active within the measurement period,

Δ_{RB} is the starting frequency offset between the allocated RB and the measured non-allocated RB (e.g. $\Delta_{RB} = 1$ or $\Delta_{RB} = -1$ for the first adjacent RB),

f_{\min} (resp. f_{\max}) is the lower (resp. upper) edge of the UL system BW,

c is the lower edge of the allocated BW, and

$Y(t, f)$ is the frequency domain signal evaluated for in-band emissions as defined in the subsection (ii)

The relative in-band emissions are, given by

$$Emissions_{relative}(\Delta_{RB}) = \frac{Emissions_{absolute}(\Delta_{RB})}{\frac{1}{|T_s| \cdot N_{RB}} \sum_{t \in T_s} \sum_c^{c+12 \cdot N_{RB}-1} |Y(t, f)|^2}$$

where

N_{RB} is the number of allocated RBs

The basic in-band emissions measurement interval is defined over one slot in the time domain.

F.4 Modified signal under test

Implicit in the definition of EVM is an assumption that the receiver is able to compensate a number of transmitter impairments. The signal under test is equalised and decoded according to:

$$Z'(t, f) = IDFT \left\{ \frac{FFT \left\{ z(v - \Delta \tilde{t}) \cdot e^{-j2\pi \Delta \tilde{f} v} \right\} e^{j2\pi \Delta \tilde{f} t}}{\tilde{a}(t, f) \cdot e^{j\tilde{\varphi}(t, f)}} \right\}$$

where

$z(v)$ is the time domain samples of the signal under test.

To minimize the error, the signal under test should be modified with respect to a set of parameters following the procedure explained below.

Notation:

$\Delta \tilde{t}$ is the sample timing difference between the FFT processing window in relation to nominal timing of the ideal signal.

$\Delta \tilde{f}$ is the RF frequency offset.

$\tilde{\varphi}(t, f)$ is the phase response of the TX chain.

$\tilde{a}(t, f)$ is the amplitude response of the TX chain.

In the following $\Delta\tilde{c}$ represents the middle sample of the EVM window of length W (defined in the next subsections) or the last sample of the first window half if W is even.

The EVM analyser shall

- detect the start of each slot and estimate $\Delta\tilde{t}$ and $\Delta\tilde{f}$,
- determine $\Delta\tilde{c}$ so that the EVM window of length W is centred
 - on the time interval determined by the measured cyclic prefix minus 16 samples of the considered OFDM symbol for symbol 0 for normal CP, i.e. the first 16 samples of the CP should not be taken into account for this step.
 - on the measured cyclic prefix of the considered OFDM symbol for symbol 1 to 6 for normal CP and for symbol 0 to 5 for extended CP.

To determine the other parameters a sample timing offset equal to $\Delta\tilde{c}$ is corrected from the signal under test. The EVM analyser shall then

- correct the RF frequency offset $\Delta\tilde{f}$ for each time slot, and
- apply an FFT of appropriate size.

The IQ origin offset shall be removed from the evaluated signal before calculating the EVM and the in-band emissions; however, the removed relative IQ origin offset power (relative carrier leakage power) also has to satisfy the applicable requirement.

At this stage the allocated RBs shall be separated from the non-allocated RBs. The signal on the non-allocated RB(s), $Y(t, f)$, is used to evaluate the in-band emissions.

Moreover, the following procedure applies only to the signal on the allocated RB(s). The UL EVM analyzer shall then estimate the TX chain equalizer coefficients $\tilde{a}(t, f)$ and $\tilde{\varphi}(t, f)$ used by the ZF equalizer for all subcarriers by

1. time averaging at each signal subcarrier of the amplitude and phase of the reference and data symbols, the time-averaging length is 1 slot. This process creates an average amplitude and phase for each signal subcarrier used by the ZF equalizer.

At this stage estimates of $\Delta\tilde{f}$, $\tilde{a}(t, f)$, $\tilde{\varphi}(t, f)$ and $\Delta\tilde{c}$ are available. $\Delta\tilde{t}$ is one of the extremities of the window W , i.e. $\Delta\tilde{t}$ can be $\Delta\tilde{c} + \alpha - \left\lfloor \frac{W}{2} \right\rfloor$ or $\Delta\tilde{c} + \left\lfloor \frac{W}{2} \right\rfloor$, where $\alpha = 0$ if W is odd and $\alpha = 1$ if W is even. The EVM analyser shall then

- calculate EVM_l with $\Delta\tilde{t}$ set to $\Delta\tilde{c} + \alpha - \left\lfloor \frac{W}{2} \right\rfloor$,
- calculate EVM_h with $\Delta\tilde{t}$ set to $\Delta\tilde{c} + \left\lfloor \frac{W}{2} \right\rfloor$.

F.5 Window length

F.5.1 Timing offset

As a result of using a cyclic prefix, there is a range of $\Delta\tilde{t}$, which, at least in the case of perfect Tx signal quality, would give close to minimum error vector magnitude. As a first order approximation, that range should be equal to the length of the cyclic prefix. Any time domain windowing or FIR pulse shaping applied by the transmitter reduces the $\Delta\tilde{t}$ range within which the error vector is close to its minimum.

F.5.2 Window length

The window length W affects the measured EVM, and is expressed as a function of the configured cyclic prefix length. In the case where equalization is present, as with frequency domain EVM computation, the effect of FIR is reduced. This is because the equalization can correct most of the linear distortion introduced by the FIR. However, the time domain windowing effect can't be removed.

F.5.3 Window length for normal CP

The table below specifies the EVM window length at channel bandwidths 1.4, 3, 5, 10, 15, 20 MHz, for normal CP. The nominal window length for 3 MHz is rounded down one sample to allow the window to be centered on the symbol.

Table F.5.3-1 EVM window length for normal CP

| Channel Bandwidth MHz | Cyclic prefix length N_{cp} for symbol 0 | Cyclic prefix length N_{cp} for symbols 1 to 6 | Nominal FFT size | Cyclic prefix for symbols 1 to 6 in FFT samples | EVM window length W | Ratio of W to CP for symbols 1 to 6* |
|--|--|--|------------------|---|-----------------------|--|
| 1.4 | 160 | 144 | 128 | 9 | [5] | [55.6] |
| 3 | | | 256 | 18 | [12] | [66.7] |
| 5 | | | 512 | 36 | [32] | [88.9] |
| 10 | | | 1024 | 72 | [66] | [91.7] |
| 15 | | | 1536 | 108 | [102] | [94.4] |
| 20 | | | 2048 | 144 | [136] | [94.4] |
| * Note: These percentages are informative and apply to symbols 1 through 6. Symbol 0 has a longer CP and therefore a lower percentage. | | | | | | |

F.5.4 Window length for Extended CP

The table below specifies the EVM window length at channel bandwidths 1.4, 3, 5, 10, 15, 20 MHz, for extended CP. The nominal window lengths for 3 MHz and 15 MHz are rounded down one sample to allow the window to be centered on the symbol.

Table F.5.4-1 EVM window length for extended CP

| Channel Bandwidth MHz | Cyclic prefix length N_{cp} | Nominal FFT size | Cyclic prefix in FFT samples | EVM window length W | Ratio of W to CP* |
|---|-------------------------------|------------------|------------------------------|-----------------------|---------------------|
| 1.4 | 512 | 128 | 32 | [28] | [87.5] |
| 3 | | 256 | 64 | [58] | [90.6] |
| 5 | | 512 | 128 | [124] | [96.9] |
| 10 | | 1024 | 256 | [250] | [97.4] |
| 15 | | 1536 | 384 | [374] | [97.4] |
| 20 | | 2048 | 512 | [504] | [98.4] |
| * Note: These percentages are informative | | | | | |

F.6 Averaged EVM

EVM is averaged over all basic EVM measurements for 20 slots in the time domain.

$$\overline{EVM} = \sqrt{\frac{1}{20} \sum_{i=1}^{20} EVM_i^2}$$

The EVM requirements should be tested against the maximum of the RMS average at the window W extremities of the EVM measurements:

Thus \overline{EVM}_l is calculated using $\Delta\tilde{t} = \Delta\tilde{t}_l$ in the expressions above and \overline{EVM}_h is calculated using $\Delta\tilde{t} = \Delta\tilde{t}_h$.

Thus we get:

$$EVM = \max(\overline{EVM}_l, \overline{EVM}_h)$$

F.7 Spectrum Flatness

The data for the subcarrier output power shall be taken from the equaliser estimation step.

Annex G (informative): Change history

Table G.1: Change History

| Date | TSG# | TSG Doc. | CR | Subject | Old | New |
|---------|-------|-----------|-------|---|-------|-------|
| 11-2007 | R4#45 | R4-72206 | | TS36.101V0.1.0 approved by RAN4 | - | |
| 12-2007 | RP#38 | RP-070979 | | Approved version at TSG RAN #38 | 1.0.0 | 8.0.0 |
| 03-2008 | RP#39 | RP-080123 | 3 | TS36.101 - Combined updates of E-UTRA UE requirements | 8.0.0 | 8.1.0 |
| 05-2008 | RP#40 | RP-080325 | 4 | TS36.101 - Combined updates of E-UTRA UE requirements | 8.1.0 | 8.2.0 |
| 09-2008 | RP#41 | RP-080638 | 5r1 | Addition of Ref Sens figures for 1.4MHz and 3MHz Channel bandwidths | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 7r1 | Transmitter intermodulation requirements | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 10 | CR for clarification of additional spurious emission requirement | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 15 | Correction of In-band Blocking Requirement | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 18r1 | TS36.101: CR for section 6: NS_06 | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 19r1 | TS36.101: CR for section 6: Tx modulation | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 20r1 | TS36.101: CR for UE minimum power | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 21r1 | TS36.101: CR for UE OFF power | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 24r1 | TS36.101: CR for section 7: Band 13 Rx sensitivity | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 26 | UE EVM Windowing | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080638 | 29 | Absolute ACLR limit | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 23r2 | TS36.101: CR for section 6: UE to UE co-existence | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 30 | Removal of [] for UE Ref Sens figures | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 31 | Correction of PA, PB definition to align with RAN1 specification | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 37r2 | UE Spurious emission band UE co-existence | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 44 | Definition of specified bandwidths | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 48r3 | Addition of Band 17 | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 50 | Alignment of the UE ACS requirement | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 52r1 | Frequency range for Band 12 | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 54r1 | Absolute power tolerance for LTE UE power control | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080731 | 55 | TS36.101 section 6: Tx modulation | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080732 | 6r2 | DL FRC definition for UE Receiver tests | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080732 | 46 | Additional UE demodulation test cases | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080732 | 47 | Updated descriptions of FRC | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080732 | 49 | Definition of UE transmission gap | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080732 | 51 | Clarification on High Speed train model in 36.101 | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080732 | 53 | Update of symbol and definitions | 8.2.0 | 8.3.0 |
| 09-2008 | RP#41 | RP-080743 | 56 | Addition of MIMO (4x2) and (4x4) Correlation Matrices | 8.2.0 | 8.3.0 |
| 12-2008 | RP#42 | RP-080908 | 94r2 | CR TX RX channel frequency separation | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 105r1 | UE Maximum output power for Band 13 | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 60 | UL EVM equalizer definition | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 63 | Correction of UE spurious emissions | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 66 | Clarification for UE additional spurious emissions | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 72 | Introducing ACLR requirement for coexistence with UTRA 1.6MHz channel from 36.803 | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 75 | Removal of [] from Section 6 transmitter characteristics | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 81 | Clarification for PHS band protection | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 101 | Alignment for the measurement interval for transmit signal quality | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 98r1 | Maximum power | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 57r1 | CR UE spectrum flatness | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 71r1 | UE in-band emission | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080909 | 58r1 | CR Number of TX exceptions | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080951 | 99r2 | CR UE output power dynamic | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080951 | 79r1 | LTE UE transmitter intermodulation | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080910 | 91 | Update of Clause 8 | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080950 | 106r1 | Structure of Clause 9 including CSI requirements for PUCCH mode 1-0 | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080911 | 59 | CR UE ACS test frequency offset | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080911 | 65 | Correction of spurious response parameters | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080911 | 80 | Removal of LTE UE narrowband intermodulation | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080911 | 90r1 | Introduction of Maximum Sensitivity Degradation | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080911 | 103 | Removal of [] from Section 7 Receiver characteristic | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080912 | 62 | Alignment of TB size n Ref Meas channel for RX characteristics | 8.3.0 | 8.4.0 |

| | | | | | | |
|---------|-------|-----------|------|---|-------|-------|
| 12-2008 | RP#42 | RP-080912 | 78 | TDD Reference Measurement channel for RX characteristics | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080912 | 73r1 | Addition of 64QAM DL reference measurement channel | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080912 | 74r1 | Addition of UL Reference Measurement Channels | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080912 | 104 | Reference measurement channels for PDSCH performance requirements (TDD) | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080913 | 68 | MIMO Correlation Matrix Corrections | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080915 | 67 | Correction to the figure with the Transmission Bandwidth configuration | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080916 | 77 | Modification to EARFCN | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080917 | 85r1 | New Clause 5 outline | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080919 | 102 | Introduction of Bands 12 and 17 in 36.101 | 8.3.0 | 8.4.0 |
| 12-2008 | RP#42 | RP-080927 | 84r1 | Clarification of HST propagation conditions | 8.3.0 | 8.4.0 |
| | | | | | | |
| | | | | | | |