



US007047515B1

(12) **United States Patent**  
Vitek et al.

(10) **Patent No.:** US 7,047,515 B1  
(45) **Date of Patent:** May 16, 2006

(54) **METHOD FOR SELECTING AND PLACING BYPASS CAPACITORS ON MULTI-LAYER PRINTED CIRCUIT BOARDS**

6,691,296 B1 \* 2/2004 Nakayama et al. .... 716/15  
6,738,249 B1 \* 5/2004 Anthony et al. .... 361/117  
6,768,208 B1 \* 7/2004 Lin et al. .... 257/777  
6,870,436 B1 \* 3/2005 Grebenkemper .... 333/12

(75) Inventors: **Clark A. Vitek**, Portland, OR (US);  
**Nitin Bhandari**, Mountain View, CA (US)

**OTHER PUBLICATIONS**

NetLogic Microsystems, Note entitled "Decoupling Capacitor Selection," Date Unknown.

Archambeault, Bruce, "Power Ground-Reference Plane Decoupling Analysis of Design Alternatives," IEEE EMC International Symposium Record (Aug. 13-17, 2001), vol. 2, pp. 1217-1220, Montreal, Canada.

Hubing, Todd H., "Power Bus Decoupling on Multilayer Printed Circuit Boards," IEEE Transactions on Electromagnetic Compatibility (May 1995), vol. 37, No. 2, pp. 155-166.

Hubing, Todd H., "Strategies for Effective Printed Circuit Board Power Bus Decoupling," Phoenix EMC Society Chapter Meeting (Feb. 2002), pp. 1-64.

(Continued)

(73) Assignee: **Extreme Networks**, Santa Clara, CA (US)

(\* ) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 250 days.

(21) Appl. No.: **10/407,398**

(22) Filed: **Apr. 4, 2003**

Primary Examiner—Vuthe Siek

(74) Attorney, Agent, or Firm—Fenwick & West LLP

(51) **Int. Cl.**  
**G06F 17/50** (2006.01)

(57) **ABSTRACT**

(52) **U.S. Cl.** ..... 716/15; 716/10; 716/13; 716/14

A method places bypass capacitors for controlling the signal integrity of a signal routed between devices on a multi-layer printed circuit board by analysis of the routing of the signal and the signal characteristics. In general, when an interconnecting signal between devices is routed adjacent to an impedance control plane that does not serve as the circuit supply voltage plane or the reference voltage plane for all devices interconnected by the signal trace, the method selects locations for addition of bypass capacitors based upon the routing of the interconnecting signal trace to improve signal integrity.



(58) **Field of Classification Search** ..... 716/8-15; 333/12; 365/51, 52; 361/117, 782; 257/777  
See application file for complete search history.

(56) **References Cited**

**U.S. PATENT DOCUMENTS**

5,162,977 A 11/1992 Paurus et al.  
6,320,758 B1 \* 11/2001 Chen et al. .... 361/782  
6,523,158 B1 \* 2/2003 Hidaka ..... 716/10  
6,535,411 B1 \* 3/2003 Jolin et al. .... 365/52  
6,629,298 B1 \* 9/2003 Camporese et al. .... 716/6

**21 Claims, 7 Drawing Sheets**



OTHER PUBLICATIONS

Smith, Larry, "Simultaneous Switching Noise and Power Plane Bounce for CMOS Technology," Date Unknown.

Smith, Larry, et al., "Power Distribution System Design Methodology and Capacitor Selection for Modern CMOS Technology," Date Unknown.

Smith, Larry, et al., "Power Plane Spice Models for Frequency and Time Domains," Date Unknown.

Xu, Minjia et al., "Power-Bus Decoupling With Embedded Capacitance in Printed Circuit Board Design," IEEE Transactions on Electromagnetic Compatibility (Feb. 2003), vol. 45, No. 1, pp. 22-30.

\* cited by examiner




FIG. 1 (PRIOR ART)




FIG. 2 (PRIOR ART)




FIG. 3 (PRIOR ART)






FIG. 5




FIG. 6




FIG. 7

1

## METHOD FOR SELECTING AND PLACING BYPASS CAPACITORS ON MULTI-LAYER PRINTED CIRCUIT BOARDS

### TECHNICAL FIELD

The present invention relates generally to controlling electronic noise in multi-layer printed circuit boards, and more specifically, to a method for selecting and placing bypass capacitors on multi-layer printed circuit boards in order to control noise and improve signal integrity.

### BACKGROUND OF THE INVENTION

Multi-layer printed circuit boards are widely used in modern electronics technology to interconnect various components in a compact and efficient manner. These components include active Integrated Circuits (ICs) or passive discrete components (resistors, capacitors, and the like). As electronic circuits become more complex and use a larger number of components, printed circuit boards must typically accommodate more electronic components in the same surface area. As a result, electronic components have become densely located and modern printed circuit boards use multiple layers to provide various supply and return voltages such as 5 V, 3.3 V, and Ground (GND). In addition, these supply and return voltage planes are used as impedance control planes (also referred to as "reference planes") for controlling the characteristic impedance of interconnecting signal routing. Modern printed circuit boards typically use multiple signal routing layers ("signal layers") adjacent to the reference planes for routing signals between components. As larger number of electronic components are used and densely located on printed circuit boards, these electronic components generate an increasing level of noise associated with power distribution among the electronic components. Various techniques (generally termed "decoupling") have been developed so far to somewhat control the noise generated on multi-layer printed circuit boards.

Capacitors have been widely used in electronic circuits to control noise in power distribution. For example, decoupling capacitors have been widely used in printed circuit boards for controlling noise from active devices on printed circuit boards. Conventional decoupling capacitors are selected and placed based upon techniques such as local decoupling, bulk decoupling, and embedded (or "buried") capacitance.

Local decoupling requires that capacitors be placed between the supply voltage (Vcc) and the return voltage (typically GND) connections of an active electronic component. As such, local decoupling capacitors provide a local source of instantaneous current for active devices (also referred to as "parts"). By supplying charge for instantaneous current demand close to the active devices, it is possible to limit the amount of transient voltage disturbance generated in the power distribution close to these active devices. Local decoupling capacitors are selected based upon analysis of the instantaneous current requirement and the acceptable transient noise between the power supply and return voltage connections of each part and are placed as close as possible to that part's power supply connection pins on each part (hence, "local decoupling capacitors"). Local decoupling capacitors typically range in value from 0.001  $\mu$ F to 22  $\mu$ F and are placed as close as possible to the power and ground pins of the individual parts.

Bulk decoupling serves the same purpose as local decoupling, but uses larger value capacitors that are typically placed further away from the parts. In other words, bulk

2

decoupling uses larger capacitance values associated with a group of parts rather than individual parts and the bulk decoupling capacitors are placed further away from each individual part. Bulk decoupling also limits the transient noise generated on the Vcc/GND power distribution. Bulk capacitors are typically in the range of 47  $\mu$ F to several 10,000  $\mu$ F.

Embedded capacitance employs closely spaced power/ground plane pairs to build a low inductance capacitor for decoupling power/ground transients from active devices. Embedded capacitance is generally more effective at higher frequencies than standard capacitor construction, and due to the relatively low capacitance value (typically less than 0.01  $\mu$ F) its purpose is typically to provide more effective high frequency local decoupling for active devices. U.S. Pat. No. 5,162,977 to Paurus et al., entitled "Printed Circuit Board Having an Integrated Decoupling Capacitive Element" describes the technique of building buried capacitance in detail. Embedded capacitance is more effective at higher frequencies than local decoupling or bulk decoupling, but its purpose is limited to controlling high frequency transient noise on the power/ground distribution generated by active devices.

As explained above, all conventional decoupling capacitors such as local decoupling, bulk decoupling, and buried capacitance, are effective only for controlling transient noise on the power/ground distribution generated by active devices. In other words, conventional decoupling capacitors are selected and placed based solely upon consideration of the power/ground noise characteristics and/or the power/ground pin locations of the active devices. The conventional decoupling capacitors are not selected based upon analysis of the interconnecting signal information or the interconnecting signal route information. Therefore, the conventional decoupling capacitor placement does not control the noise generated by the specific signal path (also referred to as "signal traces") of interconnecting routes between active devices.

In conventional systems, interconnecting signal traces are routed as traces over a plane (called "microstrip" or "stripline" transmission lines). In the typical situation on a multi-layer PCB, an interconnecting signal trace is routed on a signal layer and the immediately adjacent voltage or ground plane is used as the impedance control/signal return plane. A circuit model analysis of current flow in the transmission line structure shows that, at high frequencies, the majority of signal return current flows as the mirror image in the impedance control plane, where the total impedance of the return path in the plane is lowest. Using a field model for the microstrip or stripline transmission line structure, it is understood that the electromagnetic field density is greatest in the region of dielectric captured between the signal trace and the plane, and much lower outside of this region. Thus, the energy transfer (current flow in the circuit model) between devices occurs in the region of the PCB between the signal trace and its impedance control plane.

On modern printed circuit boards with multiple supply voltages and ground planes, the path of the return current becomes problematic when the signal trace transitions routing layers and uses different planes for impedance control. This is a particular problem if the impedance control planes used are not the same (i.e. coupled to a different potential), because in such situation the path to the nearest decoupling capacitors will determine the locations for allowing the return current to transition between reference planes. For optimum noise control and signal integrity, the signal return current should have a location for transitioning that is close

to the signal trace layer transition (called the signal “via”). FIGS. 1–3 described below show how the signal return current on the conventional signal path can create serious problems for signal integrity on multi-layer printed circuit boards.

FIG. 1 is a diagram illustrating a first conventional multi-layer printed circuit board 100 including four layers, a Vcc1 supply voltage plane 102, a Vcc2 supply voltage plane 104, a ground (GND) plane 106 with conventional local decoupling capacitors 128, 130, 132, and signal routing layer in which the signal current 134 is routed. Two active devices, device 108 (driver part), device 110 (receiver part), and another active device 112 (unrelated to devices 108 and 110) are placed on the printed circuit board 100. The devices 108, 110, 112 may be any type of device such as an active integrated circuit (IC) chip or a discrete component. Device 108 has at least three pins 114, 116, 118, device 110 has at least three pins 120, 122, 124, and device 112 has at least two pins 125, 126. Devices 108 and 110 are powered by the Vcc1 plane 102, while device 112 is powered by the Vcc2 plane 104. Device 108 is connected to the Vcc1 plane 102 via pin 114, to the GND plane 106 via pin 116, and to device 110 via pin 118. Device 110 is connected to the Vcc1 plane 102 via pin 120, to the GND plane 106 via pin 122, and to device 108 via pin 124. Device 112 is connected to the Vcc2 plane 104 via pin 126 and to the GND plane 106 via pin 125.

Capacitors 128, 130, 132 are conventional local decoupling capacitors connected between the voltage source planes and ground planes to which devices 108, 110, 112 are connected. Specifically, capacitor 128 is a local decoupling capacitor connected between pin 114 and pin 116. Capacitor 130 is a local decoupling capacitor connected between pin 120 and pin 122. Capacitor 132 is a local decoupling capacitor connected between pin 125 and pin 126.

A signal current (solid line) 134 flows on the signal path in a routing layer between pin 118 of device 108 to pin 124 of device 110 with the current propagating in the routing layer routed adjacent to part of the GND plane 106. Here, the GND plane 106 is called the “reference plane” or “impedance control plane” for the routing layer in which the signal current 134 flows. As can be seen in FIG. 1, the current signal between pins 118 and 124 is routed adjacent a reference plane 106 to which both the devices 108 and 110 are coupled. As such, the return current (dotted line) 136 required according to Kirchoff’s first law can flow back from device 110 to device 108 via pins 122, 114, on part of the GND plane 106 (reference plane), with the connection to the local decoupling capacitor 128 providing the return current path between pin 122 of device 110 and pin 114 of device 108. Therefore, as shown in FIG. 1, the local decoupling capacitor 128 alone is capable of providing the return current path for the signal path between pin 118 and pin 124, when the signal current 134 is routed against a reference plane to which the driver device and the receiver device are coupled. There is no need for additional bypass capacitors, because the loop area of the signal path is already minimized by the connecting the conventional decoupling capacitors 128, 130. It is obvious from FIG. 1 that device 112 or its local decoupling capacitor 132 plays no role in providing a return current path between devices 108, 110 for controlling noise in the signal path therebetween.

FIG. 2 is a diagram illustrating a second conventional multi-layer printed circuit board 200 including four layers, a Vcc1 supply voltage plane 202, a Vcc2 supply voltage plane 204, a GND plane 206 with conventional local decoupling capacitors 230, 232, 234, and a routing layer in which

a signal current 236 is routed. Two active devices, device 208 (driver part), device 210 (receiver part), and another active device 212 (unrelated to devices 208 and 210) are placed on the printed circuit board 200. The devices 208, 210, 212 may be any type of device such as an active integrated circuit (IC) chip or a discrete component. Device 208 has at least three pins 214, 216, 218, device 210 has at least three pins 220, 222, 224, and device 212 has at least two pins 226, 228. Devices 208 and 210 are powered by the Vcc1 plane 202, while device 212 is powered by the Vcc2 plane 204. Device 208 is connected to the Vcc1 plane 202 via pin 214, to the GND plane 206 via pin 216, and to device 210 via pin 218. Device 210 is connected to the Vcc1 plane 202 via pin 222, to the GND plane 206 via pin 224, and to device 208 via pin 220. Device 212 is connected to the Vcc2 plane 204 via pin 226 and to the GND plane 206 via pin 228.

Capacitors 230, 232, 234 are conventional local decoupling capacitors connected between the voltage source planes and ground planes to which devices 208, 210, 212 are connected. Specifically, capacitor 230 is a local decoupling capacitor connected between pin 214 and pin 216. Capacitor 232 is a local decoupling capacitor connected between pin 222 and pin 224. Capacitor 234 is a local decoupling capacitor connected between pin 226 and pin 228.

In the printed circuit board 200 of FIG. 2, a signal trace (solid line) 236 represents current that flows on the signal path in the routing layer between pin 218 of device 208 to pin 220 of device 210 with the current routed in the routing layer adjacent to part of the Vcc2 plane 204 for impedance control. Vcc2 plane 204 is not GND and does not power the devices 208, 210. This type of signal routing is a common practice that permits for improved routing efficiency in multi-layer printed circuit boards. Here, the Vcc2 plane 204 operates as an alternate reference plane (or impedance control plane) for the signal current (solid line) 236.

As can be seen in FIG. 2, the current signal 236 between pins 218 and 220 is routed in a routing layer routed adjacent to a reference plane 204 that does not power the devices 208 and 210. The devices 208 and 210 are not coupled to the Vcc2 reference plane 204. As such, the return current (dotted line) required according to Kirchoff’s law cannot flow back directly from device 210 to device 208 via pins 224, 214, because the return current does not have a local path near the devices 208 and 210 for transitioning between reference planes. Rather, the return current has to find a separate local decoupling capacitor 234 far away from the devices 208, 210 and coupled between the Vcc2 reference voltage plane 204 and the GND plane 206 for transitioning between reference planes. This local decoupling capacitor 234 for device 212 is unrelated to the signal current 236 and is located far away from devices 208, 210, but nevertheless has to provide the return current path between pins 224 and 214. Thus, the return current has to flow along a long path 238, 240, 242, 244, 246, 248, 250, 252, and 254, resulting in a large and uncontrolled return current path that leads to (i) a large loop area created by the signal current and its return current, and (ii) a large difference in path length between the signal current and its return current path. Large loop area and large difference in path length can result in increased crosstalk between active circuits due to increased inductive coupling (increased “loop area”), and in increased signal transmission line reflection due to impedance discontinuities at the signal transition locations. The increased length of the return path relative to the signal path also results in imbalance. All of these factors deteriorate signal integrity. Signal transmission line reflection due to impedance discontinuities, inductive crosstalk to other signals due to a larger loop

5

area formed by the signal trace and its return current, and imbalance due to a difference in path length of the signal trace and its return current are all generally referred to as “reduced signal integrity” herein. Therefore, the conventional local decoupling capacitors **230**, **232** alone are not capable of controlling the noise on the signal path between pin **218** and pin **224**, because the signal current is routed adjacent to an impedance control plane not powering or serving as the circuit reference (GND) between the driver and receiver devices **208**, **210**.

FIG. **3** is a diagram illustrating a third conventional multi-layer printed circuit board **300** including six layers, a Vcc1 supply voltage plane **302**, a first GND plane **304**, a Vcc2 supply voltage plane **306**, and a second GND plane **308**, with conventional local decoupling capacitors **326**, **328**, and two routing layers in which the signal currents **330** and **361** flow. Two active devices, device **310** (driver part) and device **312** (receiver part), are placed on the printed circuit board **300**. The devices **310**, **312** may be any type of device such as an active integrated circuit (IC) chip or a discrete component. Device **310** has at least three pins **314**, **316**, **318**, and device **312** has at least three pins **320**, **322**, **324**. Both devices **310** and **312** are powered by the Vcc1 plane **302**. Device **310** is connected to the Vcc1 plane **302** via pin **314**, to the GND plane **304** via pin **316**, and to device **312** via pin **318**. Device **312** is connected to the Vcc1 plane **302** via pin **322**, to the GND plane **304** via pin **324**, and to device **310** via pin **320**.

Capacitors **326**, **328** are conventional local decoupling capacitors connected between the voltage source planes and ground planes to which devices **310**, **312** are connected. Specifically, capacitor **326** is a local decoupling capacitor connected between pin **314** and pin **316**. Capacitor **328** is a local decoupling capacitor connected between pin **322** and pin **324**. These capacitors are connected to planes **302** and **304**.

In the printed circuit board **300** of FIG. **3**, a signal current (solid line) **330** flows on the signal path between pin **318** of device **310** to pin **320** of device **312** with the interconnecting signal flowing in a routing layer routed adjacent to parts of both the Vcc2 plane **306** and the second GND plane **308** for impedance control. The Vcc2 plane **306** does not power the devices **310**, **312**. Thus, the signal current **330** is routed in the routing layer adjacent to reference planes (impedance control planes) not powering the devices **310**, **312**, and is also routed in routing layers adjacent to two reference planes (impedance control planes) **306**, **308**. The signal current **330** transitions between reference planes or impedance control planes by way of “routing vias” **360**, **362**. This use of routing vias affords improved routing efficiency in multi-layer printed circuit boards as the signal trace can be routed on multiple signal layers.

As can be seen in FIG. **3**, the current signal between pins **318** and **320** is routed in a routing layer adjacent to two reference planes **306**, **308**. The devices **310** and **312** are not coupled to the Vcc2 reference plane **306**. Thus, there are no capacitors connected to the Vcc2 plane **306**. As such, the return current (dotted line) required according to Kirchoff’s first law cannot flow back directly from device **312** to device **310** via pins **324**, **314**, because the return current does not have a local path near the devices **310** and **312** for transitioning between reference planes. Specifically, the return current may have paths from pin **324** to point **336** along path **334**, from point **338** to point **342** along path **340**, from point **344** to point **348** along path **346**, from point **350** to point **354** along path **352**, and from point **356** to pin **316** along path **358**. However, there is no return current path between point

6

**336** and point **338**, between point **342** and point **344**, between **348** and point **350**, and between point **354** and point **356**. Rather, as in the printed circuit board of FIG. **2**, the return current has to find an arbitrary (uncontrolled) decoupling capacitor(s) (not shown) potentially far away from the devices **310**, **312** and coupled between the Vcc2 plane **306** and the GND planes **304**, **308** in order to transition between these reference planes. These local decoupling capacitor(s) (not shown) are unrelated to the signal current **330** and may be located far away from devices **310**, **312**, but nevertheless have to provide the missing return current paths between pins **324** and **314**. Thus, the return current (dotted line) follows a long and uncontrolled return current path that leads to (i) a large loop area created by the signal current and its return current, and (ii) a large difference in path length between the signal current and its return current path. This long return path can deteriorate signal integrity. The conventional local decoupling capacitors **326**, **328** alone are not capable of controlling noise and signal integrity on the signal path between pin **318** and pin **320**, because there are routing vias **360**, **362** in the signal current path between the driver and receiver devices.

Therefore, there is a need for a method for controlling noise and improving signal integrity in multi-layer printed circuit boards based upon analysis of the interconnecting signal information or the interconnecting signal routing information. Furthermore, there is also a need for a method for selecting and placing bypass capacitors for controlling noise and improving signal integrity in multi-layer printed circuit boards based upon analysis of the interconnecting signal information or the interconnecting signal route information.

## SUMMARY OF INVENTION

The present invention provides a method of determining locations for placing bypass capacitors for controlling the signal integrity of signals routed from a first device to a second device via an interconnecting signal trace on a multi-layer printed circuit board by analysis of the routing of the signal and its signal characteristics. In one embodiment, the printed circuit board includes at least a first layer, a second layer, a third layer, and a fourth layer. The first layer powers the first device and the second device. The second layer serves as a reference voltage plane for the first and second devices. The third layer serves as a routing layer for the interconnecting signal trace, and the fourth layer serves as an impedance control plane for the interconnecting signal trace but does not power nor serve as the voltage reference plane for the first and second devices. The method analyzes the routing of the interconnecting signal trace, and determines a location for a bypass capacitor based upon routing of the interconnecting signal trace in the third layer adjacent to the fourth layer.

In one embodiment, the method determines a location near a source point of the signal at the first device between the second layer and the fourth layer as the location for the bypass capacitor. In another embodiment, the method determines a location near a termination point of the signal at the second device between the second layer and the fourth layer as the location for the bypass capacitor.

In still another embodiment, the printed circuit board further includes a fifth layer and a sixth layer, where the fifth layer also serves as a routing layer for the interconnecting signal trace, and the sixth layer also serves as an impedance control plane for the interconnecting signal trace. The

method determines a location for a bypass capacitor near a routing via of the signal between the fourth layer and the sixth layer.

In general, when an interconnecting signal between devices on a printed circuit board is routed adjacent to an impedance control plane that does not serve as the circuit supply voltage plane or the reference voltage plane for all devices that are interconnected by the signal trace, the method of the present invention selects locations for decoupling capacitors based upon the interconnecting signal trace to provide a controlled path for the signal's return current.

By use of the bypass capacitors on multi-layer printed circuit boards, the total area of the current loop formed by the signal trace and its return current can be minimized. Signal integrity, which is influenced by factors such as impedance, inductive crosstalk to other signals, signal transmission line reflection, and balance, can be improved and noise can be well controlled.

#### BRIEF DESCRIPTION OF THE DRAWINGS

The teachings of the present invention can be readily understood by considering the following detailed description in conjunction with the accompanying drawings.

FIG. 1 is a diagram illustrating a first conventional multi-layer printed circuit board with conventional local decoupling capacitors.

FIG. 2 is a diagram illustrating a second conventional multi-layer printed circuit board with conventional local decoupling capacitors.

FIG. 3 is a diagram illustrating a third conventional multi-layer printed circuit board with conventional local decoupling capacitors.

FIG. 4 is a diagram illustrating a multi-layer printed circuit board according to a first embodiment of the present invention.

FIG. 5 is a diagram illustrating a multi-layer printed circuit board according to a second embodiment of the present invention.

FIG. 6 is a flow chart illustrating a method of adding bypass capacitors to a multi-layer printed circuit board based upon analysis of signal traces according to one embodiment of the present invention.

FIG. 7 is a flow chart illustrating a method of determining the locations to which the bypass capacitors should be added on the multi-layer printed circuit board based upon analysis of signal traces according to one embodiment of the present invention.

#### DETAILED DESCRIPTION OF EMBODIMENTS

Several embodiments of the present invention will be described below with reference to the accompanying drawings. Like reference numerals are used for like elements in the accompanying drawings.

FIG. 4 is a diagram illustrating a multi-layer printed circuit board 400 in accordance with a first embodiment of the present invention. The printed circuit board 400 shown in FIG. 4 is different from the conventional printed circuit board 200 shown in FIG. 2 in that additional bypass capacitors 440 and 442 were added. The printed circuit board 400 includes four layers, a Vcc1 supply voltage plane 402, a Vcc2 supply voltage plane 404, a GND plane 406 with conventional local decoupling capacitors 434, 436, 438, and a routing layer in which the signal current 445 flows. Two active devices, device 408 (driver part), device 410 (receiver part), and another active device 412 (unrelated to devices

408 and 410) are shown placed on the printed circuit board 400. The devices 408, 410, 412 may be any type of device such as an active integrated circuit (IC) chip or a discrete component. Device 408 has at least four pins 414, 416, 418, 420, device 410 has at least four pins 422, 424, 426, 428, and device 412 has at least two pins 430, 432. Devices 408 and 410 are powered by the Vcc1 plane 402, while device 412 is powered by the Vcc2 plane 404. Device 408 is connected to the Vcc1 plane 402 via pin 414, to the GND plane 406 via pins 416 and 418, and to device 410 via pin 420. Device 410 is connected to the Vcc1 plane 402 via pin 426, to the GND plane 406 via pins 428 and 424, and to device 408 via pin 422. Device 412 is connected to the Vcc2 plane 404 via pin 430 and to the GND plane 406 via pin 432.

In the printed circuit board 400 of FIG. 4, a signal current (solid line) 444 flows on the signal path between pin 420 of device 408 to pin 422 of device 410 with the current propagating in the routing layer routed adjacent to part of the Vcc2 plane 404 for impedance control. Vcc2 plane 404 does not power the devices 408, 410. This type of signal routing is common practice that permits for improved routing efficiency in multi-layer printed circuit boards. Here, the Vcc2 plane 404 operates as an alternate reference plane (or impedance control plane) for the signal current (solid line) 444.

Capacitors 434, 436, 438 are conventional local decoupling capacitors connected between the voltage source planes and ground planes to which devices 408, 410, 412 are connected. Specifically, capacitor 434 is a local decoupling capacitor connected between pin 414 and pin 416. Capacitor 438 is a local decoupling capacitor connected between pin 426 and pin 428. Capacitor 436 is a local decoupling capacitor connected between pin 430 and pin 432.

In addition to the conventional local decoupling capacitors 434, 436, 438, the printed circuit board 400 further comprises bypass capacitors 440, 442. Bypass capacitor 440 is adjacent to the signal source pin 420 and is connected between the impedance control plane 404 and the GND plane 406 and further coupled to pin 418, to provide a local current path between the Vcc2 impedance control plane 404 and the GND plane 406 and to the device 408. Bypass capacitor 442 is adjacent to the signal termination pin 422 and is connected between the impedance control plane 404 and the GND plane 406 and further coupled to pin 424, to provide a local current path between the Vcc2 impedance control plane 404 and the GND plane 406 and to the device 410.

As shown in FIG. 4, the current signal 444 between pins 420 and 422 is routed in a routing layer adjacent to a reference plane 404, which is separate from the GND plane 406 and does not power the devices 408 and 410. The devices 408 and 410 are not coupled to the Vcc2 reference plane (impedance control plane) 404. Nonetheless, the return current (dotted line) 446 required according to Kirchhoff's first law can flow back directly from device 410 to device 408 via pins 424, 414, because the bypass capacitors 442, 440 provide a local return current path near the devices 408 and 410 for transitioning between the reference plane 404 and the GND plane 406. Because of the placement of the bypass capacitors 442, 440, the return current does not have to divert to an arbitrary local decoupling capacitor 436 far away from the devices 408, 410 for transitioning between reference planes. Thus, the return current 446 follows a short path closer in length to the signal current 444 path, resulting in a smaller and controlled return current path that leads to (i) a smaller loop area created by the signal current and its return current, and (ii) a smaller difference in path length

between the signal current **444**, **445** and its return current path **446** (improved balance). The reduced length and the better balance of the length of the signal path improve the signal performance on the signal path.

Once the locations to add the bypass capacitors **442**, **440** have been determined as shown in FIG. 4, the value of the capacitances of the bypass capacitors **442**, **440** can be readily determined by one skilled in the art based upon analysis of factors such as frequency, rise time, duty cycle, amplitude, waveform, etc. of the signal currents on the signal path **444** in order to enhance the signal integrity. These capacitance values will vary depending upon these factors, and one skilled in the art would make sure that such capacitance values are selected so as to provide a pass band sufficient for the frequency range of interest of the signals on the signal path **444**. Furthermore, one skilled in the art would recognize how near the source pin **420** and how near the termination pin **422** the bypass capacitors **442**, **440** should be located, respectively, in order to enhance the signal integrity.

FIG. 5 is a diagram illustrating a multi-layer printed circuit board **500** according to a second embodiment of the present invention. The printed circuit board **500** of the present invention shown in FIG. 5 is different from the conventional printed circuit board **300** shown in FIG. 3 in that additional bypass capacitors **534**, **536**, **538**, **540** according to the present invention were added. The printed circuit board **500** includes six layers, a Vcc1 supply voltage plane **502**, a Vcc2 supply voltage plane **506**, and a first GND plane **504**, a second GND plane **508** with conventional local decoupling capacitors **530**, **532**, and two routing layers in which the signal currents **541**, **542**, **543** flows. Two active devices, device **510** (driver part) and device **512** (receiver part) are placed on the printed circuit board **500**. The devices **510**, **512** may be any type of device such as an integrated circuit (IC) chip or a discrete component. Device **510** has at least four pins **514**, **516**, **518**, **520**, and device **512** has at least four pins **522**, **524**, **526**, **528**. Devices **510** and **512** are powered by the Vcc1 plane **502**. Device **510** is connected to the Vcc1 plane **502** via pin **514**, to the GND plane **504** via pins **516** and **518**, and to device **512** via pin **520**. Device **512** is connected to the Vcc1 plane **502** via pin **526**, to the GND plane **504** via pins **524** and **528**, and to device **510** via pin **522**.

In the printed circuit board **500** of FIG. 5, a signal current (solid line) **542** flows on the signal path between pin **520** of device **510** to pin **522** of device **512** with the current routed on parts of both the Vcc2 plane **506** and the second GND plane **508** for impedance control. The Vcc2 plane **506** and the second GND plane **508** do not power the devices **510**, **512**. Thus, the signal current **541**, **542**, **543** is routed in routing layers adjacent to reference planes (impedance control planes) not powering the devices **510**, **512** and is also routed adjacent to two reference planes (impedance control planes) **506**, **508**. The signal current **541**, **542**, **543** transitions between reference planes or impedance control planes by way of "routing vias" **546**, **548**. This use of routing vias affords improved routing efficiency in multi-layer printed circuit boards.

Capacitors **530**, **532** are conventional local decoupling capacitors connected between the voltage source planes and ground planes to which devices **510**, **512** are connected. Specifically, capacitor **530** is a conventional local decoupling capacitor connected between pin **514** and pin **516**. Capacitor **532** is a conventional local decoupling capacitor connected between pin **526** and pin **528**.

In addition to the conventional local decoupling capacitors **530**, **532**, the printed circuit board **500** further includes bypass capacitors **534**, **536**, **538**, **540**. Bypass capacitors **534**, **536** are similar to the bypass capacitors **440**, **442** shown in FIG. 4. Specifically, bypass capacitor **534** is adjacent to the signal source pin **520** and is connected between the Vcc2 impedance control plane **506** and the GND plane **508** and further coupled to the GND plane **504** and pin **518**, to provide a local current path between the Vcc2 impedance control plane **508** and the other GND impedance control plane **508** and to the device **510**. Bypass capacitor **536** is adjacent to the signal termination pin **522** and is connected between the Vcc2 impedance control plane **506** and the GND plane **508** and further coupled to the GND plane **504** and pin **524**, to provide a local current path between the Vcc2 impedance control plane **506** and the GND impedance control plane **508** and to the device **512**.

Bypass capacitors **538**, **540** are coupled to the printed circuit board **500** in addition to the bypass capacitors **534**, **536**. Bypass capacitor **538** is connected near the routing via **546** and between the Vcc2 impedance control plane **506** and the GND plane **508**, to provide a local current path between the Vcc2 impedance control plane **506** and the GND impedance control plane **508**. Bypass capacitor **540** is connected near the routing via **548** and between the Vcc2 impedance control plane **506** and the GND impedance control plane **508**, to provide a local current path between the Vcc2 impedance control plane **506** and the GND impedance control plane **506**.

As shown in FIG. 5, the signal current (solid line) **541**, **542**, **543** between pins **520** and **522** is routed in routing layers adjacent to parts of reference planes **506** and **508** that do not power the devices **510** and **512**. The devices **510** and **512** are not coupled to the Vcc2 reference plane (impedance control plane) **506**. The signal current **541**, **542**, **543** transitions through routing vias **546**, **548**. Nonetheless, the return current (dotted line) **544** required according to Kirchhoff's first law can flow back directly from device **512** to device **510** via pins **524**, **514**, because the bypass capacitors **536**, **534** provide a local return current path near the devices **512** and **510** for transitioning between the reference plane **506** and the GND plane **508** and the bypass capacitors **538**, **540** provide a local return current path near the routing vias **546**, **548** for transitioning between the reference plane **506** and the GND plane **508**. By providing the bypass capacitors **536**, **534**, **538**, **540**, the return current does not have to divert to an arbitrary local decoupling capacitor (not shown) far away from the devices **510**, **512** for transitioning between reference planes. Thus, the return current **544** follows a short path closer in length to the signal current **541**, **542**, **543** path, resulting in a smaller and controlled return current path that leads to (i) a smaller loop area created by the signal current and its return current, and (ii) a smaller difference in path length between the signal current path and its return current path (improved balance). The reduced length and the better balance of the length of the signal path improve the signal performance on the signal path.

Once the locations to add the bypass capacitors **534**, **538**, **540**, **536** have been determined according to the present invention as shown in FIG. 5, the value of the capacitances of the bypass capacitors **534**, **538**, **540**, **536** can be readily determined by one skilled in the art based upon analysis of factors such as frequency, rise time, duty cycle, amplitude, waveform, etc. of the signal currents on the signal paths in order to improve the signal integrity. These capacitance values will vary depending upon these factors, and one skilled in the art would make sure that such capacitance

11

values are selected so as to provide a pass band sufficient for the frequency range of interest of the signals on the signal paths. Furthermore, one skilled in the art would recognize how near the routing vias **536**, **548** the bypass capacitors **536**, **538** should be located, respectively, in order to improve the signal integrity.

FIG. 6 is a flow chart illustrating a method **600** of adding bypass capacitors to a multi-layer printed circuit board based upon analysis of signal traces according to one embodiment of the present invention. The method **600** of the present invention can be used with any type of multi-layer printed circuit board and with any configurations of signal traces thereon.

As the process is started **602**, the signal traces on the multi-layer printed circuit board are analyzed **604**. Such analysis includes inspecting each signal trace on the multi-layer printed circuit board for its end to end routing and gathering signal routing information regarding (i) the planes adjacent to which the signal trace is routed for impedance control, (ii) routing vias (signal layer transitions in the end to end route in series with the signal trace that introduces impedance control plane transitions), and (iii) source/destination termination points (direct connections from the signal trace to the supply voltage/GND and/or internal part characteristics that provide signal line termination to supply voltage/GND).

Once the signal traces have been analyzed **604**, the locations where the bypass capacitors according to the present invention are needed are determined **606** based upon the analysis of the signal traces. Step **604** will be explained in more detail below with reference to FIG. 7. Then, the bypass capacitors are added **608** at the determined locations and the process ends **610**.

Once the locations to add the bypass capacitors have been determined in step **606**, the value of the capacitances of the bypass capacitors can be readily determined by one skilled in the art based upon analysis of factors such as frequency, rise time, duty cycle, amplitude, waveform, etc. of the signal currents on the signal paths in order to enhance the signal integrity. These capacitance values will vary depending upon these factors, and one skilled in the art would make sure that such capacitance values are selected so as to provide a pass band sufficient for the frequency range of interest of the signals on the signal paths.

FIG. 7 is a flow chart illustrating a method **606** of determining the locations to which the bypass capacitors should be added on the multi-layer printed circuit boards based upon analysis of signal traces according to one embodiment of the present invention. The method **606** of FIG. 7 corresponds to step **606** of FIG. 6.

As the process continues **604**, the method determines **702** the locations of source points where signals are routed in a routing layer adjacent to an impedance control plane other than GND. The bypass capacitor must be connected near the source point between the signal's impedance control plane (typically different from the supply voltage plane powering the parts) and GND. The bypass capacitor at this location provides connection from the GND to the impedance control plane during signal routing. One skilled in the art would recognize how near the source point the bypass capacitor should be located in order to improve signal integrity. The value of the bypass capacitor and the maximum distance from the source point of the part is selected based not upon analysis of the power/GND transients expected to be generated by the source device but upon the interconnecting signal characteristics (frequency and waveform) and required signal integrity. Bypass capacitor **440** of FIG. 4 and

12

bypass capacitor **534** of FIG. 5 are examples of bypass capacitors added to the locations as determined in step **702**.

The method determines **704** the locations of routing vias, i.e., transitions in signal routing layers that introduce return current transitions in two or more reference planes or impedance control planes. The bypass capacitors at these via locations are placed to interconnect the impedance control planes to GND near the signal via transition locations. One skilled in the art would recognize how near the signal routing vias the bypass capacitor should be located in order to improve signal integrity. As discussed above, the value of the bypass capacitor and the maximum distance from the vias is selected based upon the interconnecting signal characteristics (frequency and waveform) and required signal integrity. For multi-layer printed circuit boards with many routing vias, these bypass capacitors will be present in multiple locations. In one embodiment of the present invention, these bypass capacitors at the via locations are implemented as a "grid" of capacitors on the printed circuit board with the grid interval specified as a maximum dimension (e.g., 1 inch) or as a function of the signal velocity and wavelength to ensure the desired level of signal integrity and EMI (Electro-Magnetic Interference) performance. Bypass capacitors **538**, **540** of FIG. 5 are examples of bypass capacitors added to the routing via locations as determined in step **704**.

The method also determines **706** the locations of termination points where signals are routed in a routing layer adjacent to an impedance control plane other than GND. The bypass capacitor must be connected near the termination point between the signal's impedance control plane (typically different from the supply voltage plane powering the parts) and GND. The bypass capacitor at this location provides connection from the GND to the impedance control plane during signal routing. One skilled in the art would recognize how near the termination point the bypass capacitor should be located in order to improve signal integrity. The value of the bypass capacitor and the maximum distance from the termination point of the part is selected based not upon analysis of the power/GND transients expected to be generated by the receiver device but upon the interconnecting signal characteristics (frequency and waveform) and required signal integrity. Bypass capacitor **442** of FIG. 4 and bypass capacitor **536** of FIG. 5 are examples of bypass capacitors added to the locations as determined in step **706**.

With the use of the bypass capacitors on multi-layer printed circuit boards according to the present invention, the total area of the current loop formed by the signal trace and its return current can be minimized. As such, signal integrity can be improved and noise can be controlled better as compared to printed circuit boards with only conventional decoupling capacitors.

Although the present invention has been described above with respect to several embodiments, various modifications can be made within the scope of the present invention. For example, the steps **702**, **704**, **706** of FIG. 7 may be performed independently of one another and in any other order. Only one of steps **702**, **704**, **706**, or any two step combination of steps **702**, **704**, **706** in any order may be performed consistent with the present invention. The method of FIGS. 6-7 may be applied generally to any type of multi-layer printed circuit board with any devices installed thereon, for the purpose of improving signal integrity. Any type of capacitor may be used as the bypass capacitor according to the present invention, regardless of whether they are discrete component capacitors or parasitic capacitances associated with other devices on the printed circuit board. The present

13

invention may be embodied in various forms, including computer program products, methods, and printed circuit boards, etc. Accordingly, the disclosure of the present invention is intended to be illustrative, but not limiting, of the scope of the invention, which is set forth in the following claims.

What is claimed is:

1. A method of determining locations for placing bypass capacitors for controlling the signal integrity of a signal routed from a first device to a second device via an interconnecting signal trace on a multi-layer printed circuit board, the printed circuit board including at least a first layer, a second layer, a third layer, and a fourth layer, the method comprising:

analyzing the routing of the interconnecting signal trace; and

determining a location for a bypass capacitor based upon routing of the interconnecting signal trace in the third layer adjacent to the fourth layer, where the first layer powers the first and second devices, the second layer serves as a voltage reference plane for the first and second devices, the third layer serves as a routing layer for the interconnecting signal trace, and the fourth layer serves as an impedance control plane for the interconnecting signal trace but not powering nor serving as the voltage reference plane for the first and second devices, the location of the bypass capacitor decided in accordance with frequency and waveform characteristics of the interconnecting signal and required signal integrity.

2. The method of claim 1, wherein determining a location for a bypass capacitor comprises:

determining a location near a source point of the signal at the first device between the second layer and the fourth layer.

3. The method of claim 1, wherein determining a location for a bypass capacitor comprises:

determining a location near a termination point of the signal at the second device between the second layer and the fourth layer.

4. The method of claim 1, wherein determining a location for a bypass capacitor comprises:

determining a location near a source point of the signal at the first device between the second layer and the fourth layer; and

determining a location near a termination point of the signal at the second device between the second layer and the fourth layer.

5. The method of claim 1, wherein the printed circuit board further includes a fifth layer and a sixth layer, the fifth layer also serving as a routing layer for the interconnecting signal trace, and the sixth layer also serving as an impedance control plane for the interconnecting signal trace, and determining a location for a bypass capacitor comprises:

determining a location near a routing via of the signal between the fourth layer and the sixth layer.

6. The method of claim 1, wherein the printed circuit board further includes a fifth layer and a sixth layer, the fifth layer also serving as a routing layer for the interconnecting signal trace, and the sixth layer also serving as an impedance control plane for the interconnecting signal trace and determining a location for a bypass capacitor comprises:

determining a location near a source point of the signal at the first device between the second layer and the fourth layer;

determining a location near a termination point of the signal at the second device between the second layer and the fourth layer; and

14

determining a location near a routing via of the signal between the fourth layer and the sixth layer.

7. The method of claim 6, wherein:

the first layer is coupled to a first supply voltage;

the second layer is coupled to a first ground voltage;

the fourth layer is coupled to a second supply voltage; and

the sixth layer is coupled to a second ground voltage.

8. The method of claim 1, wherein the fourth layer powers a third device.

9. A printed circuit board with a first device and a second device mounted on the printed circuit board for routing a signal from the first device to the second device via an interconnecting signal trace, the multi-layer printed circuit board comprising:

a first layer coupled to and powering the first device and second device;

a second layer coupled to and serving as a voltage reference plane for the first device and second device;

a third layer serving as a routing layer for the interconnecting signal trace;

a fourth layer serving as an impedance control plane for the interconnecting signal trace but not powering nor serving as a voltage reference plane for the first device and the second device; and

at least a bypass capacitor coupled between the second and the fourth layer.

10. The printed circuit board of claim 9, wherein the bypass capacitor comprises:

a bypass capacitor coupled near a source point of the signal at the first device between the second layer and the fourth layer.

11. The printed circuit board of claim 9, wherein the bypass capacitor comprises:

a bypass capacitor coupled near a termination point of the signal at the second device between the second layer and the fourth layer.

12. The printed circuit board of claim 9, wherein the bypass capacitor comprises:

a first bypass capacitor coupled near a source point of the signal at the first device between the second layer and the fourth layer; and

a second bypass capacitor coupled near a termination point of the signal at the second device between the second layer and the fourth layer.

13. The printed circuit board of claim 9, wherein the printed circuit board further includes a fifth layer and a sixth layer, the fifth layer also serving as a routing layer for the interconnecting signal trace, and the sixth layer also serving as an impedance control plane for the interconnecting signal trace, and the printed circuit board further comprises:

a bypass capacitor coupled near a routing via between the fourth layer and the sixth layer.

14. The printed circuit board of claim 9, wherein the printed circuit board further includes a fifth layer and a sixth layer, the fifth layer also serving as a routing layer for the interconnecting signal trace, and the sixth layer also serving as an impedance control plane for the interconnecting signal trace, and the bypass capacitor comprises:

a first bypass capacitor coupled near a source point of the signal at the first device between the second layer and the fourth layer;

a second bypass capacitor coupled near a termination point of the signal at the second device between the second layer and the fourth layer; and

the printed circuit board further comprises a third bypass capacitor coupled near a signal routing via between the fourth layer and the sixth layer.

15

15. The printed circuit board of claim 14, wherein:  
the first layer is coupled to a first supply voltage;  
the second layer is coupled to a first ground voltage;  
the fourth layer is coupled to a second supply voltage; and  
the sixth layer is coupled to a second ground voltage.

16. A computer program product stored on a computer readable medium and adapted to perform a method of determining locations for placing bypass capacitors for controlling the signal integrity of a signal routed from a first device to a second device via an interconnecting signal trace on a multi-layer printed circuit board, the printed circuit board including at least a first layer, a second layer, a third layer, and a fourth layer, the first layer powering the first and second devices, the second layer serving as a voltage reference plane for the first and second devices, the third layer serving as a routing layer for the interconnecting signal trace, and the fourth layer serving as an impedance control plane for the interconnecting signal trace but not powering nor serving as the voltage reference plane for the first and second devices, the method comprising:

- analyzing the routing of the interconnecting signal trace; and
- determining a location for a bypass capacitor based upon routing of the interconnecting signal trace in the third layer adjacent to the fourth layer.

17. The computer program product of claim 16, wherein determining a location for a bypass capacitor comprises:  
determining a location near a source point of the signal at the first device between the second layer and the fourth layer.

18. The computer program product of claim 16, wherein determining a location for a bypass capacitor comprises:  
determining a location near a termination point of the signal at the second device between the second layer and the fourth layer.

16

19. The computer program product of claim 16, wherein determining a location for a bypass capacitor comprises:  
determining a location near a source point of the signal at the first device between the second layer and the fourth layer; and

determining a location near a termination point of the signal at the second device between the second layer and the fourth layer.

20. The computer program product of claim 16, wherein the printed circuit board further includes a fifth layer and a sixth layer, the fifth layer also serving as a routing layer for the interconnecting signal trace, and the sixth layer also serving as an impedance control plane for the interconnecting signal trace, and determining a location for a bypass capacitor comprises:

- determining a location near a routing via of the signal between the fourth layer and the sixth layer.

21. The computer program product of claim 16, wherein the printed circuit board further includes a fifth layer and a sixth layer, the fifth layer also serving as a routing layer for the interconnecting signal trace, and the sixth layer also serving as an impedance control plane for the interconnecting signal trace and determining a location for a bypass capacitor comprises:

- determining a location near a source point of the signal at the first device between the second layer and the fourth layer;
- determining a location near a termination point of the signal at the second device between the second layer and the fourth layer; and
- determining a location near a routing via of the signal between the fourth layer and the sixth layer.

\* \* \* \* \*