

**2005 Asia-Pacific Microwave Conference
- Volume 4 of 5**



CATALOG #

05TH8841

TK7876

.A75

0- 2005

v. 4



2005 Asia-Pacific Microwave Conference

**Suzhou, China
4-7 December 2005**


Volume 4 of 5



**IEEE Catalog Number: 05TH8841
ISBN: 0-7803-9433-X**




TK7876
.A75
2005
v.4



2005 Asia-Pacific Microwave Conference Proceedings

Volume 4



December 4-7, 2005

Suzhou International Conference Center

Suzhou, China

Proceeding Editors: Wei Hong, Tie Jun Cui, and Dagang Fang

IEEE Catalog Number: 05TH8841

ISBN 0-7803-9433-X

Responsibility for the contents of the papers published in this Proceeding rests upon the authors and not upon IEEE or any of its members.

Additional copies of this Proceeding are available from:

The Institute of Electrical and Electronic Engineers, Inc
Publication Order Department
445 Hoes Lane, Piscataway, NJ 08855-1331

IEEE Proceeding Catalog Number: 05TH8841 *ISBN 0-7803-9433-X*
Library of Congress Number: 2005930836
IEEE CD-ROM Catalog Number: 05TH8841C *ISBN: 0-7803-9434-8*

Asia-Pacific Microwave Conference

Continues: Asia-Pacific Microwave Conference Proceedings of Technical Papers
Key Title: Asia-Pacific Microwave Conference Proceedings

Sponsors: IEEE MTT Beijing Chapter, IEEE MTT Society
IEEE Nanjing Joint Chapter, IEEE AP Beijing Chapter

Co-Sponsors: Microwaves Society of CIE, Antenna Society of CIE
National Science Foundation of China
Southeast University, Tsinghua University,
University of Science and Technology of China, Soochow University

Copyright and Reprint Permission: Abstracting is permitted with credit to the source. Libraries are permitted to photocopy beyond the limit of U.S. copyright law for private use of patrons those articles in this volume that carry a code at the bottom of the first page, provided the per-copy fee indicated in the code is paid through Copyright Clearance Center, 222 Rosewood Drive, Danvers, MA 01923. For other copying, reprint or republication permission, write to IEEE Copyrights Manager, IEEE Operations Center, 445 Hoes Lane, P.O. Box 1331, Piscataway, NJ 08855-1331. All rights reserved. Copyright ©2005 by the Institute of Electrical and Electronics Engineers, Inc.

	<i>PEI-LING CHI, YU-DE LIN, SYU-SHENG WU</i> (Taipei)	
P4.50	A Broadband T-shaped Microstrip-line-fed Slot Antenna With Harmonic Suppression <i>Dong hyuk Choi, Young jun Cho, Seong ook Park</i> (Korea)	2614
P4.51	Analysis Of The Multiband Behavior On Sierpinski Carpet Fractal Antennas <i>Yao Na</i> (China)	2617
P4.52	Numerical And Experimental Study Of A Quarter-Wavelength Wideband Slot Antenna For Mobile Applicatio <i>Anping Zhao, Jussi Rahola</i> (Finland)	2621
P4.53	A New Omnidirectional Vertical Polarization Antenna With Low Profile And High Gain <i>Geng Junping, Jin Ronghong, Wang Zhiguo, Yuan Zhihao, Li Jiaqiang, Wang Wei, He Wei, Ding Min</i> (China)	2625
P4.54	Compact Circularly Polarized Enhanced Gain Microstrip Antenna On High Permittivity Substrate <i>Nasimuddin Nasimuddin</i> (Australia)	2627
P4.55	Circularly & Linearly Polarized Fan Beam Patch Antenna Arrays On Liquid Crystal Polymer Substrate Fo <i>Il Kwon Kim, Stephane Pinel, Jong-Gwan Yook, Joy Lakar</i> (Korea)	2631
P4.56	Design Of 8x8 Stacked Patch Array Antenna On LTCC Substrate Operating At 40GHz Band <i>Woojin Byun, Kichan Eun, Bongsoo Kim, Kwang sun Kim, Myungsun Song</i> (Korea)	2634
P4.57	Broadband Dielectric Loaded Trapezoidal Planar Antenna <i>Zhao Wang, Choo C Chiau, Xiaodong Chen, B. S. Collins, S. P. Kingsley, S. C. Puckey</i> (UK)	2638
P4.58	An Novel L-shape Active Leaky-Wave Antenna With Power Combining And Scanning Capability <i>I.Yu Chen</i> (Taipei)	2642
P4.59	Dual-Mode Compact Microstrip Antenna Based On Fundamental Backward Wave <i>Anthony Lai, Kevin M.K.H. Leong, Tatsuo Itoh</i> (USA)	2646
P4.60	Meander Line RFID Tag At UHF Band Evaluated With Radar Cross Sections <i>Hongil Kwon, Bomson Lee</i> (Korea)	2650
P4.61	Design Of Triple-band Planar Inverted-F Antenna <i>Hui Li, Wenhua Chen, Zhenghe Feng</i> (China)	2654
P4.62	Compact Planar Monopole Antenna For Multi-band Mobile Phones <i>Xu Jing, Zhengwei Du, Ke Gong</i> (China)	2657
P4.63	Synthesis Of Arrays With Genetic Algorithm (GA) And Nonuniform Fast Fourier Transform (NFFT) <i>Mingli Jiang, Li Zhou, Zhen Liu, Zhenhong Fan, RuShan CHEN</i> (China)	2661
P4.64	Design Of Printed Antenna With Left-Handed Array <i>Zhu Qi, Liao Huan</i> (China)	2663
P4.65	RFID Tag Antenna Moutable On Metallic Plates <i>Sung-Joo Kim, Byongkil Yu, Ho-Jun Lee, Myun-Joo Park, Frances J. Harackiewicz, Byungje Lee</i> (Korea)	2666
P4.66	DESIGN AND DEVELOPMENT OF ASYMMETRIC BEAM MONOPULSE ANTENNA SYSTEM AT Ka -BAND <i>Rama G.v. Koteswara rao, Borkar V.g.</i> (India)	2669
P4.67	A Broadband Planar Aperture Antenna Fed By Fan-shaped Microstripline <i>Liu Zhenguo, Zhang Wenxun, Liu Tinghua, Ge Zhichen, Shen Wei</i> (China)	2673
P4.68	A Novel Series-fed Taper Antenna Array <i>TAO YUAN, Jian-Ying Li, Le-Wei Li, Lei Zhang, Mook Seng Leong</i> (Singapore)	2676
P4.69	Analysis Of The Influence Of The Empennage To The Radiation Pattern Of Airborne Antenna Array	2679

Compact Planar Monopole Antenna for Multi-band Mobile Phones

Xu Jing, Zhengwei Du and Ke Gong
 State Key Lab on Microwave and Digital Communications
 Department of Electronic Engineering
 Tsinghua University, Beijing, People's Republic of China
 E-mail: jingxu99@mails.tsinghua.edu.cn

Abstract - A novel planar monopole antenna suitable for mobile handset applications is presented in this paper. The antenna is mainly composed of a rectangular radiating patch with a meandered slot on, and due to the slot three branches are constructed, two resonating branches and a tuning one. The antenna is printed on a FR4 substrate and fed by a 50Ω microstrip line. A prototype has been fabricated and studied. The resulting antenna is able to operate in the GSM, DCS, PCS, UMTS and WLAN bands with a voltage standing wave ratio (VSWR) better than 2.5. Both simulated and measured results are presented.

I. INTRODUCTION

The rapid development of modern wireless communication systems has caused wide interests in designing wide-band and multi-band antennas. A variety of antenna configurations have been reported to be promising candidates for mobile handsets, such as the planar inverted-F antenna (PIFA)[1]-[3], the planar wire antenna[4] and the planar monopole antenna[5] - [8]. PIFA usually has a compact size, but its bandwidth is relatively narrow and a sufficient height from the ground plane has to be kept to achieve the acceptable performances. The planar wire antenna exhibits a much wider bandwidth, but its large size and external configuration make it less practicable in mobile applications. The planar monopole antennas proposed in [5] generally possess compact size, sufficient bandwidth and satisfying radiation patterns. However, their structures are all 3-dimensional instead of 2-dimensional, increasing the manufacture difficulty and cost.

In this paper, a novel planar monopole antenna with a 2-dimensional structure is introduced. Both the structure and the parameters are carefully adjusted to achieve multi-resonances, sufficient bandwidths and convenient profile. Printed on a dielectric board, the antenna consists of three branches. At first, two branches are designed to resonate at certain frequencies, and then another one is added for fine tuning. With a small area of $36 \times 15 \text{ mm}^2$, the antenna meets the demand of the following communication standards: GSM (Global System for Mobile communications, 890-960 MHz), DCS (Digital Communication System, 1710-1880 MHz), PCS




Fig. 1. Configuration of the proposed planar monopole antenna. (a) General view of the antenna. (b) Detailed dimensions of the main radiating element. All dimensions are in millimeter.

(Personal Communication Services, 1850-1990MHz), UMTS (Universal Mobile Telecommunications System, 1920-2170 MHz), and WLAN (Wireless Local Area Network, 2400-2484 MHz). Details of the design are described in the second section, and measured results of the prototype in the third.

II. ANTENNA DESIGN

The general view of the proposed antenna is shown in Fig. 1(a), and details of the design dimensions in Fig. 1(b). The planar monopole occupies an area of $36 \times 15 \text{ mm}^2$, and is printed on a 0.8-mm FR4 substrate (relative permittivity 4.4). The substrate, 36 mm in width and 75 mm in length, is considered to be the typical system circuit board of a mobile phone. On the back surface of the substrate, a ground plane of 36 mm in width and 60 mm in length is printed and treated as the system ground plane. The monopole is fed by a 50Ω microstrip line, as shown in Fig. 1(a).

The main radiating element is in the shape of a rectangle. With a meandered slot on the patch, three branches are constructed, which are designated as resonant branch 1 (the longer branch), resonant branch 2 (the shorter branch) and tuning branch 3 (the additional inner branch) respectively in Fig. 1. Between the rectangular patch and the feeding microstrip line, a tapered strip of 5-mm length is printed. The width of the strip changes linearly from 1.54 mm at the feeding point to 4 mm at the edge of the patch, improving the impedance matching at the feeding point.

At the beginning of the design, only the two resonant branches 1 and 2 are taken into account, which present two surface current paths of different lengths. The length of the longer path, calculated from the feeding point to the open end of resonant branch 1, is selected to be about 75 mm. This value is very close to one-quarter wavelength of 900-MHz frequency in free space. It is instructive to note that the resonating frequency is affected by both the length of the path and the width of the open end. In the same way, the length of the shorter path, from the feeding point to the open end of resonant branch 2, is found to be about 35 mm, approximately one-quarter wavelength of 2-GHz frequency. The slight difference is mainly because of the existence of the substrate, which shortens the resonating wavelength.

The antenna with only the two resonant branches 1 and 2 is capable of dual-band operation. However, the bandwidth is not sufficient to cover all the five bands listed above, especially the WLAN band. Thus, the tuning branch 3 is added at a proper position on resonant branch 1. Simulation results have shown that by carefully adjusting the dimensions of branch 3, the fundamental and higher modes of branch 1 can be tuned to appropriate frequencies. According to the simulation data, the resonant frequency of the fundamental mode is reduced from 960 MHz to 910 MHz. As for the higher mode, the resonant frequency is changed from higher than 3 GHz to about 2.5GHz. Thus, the antenna with all the three branches is suitable for GSM/DCS/PCS/UMTS/WLAN operation. The simulated return loss of the antennas with and without tuning branch 3 is presented in Fig. 2 for reference. The results are gained through Ansoft HFSS (High Frequency Structure Simulator) software.

III. MEASURED RESULTS

A prototype was constructed according to the design dimensions, and the measured return loss is shown in Fig. 3.




Fig. 2. Simulated return loss of the antennas with and without tuning branch 3.




Fig. 3. Measured return loss of the proposed antenna.

Three resonating modes at 920, 2050 and 2460 MHz can be clearly observed. The first impedance bandwidth at 920 MHz is 45 MHz (900-945 MHz) with the VSWR (voltage standing wave ratio) better than 2.5. The second bandwidth at 2050 MHz is 560MHz (1690-2250 MHz), covering the DCS (1710-1880 MHz), PCS (1850-1990 MHz) and UMTS (1920-2170 MHz) bands. The third bandwidth at 2460 MHz is 450 MHz (2350-2800 MHz), covering the WLAN (2400-2484 MHz) band. However, it is observed that the bandwidth of the lowest resonating mode is insufficient to cover the GSM (890-960 MHz) band. More work has to be done to enhance the bandwidth, concentrating on the dimensions of resonant branch 1, the position of the feeding point, and the effects of parasitic elements.

Besides the return loss, the radiation characteristics of the proposed antenna are also studied. The measured radiation patterns in the x-y plane and y-z plane at 920 MHz, 1800 MHz, 2000 MHz and 2400 MHz are depicted in Fig. 4. A lack




Fig. 4. Measured radiation patterns of the proposed antenna at (a) 920 MHz, (b) 1800 MHz, (c) 2000 MHz and (d) 2400 MHz. of polarization purity is observed in the figure. As a matter of fact, this is not a drawback since the urban communication environments are so complicated that both vertical and horizontal polarization may exist [9].

IV. CONCLUSIONS

A compact multi-band planar monopole antenna capable of mobile handset applications is proposed in the paper. A prototype is constructed based on the design. Occupying a small area of $36 \times 15 \text{ mm}^2$, the antenna meets the demand of GSM/DCS/PCS/UMTS/WLAN multi-band operation. Good radiation characteristics have been observed. The bandwidth for GSM band is still 25 MHz insufficient, more bandwidth-enhancement work being expected.

ACKNOWLEDGMENT

This work has been supported by the National Natural Science Foundation of China under Grants 60271007 and the Chinese National High-Tech program (863-2003AA123110). The authors appreciate the help in antenna measurement from G. Yan and F. Wang, Department of Electronic Engineering, Tsinghua University.

REFERENCES

- [1] Pey-Ling Teng, Shyh-Tirng Fang, and Kin-Lu Wong, "PIFA with a bent, meandered radiating arm for GSM/DCS dual-band operation". *Antennas and Propagation Society Int. Symp.*, Vol.3, pp.107-110, Jun. 2003.
- [2] Shih-Huang Yeh, Kin-Lu Wong, Tzung-Wern Chiou, and Shyh-Tirng Fang, "Dual-band planar inverted F antenna for GSM/DCS mobile phones". *IEEE Trans. Antennas Propagat.*, Vol.51, pp.1124-1126, May. 2003.
- [3] P. Ciais, R. Staraj, G. Kossiavas, and C. Luxey, "Compact internal multiband antenna for mobile phone and WLAN standards". *Electron. Lett.*, Vol.40, Jul. 2004.
- [4] R. L. Li, G. DeJean, M. M. Tentzeris, and J. Laskar, "Novel multi-band broadband planar wire antennas for wireless communication handheld terminals". *Antennas and Propagation Society Int. Symp.*, Vol.3, pp.44-47, Jun. 2003.
- [5] Ching-Yuan Chiu, Pey-Ling Teng and Kin-Lu Wong, "Shorted, folded planar monopole antenna for dual-band mobile phone". *Electron. Lett.*, Vol.39, Sep. 2003.
- [6] Pey-Ling Teng, Hong-Twu Chen, and Kin-Lu Wong, "Multi-frequency planar monopole antenna for GSM/DCS/PCS/WLAN operation". *Microwave Opt. Technol. Lett.*, Vol.36, pp.350-352, Mar. 2003.
- [7] Pey-Ling Teng and Kin-Lu Wong, "Planar monopole folded into a compact structure for very-low-profile multiband mobile-phone antenna". *Microwave Opt. Technol. Lett.*, Vol.33, pp.22-25, Apr. 2002.
- [8] I. F. Chen and C. M. Chiang, "Multi-folded tapered monopole antennas for wideband mobile handset applications". *Electron. Lett.*, Vol.40, May. 2004.
- [9] P. Ciais, R. Staraj, G. Kossiavas, and C. Luxey, "Design of an internal quad-band antenna for mobile phones". *IEEE Microwave Wireless Comp. Lett.*, Vol.14, pp.148-150, Apr. 2004.