



Time response in carbon nanotube/Si based photodetectors

M. Salvato^{a,b,e,*}, M. Scagliotti^a, M. De Crescenzi^{a,b}, M. Boscardin^c, C. Attanasio^{d,e},
G. Avallone^{d,e}, C. Cirillo^{d,e}, P. Proposito^{b,f}, F. De Matteis^{b,f}, R. Messi^{a,b}, P. Castrucci^{a,b}

^a Dipartimento di Fisica, Università di Roma "Tor Vergata", via della Ricerca Scientifica 1, 00133 Roma, Italy

^b INFN, Università di Roma Tor Vergata, 00133 Roma, Italy

^c Micro-nano Characterization and Fabrication Facility, Fondazione Bruno Kessler (FBK), via Sommarive 18, 38123 Povo-Trento, Italy

^d Dipartimento di Fisica E.R. Caianiello, Università degli Studi di Salerno, via Giovanni Paolo II 132, 84084 Fisciano, Italy

^e CNR-SPIN c/o Dipartimento di Fisica E.R. Caianiello, Università degli Studi di Salerno, via Giovanni Paolo II 132, 84084 Fisciano, Italy

^f Dipartimento di Ingegneria Industriale and INSTM, Università di Roma Tor Vergata, via del Politecnico 1, 00133 Roma, Italy



ARTICLE INFO

Article history:

Received 31 January 2019

Received in revised form 13 March 2019

Accepted 4 April 2019

Available online 6 April 2019

Keywords:

Carbon nanotubes

Photodetector

Pulsed laser

Junction

ABSTRACT

We investigated the response of carbon nanotube/Si photodetectors to nanosecond light pulse using two electrode configurations for photovoltaic and photoconductive operations. When operating in photovoltaic mode, the devices show a linear dependence of the photocurrent as a function of the light pulse energy with rise time of 20 ns. In photoconductive mode, an increase of the maximum photocurrent as high as 30 times and a gain in the number of photogenerated charges up to 200% is recorded with a correspondent decrease in the time response below 10 ns. Current voltage characteristics measured as a function of the temperature indicate that the fast response of these devices can be ascribed to the formation of Schottky junctions at carbon nanotube/Si interface. These results make our devices comparable to most commercial photodetectors and pave the way for their use as avalanche photomultipliers.

© 2019 Elsevier B.V. All rights reserved.

1. Introduction

Photodetectors are widely used in day life as well as in research activities [1]. Their use is becoming more frequent with the developments of the control of smart systems for day life applications [2] as well as in medical [3] and scientific facilities [4] where they play the role of signal detectors for radiation sources of different kinds. Examples are distance detectors, alarm systems, medical diagnostic facilities, quality controls, thermal and high energy detectors [5]. In all the cases, the most important requirements remain a fast response, a high responsivity and a low noise [6]. Although most of the commercial available photodetectors are based on Si technology, new fields are becoming to be investigated pressed by the necessity to reduce costs and sizes of the devices. From this point of view, nanomaterials present characteristics which are unique especially if one considers the possibility of their use in Si based hybrids [7]. Carbon nanotubes (CNTs) with their nanometric size and their compatibility with Si, represent one of the most promising nanomaterials for Si technology inte-

gration [8]. Moreover, due to their good electrical conductivity and optical transparency [9], CNTs are good candidates for photodetector applications. Thanks to their properties to give rise to the formation of a rectified junction when deposited on Si surface, they were used with the double purpose of transparent window and photocharge collectors when deposited in form of thin film on the surface of a doped Si substrate (see ref. [10] and references therein). Following this insight, we recently demonstrated responsivity higher than 1 A/W when single walled CNT (SWCNT)/n-Si junctions were used in photovoltaic (PV) mode using a two terminal configuration as in the case of non-polarized photodiodes [11]. This result was well above that observed for the similar hybrid systems and comparable to the commercial photodiodes [5]. Moreover, an increase of responsivity up to 150% with respect to the non-polarized configuration was observed when the same devices were used in photoconductive (PC) mode using a three terminal configuration [12]. However, in these cases, the junctions were illuminated by using light emitter diodes (LED) which did not allow us to make accurate measurements of the time response due to the limited bandwidth of the light source. In the present work we report a detailed study of the photocurrent response when the SWCNT/n-Si junction is illuminated by a nanosecond pulsed laser emitting in the visible range. Since the photocurrent depends on the contact configuration, we investigated the effect of using a two terminal

* Corresponding author at: Dipartimento di Fisica, Università di Roma Tor Vergata, via della Ricerca Scientifica 1, 00133 Roma, Italy.

E-mail address: matteo.salvato@roma2.infn.it (M. Salvato).




Fig. 1. (a) Schematic section of the SWCNT/Si photodetector with the photocharges drifted towards the opposite electrodes by the interface built-in potential; (b) three dimensional view of the photodetector with the terminals connected for photovoltaic and (c) photoconductive measurements.

or a three terminal configuration on the time response. Beside the improvement in the rise time and responsivity, to our knowledge never observed for similar junctions, the experimental results give indications on the charge diffusion mechanism after light absorption and allow to better understand the role played by the SWCNT thin film in collecting the photo generated charges.

2. Experimental

SWCNT thin films were obtained by vacuum filtration method following a well established process developed for solar cells production as detailed elsewhere [13]. The films consist of a mixture of metallic (10%) and semiconducting (90%) SWCNTs fully characterized by transmission and reflection optical spectroscopy, X-ray photoelectron spectroscopy, Raman spectroscopy and electron microscopy [13,14]. They are semitransparent with optical transmission depending on their thickness. For the present experiment, SWCNT thin films with optical transmission of 63%, thickness of 30 nm and sheet resistance of 500 Ω/sq were synthesized. The substrates were fabricated by the Fondazione Bruno Kessler [15] and consist of *n* doped Si wafers, 150 μm thick, with donor concentration atoms of 10^{16} cm^{-3} corresponding to an electrical resistivity of 0.53 $\Omega\cdot\text{cm}$. The top surface of the Si substrates, cut in rectangular shapes of $3 \times 6 \text{ mm}^2$, is provided with two interdigitated Ti/Pt electrodes consisting of ten fingers (five per electrodes) separated by a distance of 250 μm and deposited on a template of SiO_2 structure which works as insulator between the top electrodes and the Si surface [16]. A third Cr/Au metallic electrode is deposited on the bottom surface of the Si substrate which is heavily *n*-doped to allow the formation of an Ohmic contact. A schematic drawing of the substrate is shown in Fig. 1. The SWCNT film is deposited on the top surface of the substrate by printing method and results to be in contact with the interdigitated electrodes and with the Si surface left free by the SiO_2 /electrode structure [11,12,16]. The SWCNT/Si junction is formed at the interface between the SWCNT film and the Si surface which represents the active area of the detector and, for the case studied here, results to be $A = 7.8 \text{ mm}^2$. Photocharges are generated by the absorption of the light penetrating the Si substrate through the semitransparent SWCNT thin film. Since Si is *n*

doped, electrons and holes are drifted towards the bottom metallic electrode and the top SWCNT film, respectively [12].

The junctions have been characterized by current voltage (*I-V*) measurements in dark conditions using a Keithley 2400 source/meter plunging the samples in a dewar containing liquid nitrogen for temperature measurements. For the optical measurements the samples were mounted in a metallic box with the top surface positioned under a circular pinhole of diameter of 1 mm used for the light input. The light source was a frequency doubled Q-switched Nd:YAG pulsed laser (Quantel Brilliant) emitting light at wavelength $\lambda = 532 \text{ nm}$ at a repetition rate of 10 Hz. Before to start with the measurement session, the width of the laser pulse and its maximum intensity were measured by a Si-PIN PhDiode photodetector (Antel Optronics AR-S2, nominal response time of 35 ps) positioned in the place of the sample and connected to a 30 GHz Tektronix oscilloscope. The measured laser pulse showed 5 ns at full width half maximum (FWHM) with a rise time of 2 ns, and an energy of 560 nJ which we assume to be the same delivered to the sample. In order to study the response of our samples to the incident pulse energy, the laser beam intensity was regulated by using optical attenuators which allow to obtain energy values at the sample surface in the range $\varepsilon = 56 \text{ pJ}$ 560 nJ for each pulse. The particular geometry of the electrodes allows to polarize the samples using a two-terminal or a three-terminal configuration. In the former case, hereafter also called photovoltaic (PV) mode, the top (S, D or both) and the bottom (G) electrodes (see Fig. 1b) are connected to the source/meter facility. In the latter case, hereafter also called photoconductive (PC) mode and shown in Fig. 1c, the two top electrodes (S and D) are connected to the source/meter and the bottom electrode (G) is used as a gate electrode (connected to another voltage supply). For both the terminal configurations, the photocurrent generated after the absorption of the laser pulse was recorded by the 30 GHz Tektronix oscilloscope.

3. Results and discussion

Fig. 2 shows the time dependence of the short circuit current I_{PV} , acquired in the PV mode, after the junction is illuminated by the laser pulse at different energy. I_{PV} different from zero is recorded at pulse energy down to 56 pJ (the minimum available) showing a high




Fig. 2. Photocurrent vs. time collected in the photovoltaic mode at different energies of the nanosecond light pulse.

sensitivity of our photodetectors. Moreover a rise time $\tau_{PV} \approx 20$ ns is measured as the difference between the 90% and 10% of the peak value for every pulse energy. These results are comparable to those reported for commercial photodetectors [5] confirming the high sensitivity and the fast response of our devices.

The effect of the gate voltage is shown in Fig. 3a where the current (I_{PC}) measured in PC mode, corresponding to the current flowing inside the SWCNT film, is reported as a function of the time at different gate voltages V_G when the junction is illuminated by a pulse energy $\varepsilon = 8.9$ nJ. The curves are obtained by subtracting the dark current contribution and represent the response of the photodetector to the light pulse. An increase up to 30 times of I_{PC} with respect to its value at $V_G = 0$ is observed and a reduction of the rise time to $\tau_{PC} < 10$ ns is measured. This confirms the improvement obtained by using the three terminal configuration which, in addition to increase the photodetector response, gives a reduction of the rise time ($\tau_{PC} < 10$ ns) with respect to the PV configuration ($\tau_{PV} \approx 20$ ns). The peak current I_{PCmax} of the curves in Fig. 3a is shown in Fig. 3b as a function of V_G . A double behavior in the photodetector response is observed by the change in the linear slope at $V_G \approx 9$ V. This can be ascribed to the starting of the avalanche regime which causes an increase of the photocurrent independent on the light energy. This effect is well represented by the I - V characteristics shown in the inset of the same figure and acquired for the same sample under dark (black line) and under light (red line) conditions using a d.c. LED as light source. The difference between the linear behaviour observed for $V_G > 9$ V in the main panel of Fig. 3b and the rather exponential dependence of the I - V characteristic in the inset of the same figure is due to the absence of the dark current contribution in the data reported in the main panel.

In order to better highlight the difference between the PV and the PC configurations on the photodetector response, we report in Fig. 4a the number of photocharges collected in the two operating modes. These are calculated by the area of the curves in Fig. 2 for the PV mode and by the area of the curves obtained in the PC mode at different laser pulse energy with $V_G = 0$. Therefore, in the figure the black squares represent the charges collected by using the S and G terminals (PV mode) whereas the red circles are the charges collected by the SWCNT film at S and D terminals with $V_G = 0$ (PC mode with $V_G = 0$). For both the electrode configurations the dependence is well approximated by a straight line up to about 30 nJ confirming the possibility to use the device as a linear detector. For $\varepsilon > 30$ nJ the detector saturates and its response is not proportional to the pulse energy anymore. Interestingly, a




Fig. 3. (a) Photocurrent vs. time collected in the photoconductive mode at different values of the gate voltage V_G ; (b) maximum of the curves shown in a) as a function of V_G . The straight line is a fit to the data in the range $V_G = 0$ –9 V. Inset: Current voltage characteristics of the same device measured in the photovoltaic mode under dark and light conditions.

marked difference of about one order of magnitude at any pulse energy is reported between the number of photocharges collected using the two different operation modes. This can be ascribed to the different mechanism governing the current flow in the two configurations. In the PV mode the photocharges, collected by measuring the current between the S and G terminals, are both electrons and holes produced by the light absorption and separated by the built-in potential at the SWCNT/Si interface. On the other hand, in the PC mode (with $V_G = 0$) the photocharges are collected by measuring the current between the S and D electrodes and are essentially holes driven across the junction by the action of the same built-in potential. They are less in number than the electron-hole pairs collected in the PV mode and this explains the difference in the data of Fig. 4a. Nevertheless, the number of holes collected by the SWCNT film in the PC mode can be hugely increased by the action of the gate potential V_G which, driving the junction in the avalanche regime, allows to obtain an amplified response as shown in the inset of the same figure. Here the number of charges collected by the SWCNT film, calculated by the area under the curves reported in Fig. 3a, are shown as a function of the applied voltage V_G . The action of the gate voltage in the three terminal configuration gives an increase on the response of the photodetector by a factor of about 200 when V_G ranges between 0V and 18V. This result overcomes




Fig. 4. (a) Number of photocharges collected in photovoltaic (black squares) and photoconductive (red circles) mode as a function of the light pulse energy. The lines are linear fit to the data for $\epsilon < 30$ nJ; Inset: number of photocharges collected in photoconductive mode as a function of the gate voltage V_G . (b) normalized photocurrent with respect to its maximum value as a function of the time in the photovoltaic (black lower curve) and photoconductive (red upper curve) mode. (For interpretation of the references to colour in this figure legend, the reader is referred to the web version of this article).

that obtained for similar junctions and gives a valuable perspective to these devices to be used in avalanche mode for small signal amplification. Avalanche photodetectors, in fact, work in inverse polarized mode using bias voltage of the order of 100 V which is very high especially if low size photodetectors are designed. The result to obtain such gains by using bias voltage less than 20 V is of a paramount importance in any field of applications for photodetectors and makes our devices a believable alternative to the today's Si technology.

The improvement of the photodetector performances observed in the PC mode is even more emphasized if one is interested to the time response of the device. Fig. 4b shows the photocurrents, normalized with respect to their maximum value, recorded in PV (black line) and in PC (red line, $V_G = 0$) modes for the same laser excitation pulse ($\epsilon = 8.9$ nJ). Rise time $\tau_{PV} = 19.6$ ns and $\tau_{PC} = 9.6$ ns are measured as the difference between 90% and 10% of the maximum of the curves for the PV and the PC mode, respectively. This improvement in the response is observed in all the measured devices when the photocharges are collected between the S and D electrodes and can be ascribed to the same mechanism discussed above for the photocharges collected in the two different terminal configurations. Only holes photogenerated in proximity of the SWCNT/Si junction are collected in the PC mode by the SWCNT thin film giving a faster




Fig. 5. Current-voltage characteristics for the SWCNT/Si junctions in dark conditions at different temperature. Inset: saturation current I_0 vs. temperature for the same sample of the main panel. The values of I_0 are obtained by linear extrapolation to zero voltage of the low current data ($V < 100$ mV) of the main panel. The straight line is a fit to the data which well approximates the experimental points in the range $T = 300$ K–140 K.

response with respect to the PV configuration where electrons, in order to be collected, have to reach the bottom electrode which is about $150 \mu\text{m}$ away from the SWCNT/Si junction [17]. Other minor mechanisms as charge recombination and difference between the charge mobility in SWCNT film and Si can be invoked to explain the observed difference in the response time between the two configurations. A slight decrease of τ_{PC} is recorded when V_G is increased in the PC configuration. This is expected because the action of the external potential is to increase the photocharge velocity towards the SWCNT film and, as a consequence, to decrease the drift time. Due to the limited rise time of the laser pulse, which is of the same order of the measured time response of our devices, the measured value of τ_{PC} is probably overestimated and a better response in terms of rise time should be obtained by using a faster laser pulse.

The high sensitivity and the fast response of our devices can be understood by investigating the kind of junction that is established at SWCNT/n-Si interface. Considering that the SWCNT film is a mixture of metallic (10%) and semiconducting (90%) SWCNTs, the type of junction that is expected to be established at the interface should be semiconducting-semiconducting (S-S) [18], semiconducting-metallic (S-M) [19] or a mixture of both. It is well known that S-M junctions, although more noisy than their counterpart S-S junctions, are faster because of the formation of a Schottky barrier which shows reduced switching times with respect to p - n junctions [20]. I - V characteristics at different temperature were performed on our devices in PV configuration in dark conditions and they are shown in Fig. 5 in a semi-logarithmic scale. In this contact configuration, the I - V dependence follows the diode characteristics given by $I = I_0 (e^{qV/k_B T} - 1)$ where k_B is the Boltzmann constant, q the elementary charge and T the temperature [21]. I_0 represents the saturation current and its temperature dependence univocally determines the kind of junction. In particular, in the case of Schottky junctions this dependence is given by $I_0 = A^* T^2 e^{(-q\phi_{Bn}/k_B T)}$ where A^* is the Richardson constant that for free electrons is $A^* = 120 \text{ A/cm}^2 \text{ K}^2$ and ϕ_{Bn} is the S-M contact barrier [21]. The inset of Fig. 5 shows the temperature dependence of I_0 measured by linear extrapolation at zero voltage of the low current part of the I - V curves corresponding to voltage less than 100 mV. The data, reported as I_0/T^2 vs T^{-1} in a semi-logarithmic scale, are well approximated by a linear dependence down to $T = 140$ K confirming that the junction behaves as a Schottky type well below room temperature. The result of the

fitting procedure gives $\phi_{bn} = 0.28$ eV. Such a low value of the interface potential barrier is in agreement with the low time response observed in our devices. The deviation from the linear dependence at $T < 140$ K is due to tunnel effects which become predominant at low temperature [22]. The formation of a Schottky-like junction at the SWCNT/Si interface can be ascribed to the metallic component of the SWCNT film and it is responsible for the fast component of the time response of our devices [21]. This suggests that using a higher metallic concentration in the SWCNT mixture would decrease the response time, improving the detector performance as fast light sensor. Nevertheless, it is expected that an increase of the metallic component affects the noise and therefore the right balance between the metallic and the semiconducting SWCNT components should be carefully considered for a better and proper use of the presented photodetector.

4. Conclusions

Fast photodetectors with rise time in the range of nanoseconds can be obtained by depositing SWCNT thin films on *n*-Si substrates. The experimental data show that the response of the devices is comparable to the commercial photodetectors based on Si technology with great advantages in time-consuming and costs. Operating in the photoconductive mode, the SWCNT/Si photodetectors can be used in avalanche regime with gains as high as 200 paving the way to their use for weak signal detection. From the temperature measurements we argue that Schottky barriers are the responsible of the fast response and high gains. Further developments are still possible with an optimization of the SWCNT/Si interface with a change in the metallic component of the SWCNT mixture forming the thin film. Moreover, better time resolution using femtosecond laser source could give a more accurate determination of the detector response time.

References

- [1] Ching Png, Sun Eng, Song, Bai Ping "State of the art photodetectors for optoelectronic integration at telecommunication wavelength", *Nanophotonics* 4 (2015) 277–302.
- [2] M. Kielar, O. Dhez, G. Pecastaings, A. Curutchet, L. Hirsch, Long-Term stable organic photodetectors with ultra low dark currents for high detectivity applications, *Sci.Rep.* 6 (2016) 39201, <http://dx.doi.org/10.1038/srep39201>.
- [3] R.A. Yotter, D.M. Wilson, A review of photodetectors for sensing light-emitting reporters in biological systems, *IEEE Sens. J.* 3 (2003) 288–303.
- [4] D. Renker, New trends on photodetectors, *Nucl. Instrum. Methods Phys. Res. A* 571 (2007) 1–6.
- [5] See Hamamatsu handbook at <https://www.hamamatsu.com/sp/ssd/doc.en.html>.
- [6] G. Ghione, *Semiconductor Devices for High Speed Optoelectronics*, Cambridge University Press, The Edimburg Building, Cambridge CB2 8RU, UK, 2009.
- [7] B.X. Li, H. Zhu, K. Wang, A. Cao, J. Wei, C. Li, Y. Jia, Z. Li, X. Li, D. Wu, Graphene-On-Silicon schottky junction solar cells, *Adv. Mater* 22 (2010) 2743–2748.
- [8] Young Lae Kim, Hyun Young Jung, Sora Park, Bo Li, L. Fangze, Ji Hao, Young-Kyun Kwon, Yung Joon Jung, Swastik Kar, Voltage-switchable photocurrents in single-walled carbon nanotube-silicon junctions for analog and digital optoelectronics, *Nat. Photonics* 8 (2014) 239–243.
- [9] J.L. Blackburn, T.M. Barnes, M.C. Beard, K. Yong-Hyun, R.C. Tenent, T.J. McDonald, B. To, T.J. Coutts, M.J. Heben, Transparent conductive single-walled carbon nanotube networks with precisely tunable ratios of semiconducting and metallic nanotubes, *ACS Nano* 2 (2008) 1266–1274.
- [10] D.D. Tune, B.S. Flavel, Advances in carbon nanotube-silicon heterojunctions solar cells, *Adv. Energy Mater.* (2018), <http://dx.doi.org/10.1002/aenm.201703241>.
- [11] M. Salvato, M. Scagliotti, M. De Crescenzi, M. Crivellari, P. Proposito, I. Cacciotti, P. Castrucci, Single walled carbon nanotube/Si heterojunctions for high responsivity photodetectors, *Nanotechnology* 28 (2017), pp. 435201.
- [12] M. Salvato, M. Scagliotti, M. De Crescenzi, M. Crivellari, R. Messi, P. Castrucci, Increasing efficiency in single walled carbon nanotubes/n-Si photodetectors by voltage doping, *IEEE Trans. on Nanotechnology* 17 (2018) 837–840, <http://dx.doi.org/10.1109/TNANO.2018.2844167>.
- [13] F. De Nicola, P. Castrucci, M. Scarselli, F. Nanni, I. Cacciotti, M. De Crescenzi, Multi-Fractal hierarchy of single-walled carbon nanotube hydrophobic coatings, *Sci. Rep.* 5 (2015), <http://dx.doi.org/10.1038/srep08583>.
- [14] F. De Nicola, C. Pintossi, F. Nanni, I. Cacciotti, M. Scarselli, G. Drera, S. Pagliara, L. Sangaletti, M. De Crescenzi, P. Castrucci, Controlling the Thickness of Carbon nano tube Random Network Films by the Estimation of the Absorption Coefficient, *Carbon* 95 (2015) 28–33.
- [15] A. Bagolini, et al., Micromachined silicon radiation sensors: II. Fabrication technologies, *Proc. 18th Conf. on Sensors and Microsystems AISEM* (Piscataway, NJ: IEEE), (XVIII ISEM AnnualConf. (2015) 1–4.
- [16] M. Scagliotti, M. Salvato, M. De Crescenzi, M. Boscardin, P. Castrucci, Influence of the contact geometry on single walled carbon nano tube/Si photodetector response, *Appl. Nanosci.* (2018), <http://dx.doi.org/10.1007/s13204-018-0720-1>.
- [17] A.O. Goushcha, B. Tabbert, "On response time of semiconductor photodiodes", *Optical Engineering* 59 (2017), pp. 097101.
- [18] Y. Jung, X. Li, N.K. Rajan, A.D. Taylor, M.A. Record high efficiency single-walled carbon nanotube/silicon p-n junction solar cells, *Nano Lett.* 13 (2013) 95–99.
- [19] A. Behnam, J.L. Johnson, Y. Choi, M.G. Ertoşun, A.K. Okyay, P. Kapur, K.C. Saraswat, A. Ural, "Experimental characterization of single-walled carbon nanotube film-Si Schottky contacts using metal-semiconductor-metal structures", *Appl. Phys. Lett.* 92 (2008), pp. 243116.
- [20] P.L. Ong, W.B. Euler, I.A. Levitsky, Hybrid solar cells based on single-walled carbon nanotubes/Si heterojunctions, *Nanotechnology* 21 (2010), pp. 105203.
- [21] S.M. Sze, *Physics of Semiconducting Devices*, 282 Wiley, New York, NY, USA, 1969.
- [22] A. Behnam, J. Johnson, Y. Choi, L. Noriega, M.G. Ertoşun, Z. Wu, A.G. Rinzler, P. Kapur, K.C. Saraswat, A. Ural, Metal-semiconductor-metal photodetectors based on single-walled carbon nanotube film–GaAs Schottky contacts, *Appl. Phys. Lett.* 103 (2008), pp. 114345.

Biographies

Matteo Salvato is Assistant Professor in Experimental Condensed Matter Physics at University of Rome "Tor Vergata". His starting research activity was focused on the fabrication and study of the transport and structural properties of superconducting/magnetic epitaxial thin films and multilayers obtained by MBE at University of Salerno, Salerno, Italy. Then, at University of Rome "Tor Vergata" he approached the study of Josephson effect in superconducting devices and investigated the transport properties of nanomaterials with particular attention to phenomena as localization and disorder in granular systems. Carbon nanotubes and graphene were the main topics of his research. More recently he studied the role of these materials in solar cell and photodetector applications. He has authored or co-authored more than 100 scientific publications on international journals and proceedings in international conferences on physics of the matter.

Mattia Scagliotti received the master's degree in physics in 2017 at the University of Rome "Tor Vergata" discussing a thesis on carbon nanotube/silicon heterojunction for photovoltaic and photodetector applications. From 2017 he started the PhD in physics at the University of Rome Tor Vergata and his work is focus on develop photodetectors based on 2D materials.

Maurizio De Crescenzi has a chair of Structure of Matter at University of Rome Tor Vergata, Rome, Italy. His research activity has been focused on synthesis, structural and electronic properties of surfaces and nano-materials. He has developed the EELFS electron technique for local structural investigations of surfaces and interfaces. He has demonstrated that carbon nanotubes can be used as efficient photon devices and solar cells. He has assessed in 1983 the structural properties of a layer of graphene on Ni(111) surface. He is author of about 300 publications. He has organized several International Conferences (NanoSEA) on nanostructures and their applications and Workshops. At present he is investigating silicon grown on different substrates to develop new graphene-like structures.

Maurizio Boscardin is a researcher at Microelectronics Division of the Institute for Scientific and Technological Research (ITC/irst) of Trento, Italy (now Fondazione Bruno Kessler) since 1988. Here he was initially involved in the development of CCD/CMOS technologies for optical imagers. From 1998–2008, he has been heading the Silicon Radiation Detector group. From 2009–2014, he has been in charge of the coordination of the R&D activity of Microfabrication Lab of FBK. From 2015 senior researcher of the Micro Nano Facility at FBK. The research activity of Maurizio Boscardin deals with technology development for special sensor fabrication, with particular emphasis on high resistivity silicon radiation/particle detectors. The main research topics have recently been concerned with: i) Development of planar detectors for high energy physics experiments as double side microstrip, pixel, SDD. ii) Development of special technologies for fabrication of advanced radiation/particle detectors as Active Edge, Si-3D and LGAD. He is co-authored of more than 250 articles published in international journals or presented at international conferences.

Carmine Attanasio is a Full Professor of Experimental Condensed Matter Physics at the University of Salerno, Italy. His research activity, developed in the field of experimental study of advanced and innovative materials, has been focused in the production of both low- and high-Tc superconductors in the form of thin films and multilayers and in the measure of their superconducting and transport properties also in the presence of microwave radiation. His scientific interest is from many years devoted to the study of the interaction between superconductivity and magnetism mainly in artificial layered structures and more recently it has been extended also to the study of the transport properties of superconducting ultra-thin films deposited on self-assembled templates in the nanometric scale and

one-dimensional superconductivity. He is author and co-author of more than 160 publications in international journals and he gave more than 60 talks at international conferences. He is co-owner of the Italian patent "In-situ photolithographic technique of high-Tc superconducting materials".

Guerino Avallone obtained a M.Sc. in Physics attaining the top score Cum Laude from the University of Salerno (Italy) in 2016 with a thesis entitled "Niobium Nanowire Networks at Millikelvin Temperatures". For his Masters project, he fabricated and investigated the transport properties at very low temperatures of interconnected nano-networks, consisting of ultrathin superconducting Nb nanowires, achieved by using an innovative self-assembled technique. Currently working towards a Ph.D. within the Department of Physics at the University of Salerno. His interests are focused on quantum-enhanced devices. In particular, creation, control and manipulation of quantum states to design systems with functionality that could not be achieved in a "non-quantum world".

Carla Cirillo is researcher at SPIN-CNR Institute, Salerno, Italy. The main part of her activity is on superconducting materials and it is essentially focused on the study of the transport properties of artificial hybrids involving in particular superconductor/ferromagnetic thin film hybrids. Recently, the interest extended to the study of the transport properties of strongly correlated electron materials. In the framework of this research expertise has been acquired in the following main activities: thin films and superlattices fabrication by sputtering technique and their electric characterization; X-Ray reflectivity and high angle diffraction; optical and e-beam lithographic processing; vacuum and cryogenic skills; magnetic characterization of ferromagnetic thin films by SQUID magnetometer. She is co-author of about 90 articles on refereed international journals (about 600 citations, ISI-web h-factor=14). She is Referee of several international scientific journals such as for example Physical Review Letters, Physical Review B, Physical Review Materials from APS.

Paolo Proposito is assistant professor at the Industrial Engineering Department of the University of Rome "Tor Vergata". Main skills and expertise are on experimental Physics with special regard on Material Science and Optical Spectroscopy. He is author of about 100 papers on international peer reviewed scientific journals and one patent.

Fabio De Matteis graduated in Physics at the University of Rome-La Sapienza, in 1987 and received a PhD in Physics from the University of Antwerp, Belgium in 1993. He is at University of Rome Tor Vergata since 1995. His scientific interest has been devoted to: synthesis and optical characterization of dielectric materials for photonics studied by means of several spectroscopic techniques (absorption and luminescence, static and time resolved by ultra-fast techniques, Raman); synthesis and nonlinear optical characterization of materials functionalized by electrooptic molecular moieties for optoelectronics; polar ordering of nonlinear chromophores induced by corona and electrode poling; surface nanostructuring (mono and bi-dimensional gratings) in insulating materials by photolithographic techniques; bio-polymeric scaffolds by two-photon polymerization for tissue engineering; impedance spectroscopy of solid electrolyte materials showing ionic conduction.

Roberto Messi is Associate Professor in Experimental Physics at University of Roma "Tor Vergata". His research activity was developed in different fields as condensed matter, electronics, high energy, particles detection taking part in a number of projects and experiments in collaboration with INFN groups at Frascati, Italy and CERN International laboratories. Recently he took part in some important experiments as LHCb and KLOE involving LHC at CERN.

Paola Castrucci is Associate Professor of Experimental Physics of Matter at the Department of Physics of the University of Roma "Tor Vergata" and since 2016 has been approved to the role of Full Professor in Experimental Physics of Matter with overall rating Excellent at the National Scientific Enabling procedure. Her research activity dealt with nanostructures as nanowires, nanotubes and two dimensional materials. Her expertise spans from the growth of these systems to their structural and electronic characterizations through several spectroscopies, microscopies and diffraction techniques. She worked on photovoltaic measurements of a new generation solar cells based on carbon nanotubes and silicon and currently she is involved in the application of similar systems as photodetectors. She participated and/or was/is the coordinator of a number of funded research projects and is referee for national and international agency. She is current referee of more than 20 ISI-classified journals. She participated at many conferences presenting posters, oral and invited communications. She is among the organizers of 8 international conferences. She is co-author of more than 130 papers published on ISI international peer reviews, achieving an h-index of 23 (Scopus) with more than 1900 citations.

